



REPORT No. : SZ18100073S01

TEST REPORT

APPLICANT : BLU Products, Inc.
PRODUCT NAME : 3G Feature Phone
MODEL NAME : JOY 3G
BRAND NAME : BLU
FCC ID : YHLBLUJOY3G
STANDARD(S) : FCC 47 CFR 2.1093
IEEE 1528-2013
TEST DATE : 2018-10-28
ISSUE DATE : 2018-11-12

Edited by:

Su Jinhai
Su Jinhai (Rapporteur)

Approved by:

Peng Huarui
Peng Huarui (Supervisor)

NOTE: This document is issued by MORLAB, the test report shall not be reproduced except in full without prior written permission of the company. The test results apply only to the particular sample(s) tested and to the specific tests carried out which is available on request for validation and information confirmed at our website.

MORLAB

SHENZHEN MORLAB COMMUNICATIONS TECHNOLOGY Co., Ltd.
FL1-3, Building A, FeiYang Science Park, No.8 LongChang Road,
Block67, BaoAn District, ShenZhen , Guangdong Province, P. R. China

Tel: 86-755-36698555

Fax: 86-755-36698525

Http://www.morlab.cn

E-mail: service@morlab.cn





DIRECTORY

| | |
|--|----|
| 1 SAR Results Summary..... | 5 |
| 2 Technical Information..... | 6 |
| 2.1 Applicant and Manufacturer Information..... | 6 |
| 2.2 Equipment Under Test (EUT) Description..... | 6 |
| 2.3 Environment of Test Site..... | 7 |
| 3 Introduction..... | 8 |
| 3.1 Introduction..... | 8 |
| 3.2 SAR Definition..... | 8 |
| 4 RF Exposure Limits..... | 9 |
| 5 Applied Reference Documents..... | 9 |
| 6 SAR Measurement System..... | 10 |
| 6.1 E-Field Probe..... | 11 |
| 6.2 Data Acquisition Electronics (DAE)..... | 12 |
| 6.3 Robot..... | 13 |
| 6.4 Measurement Server..... | 13 |
| 6.5 Light Beam Unit..... | 13 |
| 6.6 Phantom..... | 14 |
| 6.7 Device Holder..... | 14 |
| 6.8 Data storage and Evaluation..... | 15 |
| 6.9 Test Equipment List..... | 17 |
| 6.10 Tissue Simulating Liquids..... | 18 |
| 7 SAR System Verification..... | 20 |
| 8 EUT Testing Position..... | 22 |
| 8.1 Handset Reference Points..... | 22 |
| 8.2 Positioning for Cheek / Touch..... | 23 |
| 8.3 Positioning for Ear / 15° Tilt..... | 23 |
| 8.4 SAR Evaluations near the Mouth/Jaw Regions of the SAM Phantom..... | 24 |
| 8.5 Body Worn Accessory Configurations..... | 24 |
| 9 Measurement Procedures..... | 25 |



| | |
|---|----|
| 9.1 Spatial Peak SAR Evaluation..... | 25 |
| 9.2 Power Reference Measurement..... | 26 |
| 9.3 Area Scan Procedures..... | 26 |
| 9.4 Zoom Scan Procedures..... | 26 |
| 9.5 SAR Averaged Methods..... | 26 |
| 9.6 Power Drift Monitoring..... | 26 |
| 10 Conducted RF Output Power..... | 27 |
| 10.1 GSM Conducted Power..... | 27 |
| 10.2 WCDMA Conducted Power..... | 28 |
| 10.3 Bluetooth Conducted Power..... | 31 |
| 11 Exposure Positions Consideration..... | 32 |
| 11.1 EUT Antenna Location..... | 32 |
| 11.2 Test Positions Consideration..... | 32 |
| 12 Block diagram of the tests to be performed..... | 33 |
| 12.1 Head..... | 33 |
| 12.2 Body..... | 34 |
| 13 Test Results List..... | 35 |
| 14 SAR Test Results Summary..... | 36 |
| 14.1 Standalone Head SAR..... | 36 |
| 14.2 Standalone Body SAR..... | 37 |
| 14.3 Repeated SAR measurement..... | 38 |
| 14.4 Multi-Band Simultaneous Transmission Considerations..... | 39 |
| 14.5 SAR Simultaneous Transmission Analysis..... | 40 |
| 14.6 DUT holder perturbation uncertainty evaluation..... | 42 |
| 15 Measurement Uncertainty..... | 43 |
| 16 Measurement Conclusion..... | 45 |
| Annex A General Information | |
| Annex B Test Setup Photos | |
| Annex C Plots of System Performance Check | |
| Annex D Plots of Maximum SAR Test Results | |
| Annex E DASY Calibration Certificate | |



REPORT No. : SZ18100073S01

| Version No. | Date | Description |
|-------------|------------|-------------|
| 1.0 | 2018-11-12 | Original |
| | | |
| | | |
| | | |
| | | |



1 SAR Results Summary

The maximum results of Specific Absorption Rate (SAR) found during test as bellows:

<Highest Reported standalone SAR Summary>

| Frequency Band | | Highest SAR Summary (1g SAR (W/kg)) | |
|-----------------------------------|------------|-------------------------------------|-------------------|
| | | Head | Body-worn |
| | | (Separation 0mm) | (Separation 10mm) |
| GSM | GSM 850 | 0.561 | 1.241 |
| | GSM 1900 | 0.797 | 1.114 |
| WCDMA | WCDMA 850 | 0.099 | 0.674 |
| | WCDMA 1900 | 1.184 | 1.259 |
| 2.4GHz Band | Bluetooth | 0.074 | 0.037 |
| Highest Simultaneous Transmission | | 1.258 | 1.296 |

| | | | |
|--------------------------------------|------------|------------|-----------------------|
| Max Scaled SAR _{1g} (W/Kg): | Head: | 1.184 W/kg | Limit(W/kg): 1.6 W/kg |
| | Body-worn: | 1.259 W/kg | |

Note:

1. This device is compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure limits (1.6 W/kg) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-2005, and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013.



2 Technical Information

Note: Provide by manufacturer.

2.1 Applicant and Manufacturer Information

| | |
|------------------------------|--|
| Applicant: | BLU Products, Inc. |
| Applicant Address: | 10814 NW 33rd St # 100 Doral, FL 33172,USA |
| Manufacturer: | BLU Products, Inc. |
| Manufacturer Address: | 10814 NW 33rd St # 100 Doral, FL 33172,USA |

2.2 Equipment Under Test (EUT) Description

| | |
|-------------------------------|---|
| EUT Type: | 3G Feature Phone |
| Hardware Version: | 3703-MB-V0.3 |
| Software Version: | 3708_03C_CFZZ_BLU_QQVGA_Y64_BT_FM_SC_V01_20181103_1623 |
| Frequency Bands: | GSM850: 824.2 MHz ~ 848.8 MHz GSM1900: 1850.2 MHz ~ 1909.8 MHz WCDMA Band II: 1850 MHz ~1910 MHz WCDMA Band V: 824 MHz ~ 849 MHz Bluetooth: 2402 MHz ~ 2480 MHz |
| Modulation Mode: | GSM/GPRS: GMSK WCDMA: QPSK Bluetooth: GFSK, $\pi/4$ -DQPSK, 8-DPSK |
| Multi-slot Class: | Multi-Slot Class 12 |
| Operation Class | Class B |
| Hotspot Mode: | Not Support |
| Antenna Type: | PIFAAntenna |
| SIM cards description: | For dual SIM card version, SIM 1 and SIM 2 are the same chipset unit and tested as a single chipset, the SIM 1 is chosen for test |

Note: For a more detailed description, please refer to specification or user's manual supplied by the applicant and/or manufacturer.

2.3 Environment of Test Site

| | |
|------------------------------|------------------|
| Temperature: | 20 ... 25 ° C |
| Humidity: | 30 ... 75 % |
| Atmospheric Pressure: | 980 ... 1020 hPa |

| | |
|------------------------|--|
| Test frequency: | GSM 850MHz/1900MHz; WCDMA Band II/V; Bluetooth; |
| Operation mode: | Call established |
| Power Level: | GSM 850MHz Maximum output power(level 5) GSM 1900MHz Maximum output power(level 0) WCDMA Band II/V (All Up Bits) Bluetooth; |

During SAR test, EUT is in Traffic Mode (Channel Allocated) at Normal Voltage Condition. A communication link is set up with a System Simulator (SS) by air link, and a call is established.

The EUT shall use its internal transmitter. The antenna(s), battery and accessories shall be those specified by the Factory. The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power output. If a wireless link is used, the antenna connected to the output of the base station simulator shall be placed at least 50 cm away from the handset.

The signal transmitted by the simulator to the antenna feeding point shall be lower than the output power level of the handset by at least 35 dB.

For SAR testing, EUT is in GPRS mode. In GPRS link mode, its crest factor is 2, because EUT is set in GPRS multi-slot class 12 with 4 uplink slots. In WCDMA mode, its crest factor is 1.

3 Introduction

3.1 Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational/controlled and general population/uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational/controlled exposure limits are higher than the limits for general population/uncontrolled.

3.2 SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy (dW) absorbed by (dissipated in) an incremental mass (dm) contained in a volume element (dv) of a given density (ρ). The equation description is as below:

$$SAR = \frac{d}{dt} \left(\frac{dU}{dm} \right) = \frac{d}{dt} \left(\frac{dU}{\rho dv} \right)$$

SAR is expressed in units of Watts per kilogram (W/kg)

SAR measurement can be either related to the temperature elevation in tissue by

$$SAR = C \left(\frac{\delta T}{\delta t} \right)$$

Where: C is the specific heat capacity, δT is the temperature rise and δt is the exposure duration, or related to the electrical field in the tissue by

$$SAR = \frac{\sigma \cdot E^2}{\rho}$$

Where: σ is the conductivity of the tissue, ρ is the mass density of the tissue and E is the RMS electrical field strength. However for evaluating SAR of low power transmitter, electrical field measurement is typically applied.



4 RF Exposure Limits

Limits for General Population/Uncontrolled Exposure (W/kg)

| Type Exposure | Uncontrolled Environment Limit |
|--|--------------------------------|
| Spatial Peak SAR (1g cube tissue for head and trunk) | 1.60W/kg |
| Spatial Peak SAR (10g cube tissue for limbs) | 4.00W/kg |
| Spatial Peak SAR (1g cube tissue for whole body) | 0.08 W/kg |

Note:

1. This limit is according to recommendation 1999/519/EC, Annex II (Basic Restrictions)
2. Occupational/Uncontrolled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure, (i.e. as a result of employment or occupation)

5 Applied Reference Documents

Leading reference documents for testing:

| No. | Identity | Document Title |
|-----|----------------------|--|
| 1 | 47 CFR§2.1093 | Radio Frequency Radiation Exposure Evaluation: Portable Devices |
| 2 | IEEE 1528-2013 | IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques |
| 3 | KDB 447498 D01v06 | General RF Exposure Guidance |
| 4 | KDB 865664 D01v01r04 | SAR Measurement 100 MHz to 6 GHz |
| 5 | KDB 865664 D02v01r02 | RF Exposure Reporting |
| 7 | KDB 648474 D04v01r03 | Handset SAR |
| 8 | KDB 941225 D01v03r01 | 3G SAR Measurement Procedures |

6 SAR Measurement System




Fig.6.1 SPEAG DASY System Configurations

The DASY system for performance compliance tests is illustrated above graphically. This system consists of the following items:

- A standard high precision 6-axis robot with controller, a teach pendant and software
- A data acquisition electronic (DAE) attached to the robot arm extension
- A dosimetric probe equipped with an optical surface detector system
- The electro-optical converter (EOC) performs the conversion between optical and electrical signals
- A measurement server performs the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the accuracy of the probe positioning
- A computer operating Windows XP
- DASY software
- Remote control with teach pendant and additional circuitry for robot safety such as warning lamps, etc.
- The SAM twin phantom
- A device holder
- Tissue simulating liquid
- Dipole for evaluating the proper functioning of the system

Component details are described in the following sub-sections.

6.1 E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG). The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

➤ E-Field Probe Specification <EX3DV3 Probe>


| | | |
|----------------------|---|--|
| Construction | Symmetrical design with triangular core Built-in optical fiber for surface detection system. Built-in shielding against static charges. PEEK enclosure material (resistant to organic solvents, e.g., DGBE) |  |
| Frequency | 10 MHz to 3 GHz; Linearity: ± 0.2 dB | |
| Directivity | ± 0.2 dB in HSL (rotation around probe axis) ± 0.4 dB in HSL (rotation normal to probe axis) | |
| Dynamic Range | 5 μ W/g to 100 mW/g; Linearity: ± 0.2 dB | |
| Dimensions | Overall length: 330 mm (Tip: 16 mm) Tip diameter: 6.8 mm (Body: 12 mm) Distance from probe tip to dipole centers: 2.7 mm | |

Fig 6.2 Photo of ES3DV3

<EX3DV4 Probe>


| | | |
|----------------------|---|--|
| Construction | Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE) |  |
| Frequency | 10 MHz to 6 GHz; Linearity: ± 0.2 dB | |
| Directivity | ± 0.3 dB in HSL (rotation around probe axis) ± 0.5 dB in tissue material (rotation normal to probe axis) | |
| Dynamic Range | 10 μ W/g to 100 mW/g; Linearity: ± 0.2 dB | |
| Dimensions | Overall length: 330 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm | |

Fig 6.3 Photo of EX3DV4

➤ E-Field Probe Calibration

Each probe needs to be calibrated according to a dosimetric assessment procedure with accuracy better than $\pm 10\%$. The spherical isotropy shall be evaluated and within ± 0.25 dB. The sensitivity parameters (Norm X, Norm Y and Norm Z), the diode compression parameter (DCP) and the conversion factor (ConvF) of the probe are tested. The calibration data can be referred to appendix E of this report.

6.2 Data Acquisition Electronics (DAE)

The Data acquisition electronics (DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast 16 bit AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The input impedance of the DAE is 200 MOhm; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.




Fig. 6.4 Photo of DAE

6.3 Robot

The SPEAG DASY system uses the high precision robots (DASY5: TX60XL) type from Stäubli SA (France). For the 6-axis controller system, the robot controller version (DASY5: CS8c) from Stäubli is used. The Stäubli robot series have many features that are important for our application:

- High precision (repeatability 0.02 mm)
- High reliability (industrial design)
- Low maintenance costs (virtually maintenance free due to direct drive gears; nobelt drives)
- Jerk-free straight movements
- Low ELF interference (motor control fields shielded via the closed metallic construction shields)



Fig. 6.5 Photo of Robot

6.4 Measurement Server

The measurement server is based on a PC/104 CPU board with CPU (DASY 5: 400MHz, Intel Celeron), chip-disk (DASY5: 128 MB), RAM (DASY5: 128 MB). The necessary circuits for communication with the DAE electronic box, as well as the 16 bit AD converter system for optical detection and digital I/O interface are contained on the DASY I/O board, which is directly connected to the PC/104 bus of the CPU board. The measurement server performs all the real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operations.



Fig. 6.6 Photo of Server for DASY5

6.5 Light Beam Unit

The light beam switch allows automatic "tooling" of the probe. During the process, the actual position of the probe tip with respect to the robot arm is measured, as well as the probe length and the horizontal probe offset. The software then corrects all movements, such that the robot coordinates are valid for the probe tip.

The repeatability of this process is better than 0.1 mm. If a position has been taught with an aligned probe, the same position will be reached with another aligned probe within 0.1 mm, even if the other probe has different dimensions. During probe rotations, the probe tip will keep its actual position.



Fig. 6.7 Photo of Light Beam

6.6 Phantom

<SAM Twin Phantom>

| | |
|------------------------------|---|
| Shell Thickness | 2 ± 0.2 mm (sagging: <1%) Center ear point: 6 ± 0.2 mm |
| Filling Volume Dimensions | Approx. 25 liters Length: 1000 mm; Width: 500 mm; Height: adjustable feet |
| Measurement Areas | Left Head, Right Head, Flat phantom |



Fig. 6.8Photo of SAM Phantom

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

6.7 Device Holder

<Device Holder for SAM Twin Phantom>

The SAR in the phantom is approximately inversely proportional to the square of the distance between the source and the liquid surface. For a source at 5 mm distance, a positioning uncertainty of ±0.5 mm would produce a SAR uncertainty of ± 20 %. Accurate device positioning is therefore crucial for accurate and repeatable measurements. The positions in which the devices must be measured are defined by the standards.

The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation center for both scales is the ear reference point (ERP).

Thus the device needs no repositioning when changing the angles.

The DASY device holder is constructed of low-loss POM material having the following dielectric parameters: relative permittivity $\epsilon = 3$ and loss tangent $\delta = 0.02$. The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.




Fig. 6.9Photo of Device Holder

<Laptop Extension Kit>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.

Fig 6.10 Laptop Extension Kit



6.8 Data storage and Evaluation

➤ Data Storage

The DASY software stores the assessed data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all the necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The post-processing software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verifications of the complete software setup even after the measurement and allows correction of erroneous parameter settings. For example, if a measurement has been performed with an incorrect crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be reevaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type (e.g., [V/m], [mW/g]). Some of these units are not available in certain situations or give meaningless results, e.g., a SAR-output in a non-lose media, will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

➤ Data Evaluation

The DASY post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

| | | |
|---------------------------|---------------------------|---|
| Probe Parameters: | - Sensitivity | Norm _i , a _{i0} , a _{i1} , a _{i2} |
| | - Conversion | ConvF _i |
| | - Diode compression point | dcp _i |
| Device Parameters: | - Frequency | f |
| | - Crest | cf |



| | | |
|--------------------------|----------------|----------|
| Media Parameters: | - Conductivity | σ |
| | - Density | ρ |

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multi-meter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power.

The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

With V_i = compensated signal of channel i , ($i = x, y, z$)

U_i = input signal of channel i , ($i = x, y, z$)

cf = crest factor of exciting field (DASY parameter)

dcp_i = diode compression point (DASY parameter)

From the compensated input signals, the primary field data for each channel can be evaluated:

$$\text{E- Field Probes: } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

$$\text{H-Field Probes: } H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}$$

With V_i = compensated signal of channel i , ($i = x, y, z$)

Norm_i = sensor sensitivity of channel i , ($i = x, y, z$), $\mu\text{V}/(\text{V/m})^2$

ConvF = sensitivity enhancement in solution

a_{ij} = sensor sensitivity factors for H-field probes

f = carrier frequency (GHz)

E_i = electric field strength of channel i in V/m

H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$\text{SAR} = E_{\text{tot}}^2 \cdot \frac{\sigma}{\rho \cdot 1000}$$

With SAR = local specific absorption rate in mW/g

E_{tot} = total field strength in V/m

σ = conductivity in (mho/m) or (Siemens/m)

ρ = equipment tissue density in g/cm^3

Note that the density is set to 1, to account for actual head tissue density rather than the density of the tissue simulating liquid.



6.9 Test Equipment List

| Manufacturer | Name of Equipment | Type/Model | Serial Number | Calibration | |
|---------------|-------------------------------|------------------------------------|---------------|-------------|------------|
| | | | | Last Cal. | Due Date |
| SPEAG | 835MHz System Validation Kit | D835V2 | 4d227 | 2018.06.22 | 2019.06.21 |
| SPEAG | 1900MHz System Validation Kit | D1900V2 | 5d221 | 2018.06.22 | 2019.06.21 |
| SPEAG | Dosimetric E-Field Probe | ES3DV3 | 3154 | 2017.10.30 | 2018.10.29 |
| SPEAG | Data Acquisition Electronics | DAE4 | 1516 | 2018.07.14 | 2019.07.13 |
| SPEAG | SAM Twin Phantom 1 | QD 000 P40 CB | TP-1471 | NCR | NCR |
| SPEAG | SAM Twin Phantom 2 | QD 000 P40 CB | TP-1464 | NCR | NCR |
| SPEAG | Phone Positioner | N/A | N/A | NCR | NCR |
| R&S | Network Emulator | CMW500 | 124534 | 2018.04.17 | 2019.04.16 |
| Agilent | Network Emulator | 8960 | 10752 | 2018.04.17 | 2019.04.16 |
| Agilent | Network Analyzer | E5071B | MY42404762 | 2018.04.17 | 2019.04.16 |
| mini-circuits | Amplifier | ZHL-42W+ | 608501717 | NCR | NCR |
| Agilent | Signal Generator | SMP_02 | N/A | 2018.04.17 | 2019.04.16 |
| Agilent | Signal Generator | N5182B | MY53050509 | 2018.04.17 | 2019.04.16 |
| Agilent | Power Sensor | N8482A | MY41091706 | 2018.04.17 | 2019.04.16 |
| Agilent | Power Meter | E4416A | MY45102093 | 2018.04.17 | 2019.04.16 |
| Anritsu | Power Sensor | MA2411B | N/A | 2018.04.17 | 2019.04.16 |
| R&S | Power Meter | NRVD | 101066 | 2018.04.17 | 2019.04.16 |
| MCL | Attenuation1 | 351-218-010 | N/A | NA | NA |
| THERMOMETER | Thermo meter | DC-803 | N/A | 2017.12.08 | 2018.12.07 |
| N/A | Tissue Simulating Liquids | HSL 800-2000MHz MSL 800-2000MHz | N/A | 24H | |

Note:

1. The calibration certificate of DASY can be referred to appendix C of this report.
2. Referring to KDB 865664 D01v01r04, the dipole calibration interval can be extended to 3 years with justification. The dipoles are also not physically damaged, or repaired during the interval.
3. The Insertion Loss calibration of Dual Directional Coupler and Attenuator were characterized via the network analyzer and compensated during system check.
4. The dielectric probe kit was calibrated via the network analyzer, with the specified procedure (calibrated in pure water) and calibration kit (standard) short circuit, before the dielectric measurement. The specific procedure and calibration kit are provided by Speag.
5. In system check we need to monitor the level on the power meter, and adjust the power amplifier level to have precise power level to the dipole; the measured SAR will be normalized to 1W input power according to the ratio of 1W to the input power to the dipole. For system check, the calibration of the power amplifier is deemed not critically required for correct measurement; the power meter is critical and we do have calibration for it.
6. Attenuator insertion loss is calibrated by the network Analyzer, which the calibration is valid, before system check.
7. N.C.R means No Calibration Requirement.

6.10 Tissue Simulating Liquids

For the measurement of the field distribution inside the SAM phantom with DASY, the phantom must be filled with around 25 liters of homogeneous body tissue simulating liquid. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 6.11, for body SAR testing, the liquid height from the center of the flat phantom to liquid top surface is larger than 15 cm, which is shown in Fig. 6.12.




Fig 6.11 Photo of Liquid Height for Head SAR



Fig 6.12 Photo of Liquid Height for Body SAR

The following table gives the recipes for tissue simulating liquids

| Frequency (MHz) | Water (%) | Sugar (%) | Cellulose (%) | Salt (%) | Preventol (%) | DGBE (%) | Conductivity (σ) | Permittivity (ϵ_r) |
|------------------|-----------|-----------|---------------|----------|---------------|----------|---------------------------|-------------------------------|
| Head | | | | | | | | |
| 750 | 41.1 | 57.0 | 0.2 | 1.4 | 0.2 | 0 | 0.89 | 41.9 |
| 835 | 40.3 | 57.9 | 0.2 | 1.4 | 0.2 | 0 | 0.90 | 41.5 |
| 1800, 1900, 2000 | 55.2 | 0 | 0 | 0.3 | 0 | 44.5 | 1.40 | 40.0 |
| 2450 | 55.0 | 0 | 0 | 0 | 0 | 45.0 | 1.80 | 39.2 |
| 2600 | 54.8 | 0 | 0 | 0.1 | 0 | 45.1 | 1.96 | 39.0 |
| Body | | | | | | | | |
| 750 | 51.7 | 47.2 | 0 | 0.9 | 0.1 | 0 | 0.96 | 55.5 |
| 835 | 50.8 | 48.2 | 0 | 0.9 | 0.1 | 0 | 0.97 | 55.2 |
| 1800, 1900, 2000 | 70.2 | 0 | 0 | 0.4 | 0 | 29.4 | 1.52 | 53.3 |
| 2450 | 68.6 | 0 | 0 | 0 | 0 | 31.4 | 1.96 | 52.7 |
| 2600 | 68.1 | 0 | 0 | 0.1 | 0 | 31.8 | 2.16 | 52.5 |

Simulating Liquid for 5GHz, Manufactured by SPEAG

| Ingredients | (% by weight) |
|--------------------|---------------|
| Water | 64~78% |
| Mineral oil | 11~18% |
| Emulsifiers | 9~15% |
| Additives and Salt | 2~3% |



The relative permittivity and conductivity of the tissue material should be within $\pm 5\%$ of the values given in the table below recommended by the FCC OET 65 supplement C and RSS 102 Issue 5.

| Target Frequency (MHz) | Head | | Body | |
|---------------------------|--------------|----------------|--------------|----------------|
| | ϵ_r | σ (S/m) | ϵ_r | σ (S/m) |
| 150 | 52.3 | 0.76 | 61.9 | 0.80 |
| 300 | 45.3 | 0.87 | 58.2 | 0.92 |
| 450 | 43.5 | 0.87 | 56.7 | 0.94 |
| 835 | 41.5 | 0.90 | 55.2 | 0.97 |
| 900 | 41.5 | 0.97 | 55.0 | 1.05 |
| 915 | 41.5 | 0.98 | 55.0 | 1.06 |
| 1450 | 40.5 | 1.20 | 54.0 | 1.30 |
| 1610 | 40.3 | 1.29 | 53.8 | 1.40 |
| 1800-2000 | 40.0 | 1.40 | 53.3 | 1.52 |
| 2450 | 39.2 | 1.80 | 52.7 | 1.95 |
| 3000 | 38.5 | 2.40 | 52.0 | 2.73 |
| 5800 | 35.3 | 5.27 | 48.2 | 6.00 |

(ϵ_r = relative permittivity, σ = conductivity and $\rho = 1000 \text{ kg/m}^3$)

The dielectric parameters of liquids were verified prior to the SAR evaluation using a Speag Dielectric Probe Kit and an Agilent Network Analyzer.

The following table shows the measuring results for simulating liquid.

| Frequency (MHz) | Tissue Type | Liquid Temp. (°C) | Conductivity (σ) | Conductivity Target (σ) | Delta (σ) (%) | Limit (%) | Date |
|-----------------|-------------|-------------------|---------------------------|----------------------------------|------------------------|-----------|------------|
| 835 | HSL | 22.2 | 0.890 | 0.90 | -1.11 | ± 5 | 2018.10.28 |
| 1900 | HSL | 22.2 | 1.430 | 1.40 | 2.14 | ± 5 | 2018.10.28 |
| 835 | MSL | 22.2 | 0.956 | 0.97 | -1.44 | ± 5 | 2018.10.28 |
| 1900 | MSL | 22.2 | 1.533 | 1.52 | 0.86 | ± 5 | 2018.10.28 |

| Frequency (MHz) | Tissue Type | Liquid Temp. (°C) | Permittivity (ϵ_r) | Permittivity Target (ϵ_r) | Delta (ϵ_r) (%) | Limit (%) | Date |
|-----------------|-------------|-------------------|-------------------------------|--------------------------------------|----------------------------|-----------|------------|
| 835 | HSL | 22.2 | 41.760 | 41.50 | 0.63 | ± 5 | 2018.10.28 |
| 1900 | HSL | 22.2 | 40.885 | 40.00 | 2.21 | ± 5 | 2018.10.28 |
| 835 | MSL | 22.2 | 54.343 | 55.20 | -1.55 | ± 5 | 2018.10.28 |
| 1900 | MSL | 22.2 | 52.385 | 53.30 | -1.72 | ± 5 | 2018.10.28 |

7 SAR System Verification

Each DASY system is equipped with one or more system validation kits. These units, together with the predefined measurement procedures within the DASY software, enable the user to conduct the system performance check and system validation. System validation kit includes a dipole, tripod holder to fix it underneath the flat phantom and a corresponding distance holder.

➤ Purpose of System Performance check

The system performance check verifies that the system operates within its specifications. System and operator errors can be detected and corrected. It is recommended that the system performance check be performed prior to any usage of the system in order to guarantee reproducible results. The system performance check uses normal SAR measurements in a simplified setup with a well characterized source. This setup was selected to give a high sensitivity to all parameters that might fail or vary over time. The system check does not intend to replace the calibration of the components, but indicates situations where the system uncertainty is exceeded due to drift or failure.

➤ System Setup

In the simplified setup for system evaluation, the EUT is replaced by a calibrated dipole and the power source is replaced by a continuous wave that comes from a signal generator. The calibrated dipole must be placed beneath the flat phantom section of the SAM twin phantom with the correct distance holder. The distance holder should touch the phantom surface with a light pressure at the reference marking and be oriented parallel to the long side of the phantom. The equipment setup is shown below:




Fig.7.1 System Verification Setup Diagram




Fig.7.2 Photo of Dipole setup



➤ **System Verification Results**

Comparing to the original SAR value provided by SPEAG, the verification data should be within its specification of 10%. Below table shows the target SAR and measured SAR after normalized to 1W input power. The table as below indicates the system performance check can meet the variation criterion and the plots can be referred to Appendix C of this report.

<1g SAR>

| Date | Freq. (MHz) | Tissue Type | Input Power (mW) | Dipole S/N | Probe S/N | DAE S/N | Measured 1g SAR (W/kg) | Targeted 1g SAR (W/kg) | Normalized 1g SAR (W/kg) | Deviation (%) |
|------------|----------------|----------------|------------------------|---------------|--------------|------------|------------------------------|------------------------------|--------------------------------|------------------|
| 2018.10.28 | 835 | HSL | 250 | D835V2-4d227 | 3154 | 1516 | 2.45 | 9.46 | 9.8 | 3.59 |
| 2018.10.28 | 1900 | HSL | 250 | D1900V2_5d221 | 3154 | 1516 | 10.23 | 39.30 | 40.92 | 4.12 |
| 2018.10.28 | 835 | MSL | 250 | D835V2-4d227 | 3154 | 1516 | 2.49 | 9.56 | 9.96 | -4.02 |
| 2018.10.28 | 1900 | MSL | 250 | D1900V2_5d221 | 3154 | 1516 | 9.99 | 40.40 | 39.96 | 1.10 |

<10g SAR>

| Date | Freq. (MHz) | Tissue Type | Input Power (mW) | Dipole S/N | Probe S/N | DAE S/N | Measured 10g SAR (W/kg) | Targeted 10g SAR (W/kg) | Normalized 10g SAR (W/kg) | Deviation (%) |
|------------|----------------|----------------|------------------------|---------------|--------------|------------|-------------------------------|-------------------------------|---------------------------------|------------------|
| 2018.10.28 | 835 | HSL | 250 | D835V2-4d227 | 3154 | 1516 | 1.57 | 6.11 | 6.28 | 2.78 |
| 2018.10.28 | 1900 | HSL | 250 | D1900V2_5d221 | 3154 | 1516 | 5.26 | 20.50 | 21.04 | 2.63 |
| 2018.10.28 | 835 | MSL | 250 | D835V2-4d227 | 3154 | 1516 | 1.56 | 6.28 | 6.24 | 0.64 |
| 2018.10.28 | 1900 | MSL | 250 | D1900V2_5d221 | 3154 | 1516 | 5.53 | 21.30 | 22.12 | -3.71 |

Note: System checks the specific test data please see Annex C

8 EUT Testing Position

This EUT was tested in ten different positions. They are right cheek/right tilted/left cheek/left tilted for head, Front/Back/Right Side/Top Side/Bottom Side of the EUT with phantom 10 mm gap, as illustrated below, please refer to Appendix B for the test setup photos.

8.1 Handset Reference Points

- The vertical centreline passes through two points on the front side of the handset – the midpoint of the width w_t of the handset at the level of the acoustic output, and the midpoint of the width w_b of the bottom of the handset.
- The horizontal line is perpendicular to the vertical centreline and passes the center of the acoustic output. The horizontal line is also tangential to the handset at point A.
- The two lines intersect at point A. Note that for many handsets, point A coincides with the center of the acoustic output; however, the acoustic output may be located elsewhere on the horizontal line. Also note that the vertical centreline is not necessarily parallel to the front face of the handset, especially for clamshell handsets, handsets with flip covers, and other irregularly shaped handsets.



Fig.8.1 Illustration for Front, Back and Side of SAM Phantom




Fig. 8.2 Illustration for Handset Vertical and Horizontal Reference Lines

8.2 Positioning for Cheek / Touch

- To position the device with the vertical center line of the body of the device and the horizontal line crossing the center piece in a plane parallel to the sagittal plane of the phantom. While maintaining the device in this plane, align the vertical center line with the reference plane containing the three ear and mouth reference point (M: Mouth, RE: Right Ear and LE: Left Ear) and align the center of the ear piece with the line RE-LE.
- To move the device towards the phantom with the ear piece aligned with the line LE-RE until the phone touched the ear. While maintaining the device in the reference plane and maintaining the phone contact with the ear, move the bottom of the phone until any point on the front side is in contact with the cheek of the phantom or until contact with the ear is lost (see below figure)



Fig. 8.3 Illustration for Cheek Position

8.3 Positioning for Ear / 15° Tilt

- To position the device in the “cheek” position described above.
- While maintaining the device the reference plane described above and pivoting against the ear, moves it outward away from the mouth by an angle of 15 degrees or until contact with the ear is lost (see figure below).



Fig.8.4 Illustration for Tilted Position

8.4 SAR Evaluations near the Mouth/Jaw Regions of the SAM Phantom

Antennas located near the bottom of a phone may require SAR measurements around the mouth and jaw regions of the SAM head phantom. This typically applies to clam-shell style phones that are generally longer in the unfolded normal use positions or to certain older style long rectangular phones.

Under these circumstances, the following procedures apply, adopted from the FCC guidance on SAR handsets document FCC KDB Publication 648474 D04v01r03. The SAR required in these regions of SAM should be measured using a flat phantom. The phone should be positioned with a separation distance of 4 mm between the ear reference point (ERP) and the outer surface of the flat phantom shell. While maintaining this distance at the ERP location, the low (bottom) edge of the phone should be lowered from the phantom to establish the same separation distance between the peak SAR locations identified by the truncated partial SAR distribution measured with the SAM phantom. The distance from the peak SAR location to the phone is determined by the straight line passing perpendicularly through the phantom surface. When it is not feasible to maintain 4 mm separation at the ERP while also establishing the required separation at the peak SAR location, the top edge of the phone will be allowed to touch the phantom with a separation < 4 mm at the ERP. The phone should not be tilted to the left or right while placed in this inclined position to the flat phantom.

8.5 Body Worn Accessory Configurations

- To position the device parallel to the phantom surface with either keypad up or down.
- To adjust the device parallel to the flat phantom.
- To adjust the distance between the device surface and the flat phantom to 10 mm or holster surface and the flat phantom to 0 mm.




Fig.8.5 Illustration for Body Worn Position

9 Measurement Procedures

The measurement procedures are as bellows:

<Conducted power measurement>

- For WWAN power measurement, use base station simulator to configure EUT WWAN transition in conducted connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- Read the WWAN RF power level from the base station simulator.
- For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power in each supported wireless interface and frequency band.
- Connect EUT RF port through RF cable to the power meter or spectrum analyzer, and measure WLAN/BT output power.

<Conducted power measurement>

- Use base station simulator to configure EUT WWAN transmission in radiated connection, and engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power, in the highest power channel.
- Place the EUT in positions as Appendix B demonstrates.
- Set scan area, grid size and other setting on the DASY software.
- Measure SAR results for the highest power channel on each testing position.
- Find out the largest SAR result on these testing positions of each band.
- Measure SAR results for other channels in worst SAR testing position if the Reported SAR or highest power channel is larger than 0.8 W/kg.

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- Power reference measurement
- Area scan
- Zoom scan
- Power drift measurement

9.1 Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value.

The base for the evaluation is a “cube” measurement. The measured volume must include the 1g and 10 g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.

The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- Extraction of the measured data (grid and values) from the Zoom Scan.
- Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters).
- Generation of a high-resolution mesh within the measured volume.
- Interpolation of all measured values from the measurement grid to the high-resolution grid
- Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface
- Calculation of the averaged SAR within masses of 1g and 10g.



9.2 Power Reference Measurement

The Power Reference Measurement and Power Drift Measurement are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to phantom surface. This distance cannot be smaller than the distance of sensor calibration points to probe tip as defined in the probe properties.

9.3 Area Scan Procedures

Area scans are defined prior to the measurement process being executed with a userdefined variable spacing between each measurement point (integral) allowing lowuncertainty measurements to be conducted. Scans defined for FCC applications utilize a 10mm^2 step integral, with 1mm interpolation used to locate the peak SAR area used for zoom scan assessments.

When an Area Scan has measured all reachable points, it computes the field maxima found in the scanned area, within a range of the global maximum. The range (in dB) is specified in the standards for compliance testing. For example, a 2 dB range is required in IEEE1528-2003, EN 50361 and IEC 62209 standards, whereby 3 dB is a requirement when compliance is assessed in accordance with the ARIB standard (Japan).

9.4 Zoom Scan Procedures

Zoom Scans are used to assess the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. A density of 1000 kg/m^3 is used to represent the head and body tissue density and not the phantom liquid density, in order to be consistent with the definition of the liquid dielectric properties, i.e. the side length of the 1g cube is 10mm, with the side length of the 10 g cube 21,5mm. The zoom scan integer steps can be user defined so as to reduce uncertainty, but normal practice for typical test applications utilize a physical step of $5\times 5\times 7$ (8mmx8mmx5mm) providing a volume of 32mm in the X & Y axis, and 30mm in the Z axis.

9.5 SAR Averaged Methods

In DASY, the interpolation and extrapolation are both based on the modified Quadratic Sheppard's method. The interpolation scheme combines a least-square fitted function method and a weighted average method which are the two basic types of computational interpolation and approximation.

Extrapolation routines are used to obtain SAR values between the lowest measurement points and the inner phantom surface. The extrapolation distance is determined by the surface detection distance and the probe sensor offset. The uncertainty increases with the extrapolation distance. To keep the uncertainty within 1% for the 1g and 10g cubes, the extrapolation distance should not be larger than 5 mm.

9.6 Power Drift Monitoring

All SAR testing is under the EUT install full charged battery and transmit maximum output power. In DASY measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of EUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drifts more than 5%, the SAR will be retested.



10 Conducted RF Output Power

10.1 GSM Conducted Power

| GSM850 | Burst Average Power (dBm) | | | Tune-up Limit (dBm) | Frame-Average Power (dBm) | | | Tune-up Limit (dBm) |
|-----------------|---------------------------|-------|--------------|---------------------------|---------------------------|-------|-------|---------------------------|
| TX Channel | 128 | 189 | 251 | | 128 | 189 | 251 | |
| Frequency (MHz) | 824.2 | 836.4 | 848.8 | | 824.2 | 836.4 | 848.8 | |
| GSM | 32.73 | 32.88 | 32.97 | 33.00 | 23.73 | 23.88 | 23.97 | 24.00 |
| GPRS 1Tx slots | 32.72 | 32.87 | 32.96 | 33.00 | 23.72 | 23.87 | 23.96 | 24.00 |
| GPRS 2Tx slots | 29.94 | 30.18 | 30.42 | 30.00 | 23.94 | 24.18 | 24.42 | 24.00 |
| GPRS 3Tx slots | 28.03 | 28.28 | 28.43 | 28.50 | 23.77 | 24.02 | 24.17 | 24.24 |
| GPRS 4Tx slots | 25.90 | 26.24 | 26.58 | 27.00 | 22.90 | 23.24 | 23.58 | 24.00 |

| GSM1900 | Burst Average Power (dBm) | | | Tune-up Limit (dBm) | Frame-Average Power (dBm) | | | Tune-up Limit (dBm) |
|-----------------|---------------------------|--------------|--------|---------------------------|---------------------------|-------|--------|---------------------------|
| TX Channel | 512 | 661 | 810 | | 512 | 661 | 810 | |
| Frequency (MHz) | 1850.2 | 1880 | 1909.8 | | 1850.2 | 1880 | 1909.8 | |
| GSM | 29.37 | 29.51 | 29.44 | 30.00 | 20.37 | 20.51 | 20.44 | 21.00 |
| GPRS 1Tx slots | 29.34 | 29.52 | 29.45 | 30.00 | 20.34 | 20.52 | 20.45 | 21.00 |
| GPRS 2Tx slots | 27.20 | 27.38 | 27.31 | 27.50 | 21.20 | 21.38 | 21.31 | 21.50 |
| GPRS 3Tx slots | 25.31 | 25.51 | 25.49 | 26.00 | 21.05 | 21.25 | 21.23 | 21.74 |
| GPRS 4Tx slots | 23.27 | 23.48 | 23.43 | 23.50 | 20.27 | 20.48 | 20.43 | 20.50 |

Timeslot consignations:

Remark:

- The frame-averaged power is linearly reported the maximum burst averaged power over 8 time slots. The calculated method are shown as below:
The duty cycle "x" of different time slots as below:
1 TX slot is 1/8, 2 TX slots is 2/8, 3 TX slots is 3/8 and 4 TX slots is 4/8
Based on the calculation formula:
Frame-averaged power = Burst averaged power + 10 log (x)
So,
Frame-averaged power (1 TX slot) = Burst averaged power (1 TX slot)– 9.03
Frame-averaged power (2 TX slots) = Burst averaged power (2 TX slots)– 6.02
Frame-averaged power (3 TX slots) = Burst averaged power (3 TX slots)– 4.26
Frame-averaged power (4 TX slots) = Burst averaged power (4 TX slots) – 3.01
- CS1 coding scheme was used in GPRS conducted power measurements and SAR testing, MCS5 coding scheme was used in EGPRS conducted power measurements and SAR testing (if necessary).

| No. of Slots: | Slot 1 | Slot 2 | Slot 3 | Slot 4 |
|--------------------|----------|----------|----------|----------|
| Slot Consignation: | 1Up4Down | 2Up3Down | 3Up2Down | 4Up1Down |
| Duty Cycle: | 1:8.3 | 1:4.15 | 1:2.77 | 1:2.08 |
| Correct Factor: | -9.03dB | -6.02dB | -4.26dB | -3.01dB |

10.2 WCDMA Conducted Power

The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification.

A summary of these settings are illustrated below:

HSDPA Setup Configuration:

- a. The EUT was connected to Base Station Rohde & Schwarz CMW500 referred to the SetupConfiguration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting:
 - i. Set Gain Factors (β_c and β_d) and parameters were set according to each
 - ii. Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - iii. Set RMC 12.2kbps + HSDPA mode.
 - iv. Set Cell Power = -86 dBm
 - v. Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - vi. Select HSDPA Uplink Parameters
 - vii. Set Delta ACK, Delta NACK and Delta CQI = 8
 - viii. Set Ack-Nack Repetition Factor to 3
 - ix. Set CQI Feedback Cycle (k) to 4 ms
 - x. Set CQI Repetition Factor to 2
 - xi. Power Ctrl Mode = All Up bits
- d. The transmitted maximum output power was recorded.

Table 1

| Sub-test | β_c | β_d | β_d (SF) | β_c/β_d | $\beta_{hs}^{(1)}$ | CM (dB) ⁽²⁾ |
|--|----------------------|----------------------|-------------------|----------------------|--------------------|------------------------|
| 1 | 2/15 | 15/15 | 64 | 2/15 | 4/15 | 0.0 |
| 2 | 12/15 ⁽³⁾ | 15/15 ⁽³⁾ | 64 | 12/15 ⁽³⁾ | 24/15 | 1.0 |
| 3 | 15/15 | 8/15 | 64 | 15/8 | 30/15 | 1.5 |
| 4 | 15/15 | 4/15 | 64 | 15/4 | 30/15 | 1.5 |
| Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$ Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. Note 3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$. | | | | | | |

HSDPA Sub-test setup configuration

HSUPA Setup Configuration:

- a. The EUT was connected to Base Station Rohde & Schwarz CMW500 referred to the SetupConfiguration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting * :
 - i. Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - ii. Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121
 - iii. Set Cell Power = -86 dBm
 - iv. Set Channel Type = 12.2k + HSPA
 - v. Set UE Target Power
 - vi. Power Ctrl Mode= Alternating bits
 - vii. Set and observe the E-TFCI
 - viii. Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtest's E-TFCI
- d. The transmitted maximum output power was recorded.

Table 2

| Sub-test | β_c | β_d | β_d (SF) | β_c/β_d | $\beta_{hs}^{(1)}$ | β_{ec} | β_{ed} | β_{ed} (SF) | β_{ed} (codes) | CM ⁽²⁾ (dB) | MPR (dB) | AG ⁽⁴⁾ Index | E-TFCI |
|----------|----------------------|----------------------|----------------|----------------------|--------------------|--------------|--|-------------------|----------------------|------------------------|----------|-------------------------|--------|
| 1 | 11/15 ⁽³⁾ | 15/15 ⁽³⁾ | 64 | 11/15 ⁽³⁾ | 22/15 | 209/225 | 1039/225 | 4 | 1 | 1.0 | 0.0 | 20 | 75 |
| 2 | 6/15 | 15/15 | 64 | 6/15 | 12/15 | 12/15 | 94/75 | 4 | 1 | 3.0 | 2.0 | 12 | 67 |
| 3 | 15/15 | 9/15 | 64 | 15/9 | 30/15 | 30/15 | $\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$ | 4 | 2 | 2.0 | 1.0 | 15 | 92 |
| 4 | 2/15 | 15/15 | 64 | 2/15 | 4/15 | 2/15 | 56/75 | 4 | 1 | 3.0 | 2.0 | 17 | 71 |
| 5 | 15/15 ⁽⁴⁾ | 15/15 ⁽⁴⁾ | 64 | 15/15 ⁽⁴⁾ | 30/15 | 24/15 | 134/15 | 4 | 1 | 1.0 | 0.0 | 21 | 81 |

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Table 5.1g.

Note 6: β_{ed} cannot be set directly; it is set by Absolute Grant Value.

HSUPA Sub-test setup configuration



| Band | | WCDMA II | | | Tune-up Limit (dBm) |
|-----------------|-----------------|----------|-------|--------------|---------------------------|
| TX Channel | | 9262 | 9400 | 9538 | |
| Rx Channel | | 9662 | 9800 | 9938 | |
| Frequency (MHz) | | 1852.4 | 1880 | 1907.6 | |
| 3GPP Rel 99 | AMR 12.2Kbps | 21.21 | 21.01 | 21.26 | 21.50 |
| 3GPP Rel 99 | RMC 12.2Kbps | 21.23 | 21.10 | 21.29 | 21.50 |
| 3GPP Rel 6 | HSDPA Subtest-1 | 21.25 | 21.34 | 21.24 | 21.50 |
| 3GPP Rel 6 | HSDPA Subtest-2 | 21.13 | 21.25 | 21.12 | 21.50 |
| 3GPP Rel 6 | HSDPA Subtest-3 | 20.68 | 20.85 | 20.65 | 21.00 |
| 3GPP Rel 6 | HSDPA Subtest-4 | 20.75 | 20.73 | 20.54 | 21.00 |
| 3GPP Rel 6 | HSUPA Subtest-1 | 21.26 | 21.11 | 21.25 | 21.50 |
| 3GPP Rel 6 | HSUPA Subtest-2 | 19.25 | 19.34 | 19.21 | 19.50 |
| 3GPP Rel 6 | HSUPA Subtest-3 | 20.20 | 20.31 | 20.50 | 21.00 |
| 3GPP Rel 6 | HSUPA Subtest-4 | 19.17 | 19.13 | 19.15 | 19.50 |
| 3GPP Rel 6 | HSUPA Subtest-5 | 21.16 | 21.14 | 21.16 | 21.50 |

| Band | | WCDMA V | | | Tune-up Limit (dBm) |
|-----------------|-----------------|--------------|-------|-------|---------------------------|
| TX Channel | | 4132 | 4182 | 4233 | |
| Rx Channel | | 4357 | 4407 | 4458 | |
| Frequency (MHz) | | 826.4 | 836.4 | 846.6 | |
| 3GPP Rel 99 | AMR 12.2Kbps | 22.03 | 21.52 | 21.91 | 22.50 |
| 3GPP Rel 99 | RMC 12.2Kbps | 22.06 | 21.68 | 22.05 | 22.50 |
| 3GPP Rel 6 | HSDPA Subtest-1 | 21.53 | 21.42 | 21.27 | 22.00 |
| 3GPP Rel 6 | HSDPA Subtest-2 | 21.46 | 21.63 | 21.62 | 22.00 |
| 3GPP Rel 6 | HSDPA Subtest-3 | 21.08 | 21.07 | 21.09 | 21.50 |
| 3GPP Rel 6 | HSDPA Subtest-4 | 21.11 | 21.21 | 21.17 | 21.50 |
| 3GPP Rel 6 | HSUPA Subtest-1 | 21.68 | 21.69 | 21.78 | 22.00 |
| 3GPP Rel 6 | HSUPA Subtest-2 | 19.85 | 19.87 | 19.89 | 20.00 |
| 3GPP Rel 6 | HSUPA Subtest-3 | 20.57 | 20.84 | 20.75 | 21.00 |
| 3GPP Rel 6 | HSUPA Subtest-4 | 19.94 | 19.96 | 19.97 | 20.00 |
| 3GPP Rel 6 | HSUPA Subtest-5 | 21.85 | 21.76 | 21.84 | 22.00 |

10.3 Bluetooth Conducted Power

| Mode | Channel | Frequency (MHz) | Peak power (dBm) | | |
|---------------------|---------|-----------------|------------------|-------|--------------|
| | | | 1Mbps | 2Mbps | 3Mbps |
| BR / EDR | CH 00 | 2402 | 0.390 | 0.385 | 1.660 |
| | CH 39 | 2441 | 0.981 | 0.913 | 2.174 |
| | CH 78 | 2480 | 0.821 | 0.834 | 2.073 |
| Tune-up Limit (dBm) | | | 1.000 | 1.000 | 2.500 |

Note:

- Per KDB 447498 D01v06, the 1-g SAR test exclusion thresholds for 100 MHz to 6 GHz at *test separation distances* ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$ for 1-g SAR, where

- $f(\text{GHz})$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation
- The result is rounded to one decimal place for comparison

| Channel | Frequency (GHz) | Max. tune-up Power (dBm) | Max. Power (mW) | Test distance (mm) | Result | exclusion thresholds for 1-g SAR |
|---------|-----------------|--------------------------|-----------------|--------------------|--------|----------------------------------|
| CH 39 | 2.441 | 2.5 | 1.78 | 5 | 0.56 | 3.0 |

- The max. tune-up power was provided by manufacturer, base on the result of note 1, RF exposure evaluation is not required.
- The output power of all data rate were pre-scan, just the worst case of all mode were shown in report.
- When the minimum *test separation distance* is < 5 mm, a distance of 5 mm according is applied to determine SAR test exclusion.



11 Exposure Positions Consideration

11.1 EUT Antenna Location

Note: EUT Antenna Location please see Annex B

11.2 Test Positions Consideration

| Distance of Antennas to EUT edge/surface Test distance: 10mm | | | | | | |
|---|-------|-------|----------|-------------|------------|-----------|
| Antennas | Back | Front | Top Side | Bottom Side | Right Side | Left Side |
| GSM/WCDMA | <25mm | <25mm | 88mm | <25mm | <25mm | <25mm |


| Test Positions Test distance: 10mm | | | | | | |
|---------------------------------------|------|-------|----------|-------------|------------|-----------|
| Antennas | Back | Front | Top Side | Bottom Side | Right Side | Left Side |
| GSM/WCDMA | Yes | Yes | No | No | No | No |

Note:

1. Head/Body-worn mode SAR assessments are required.
2. Per KDB 447498 D01v06, for handsets the test separation distance is determined by the smallest distance between the outer surface of the device and the user, which is 0 mm for head SAR and 10 mm for body-worn SAR.

12 Block diagram of the tests to be performed

12.1 Head



IEC 228/05

12.2 Body




Figure 12b – General procedure



13 Test Results List

Test Guidance:

1. The reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - d. For Bluetooth: Reported SAR(W/kg) = Measured SAR(W/kg) * Duty Cycle scaling factor * Tune-up scaling factor
2. The SAR testing shall be performed at the middle frequency channels of each operating mode as the primary test channel. If the SAR measured at the middle channel for each test configuration is at least 3.0dB lower than the SAR limit, testing at the high and low channels is optional. And the High and Low frequency channels must be tested at a worst exposure position, and if the primary test channel reported SAR is ≥ 0.8 W/kg at the test exposure position, the High and Low frequency channels are also must be required.



14 SAR Test Results Summary

14.1 Standalone Head SAR

➤ GSM Head SAR

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|---------------|---------------|-----|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| | GSM850/Voice | Right Cheek | 251 | 32.97 | 33.00 | 1.007 | 0.525 | 0.529 |
| | GSM850/Voice | Right Tilted | 251 | 32.97 | 33.00 | 1.007 | 0.275 | 0.277 |
| 1# | GSM850/Voice | Left Cheek | 251 | 32.97 | 33.00 | 1.007 | 0.557 | 0.561 |
| | GSM850/Voice | Left Tilted | 251 | 32.97 | 33.00 | 1.007 | 0.266 | 0.268 |
| | GSM1900/Voice | Right Cheek | 661 | 29.51 | 30.00 | 1.119 | 0.467 | 0.523 |
| | GSM1900/Voice | Right Tilted | 661 | 29.51 | 30.00 | 1.119 | 0.250 | 0.280 |
| 2# | GSM1900/Voice | Left Cheek | 661 | 29.51 | 30.00 | 1.119 | 0.712 | 0.797 |
| | GSM1900/Voice | Left Tilted | 661 | 29.51 | 30.00 | 1.119 | 0.275 | 0.308 |

➤ WCDMA Head SAR

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|--------------------|-------------------|-------------|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| 3# | Band V/RMC | Right Cheek | 4132 | 22.06 | 22.50 | 1.107 | 0.090 | 0.099 |
| | Band V/RMC | Right Tilted | 4132 | 22.06 | 22.50 | 1.107 | 0.021 | 0.024 |
| | Band V/RMC | Left Cheek | 4132 | 22.06 | 22.50 | 1.107 | 0.078 | 0.086 |
| | Band V/RMC | Left Tilted | 4132 | 22.06 | 22.50 | 1.107 | 0.021 | 0.024 |
| | Band II/RMC | Right Cheek | 9538 | 21.29 | 21.50 | 1.050 | 0.552 | 0.579 |
| | Band II/RMC | Right Tilted | 9538 | 21.29 | 21.50 | 1.050 | 0.361 | 0.379 |
| | Band II/RMC | Left Cheek | 9538 | 21.29 | 21.50 | 1.050 | 1.030 | 1.081 |
| | Band II/RMC | Left Tilted | 9538 | 21.29 | 21.50 | 1.050 | 0.403 | 0.423 |
| | Band II/RMC | Left Cheek | 9262 | 21.23 | 21.50 | 1.064 | 1.040 | 1.107 |
| 4# | Band II/RMC | Left Cheek | 9400 | 21.10 | 21.50 | 1.096 | 1.080 | 1.184 |
| | Band II/RMC | Left Cheek | 9400 | 21.10 | 21.50 | 1.096 | 1.076 | 1.180 |

Note:

1. Per KDB 447498 D01v06, for each exposure position, if the highest output channel Reported SAR $\leq 0.8\text{W/kg}$, other channels SAR testing is not necessary.
2. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is $\geq 0.8\text{W/kg}$.
3. Highlight part of test data means repeated test.

14.2 Standalone Body SAR

➤ GSM Body SAR

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|---------------------------|---------------|------------|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| | GPRS850/3TX Slots | Front | 251 | 28.43 | 28.50 | 1.016 | 0.514 | 0.522 |
| | GPRS850/3TX Slots | Back | 251 | 28.43 | 28.50 | 1.016 | 1.030 | 1.047 |
| | GPRS850/3TX Slots | Back | 128 | 28.03 | 28.50 | 1.114 | 0.893 | 0.995 |
| 5# | GPRS850/3TX Slots | Back | 189 | 28.28 | 28.50 | 1.052 | 1.180 | 1.241 |
| | GPRS850/3TX Slots | Back | 189 | 28.28 | 28.50 | 1.052 | 1.178 | 1.239 |
| | GPRS1900/3TX Slots | Front | 661 | 25.51 | 26.00 | 1.119 | 0.585 | 0.655 |
| 6# | GPRS1900/3TX Slots | Back | 661 | 25.51 | 26.00 | 1.119 | 0.995 | 1.114 |
| | GPRS1900/3TX Slots | Back | 661 | 25.51 | 26.00 | 1.119 | 0.983 | 1.100 |
| | GPRS1900/3TX Slots | Back | 512 | 25.31 | 25.50 | 1.045 | 0.958 | 1.001 |
| | GPRS1900/3TX Slots | Back | 810 | 25.49 | 25.50 | 1.002 | 0.979 | 0.981 |

➤ GSM Body SAR With Headset

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|--------------|---------------|------------|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| 7# | GSM850/Voice | Back | 189 | 28.28 | 28.50 | 1.052 | 1.156 | 1.216 |
| | GSM850/Voice | Back | 189 | 28.28 | 28.50 | 1.052 | 1.151 | 1.211 |
| | GSM850/Voice | Back | 128 | 28.03 | 28.50 | 1.114 | 0.823 | 0.917 |
| | GSM850/Voice | Back | 251 | 28.43 | 28.50 | 1.016 | 0.957 | 0.972 |

➤ WCDMA Body SAR

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|--------------------|---------------|-------------|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| | Band V/RMC | Front | 4132 | 22.06 | 22.50 | 1.107 | 0.563 | 0.623 |
| 8# | Band V/RMC | Back | 4132 | 22.06 | 22.50 | 1.107 | 0.609 | 0.674 |
| | Band II/RMC | Front | 9538 | 21.29 | 21.50 | 1.050 | 0.431 | 0.452 |
| 9# | Band II/RMC | Back | 9538 | 21.29 | 21.50 | 1.050 | 1.200 | 1.259 |
| | Band II/RMC | Back | 9538 | 21.29 | 21.50 | 1.050 | 1.187 | 1.246 |
| | Band II/RMC | Back | 9262 | 21.23 | 21.50 | 1.064 | 0.957 | 1.018 |
| | Band II/RMC | Back | 9400 | 21.10 | 21.50 | 1.096 | 1.130 | 1.239 |

➤ WCDMA Body SAR With Headset

| Plot No. | Band/Mode | Test Position | CH. | Ave. Power (dBm) | Tune-Up Limit (dBm) | Tune-Up Scaling Factor | Meas. SAR _{1g} (W/kg) | Reported SAR _{1g} (W/kg) |
|----------|--------------------|---------------|-------------|------------------|---------------------|------------------------|--------------------------------|-----------------------------------|
| 10# | Band II/RMC | Back | 9538 | 21.29 | 21.50 | 1.050 | 1.041 | 1.093 |
| | Band II/RMC | Back | 9538 | 21.29 | 21.50 | 1.050 | 1.027 | 1.078 |
| | Band II/RMC | Back | 9262 | 21.23 | 21.50 | 1.064 | 0.865 | 0.920 |
| | Band II/RMC | Back | 9400 | 21.10 | 21.50 | 1.096 | 0.992 | 1.087 |

Note:

- Per KDB 447498 D01v06, for each exposure position, if the highest output channel Reported SAR $\leq 0.8\text{W/kg}$, other channels SAR testing is not necessary.
- Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. If HSDPA output power is $< 0.25\text{dB}$ higher than RMC 12.2kbps, or Reported SAR with RMC 12.2kbps setting is $\leq 1.2\text{W/kg}$, HSDPA SAR evaluation can be excluded.
- Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is $\geq 0.8\text{W/kg}$.

7. Per KDB 648474 D04v01r03, when the Reported SAR for a body-worn accessory measured without a headset connected to the handset is $> 1.2 \text{ W/kg}$, SAR testing with a headset connected to the handset is required.
8. According to KDB 865664 D02v01r02, SAR plot is required for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination.
9. Highlight part of test data means repeated test.

14.3 Repeated SAR measurement

| Band/ Mode | Test Position | CH. | Measured SAR (W/kg) | | | | |
|--------------------|-------------------|------|---------------------|--------------------------|-------|--------------------------|-------|
| | | | Original | 1 st Repeated | | 2 nd Repeated | |
| | | | | Value | Ratio | Value | Ratio |
| Band II/RMC | Left Cheek | 9400 | 1.080 | 1.073 | 1.01 | / | / |
| GPRS850/3TX Slots | Back | 189 | 1.180 | 1.178 | 1.01 | / | / |
| GPRS1900/3TX Slots | Back | 661 | 0.995 | 0.983 | 1.01 | / | / |
| Band II/RMC | Back | 9538 | 1.200 | 1.187 | 1.01 | / | / |
| GSM850/Voice | Back With Headset | 189 | 1.216 | 1.211 | 1.01 | / | / |
| Band II/RMC | Back With Headset | 9538 | 1.093 | 1.078 | 1.01 | / | / |

Note:

1. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is $\geq 0.8 \text{ W/kg}$
2. Per KDB 865664 D01v01r04, if the ratio of *original* and *repeated* is ≤ 1.2 and the measured SAR $< 1.45 \text{ W/kg}$, only one repeated measurement is required.

14.4 Multi-Band Simultaneous Transmission Considerations

➤ Simultaneous Transmission Capabilities

According to FCC KDB Publication 447498 D01v06, transmitters are considered to be transmitting simultaneously when there is overlapping transmission, with the exception of transmissions during network hand-offs with maximum hand-off duration less than 30 seconds. Possible transmission paths for the EUT are shown in below Figure and are color-coded to indicate communication modes which share the same path. Modes which share the same transmission path cannot transmit simultaneously with one another.

Fig.14.1 Simultaneous Transmission Paths

➤ Simultaneous Transmission Procedures

This device contains transmitters that may operate simultaneously. Therefore simultaneous transmission analysis is required. Per FCC KDB 447498 D01v06, simultaneous transmission SAR test exclusion may be applied when the sum of the 1-g SAR for all the simultaneous transmitting antennas in a specific physical test configuration is ≤ 1.6 W/kg. When standalone SAR is not required to be measured, per FCC KDB 447498 D01v06 4.3.2), the following equation must be used to estimate the standalone 1g SAR for simultaneous transmission assessment involving that transmitter.

$$\text{Estimated SAR} = \frac{\sqrt{f(\text{GHz})}}{7.5} \cdot \frac{\text{Max. power of channel, mW}}{\text{Min. Separation Distance, mm}}$$

| Mode | Max. tune-up Power (dBm) | Exposure Position | Head | Body |
|-----------|--------------------------|----------------------|-------|-------|
| | | Test Distance (mm) | 0 | 10 |
| Bluetooth | 2.5 | Estimated SAR (W/kg) | 0.074 | 0.037 |

Note:

- When the minimum *test separation distance* is < 5 mm, a distance of 5 mm according is applied to determine estimated SAR.

➤ Multi-Band simultaneous Transmission Consideration

| Simultaneous Transmission Consideration | Position | Applicable Combination |
|---|----------|------------------------|
| | Head | 2G/3G + Bluetooth |
| | Body | 2G/3G + Bluetooth |

Note:

- GSM/WCDMA shares the same antenna, and cannot transmit simultaneously.
- The Report SAR summation is calculated based on the same configuration and test position.
- Per KDB 447498 D01v06, simultaneous transmission SAR is compliant if,
 - Scalar SAR summation < 1.6W/kg.
 - $\text{SPLSR} = (\text{SAR}_1 + \text{SAR}_2)^{1.5} / (\text{min. separation distance, mm})$, and the peak separation distance is determined from the square root of $[(x_1-x_2)^2 + (y_1-y_2)^2 + (z_1-z_2)^2]$, where (x_1, y_1, z_1) and (x_2, y_2, z_2) are the coordinates of the extrapolated peak SAR locations in the zoom scan. If $\text{SPLSR} \leq 0.04$, simultaneously transmission SAR measurement is not necessary.
 - Simultaneously transmission SAR measurement, and the Reported multi-band SAR < 1.6W/kg



14.5 SAR Simultaneous Transmission Analysis

➤ Head Simultaneous Transmission

| WWAN Band | | Exposure Position | 1 | 2 | 1+2 Summed 1g SAR (W/kg) |
|-----------|------------|-------------------|------------------|----------------------------|--------------------------------|
| | | | WWAN | Bluetooth | |
| | | | 1g SAR (W/kg) | Estimated 1g SAR (W/kg) | |
| GSM | GSM 850 | Right Cheek | 0.529 | 0.074 | 0.603 |
| | | Right Tilt | 0.277 | 0.074 | 0.351 |
| | | Left Cheek | 0.561 | 0.074 | 0.635 |
| | | Left Tilt | 0.268 | 0.074 | 0.342 |
| | GSM 1900 | Right Cheek | 0.523 | 0.074 | 0.597 |
| | | Right Tilt | 0.280 | 0.074 | 0.354 |
| | | Left Cheek | 0.797 | 0.074 | 0.871 |
| | | Left Tilt | 0.308 | 0.074 | 0.382 |
| WCDMA | WCDMA 850 | Right Cheek | 0.099 | 0.074 | 0.173 |
| | | Right Tilt | 0.024 | 0.074 | 0.098 |
| | | Left Cheek | 0.086 | 0.074 | 0.16 |
| | | Left Tilt | 0.024 | 0.074 | 0.098 |
| | WCDMA 1900 | Right Cheek | 0.579 | 0.074 | 0.653 |
| | | Right Tilt | 0.379 | 0.074 | 0.453 |
| | | Left Cheek | 1.184 | 0.074 | 1.258 |
| | | Left Tilt | 0.423 | 0.074 | 0.497 |



➤ **Body worn Simultaneous Transmission**

| WWAN Band | | Exposure Position | 1 | 2 | 1+2 Summed 1g SAR (W/kg) |
|-----------|------------|-------------------|---------------|-------------------------|--------------------------|
| | | | WWAN | Bluetooth | |
| | | | 1g SAR (W/kg) | Estimated 1g SAR (W/kg) | |
| GSM | GSM 850 | Front | 0.522 | 0.037 | 0.559 |
| | | Back | 1.241 | 0.037 | 1.278 |
| | GSM 1900 | Front | 0.655 | 0.037 | 0.692 |
| | | Back | 1.114 | 0.037 | 1.151 |
| WCDMA | WCDMA 850 | Front | 0.623 | 0.037 | 0.66 |
| | | Back | 0.674 | 0.037 | 0.711 |
| | WCDMA 1900 | Front | 0.452 | 0.037 | 0.489 |
| | | Back | 1.259 | 0.037 | 1.296 |

14.6 DUT holder perturbation uncertainty evaluation

1. According to TCB workshop, Oct 2016:

When the highest reported SAR of an antenna is > 1.2 W/kg, holder perturbation verification is required for each antenna, using the highest SAR configuration among all applicable frequency bands.

2. According to IEEE 1528-2013 section E.4.1, When it is unknown if a device holder perturbs the fields of a test device, the SAR uncertainty shall be assessed with a flat phantom (see Clause 5) by comparing the SAR with and without the device holder according to the following tests:

a) With device holder: 1 g or 10 g peak spatial-average SAR is measured with the handset fixed in the holder in a manner similar to the way it was held when tested for the head SAR position. The handset horizontal and vertical centerlines (see Clause 6) are aligned parallel to the bottom of the flat phantom and the device is in direct contact with the phantom. The test shall be performed with the antenna position and device operational configuration corresponding to that where the highest head SAR was previously measured for each frequency band.

b) Without device holder: 1 g or 10 g peak spatial-average SAR is measured with the handset placed on a low-loss foam block or support in the position identical to that tested with the device holder. The relative permittivity and loss tangent of the foam material shall be less than 1.2 and 10–5, respectively.

Test result:

| Plot | Band/ Mode | Test Position | CH. | Freq. (MHz) | Test configuration | Measured SAR (W/kg) Averaged over 1g |
|------|-------------|---------------|------|-------------|-----------------------|---|
| 1 | Band II/RMC | Back | 9538 | 1907.6 | With device holder | 3.29 |
| 2 | Band II/RMC | Back | 9538 | 1907.6 | Without device holder | 3.13 |

Note:

1. The plots of test result please check Appendix D

The following equation is used to computed the SAR tolerance,

$$SAR_{\text{tolerance}}[\%] = 100 \times \left(\frac{SAR_{w/\text{holder}} - SAR_{w/o \text{ holder}}}{SAR_{w/o \text{ holder}}} \right)$$

Therefore, the $SAR_{\text{tolerance}} = 100 \times [(3.29 - 3.13) / 3.13] = 5.11\%$.

15 Measurement Uncertainty

The component of uncertainty may generally be categorized according to the methods used to evaluate them. The evaluation of uncertainty by the statistical analysis of a series of observations is termed a Type A evaluation of uncertainty. The evaluation of uncertainty by means other than the statistical analysis of a series of observation is termed a Type B evaluation of uncertainty. Each component of uncertainty, however evaluated, is represented by an estimated standard deviation, termed standard uncertainty, which is determined by the positive square root of the estimated variance.

A Type A evaluation of standard uncertainty may be based on any valid statistical method for treating data. This includes calculating the standard deviation of the mean of a series of independent observations; using the method of least squares to fit a curve to the data in order to estimate the parameter of the curve and their standard deviations; or carrying out an analysis of variance in order to identify and quantify random effects in certain kinds of measurement.

A Type B evaluation of standard uncertainty is typically based on scientific judgment using all of the relevant information available. These may include previous measurement data, experience, and knowledge of the behavior and properties of relevant materials and instruments, manufacture's specification, data provided in calibration reports and uncertainties assigned to reference data taken from handbooks. Broadly speaking, the uncertainty is either obtained from an outdoor source or obtained from an assumed distribution, such as the normal distribution, rectangular or triangular distributions indicated in below Table.

| Uncertainty Distributions | Normal | Rectangular | Triangular | U-Shape |
|---------------------------|----------|--------------|--------------|--------------|
| Multi-plying Factor | $1/k(b)$ | $1/\sqrt{3}$ | $1/\sqrt{6}$ | $1/\sqrt{2}$ |

Standard Uncertainty for Assumed Distribution

The combined standard uncertainty of the measurement result represents the estimated standard deviation of the result. It is obtained by combining the individual standard uncertainties of both Type A and Type B evaluation using the usual "root-sum-squares" (RSS) methods of combining standard deviations by taking the positive square root of the estimated variances.

Expanded uncertainty is a measure of uncertainty that defines an interval about the measurement result within which the measured value is confidently believed to lie. It is obtained by multiplying the combined standard uncertainty by a coverage factor. Typically, the coverage factor ranges from 2 to 3. Using a coverage factor allows the true value of a measured quantity to be specified with a defined probability within the specified uncertainty range. For purpose of this document, a coverage factor two is used, which corresponds to confidence interval of about 95 %. The DASY uncertainty Budget is shown in the following tables.



| a | b | c | d | e= f(d,k) | f | g | h= c*f/e | i= c*g/e | k |
|---|-------------|--------------|----------------|--------------|------------|-------------|----------------|-----------------|-----|
| Uncertainty Component | Sec. | Tol (+-%) | Prob. Dist. | Div. | Ci (1g) | Ci (10g) | 1g Ui (+-%) | 10g Ui (+-%) | Vi |
| Measurement System | | | | | | | | | |
| Probe calibration | E.2.1 | 5.83 | N | 1 | 1 | 1 | 5.83 | 5.83 | ∞ |
| Axial Isotropy | E.2.2 | 3.5 | R | $\sqrt{3}$ | 1 | 1 | 2.02 | 2.02 | ∞ |
| Hemispherical Isotropy | E.2.2 | 5.9 | R | $\sqrt{3}$ | 1 | 1 | 3.41 | 3.41 | ∞ |
| Boundary effect | E.2.3 | 1.0 | R | $\sqrt{3}$ | 1 | 1 | 0.58 | 0.58 | ∞ |
| Linearity | E.2.4 | 4.7 | R | $\sqrt{3}$ | 1 | 1 | 2.71 | 2.71 | ∞ |
| System detection limits | E.2.5 | 1.0 | R | $\sqrt{3}$ | 1 | 1 | 0.58 | 0.58 | ∞ |
| Readout Electronics | E.2.6 | 0.5 | N | 1 | 1 | 1 | 0.5 | 0.5 | ∞ |
| Reponse Time | E.2.7 | 3.0 | R | $\sqrt{3}$ | 1 | 1 | 3.0 | 3.0 | ∞ |
| Integration Time | E.2.8 | 1.4 | R | $\sqrt{3}$ | 1 | 1 | 0.81 | 0.81 | ∞ |
| RF ambient Conditions | E.6.1 | 3.0 | R | $\sqrt{3}$ | 1 | 1 | 1.73 | 1.73 | ∞ |
| Probe positioner Mechanical Tolerance | E.6.2 | 1.4 | R | $\sqrt{3}$ | 1 | 1 | 0.81 | 0.81 | ∞ |
| Probe positioning with respect to Phantom Shell | E.6.3 | 1.4 | R | $\sqrt{3}$ | 1 | 1 | 0.81 | 0.81 | ∞ |
| Extrapolation, interpolation and integration Algorithms for Max. SAR Evaluation | E.5.2 | 2.3 | R | $\sqrt{3}$ | 1 | 1 | 1.33 | 1.33 | ∞ |
| Test sample Related | | | | | | | | | |
| Test sample positioning | E.4.2. 1 | 2.6 | N | 1 | 1 | 1 | 2.6 | 2.6 | N-1 |
| Device Holder Uncertainty | E.4.1. 1 | 3.0 | N | 1 | 1 | 1 | 5.11 | 5.11 | ∞ |
| Output power Power drift - SAR drift measurement | 6.6.2 | 5.0 | R | $\sqrt{3}$ | 1 | 1 | 2.89 | 2.89 | ∞ |
| Phantom and Tissue Parameters | | | | | | | | | |
| Phantom Uncertainty (Shape and thickness tolerances) | E.3.1 | 4.0 | R | $\sqrt{3}$ | 1 | 1 | 2.31 | 2.31 | ∞ |
| Liquid conductivity - deviation from target value | E.3.2 | 2.0 | R | $\sqrt{3}$ | 0.6 4 | 0.43 | 1.69 | 1.13 | ∞ |
| Liquid conductivity - measurement uncertainty | E.3.3 | 2.5 | N | 1 | 0.6 4 | 0.43 | 3.20 | 2.15 | M |
| Liquid permittivity - deviation from target value | E.3.2 | 2.5 | R | $\sqrt{3}$ | 0.6 | 0.49 | 1.28 | 1.04 | ∞ |
| Liquid permittivity - measurement uncertainty | E.3.3 | 5.0 | N | 1 | 0.6 | 0.49 | 6.00 | 4.90 | M |
| Liquid conductivity – temperature uncertainty | E.3.4 | | R | $\sqrt{3}$ | 0.7 8 | 0.41 | | | ∞ |
| Liquid permittivity – temperature uncertainty | E.3.4 | | R | $\sqrt{3}$ | 0.2 3 | 0.26 | | | ∞ |
| Combined Standard Uncertainty | | | RSS | | | | 11.55 | 12.07 | |



| | | | | | | | | | |
|---|--|--|-----|--|--|--|--------|--------|--|
| Expanded Uncertainty (95% Confidence interval) | | | K=2 | | | | ±23.20 | ±24.17 | |
|---|--|--|-----|--|--|--|--------|--------|--|

16 Measurement Conclusion

The SAR evaluation indicates that the EUT complies with the RF radiation exposure limits of the India, with respect to all parameters subject to this test. These measurements were taken to simulate the RF effects of RF exposure under worst-case conditions. Precise laboratory measures were taken to assure repeatability of the tests. The results and statements relate only to the item(s) tested. Please note that the absorption and distribution of electromagnetic energy in the body are very complex phenomena that depend on the mass, shape, and size of the body, the orientation of the body with respect to the field vectors, and the electrical properties of both the body and the environment. Other variables that may play a substantial role in possible biological effects are those that characterize the environment (e.g. ambient temperature, air velocity, relative humidity, and body insulation) and those that characterize the individual (e.g. age, gender, activity level, debilitation, or disease). Because various factors may interact with one another to vary the specific biological outcome of an exposure to electromagnetic fields, any protection guide should consider maximal amplification of biological effects as a result of field-body interactions, environmental conditions, and physiological variables.