Bluetooth Wireless Keyboard

Model: K331

User Manual

FCC ID: ZH4K331

User' Guide

Bluetooth Wireless Keyboard
### Made for iPad /iMac /iPhone

CAUTION: To use this product properly, please read the user's guide before installation

---

Schematic diagram

Protective Case
iPad 2
Keyboard
Keyboard Stand
Angle Adjuster Assembly (slidable)

Using

Horizontal display

Vertical lay

Using drawer structure sliding forward and backward, also can moveable the keyboard to use separateness.

## Install iPad 2

(1)

(2)

---

1) Insert iPad 2
2) Push the iPad 2 into the protective case

(1) (2) (3)

1) Put the iPad 2 screen side on the keyboard stand.
2) Install the protective case to the keyboard base in correct direction
3) iPad 2 and keyboard stand will in one combined, easy to take.

Angle adjust

45°   60°   75°

Push forward the angle adjust assembly which on the back of the iPad 2 to adjust the angle from 45 degree to 60 degree or 75 degree.

RETURN BUTTON

Press the angle adjust assembly and push backward the iPad 2 to adjust the angle from 75 degree to 60 degree or 45 degree.

45°   45°

✓   ✗

When the angle is in 45 degree, please install the keyboard to the stand when using.

Keyboard

DC.5V. Input

Welcome

Congratulation on selecting the Bluetooth Wireless Keyboard as your input device. The super slim keyboard is very quiet and crafted with the soft touch design .In the present state of artistic technology, this is the ideal product for your iPad/iMac/iPhone and other Bluetooth enabled device.

Overview

☐ Main screen/Esc		◀◀ PrevTrack		☐ Select All
☼ Brightness -		▶◀ Play/pause		☐ Copy
☼ Brightness +		▶▶ NextTrack		☐ Paste
☐ Virtual Keyboard		◀ Mute		☐ Cut
☐ Search		◀ Volume -		☐ Lock screen
☐ Preview photo		◀) Volume +		☐ Change Language

● Change Language-Press Fn-Language to select the language previously activated on your iPad.
● The PAGE UP key, PAGE DOWN key, HOME key,and END key work when pressed along with the FN key.

Prompted

Blue LED Blinking: Pairing
Red LED on: Charging
Green LED on: Battery is fully charged
Green LED blinking: Low in Battery
Yellow LED on: Caps lock

Installation Guide

Step 1. Charging the battery
1. For the first time user, Please charge the keyboard for at least 6 hours before using it. Thereafter, charge for at least 2 hours when the battery runs low.
2. The LED blinks green when battery is low. The LED light is green when it is fully charged.
3.Connection Charging Cable

ON ☐ OFF ✗
ON ☐ OFF ✓

How to Charge the battery:

To charge the keyboard, Connect the 5V.DC input form the keyboard into the computer USB port with the connector cable provided. The Keyboard can function while charging.

Step 2.Pairing your Bluetooth Keyboard with your iPad/iMac/iPhone or other Bluetooth enabled device.
The following sample shows how to pair the Bluetooth keyboard with your iPad.

Before you can use your keyboard, you have to pair it with your iPad. Pairing allows your keyboard to communicate wirelessly with your iPad.You only have to perform the pairing once.

1. Turn on the keyboard and press the CONNECT key on the keyboard. The LED light will blink blue. Then on the screen of the iPad, you search for Settings-->General-->Bluetooth.

2.Enable the Bluetooth function, and it will search for the Bluetooth keyboard automatically. When the Bluetooth keyboard is discovered, select the "Bluetooth keyboard" from the ipad screen, a passkey will appear on the screen of the iPad. Type in the passkey provided and press the ENTER key on the keyboard. Your Bluetooth keyboard will then be successfully paired with your iPad.

Picture Frame
General
Mail, Contacts, Calendars

(1) (2)

Network
Bluetooth   Off
Location Services   ON

(3)

Bluetooth
Bluetooth   OFF

(4)

Bluetooth   ON
Devices
Bluetooth Keyboard   Not Connected
Now Discoverable

(5)

"Bluetooth Keyboard" would like to pair with your iPad.
Enter the passkey "722867" on "Bluetooth Keyboard", followed by the return or enter key.
Cancel

(6)

Bluetooth   ON
Devices
Bluetooth Keyboard   Connected
Now Discoverable

(6)

Troubleshooting

If the keyboard is not working with the iPad (or other Bluetooth devices) make sure:

1) The Bluetooth function on the iPad (or other Bluetooth devices) is enabled.
2) The Bluetooth keyboard is within 33feet of the iPad.
3) The passkey is entered correctly.
4) Restart the computer (or other Bluetooth devices).
5) Battery which built-in keyboard in low power station, please recharge it.
6) If you by accidently press the CONNECT key when the two devices have been connected, it will cause the malfunction of the keyboard. The LED light of the CONNECT key will keep blinking. To solve this problem, you just simply restart the keyboard by turning it on again. A pairing will not be required if it has been previously done.

Product Specifications

1)Bluetooth Specification: Version 2.0 Class 2
2)Range of Frequency: 2.4GHz Spectrum
3)Operating Voltage: 3.7Vdc (powered by Li-ion)
4)Operation current: <5mA
5)Standby Current: 1.2mA
6)Sleep current: <0.7mA
7)Transmit Range: up to 10 meters

This device complies with Part 15 of the FCC Rules: Operation is subject to the following two conditions:
1. This device may not cause harmful interference and
2. This device must accept any interference that is received, including any interference that may cause undesired operation.

FCC ID: ZH4K331

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

 -- Reorient or relocate the receiving antenna.
 -- Increase the separation between the equipment and receiver.
 -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 -- Consult the dealer or an experienced radio/TV technician for help.

IMPORTANT REGULATORY INFORMATION

This device complies with Part 15 of the FCC Rules: Operation is subject to the

following two conditions:
1. This device may not cause harmful interference
and
2. This device must accept any interference that is received, including
     any interference that may cause undesired operation.

 Caution:
Changes or modifications to this unit not expressly approved by the party responsible for
 compliance could void the user's authority to operate the equipment.