

Corrigé Type

$$\begin{aligned}
 1/ \quad (1A8D,03)_{16} &= D \times 16^0 + 8 \times 16^1 + A \times 16^2 + 1 \times 16^3 + 0 \times 16^{-1} + 3 \times 16^{-2} \\
 &= 13 \times 1 + 128 + 10 \times 256 + 4096 + 0,01 \\
 &= (6797,01)_{10}
 \end{aligned}$$

$$\begin{aligned}
 (1A8D,03)_{16} &= \\
 &= (0001 \ 1010 \ 1000 \ 1101 . 0000 \ 0011)_2
 \end{aligned}$$

2/

$$\begin{array}{r}
 (623) \\
 \times (13.3)_8 \\
 \hline
 2271 \\
 2271. \\
 623. \\
 \hline
 (10750,1)_8
 \end{array}$$

3/

$$\begin{array}{r}
 27A8 \\
 - 24 \\
 \hline
 03A \\
 - 36 \\
 \hline
 048 \\
 - 48 \\
 \hline
 00
 \end{array}$$

$$\begin{array}{r}
 12 \\
 \hline
 234
 \end{array}$$

Table de multiplication de 12 en base 12

$$\begin{aligned}
 12 \times 1 &= 12 \\
 12 \times 2 &= 24 \\
 12 \times 3 &= 36 \\
 12 \times 4 &= 48
 \end{aligned}$$

$$(27A8/12)_{12} = (234)_{12}$$

Corrigé Type .

$$\begin{aligned}
 1) (EB5A,02)_{16} &= A \times 16^0 + 5 \times 16^1 + B \times 16^2 + E \times 16^3 + 0 \times 16^{-1} + 2 \times 16^{-2} \\
 &= 10 \times 1 + 80 + 11 \times 256 + 14 \times 4096 + 0,004 \\
 &= (60250,004)_{10}
 \end{aligned}$$

$$(EB5A,02)_{16} = (1110 \ 1011 \ 0101 \ 1010,0000 \ 0010)_2$$

$$\begin{array}{r}
 2) \quad \begin{array}{r}
 \begin{array}{r}
 \begin{array}{r}
 A19,1 \\
 \times 16,3_{13}
 \end{array} \\
 \hline
 24513 \\
 48A26. \\
 A191.. \\
 \hline
 \end{array} \\
 = (11CA8,73)_{13}
 \end{array}
 \end{array}$$

Table de multiplication de 23 en base 4

$$\begin{aligned}
 23 \times 1 &= 23 \\
 23 \times 2 &= 112 \\
 23 \times 3 &= 201
 \end{aligned}$$

$$\begin{array}{r}
 3) \quad \begin{array}{r}
 \begin{array}{r}
 13233 \\
 - 11211 \\
 \hline
 02031 \\
 - 2011 \\
 \hline
 0023 \\
 - 23 \\
 \hline
 00
 \end{array}
 \end{array}
 \end{array}$$

$$(13233 / 23)_4 = (231)_4$$

Corrigé Type .

$$\begin{aligned}
 1/ \quad (4B0C, 04)_{16} &= C \times 16^0 + 0 \times 16^1 + B \times 16^2 + 4 \times 16^3 + 0 \times 16^{-1} + 4 \times 16^{-2} \\
 &= 12 \times 1 + 11 \times 256 + 4 \times 4096 + 4 \times 0,01 \\
 &= (19212, 01)_{10}
 \end{aligned}$$

$$(4B0C, 04)_{16} =$$

$$(0100 \ 1011 \ 0000 \ 1100, 0000 \ 0100)_2$$

$$\begin{array}{r}
 2/ \quad (36, 04)_{13} \\
 \times \quad 23 \\
 \hline
 A50C \\
 6C08. \\
 \hline
 = (795, 8C)_{13}
 \end{array}$$

$$\begin{array}{r}
 3/ \quad \overline{10136} \\
 - \underline{101} \quad i \\
 \hline
 00036 \\
 - \underline{34} \\
 \hline
 02
 \end{array}
 \quad
 \begin{array}{r}
 34 \\
 \hline
 201
 \end{array}$$

Table de multiplication de 34 en base 7

$$\begin{aligned}
 34 \times 1 &= 34 \\
 34 \times 2 &= 101 \\
 34 \times 3 &= 135
 \end{aligned}$$

$$(10136 / 34)_7 = (201)_7 \text{ reste } 02.$$