

Outline-OPS-001：版本迭代更新出现500 Runbook

Metadata

- 环境: 生产
- 服务名称: Outline
- 告警名称: 500
- 负责人: @sre-oncall
- 最后更新: 2026-08-04
- 下次演练: xxx
- 预计耗时: 5-20 分钟
- 严重级别: P1 (全量不可用)

触发条件

☒ 用户反馈：Outline Web页面无法报500错误码

快速诊断

步骤1: 查看容器运行状态

```
# docker ps
CONTAINER ID   IMAGE                                COMMAND
CREATED        STATUS          PORTS          NAMES
7b5ec0edc477   outlinewiki/outline:1.9.2          "docker-entrypoint.s..."
  7 minutes ago Up 7 minutes (healthy)  0.0.0.0:3000->3000/tcp, :::3000->3000/tcp  outline_1.9.2-1
7d3abef791d1   keycloak/keycloak:26.1.4          "/opt/bitnami/script..."
  10 days ago   Up 10 days      8443/tcp, 0.0.0.0:8080->8080/tcp, :::8080->8080/tcp, 9000/tcp  keycloak-1
a54b1beb1879   postgres:15.12                    "docker-entrypoint.s..."
  4 months ago Up 8 weeks      0.0.0.0:5432->5432/tcp, :::5432->5432/tcp  postgres
3bbedc2c930d   minio/minio:RELEASE.2025-03-12T18-04-18Z "/usr/bin/docker-ent..."
  4 months ago Up 8 weeks      0.0.0.0:29000->9000/tcp, :::29000->9000/tcp, 0.0.0.0:29001->9001/tcp, :::29001->9001/tcp  minio-cp
97782cbe3025   redis:7.4.2-alpine                "docker-entrypoint.s..."
  16 months ago Up 8 weeks      0.0.0.0:6379->6379/tcp, :::6379->6379/tcp  redis

# 依赖的服务status全部正常
```

步骤2: 查看outline容器日志

```
# docker logs --tail 33 <outline_container>
{"label":"lifecycle","level":"info","message":"Listening on http://localhost:3000 / http://192.168.13.23"}
```

Error: Cannot send secure cookie over unencrypted connection

- at Cookies.set (/opt/outline/node_modules/cookies/index.js:126:11)
- at StateStore.store (/opt/outline/build/server/utils/passport.js:126:23)
- at OAuth2Strategy.authenticate (/opt/outline/node_modules/passport-oauth2/lib/strategy.js:291:28)
- at OIDCStrategy.authenticate (/opt/outline/build/plugins/oidc/server/auth/OIDCStrategy.js:19:11)
- at attempt (/opt/outline/node_modules/@outlinewiki/koa-passport/node_modules/passport/lib/middleware/authenticate.js:369:16)
- at authenticate (/opt/outline/node_modules/@outlinewiki/koa-passport/node_modules/passport/lib/middleware/authenticate.js:370:7)
- at /opt/outline/node_modules/@outlinewiki/koa-passport/lib/framework/koa.js:194:7
- at new Promise (<anonymous>)
- at /opt/outline/node_modules/@outlinewiki/koa-passport/lib/framework/koa.js:193:12
- at /opt/outline/node_modules/@outlinewiki/koa-passport/lib/framework/koa.js:143:7
- at new Promise (<anonymous>)
- at passportAuthenticate (/opt/outline/node_modules/@outlinewiki/koa-passport/lib/framework/koa.js:107:15)
- at passportAuthenticate (/opt/outline/node_modules/dd-trace/packages/datadog-instrumentations/src/koa.js:90:57)
- at dispatch (/opt/outline/node_modules/koa-router/node_modules/koa-compose/index.js:44:32)
- at next (/opt/outline/node_modules/koa-router/node_modules/koa-compose/index.js:45:18)
- at startOAuthFlow (/opt/outline/build/server/utils/passport.js:56:12)

步骤3: 日志分析

Outline 的 OIDC 登录流程需要设置一个 secure cookie (用于存储 OAuth state)，而 secure cookie 只能通过 HTTPS 发送，不能通过 HTTP 发送。

从日志看，outline 当前运行在 http://192.168.13.23 (明文 HTTP)，所以触发了这个报错。

Outline 1.8.x 在 production 模式下，OIDC 认证流程中的 state cookie (用于防 CSRF) 代码里写死了 secure: `_env.default.isProduction`，即 secure: `true`。

而访问方式是纯 HTTP (http://192.168.13.23)，Node.js 的 cookies 库会拒绝在 HTTP 连接上发送 secure cookie，所以直接报错：

Error: Cannot send secure cookie over unencrypted connection

分析容器运行的变量，必须使用https协议，变更变量的值

```
# docker run -d      -p 80:3000      --name outline_1.8.2-0      --network keycloak-  
network      -v ~/docker-data/outline-data:/var/lib/outline/data      -e  
DATABASE_URL=postgres://iotcloud:iotcloud@postgres/outline2      -e  
REDIS_URL=redis://:iotcloud@192.168.13.23:6379/0      -e PGSSLMODE=disable      -e  
FORCE_HTTPS=false      -e  
SECRET_KEY=22a3dbd6fd96864cb125504826b153cf60a454e43a019afe4692e06f6cacd700      -  
e UTILS_SECRET=11121c684ca0dc0352bf7567db9aaf9bc26c45fc34cacd5dbe883c086d7c7e00  
      -e URL=http://192.168.13.23      -e OIDC_CLIENT_ID=outline      -e  
OIDC_CLIENT_SECRET=y3WktIycbXAYnmYu7zPxNpOcEy034EOn      -e  
OIDC_AUTH_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-  
connect/auth      -e  
OIDC_TOKEN_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-  
connect/token      -e  
OIDC_USERINFO_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-  
connect/userinfo      -e  
OIDC_LOGOUT_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-  
connect/logout?redirect_uri=http%3A%2F%2F192.168.13.23      -e  
OIDC_USERNAME_CLAIM=preferred_username      -e OIDC_DISPLAY_NAME=keycloak      -e  
OIDC_SCOPES="openid profile email"      -e AWS_ACCESS_KEY_ID=iotcloud      -e  
AWS_SECRET_ACCESS_KEY=iotcloud@2025      -e  
AWS_S3_UPLOAD_BUCKET_URL=http://192.168.13.23:29000      -e  
AWS_S3_UPLOAD_BUCKET_NAME=outline      -e AWS_REGION=cn-homelab-1      -e  
FILE_STORAGE_UPLOAD_MAX_SIZE=5621440000      -e AWS_S3_FORCE_PATH_STYLE=true      -  
e AWS_S3_ACL=private      -e SMTP_HOST=smtp.exmail.qq.com      -e SMTP_PORT=465  
-e SMTP_USERNAME=iot-cloud@tian-power.com      -e SMTP_PASSWORD=Vb4Ca8H0fi316AE  
      -e SMTP_FROM_EMAIL=iot-cloud@tian-power.com      -e EMAIL_ENABLED=true -e  
GITLAB_CLIENT_ID=43c97e179744f685cd6528e35ad5352b1e9c37dcf9790679476a537635176c08  
-e GITLAB_CLIENT_SECRET=gloas-  
988dd8d9d59aa6f6f0fd0c5e3a30f0d98e997752995174b4469ad83658d4adec -e  
GITLAB_BASE_URL=https://gitlab.tian-power.cloud -e DEFAULT_LANGUAGE=zh_CN -e  
WEB_CONCURRENCY=256 -e ALLOWED_PRIVATE_IP_ADDRESSES=192.168.13.76  
outlinewiki/outline:1.8.2
```

#现使用的是http协议

FORCE_HTTPS=false

URL=http://192.168.13.23

步骤4: 解决方案

nginx web服务作为反向代理

使用nginx web服务作为反向代理到容器启动的outline服务

vim outline-web.conf

```
server {  
    listen 80;  
    server_name outline.tian-power.cloud;  
  
    # 自动重定向到 HTTPS  
    return 301 https://$server_name$request_uri;  
}  
  
server {
```

```

listen 443 ssl;
server_name outline.tian-power.cloud;

ssl_certificate /etc/nginx/conf.d/ssl/tian-power.cloud.pem;
ssl_certificate_key /etc/nginx/conf.d/ssl/tian-power.cloud.key;

access_log /data/wwwlog/web-access.log;
error_log /data/wwwlog/web-error.log;

ssl_session_cache shared:SSL:10m;
ssl_session_timeout 10m;
ssl_protocols TLSv1.2 TLSv1.3;
ssl_ciphers HIGH:!aNULL:!MD5;
ssl_prefer_server_ciphers on;

location / {

    proxy_http_version 1.1;
    # 关键：必须传递这些头，让 Outline 知道实际是 HTTPS
    proxy_set_header X-Forwarded-Proto $scheme;
    proxy_set_header X-Forwarded-Host $host;
    proxy_set_header X-Forwarded-For $proxy_add_x_forwarded_for;
    proxy_set_header X-Real-IP $remote_addr;
    proxy_set_header Host $host;

    # WebSocket 支持（Outline 实时协作需要）
    proxy_set_header Upgrade $http_upgrade;
    proxy_set_header Connection "upgrade";

    # 超时设置
    proxy_read_timeout 86400;
    proxy_send_timeout 86400;

    proxy_pass http://127.0.0.1:3000;
    proxy_connect_timeout 20s;
}
}

```

修改outline容器启动方式

```
# 主要针对的是FORCE_HTTPS=true和URL=https://outline.tian-power.cloud协议域名指定
docker run -d -p 80:3000 --name outline_1.9.2 --network keycloak-network -v ~/docker-data/outline-data:/var/lib/outline/data -e DATABASE_URL=postgres://iotcloud:iotcloud@postgres/outline2 -e REDIS_URL=redis://:iotcloud@192.168.13.23:6379/0 -e PGSSLMODE=disable -e FORCE_HTTPS=true -e SECRET_KEY=22a3dbd6fd96864cb125504826b153cf60a454e43a019afe4692e06f6cacd700 -e UTILS_SECRET=11121c684ca0dc0352bf7567db9aaf9bc26c45fc34cacd5dbe883c086d7c7e00 -e URL=https://outline.tian-power.cloud -e OIDC_CLIENT_ID=outline -e OIDC_CLIENT_SECRET=y3WktIycbXAYnmYu7zPXNpOceY034EOn -e OIDC_AUTH_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-connect/auth -e OIDC_TOKEN_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-connect/token -e OIDC_USERINFO_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-connect/userinfo -e OIDC_LOGOUT_URI=http://192.168.13.23:8080/realms/outline/protocol/openid-connect/logout?redirect_uri=http%3A%2F%2F192.168.13.23 -e OIDC_USERNAME_CLAIM=preferred_username -e OIDC_DISPLAY_NAME=keycloak -e OIDC_SCOPES="openid profile email" -e AWS_ACCESS_KEY_ID=iotcloud -e AWS_SECRET_ACCESS_KEY=iotcloud@2025 -e AWS_S3_UPLOAD_BUCKET_URL=http://192.168.13.23:29000 -e AWS_S3_UPLOAD_BUCKET_NAME=outline -e AWS_REGION=cn-homelab-1 -e FILE_STORAGE_UPLOAD_MAX_SIZE=5621440000 -e AWS_S3_FORCE_PATH_STYLE=true -e AWS_S3_ACL=private -e SMTP_HOST=smtp.exmail.qq.com -e SMTP_PORT=465 -e SMTP_USERNAME=iot-cloud@tian-power.com -e SMTP_PASSWORD=Vb4Ca8H0fi3l6AE -e SMTP_FROM_EMAIL=iot-cloud@tian-power.com -e EMAIL_ENABLED=true -e GITLAB_CLIENT_ID=43c97e179744f685cd6528e35ad5352b1e9c37dcf9790679476a537635176c08 -e GITLAB_CLIENT_SECRET=gloas-988dd8d9d59aa6f6f0fd0c5e3a30f0d98e997752995174b4469ad83658d4adec -e GITLAB_BASE_URL=https://gitlab.tian-power.cloud -e DEFAULT_LANGUAGE=zh_CN -e WEB_CONCURRENCY=256 -e ALLOWED_PRIVATE_IP_ADDRESSES=192.168.13.76
outlinewiki/outline:1.9.2
```

步骤5: 登录outline

进入Keycloak登录界面报错: Invalid parameter: redirect_uri

分析得到Keycloak 中 Outline 客户端的 Valid Redirect URIs 没有包含

`https://outline.tian-power.cloud/auth/oidc.callback`

步骤6: Keycloak修复

1. 找到 Outline 客户端

- 进入你的 Realm (如 `outline`)
- 左侧菜单 → **Clients** → 点击 `outline`

2. 修改 Valid Redirect URIs

- Root URL: <https://outline.tian-power.cloud/>
- Home URL: <https://outline.tian-power.cloud/>
- Valid redirect URIs: <https://outline.tian-power.cloud/auth/oidc.callback>
- Valid post logout redirect URIs: <https://outline.tian-power.cloud/>*

- Web origins: <https://outline.tian-power.cloud>
- Admin URL: <https://outline.tian-power.cloud/>

步骤7: 验证

`https://outline.tian-power.cloud`域名登录，正常显示

查看outline容器日志，无报错

```
docker logs --tail 33 <outline_container>
```