

Lib_Plu sdk User manual

1. Create a PluManage object and initialize it

```
public void init() {
    pluManage = new PluManage(ProtTypeEnum.Prot_Rongta2); //Default is Rongta protocol 2
    pluManage.setIpAndport( " 192.168.8.100 " ,5001); //Set the IP and port of the scale
    pluManage.setCodeLen(10); //Set the default length of the product number to 10. For Indian customers, it is 13. The lower machine needs to be customized
    pluManage.setLfcodeLen(6); //Set the default length of the fresh food code to 6. Some customers also use 7. The lower machine needs to be customized
    pluManage.setCharset("UTF-8"); //The encoding format of the product name, the default is UTF-8
    pluManage.setDecimalDigits(2); //Set the number of decimal places for the price, the default is 2
    pluManage.setIsUsePluName2(false); //Set whether to enable the second product name, the default is false
    pluManage.setIsUseMessage2(false); //Whether to enable message2, the default is false
}
```

2. Connection Test

```
pluManage.connect( " 192.168.8.100 " , 5001);
```

3. Download products and hotkeys

```
private void write() {
    ArrayList<PluInfoBean> plulist = new ArrayList<>();
    for (int i = 1; i < 10 ; i++) {

        PluInfoBean pluInfoBean = new PluInfoBean(); //Create bean
        pluInfoBean.setPluLfcode((long) (100+i)); //Fresh food code, unique product code (0~999999)
        pluInfoBean.setPluName("pluname"+String.valueOf(i)); //Product name 36 bytes
        pluInfoBean.setPluName2("pluname 2"); //Second product name 36 bytes
        pluInfoBean.setPluItemNum("20001"); //Product number
        pluInfoBean.setPluUnitPrice(20.5+i); //Unit price
        //Unit, refer to the definition of WeightUnitEnum
        pluInfoBean.setPluWeightUnit(WheelUnitEnum.UNIT_KG); pluInfoBean.setPluBarcodeType(2);
        //Barcode type, according to the setting of Rongda host computer (1-110), 1-98 is system built-in, 99, 101-110 are custom barcodes
    }
}
```

```

pluInfoBean.setPluShelfDays(20); //Shelf life 0~9999
pluInfoBean.setPluDiscount(0); //Discount 0~127, enter 85 for 15% off
pluInfoBean.setPluDepartment(3); //Department 0~99
pluInfoBean.setTolerance(0); //Tolerance 0~20
pluInfoBean.setPluLabelIndexEnum(LabelIndexEnum.D0); //Label template corresponds to host computer
//Message1, if Message2 is not enabled, the maximum value of Message1 can be 10000, otherwise it is only 255
pluInfoBean.setPluMsg1(0);
pluInfoBean.setPluMsg2(0); //Message2 maximum value 255
pluInfoBean.setQtyUnit(0); //Piece unit 0~15, default is 0, refer to Rongda host computer
pluInfoBean.setPlupackageWeight(0.0); //Packaging weight, if the unit is kg, the maximum value is 15, if the unit is lb, the maximum value is 33.07, if it is 500g, the maximum value is 9999.0
pluInfoBean.setPluTareWeight(0.0); //Default tare weight, usually 0, maximum value: according to the maximum tare weight supported by the scale
pluInfoBean.setSalemode( 3 ); //Sales mode, Indian customized customers: 3: regular sales; 0: discount mode; 4: special discount mode
pluInfoBean.setPricemode(3); //Price mode, Indian customized customers: 0: Priced by weight; 1, equal to price based on quantity
pluInfoBean.setManufacturedate("20231012"); //Manufacturing date, Indian customized customers
plulist.add(pluInfoBean);
}
boolean b=pluManage.writePluInfo(plulist); //Start writing to PLU
Log.e("rtDebug", "writePluInfo="+String.valueOf(b));
ArrayList<Long> hotkeyList = new ArrayList<>();

for (int i = 1; i < 225 ; i++) {
    hotkeyList.add((long) 100+i); //The hotkey table contains fresh food codes
}
pluManage.writeHotkey(hotkeyList); //Write hotkey
}

```

4. Clear PLU

```

private void clearPluData(){
    pluManage.clearPluData(); //Can be used to clear before downloading. If you update PLU frequently, it is recommended to call this function every few days to prevent slow download due to junk data
}

```

5. Upload PLU

```

private void read() {
    ArrayList<PluInfoBean> list = pluManage.getPluInfoList();
    for (PluInfoBean bean:list) {
        Log.e(TAG,bean.toString());
            bean.getpluLfcode() ;//Fresh food code

            bean.getHotKey() //Hot key
            .....
    }

}

```

6. Upload Hotkey

```

ArrayList<HotKeybean> hotKeylist = pluManage.getPluHotKey();
    for (HotKeybean bean:hotKeylist) {
        Log.e(TAG,String.format("%d=%s",bean.getHotkeyid(),bean.lfcode));
    }

```

7. Upload sales data

```

private void getSalesReport() {
    boolean isok=pluManage.getPluSales(new CallbackListener() {
        @Override
        public void onSaleDataOut(PluSaleBean SaleBean) {
            Log.d("rtdebug",SaleBean.toString());
                SaleBean.getLlfCode(); //Fresh food code
                SaleBean . getPluName() ; //Product name
                SaleBean.getPluUnitPrice(); //Unit priceSaleBean.getWeight
                (); //WeightSaleBean.getWeightUnitEnum
                (); //Unit
                SaleBean.getSaleDate() ; //Sales time
                SaleBean.getSumPrice () ; //Total price
                SaleBean.getDiscount () ; //discount
                SaleBean.getAddedDate () ; //Listing date
                SaleBean . getQuantity() ; //Quantity
                SaleBean . getClerk() ;//Cashier
                SaleBean . getUserID_IP () ; // scale's IP address

                .....
        }
    }
}

```

```
});
```

8. Clear sales data

If the sales data is uploaded, this function should be called to clear the sales data on the scale to avoid data duplication.

```
private void clearSaledata(){  
    pluManage.clearSaledata();  
}
```