Incandecent, LED, CFL, Low Voltage and Fan Speed Controls										
	Vizia +	Vizia RF +	True Touch	Toggletouch	IllumaTech Slide	IllumaTech Rotary	SureSlide	Trimatron	Mural	Toggle
Incandescent 600W	VPI06-1L[1	VRI06-1L[2]	TTI06-1L[3]	TGI06-1L[4]	IPI06-1L, IPL06-10[5]	RPI06-1L, RPI06-10[6]	6631-L, 6633-PL, 6674-10[7]	6602, 6681, 6683	MDI06-1L[9]	6641, 6643 6691, 6693 [10]
Incandescent 1000W	VPM10-1L	VRI10-1L, VRMX1-1L [12]	TTI10-1L[3]	TGI10-1L[13]	IPI10-1L[14]	*	*	*	MDI10-1L[9]	-
Incandescent 1500W	*	*	*	*	*	*	*	*	*	-
Incandescent 2000W	*	*	*	*	*	*	*	*	*	-
LED and CFL 150W	-	-	-	-	IPL06-10[15]	-	6674-10[16]	-	-	-
Electronic Low Voltage 350VA	-	-	-	-	-	-	-	-	MDE03-1LW	-
Electronic Low Voltage 400VA	-	-	-	-	IPE04-1L[18]	-	-	-	-	-
Electronic Low Voltage 300W	-	-	-	-	-	-	6615-P[19]	-	-	-
Electronic Low Voltage 400W	VPE04-1L[	-	-	-	-	-	-	-	-	-
Electronic Low Voltage 600W	VPE06-1L[	VRE06-1L[22	-	-	-	-	-	-	-	-
Magnetic Low Voltage 300VA Dual Slide Dimmer	-	-	-	-	-	-	6628[23]	-	-	-
Magnetic Low Voltage 600VA	VPM06-1L	-	-	-	IPM06-1L[24]	*	6613-PL[25]	*	MDM06-1L[9	-
Magnetic Low Voltage 1000VA	VPM10-1L	VRMX1-1L[2	TTM10-1L[3]	TGM10-1L[26]	IPM10-1L[24]	*	-	*	MDM10-1L[9	-
Magnetic Low Voltage 1500VA	*	*	*	*	*	*	*	*	*	-
Fan Speed Control 1.5 Amp & Dimmer 300W	-	-	-	-	-	RTD01-10[27]	-	-	-	-
Fan Speed Control Quiet 1.5Amp	VPF01-1L[	VRF01-1L[22	-	-	IPF01-1L[29]	RTF01-10[27]	6629-3[25]	6639[30]	MDF01-1L[3	-
Fan Speed Control Variable 5Amp	-	-	-	-	IPF05-1L[32]	-	6627-1, 6637-P[3	6616-X[34]	-	-

Fluorescent				
	Vizia +	Vizia RF +	IllumaTech Slide	SureSlide
Fluorescent Electronic Mark 10 Powerline 120V 500W	-	-	-	6668[35]
Fluorescent Electronic Mark 10 Powerline 120V 600VA	-	-	IPX06-10[36]	-
Fluorescent Electronic Mark 10 Powerline 120V 1000VA	VPX10-1L[	VRMX1-1[22	IPX10-10[36]	-
Fluorescent Electronic Mark 10 Powerline 120V 1500VA	*	-	-	-
Fluorescent Electronic Mark 10 Powerline 277V 600VA	-	-	IPX06-70[36]	-
Fluorescent Electronic Mark 10 Powerline 277V 1200VA	VPX12-7L[	-	IPX12-70[36]	-
Fluorescent Electronic Mark 10 Powerline 277V 2000VA	*	-	*	-

	Vizia +	Vizia RF +	True Touch	Mural
Fluorescent Electronic Mark 10 Powerline 277V 3000VA	*	-	-	-
Fluorescent Electronic 0-10VDC Mark 7 or Quicktronic Helios 120V 1200VA	-	-	IP710-DL[18]	-
Fluorescent Electronic 0-10VDC Mark 7 or Quicktronic Helios 277V 1500VA	-	-	IP710-DL[18]	-
Fluorescent Dimmer for Hi-Lume or Eco-10 8A-120VAC	VPH08-1L[	-	-	-
Fluorescent Dimmer for Hi-Lume or Eco-10 6A-277VAC	VPH06-7L[	-	-	-

Switches and Remotes				
	Vizia +	Vizia RF +	True Touch	Mural
Switch 5A Incandescent Only	-	VRS05-1L[40	-	-
Switch 15A-120VAC	VPS15-1L[	VRS15-1L[42	-	-
Dimmer Remote Matching 120VAC	VP00R-1L[	VP00R-1L[44	-	-
Dimmer Remote Coordinating 120VAC	VP00R-10[	VP00R-10[46	TT00R-10[47]	MS00R-10[48]
Dimmer Remote Matching 277VAC	VP00R-7L[	-	-	-
Switch Remote Matching 120VAC	VP0SR-1L[	VP0SR-1L[51	-	-
Switch Remote Coordinating 120VA	VP0SR-10[	VP0SR-10[53	-	-
Appliance Module 15A 120VAC	-	VRP15-1L[54	-	-
Lamp Dimming Module 300W 120VAC	-	VRP03-1L[54	-	-
RS232 Interface	-	VRC0P-1L[55	-	-
Receptacle 1800W/1800VA	-	VRR15-1L[56	-	-
4-Button Scene Controller 120VAC	-	VRCS4-M0[5	-	-
4-Button Zone Controller 120VAC	-	VRCZ4-M0[5	-	-
4-Button Scene Combo Controller 1800W/1800VA, ½ HP	-	VRCS4-MR[5	-	-
4-Button Zone Combo Controller 1800W/1800VA, ½ HP	-	VRCZ4-MR[6	-	-
2-Button Scene Controller 1000W/1000VA, ¼ HP per switch	-	VRCS2-MR[6	-	-
1-Button Scene Controller 120VAC	-	VRCS1-1L[62	-	-
1-Button Zone Controller 120VAC	-	VRCZ1-1L[63	-	-
Primary Remote	-	VRCPG-0SG, VRCPG-BSG[64]	-	-
IR Remote	-	VRMR1-0SG	-	-

| Installer Tool Software & USB | - | VRUSB-000 | - | - | | | | | | |

1. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z, W, T
Neutral Required: No

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
2. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VRCZ1-1L, VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: No

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

3. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with TT00R remote
Device Colors: Z, GS
Neutral Required: No

Color Kits: TTKIT
Kit Colors: W, I, T, G, E, WS, GI, BG

Wallplates: Decora screwless or Decora standard, sold separately

4. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W, I, T, B
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately

5. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: no

Color Kits: IPKIT-00, IPKIT-LN (For IPL06, no LED)
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
6. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

7. Multi Location Control: 6631 is Single Pole Only. 6633 and 6674 are Single Pole or 3-way control when used with 3-way switch
Device Colors: 6631 = W, I, T;
6633 = W, I, T, G, E;
6674 = W, I, T, E, B
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately
8. Multi Location Control: 6602 and 6681 are Single Pole Only. 6683 is Single Pole or 3-way control when used with 3-way switch
Device Colors: 6602 = W; 6681 = W, I; 6683 = Z
Neutral Required: no

Color Kits: 80400, 26115 (metal insert)
Kit Colors: W, I, T, E, B*
* available in brown w/no suffix
No light almond kit for 80400
Wallplates: Standard toggle wallplate, sold separately

9. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with MS00R remote
Device Colors: W, I
Neutral Required: No

Color Kits: DRKDD-1L
Kit Colors: W, I, G, E, B

Wallplates: Decora screwless or Decora standard, sold separately

10. Multi Location Control: 6641 and 6691 are Single Pole Only. 6643 and 6693 are Single Pole or 3-way control when used with 3-way switch
Device Colors: 6641 and 6643 = W, I; 6691 and 6693 = Clear
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately
11. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z, T
Neutral Required: No

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

12. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VRCZ1-1L, VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: VRI10 = No; VRMX1 = yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

13. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W, I, T, G
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately

14. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: no

Color Kits: IPKIT-00
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

15. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: no

Color Kits: IPKIT-LN
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

16. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W, I, T, E, B
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately
17. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with MSE0R remote
Device Colors: W
Neutral Required: yes

Color Kits: DRKDD-1L
Kit Colors: W, I, G, E, B

Wallplates: Decora screwless or Decora standard, sold separately

18. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z

Neutral Required: yes

Color Kits: IPKIT-00
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

19. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W,T
Neutral Required: yes

Wallplates: Decora screwless or Decora standard, sold separately

20. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z, T
Neutral Required: Yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

21. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z, T
Neutral Required: yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
22. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VRCZ1-1L, VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

23. Multi Location Control: Two Single Pole Loads
Device Colors: W, I
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

24. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: no

Color Kits: IPKIT-00
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

25. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W, I, T
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

26. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: W, I, T
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately

27. Multi Location Control: Single Pole Only
Device Colors: Z
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

28. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: Yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

29. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: yes

Color Kits: IPQFK-00
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

30. Multi Location Control: Single Pole Only.
Device Colors: Z
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately

31. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location control with MSE0R remote
Device Colors: W
Neutral Required: yes

Color Kits: DRKDD-1L
Kit Colors: W, I, G, E, B

Wallplates: Decora screwless or Decora standard, sold separately

32. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z
Neutral Required: yes

Color Kits: IPQFK-00
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

33. Multi Location Control: 6627 is Single Pole Only. 6637 is Single Pole or 3-way control when used with 3-way switch
Device Colors: 6627 = W, I, B;
6637 = W, I, T
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

34. Multi Location Control: Single Pole Only.
Device Colors: W, I
Neutral Required: no

Wallplates: Standard toggle wallplate, sold separately

35. Multi Location Control: Single Pole Only
Device Colors: W, I
Neutral Required: no

Wallplates: Decora screwless or Decora standard, sold separately

36. Multi Location Control: Single Pole or 3-way control when used with 3-way switch
Device Colors: Z

Neutral Required: yes

Color Kits: IPKIT-0N
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

37. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z, T
Neutral Required: yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

38. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

39. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location dimming with VP00R-1L or VP00R-10 remotes
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MD, VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
40. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location control with VRCS1-1L, VP0SR-1L or VP0SR-10 remotes
Device Colors: Z
Neutral Required: no

Color Kits: VPKIT-MS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

41. Multi Location Control: Non-dimming electronic switch provides Single Pole, 3-way or Multi-Location control with VP0SR-1L or VP0SR-10 remotes
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MS, VPKIT-CS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

42. Multi Location Control: Digital circuitry provides Single Pole, 3-way or Multi-Location control with VRCS1-1L, VP0SR-1L or VP0SR-10 remotes
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

43. Multi Location Control: Matching Remote Dimmer for 3-way or up to 5 locations
Device Colors: Z, W
Neutral Required: yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
44. Multi Location Control: Non-RF Matching Remote Dimmer for 3-way or up to 5 locations
Device Colors: Z, W
Neutral Required: yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
45. Multi Location Control: Coordinating Remote Dimmer for 3-way or up to 10 locations
Device Colors: Z
Neutral Required: yes, except when used with incandescent or magnetic low voltage devices

Color Kits: VPKIT-CD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

46. Multi Location Control: Non-RF Coordinating Remote Dimmer for 3-way or up to 10 locations
Device Colors: Z
Neutral Required: yes, except when used with incandescent or magnetic low voltage devices

Color Kits: VPKIT-CD

Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

47. Multi Location Control: Coordinating Remote Dimmer for 3-way or up to 10 locations
Device Colors: Z, GS
Neutral Required: no

Color Kits: TTKTR
Kit Colors: W, I, T, G, E, WS, GI, BG

Wallplates: Decora screwless or Decora standard, sold separately

48. Multi Location Control: Coordinating Remote Dimmer/Fan Speed Controls for 3-way or up to 10 locations, no LED
Device Colors: W, I
Neutral Required: no

Color Kits: DRK0R-00
Kit Colors: W, I, G, E, B

Wallplates: Decora screwless or Decora standard, sold separately

49. Multi Location Control: Matching Remote Dimmer for 3-way or up to 5 locations
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

50. Multi Location Control: Matching Remote Switch for 3-way or up to 5 locations
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

51. Multi Location Control: Non-RF Matching Remote Switch for 3-way or up to 5 locations
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MS

Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

52. Multi Location Control: Coordinating Remote Switch for 3-way or up to 10 locations
Device Colors: Z
Neutral Required: yes, except when used with incandescent or magnetic low voltage devices

Color Kits: VPKIT-CS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

53. Multi Location Control: Non-RF Coordinating Remote Switch for 3-way or up to 10 locations
Device Colors: Z
Neutral Required: yes, except when used with incandescent or magnetic low voltage devices

Color Kits: VPKIT-CS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

54. Supports beaming which is the ability to communicate with battery operated frequently listening nodes (FLiRS) such as door locks and sensors

55. Supports beaming which is the ability to communicate with battery operated frequently listening nodes (FLiRS) such as door locks and sensors

Reflashable for firmware updates

56. ½ HP Split Tamper-Resistant Duplex Wall Receptacle with Top Outlet Scene Capable Switch for Single Pole Applications
Device Colors: Z

Color Kits: VRKIT-R0
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately
57. Multi Location Control: Scene Controller for
Multi-Location Scene Control with IR Remote Capability
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-S4
Kit Colors: W, I, T, G, E, B, R

Button Label Kits: VPSLB-S4
Custom Engraved Buttons: Visit www.leviton.com/buttons to download order form

Wallplates: Decora screwless or Decora standard, sold separately

58. Multi Location Control: Zone Controller for
Multi-Location Control with IR Remote Capability
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-Z4
Kit Colors: W, I, T, G, E, B, R
Button Label Kits: VPZLB-Z4
Custom Engraved Buttons: Visit www.leviton.com/buttons to download order form

Wallplates: Decora screwless or Decora standard, sold separately

59. Multi Location Control: Scene Controller with Single Pole Scene Capable Switch for Multi-Location Scene Control with IR Remote Capability
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-S4
Kit Colors: W, I, T, G, E, B, R
Button Label Kits: VPSLB-S4
Custom Engraved Buttons: Visit www.leviton.com/buttons to download order form

Wallplates: Decora screwless or Decora standard, sold separately

60. Multi Location Control: Zone Controller with Single Pole Scene Capable Switch for Multi-Location Zone Control with IR Remote Capability
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-Z4
Kit Colors: W, I, T, G, E, B, R
Button Label Kits: VPZLB-Z4
Custom Engraved Buttons: Visit www.leviton.com/buttons to download order form

Wallplates: Decora screwless or Decora standard, sold separately

61. Multi Location Control: Scene Controller with 2 Single Pole Scene Capable Switches
Device Colors: Z
Neutral Required: yes

Color Kits: VRKIT-DS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

62. Multi Location Control: Controller/Virtual Switch Remote 3-Way RF Controller for Multi-Location Control
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MS
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

63. Multi Location Control: Controller/Virtual Dimming Remote 3-Way RF Controller for Multi-Location Control
Device Colors: Z
Neutral Required: yes

Color Kits: VPKIT-MD
Kit Colors: W, I, T, G, E, B, R

Wallplates: Decora screwless or Decora standard, sold separately

64. VRCPG-BSG = Remote Controller Programmer
VRCPG-0SG = Remote Controller Programmer with Timer
65. IR Handheld Remote Controller for Zone and Scene Control

66. System Programming:
Download RF Installer Tool from www.leviton.com/rfinstallertool