



PROCESS FAILURE MODE AND EFFECTS ANALYSIS

Doc: GF182

Version: 1

Component Information

Component	<i>fibrichk-react-native-camera-sdk</i>
Component Version	1.0.6

Initial Risk Analysis										After Risk Control Measure								
ID	Risk type	Potential Failure Mode	Primary Hazard	Sev.	Possible causes of failure	Occ.	Detection Methods	Det.	RPN	Mitigation			mOcc.	mDet.	mRPN	Remarks	Risk Control	ALAP Motivation
3EE7	User	Misinterpretation of intended use	No measurement possible	1	Misinterpretations of the product claims	3	None	10	30	Method	Specifications	Tests						
E007	Test subject environment	Errors related to environment of use	Poor quality of measurements	1	Too much ambient noise to perform a high quality measurement	3	None	10	30	Method	Specifications	Tests						
9CE4	Test subject environment	Errors related to environment of use	Poor quality of measurements	1	The Camera SDK is used during activities that require undivided attention (e.g. driving, flying...)	3	None	10	30	Method	Specifications	Tests						
C21F	Measurement	User error	Poor quality of measurements	1	Poor finger positioning	5	None	10	50	Method	Specifications	Tests						
33E1	Measurement	User error	No measurement possible	1	Movements during measurement	5	None	10	50	Method	Specifications	Tests						
71DF	Measurement	User error	No measurement possible	1	Unclean fingers	3	None	10	30	Method	Specifications	Tests						
61C7	Measurement	User error	No measurement possible	1	Wet or damp fingers	3	None	10	30	Method	Specifications	Tests						
F6A6	Measurement	User error	Poor quality of measurements	1	Unnatural colorations (e.g. tattoos, ink...)	1	None	10	10	Method	Specifications	Tests						
34F2	Measurement	User error	No measurement possible	1	Deposits are present on the camera lens, flash or screen	5	None	10	50	Method	Specifications	Tests						
AEF3	Measurement	User error	Poor quality of measurements	1	SUT with conditions that impact the blood circulation in the fingers (e.g. pernio, cold fingers...)	3	None	10	30	Method	Specifications	Tests						
CD59	Measurement	User error	Poor quality of measurements	1	SUT is speaking during measurement	5	None	10	50	Method	Specifications	Tests						
1C18	Measurement	Hardware error	No measurement possible	1	No measurement possible due to hardware related problems	3	None	10	30	Method	Specifications	Tests						

3BD3	Software	Software error preventing correct use of device	No measurement possible	1	Software does not launch	1	None	1 0	10	Method	Specifications	Tests						
FE19	Software	Software error preventing correct use of device	No measurement possible	1	The Camera SDK does not perform the indicated function	3	None	1 0	30	Method	Specifications	Tests						
4D5D	Software	Software error preventing correct use of device	No measurement possible	1	Insufficient testing coverage	1	None	1 0	10	Method	Specifications	Tests						
CD35	Software	Software error preventing correct use of device	No measurement possible	1	Changes or updates in Operating System	3	None	1 0	30	Method	Specifications	Tests						
3F1F	Software	Software error preventing correct use of device	No measurement possible	1	Memory failure	3	None	1 0	30	Method	Specifications	Tests						
4555	Shelf-life	User error	No measurement possible	1	User did not update app	1	None	1 0	10	Method	Specifications	Tests						
8AB4	Errors due to UI design features	Unclear user interface prevents correct use of device	Poor quality of measurements	1	Insufficient visibility, audibility and tactility	3	None	1 0	30	Method	Specifications	Tests						
019F	Device mobile or portable	Hardware error	No measurement possible	1	Device failure	1	None	1 0	10	Method	Specifications	Tests						
39D0	Device mobile or portable	Hardware limitation	No measurement possible	1	Flash/LED gets too hot	3	None	1 0	30	Method	Specifications	Tests						
DE8B	Device mobile or portable	Hardware error	No measurement possible	1	Processor of device is overloaded	3	None	1 0	30	Method	Specifications	Tests						
A026	Device mobile or portable	Hardware error	No measurement possible	1	Inadequate disclosure of limitations	3	None	1 0	30	Method	Specifications	Tests						
3F6B	Device mobile or portable	Hardware error	No measurement possible	1	Environmental factors that can impair the hardware to perform the required processing for the software (i.e. Electromagnetic interference, temperature, moist...)	1	None	1 0	10	Method	Specifications	Tests						
626B	Control interface	User error	No measurement possible	1	Complex or confusing control system	3	None	1 0	30	Method	Specifications	Tests						

Version History

Version	Date (yyyy-mm-dd)	Current vs previous version	Author
1	2022-02-25	First Version of the Process Failure Mode and Effects Analysis	

Approval of document

	<i>Name Date Signature</i>
<i>Performed By:</i>	
<i>Approved By:</i>	