

Lab 04 - Motor Schemas

Author: Diego Coli - diego.coli@studio.unibo.it

Idea

Each behavior is modeled as a **potential field** producing a force vector. All vectors are summed into a single resultant, converted to differential wheel velocities.

Controller architecture

The controller (`controller-ms.lua`) uses `vector.lua` for polar/cartesian operations and implements four perceptual schemas:

- **Phototaxis (attractive):** sums all 24 light sensor readings as polar vectors. The result points toward the brightest region, scaled by `LIGHT_GAIN = 80`.
- **Obstacle avoidance (repulsive):** each proximity sensor produces a vector in the opposite direction ($\text{angle} + \pi$), scaled by `OBSTACLE_GAIN = 12`.
- **Uniform forward drive:** constant vector $\{\text{length} = 8, \text{angle} = 0\}$ to keep the robot moving when no stimulus is perceived.
- **Halt on black spot:** when a ground sensor reads below `HALT_THRESHOLD = 0.1`, a strong backward vector (`HALT_GAIN = 101`) overrides motion, stopping the robot on the target.
- **LED feedback:** red when halted, yellow when light is perceived, green otherwise.

All schema vectors are summed with `vec2_polar_sum()`. The resultant is converted to wheel speeds via the differential drive model:

- `v = clamp(|r|, 0, 15)`
- `w = 1.5 * angle(r)`
- `vl = v - w * L / 2, vr = v + w * L / 2`.

Expected behavior

- The robot steers toward the light (phototaxis) while the uniform drive ensures continuous forward motion.
- Obstacles are avoided via the repulsive field without stopping forward progress.
- On reaching the black spot under the light, the halt schema dominates and the robot stops.