

QOREVA™ DOCUMENT INTELLIGENCE VALIDATION

Group Lockout / Energy Control Plan — Synthetic Test Document

TEST ONLY — NOT AUTHORIZATION FOR FIELD EXECUTION. This synthetic work package intentionally contains a mixture of complete controls and selected planning gaps. It is designed to test whether Qoreva can distinguish resolved energy-control information from material missing information.

Project	Qoreva Validation Project
Task	Electrical isolation for conveyor motor replacement
Equipment	Conveyor CV-204 / Motor M-204
Location	Process Building — Level 1
Work group	Mechanical + Electrical maintenance crew
LOTO Coordinator	Jordan Ellis
Authorized Electrician	Morgan Reed
Planned date	October 14, 2026

1. Scope of Work

The crew will isolate conveyor CV-204 so the existing electric motor M-204 can be disconnected and replaced. Work includes shutdown, isolation, application of personal locks through a group lock box, verification of zero-energy state, motor replacement, inspection, removal of locks, controlled re-energization, and operational testing.

2. Identified Hazardous Energy Sources

The primary electrical energy source is 480 VAC three-phase power supplied from MCC-2, bucket 17B, labeled “CV-204 MOTOR.” The conveyor may also contain stored mechanical energy due to belt tension and rotating components. The conveyor will be allowed to coast to a complete stop before work begins. The crew will verify that moving components have stopped and will maintain guarding/positioning controls during the work.

3. Shutdown and Isolation Sequence

Jordan Ellis will coordinate the shutdown with the operating area. The conveyor will be stopped using its normal operating control. Morgan Reed will open the disconnecting means at MCC-2 bucket 17B. The disconnect will be placed in the OFF/open position and locked using the designated energy-isolation lock. The key for the isolation lock will be placed inside the group lock box. Each authorized employee performing servicing will apply a uniquely keyed personal lock to the group lock box before beginning work.

4. Notification

Affected employees in the immediate operating area will be informed before shutdown that CV-204 will be removed from service for maintenance. The LOTO Coordinator will notify the operating area again before locks are removed and the equipment is returned to service.

5. Verification of Isolation

After the disconnect is opened and locked, the normal conveyor start control will be operated to verify the equipment does not start. The control will then be returned to the OFF/neutral position. An electrically qualified person will perform absence-of-voltage verification before electrical conductors are handled. Test equipment will be verified on a known live source before and after the absence-of-voltage test.

6. Group Lock Box Control

The energy-isolation lock key will remain secured inside the group lock box for the duration of servicing. Every authorized employee exposed to the hazardous energy will apply a personal lock before beginning work and remove that personal lock when

their work is complete. The LOTO Coordinator will verify the lock-box roster against the workers participating in the task.

7. Shift / Personnel Change

If an authorized employee leaves the work area before the task is complete, that employee will remove their personal lock unless a documented transfer is performed. Incoming authorized employees must apply their personal locks before assuming protected work. The LOTO Coordinator will maintain continuity of protection during personnel changes.

8. Restoration to Service

Before re-energization, the work area will be inspected to confirm tools, temporary materials, and nonessential items are removed; guards/components required for operation are restored; and employees are positioned clear. Authorized employees will remove their own personal locks. After the group lock box is clear, the LOTO Coordinator will authorize removal of the energy-isolation lock and coordinate re-energization with the operating area.

9. Energy Isolation / Verification Table

Energy / Hazard	Isolation Point	Method	Verification
480 VAC electrical	MCC-2 / Bucket 17B	Open disconnect; lock; key in group lock box	Try-start + absence-of-voltage test
Stored mechanical / rotation	CV-204 belt & rotating components	Normal stop; allow motion to cease	Visual confirmation of complete stop

10. Personal Lock Removal When Employee Is Unavailable

If an employee's personal lock remains on the group lock box after the employee has left the site or cannot be located, supervision will follow the site's approved lock-removal process before the lock is removed. The details of that process are maintained separately and are not included in this work package.

11. Electrical Test Equipment

A properly rated digital multimeter will be used for absence-of-voltage verification. The specific meter identification, CAT rating, calibration/inspection status, and the identity of the qualified person performing the test will be confirmed at the work location before testing.

12. Unexpected Energy / Abnormal Conditions

If the identified isolation does not produce the expected zero-energy condition, work will stop and the isolation will be re-evaluated before servicing proceeds.

13. Pre-Work Verification

Item	Status
Equipment identity CV-204 / M-204 confirmed	Complete
Electrical isolation point MCC-2 / 17B identified	Complete
Affected-employee notification plan established	Complete
Group lock box available	Complete
Personal locks available for authorized employees	Complete
Specific electrical meter / tester details	To be confirmed
Formal absent-person lock removal procedure attached	Not attached

14. Review / Sign-Off

LOTO Coordinator: Jordan Ellis — Reviewed for validation

Authorized Electrician: Morgan Reed — Reviewed for validation

Operating Area Representative: _____ — Pending

Validation note: This document intentionally contains enough information to establish a credible group-lockout plan while leaving selected details incomplete. Qoreva should recognize the identified electrical isolation point, group lock-box sequence, try-start/absence-of-voltage verification, notification, and restoration controls as documented. It should scrutinize material gaps without inventing additional project facts.