ETAS ISOLAR-A/B V12.7.0

ISOLAR-B

Error Description Help Document

www.etas.com

Copyright

The data in this document may not be altered or amended without special notification from ETA S GmbH. ETAS GmbH undertakes no further obligation in relation to this document. The software described in it can only be used if the customer is in possession of a general license agreement or single license. Using and copying is only allowed in concurrence with the specifications stipulated in the contract.

Under no circumstances may any part of this document be copied, reproduced, transmitted, stored in a retrieval system or translated into another language without the express written permission of ETAS GmbH.

© Copyright 2023 ETAS GmbH, Stuttgart

The names and designations used in this document are trademarks or brands belonging to the respective owners.

ETAS ISOLAR-A/B V12.7.0 – Error Description Help Document R01 EN – 04.2025

Contents

1 Safety and Privacy Information 5

1.1 Intended Use 5

1.2 Target Group 5

1.3 Classification of Safety Messages 5

1.4 Safety Information 5

1.5 Privacy 5

1.6 Definitions and Abbreviations 5

2 About this Manual 6

3 BSW Validations 7

3.1 BSW AR4x Validations 8

3.1.1 BCT001 8
3.1.2 BCT002 8
3.1.3 BCT003 8
3.1.4 BCT004 9
3.1.5 BCT005 9
3.1.6 BCT006 9
3.1.7 BCT007 10
3.1.8 BCT008 10
3.1.9 BCT009 10
3.1.10 BCT009b 11
3.1.11 BCT011 11
3.1.12 BCT012 11
3.1.13 BCT013 12
3.1.14 BCT014 12
3.1.15 BCT015 12
3.1.16 BCT016 12
3.1.17 BCT017 13
3.1.18 BCT018 13
3.1.19 BCT042 13
3.1.20 BCT047 14
3.1.21 BCT048 14
3.1.22 BCT049 14
3.1.23 BCT051 15
3.1.24 BCT053 15
3.1.25 BCT054 16
3.1.26 BCT055 16
3.1.27 BCT056 16
3.1.28 BCT057 17
3.1.29 BCT059 17
3.1.30 BCT060 17
3.1.31 BCT062 18
3.1.32 BCT063 18
3.1.33 BCT064 18
3.1.34 BCT065 18
3.1.35 BCT066 19
3.1.36 BCT067 19
3.1.37 BCT068 20
3.1.38 BCT069 20
3.1.39 BCT070 20

3.2 Parameter Definition Validations 21
3.2.1 BCTD01 21
3.2.2 BCTD02 21
3.2.3 BCTD03 22
3.2.4 BCTD04 22
3.2.5 BCTD05 22
3.2.6 BCTD06 22
3.2.7 BCTD07 23
3.2.8 BCTD08 23
3.3 Code Generation Validation 24
3.3.1 BAMF005 24
3.3.2 BCT403 24
3.4 Domain Validations 25
4 Contact Information 26

1 Safety and Privacy Information

1.1 Intended Use

1.2 Target Group

1.3 Classification of Safety Messages

The safety messages used here warn of dangers that can lead to personal injury or damage to property:

DANGER

DANGER indicates a hazardous situation that, if not avoided, will result in death or serious injury.

WARNING

WARNING indicates a hazardous situation that, if not avoided, could result in death or serious injury.

CAUTION

CAUTION indicates a hazardous situation that, if not avoided, could result in minor or moderate injury.

NOTICE

NOTICE indicates a situation that, if not avoided, could result in damage to property.

1.4 Safety Information

1.5 Privacy

1.6 Definitions and Abbreviations

Term/Abbreviation	Definition
HW	**H**ard**W**are
SW	**S**oft**W**are
ASW	AUTOSAR **A**pplication **S**oft**W**are
BSW	AUTOSAR **B**asic **S**oft**W**are

2 About this Manual

This document provides list of validations error. For each error message a description of the cause and possible solutions are included.

3 BSW Validations

This section deals with the error description of BSW validations. This is applicable for all the AUTOSAR elements.

- BSW AR4x Validations
- BSW ParamDef Merge Validations
- Code Generation Validations

3.1 BSW AR4x Validations

This section describes about BSW general validations.

3.1.1 BCT001

3.1.1.1 Error Description

The short name of any container value or module configuration value with an upper multiplicity of one (UM=1) should always be identical to the short name of the corresponding parameter definition.

Exceptions:

- If the symbolic name (Only present for parameters) of its immediate children is set to TRUE, then this check is ignored irrespective of UM=1.
- If Multiple Configuration Container (MCC) is set to true for the element, then UM=1 is overridden and hence this check is ignored.

3.1.1.2 How To Solve

To have short name of container same as that of parameter definition when UM=1.

3.1.1.3 Error Description Syntax

The short name of <Element Type> <Element definition short name> is configured as <Element short name> but it should be < Element definition short name >. Hint: The short name of any ECUC <Element Type> value with an upper multiplicity of 1 should always be identical to the short name of the corresponding ParamDef as a convention for easy merging

3.1.2 BCT002

3.1.2.1 Error Description

The value configured for any boolean parameter must be of type boolean.

3.1.2.2 How To Solve

Configure boolean values for boolean parameters.

3.1.2.3 Error Description Syntax

The value <Parameter Value> of element <FQN of parameter> is not boolean.

3.1.3 BCT003

3.1.3.1 Error Description

The value configured for any integer parameter must be of type integer.

3.1.3.2 How To Solve

Configure integer values for integer parameters.

3.1.3.3 Error Description Syntax

The value <Parameter value> of element <FQN of parameter> is not an integer number.

3.1.4 BCT004

3.1.4.1 Error Description

The value configured for any float parameter must be of type float.

3.1.4.2 How To Solve

Configure float values for float parameters.

3.1.4.3 Error Description Syntax

The value <Parameter value> of element <FQN of parameter> is not a floating-point number.

3.1.5 BCT005

3.1.5.1 Error Description

The value configured for any enumeration parameter must be of type enumeration.

3.1.5.2 How To Solve

Configure enumeration values for enumeration parameters.

3.1.5.3 Error Description Syntax

The value <Parameter Value> of element <FQN for parameter> is not a valid literal. See ECU Documentation view for allowed literals.

3.1.6 BCT006

3.1.6.1 Error Description

- Multiple sub-containers should not be configured for a choice container.
- If no sub-container is configured for a choice container.

3.1.6.2 How To Solve

- Only one sub-container configured among the choices provided.
- Configure only one sub-container for a choice container, among the choices provided, if mandatory.

3.1.6.3 Error Description Syntax

- Multiple sub-containers are present for the choice container <FQN of the container>. Only one sub-container is allowed.

- The choice container <FQN of the container>, must have one sub-container mandatorily configured. Hint: Check sub-containers for existence and system conditions that may evaluate as FALSE.

3.1.7 BCT007

3.1.7.1 Error Description

If the configured reference value for a container is invalid.

3.1.7.2 How To Solve

Configure valid reference value for a container.

3.1.7.3 Error Description Syntax

The element <Reference value> referenced by <FQN of reference> does not exist or is inactive.

3.1.8 BCT008

3.1.8.1 Error Description

If short name of an Identifiable exceeds the default length of characters.

3.1.8.2 How To Solve

Configure short name for an Identifiable within specified length of character.

3.1.8.3 Error Description Syntax

ShortName exceeds the default length of <short name length of element> characters. The default length can be set up to 128 characters in Window-> Preferences-> BSW -> Autosar ShortName Length.

3.1.9 BCT009

3.1.9.1 Error Description

All Identifiable (e.g., Containers that has a short name) should have a non-unique short name.

3.1.9.2 How To Solve

- To have only one of the identifiable elements with a unique short name.
- Give different absolute qualified paths for the two elements.

3.1.9.3 Error Description Syntax

Non-unique short name for the element <FQN of the element>.

3.1.10 BCT009b

3.1.10.1 Error Description

When the same short name is used for several sub container under same parent container in a same resource. The limitations considered are, elements created in model by forwarding will not be considered for validation and elements with System condition/Post Build variation points configured will not be validated.

3.1.10.2 How To Solve

Configure distinct short name for sub containers which are of different parameter definition.

3.1.10.3 Error Description Syntax

Multiple elements with name <FQN of Identifiable> are configured in resource <value file name>.

3.1.11 BCT011

3.1.11.1 Error Description

The function value of the textual parameter is not within the regular expression pattern.

3.1.11.2 How To Solve

Provide a function value for the textual parameter which follows the regular expression pattern.

3.1.11.3 Error Description Syntax

<Value of parameter> is an invalid function with special characters.

3.1.12 BCT012

3.1.12.1 Error Description

When the value provided for function name parameter is not matching regex pattern:

- For version lesser than AR4.2.2 - [a-zA-Z]([a-zA-Z0-9]|_[a-zA-Z0-9])*_?
- For version greater than AR4.2.2 - [a-zA-Z][a-zA-Z0-9_]*

3.1.12.2 How To Solve

Provide a function value for the textual parameter which follows the regular expression pattern.

3.1.12.3 Error Description Syntax

ShortName <Parameter short name> is invalid. It must follow the pattern <regular expression specific to version>.

3.1.13 BCT013

3.1.13.1 Error Description

If value file contains modules/containers/parameters/references for which no parameter definition or rule exist.

3.1.13.2 How To Solve

Modules/containers/parameters/references should contain parameter definition or rule configured.

3.1.13.3 Error Description Syntax

Invalid field: There is no rule/definition for the configured element <short name of element>.

3.1.14 BCT014

3.1.14.1 Error Description

If the lower multiplicity of a module/container/parameter/reference is breached.

3.1.14.2 How To Solve

Configure module/container/parameter/reference values to meet the lower multiplicity.

3.1.14.3 Error Description Syntax

The number of instances of element <definition name of element> in parent <FQN of parent element> is less than the lower multiplicity of <lower multiplicity value of element> <post build variant name for lower multiplicity>.

3.1.15 BCT015

3.1.15.1 Error Description

If the upper multiplicity of a module/container/parameter/reference is breached.

3.1.15.2 How To Solve

Configure module/container/parameter/reference values to meet the upper multiplicity.

3.1.15.3 Error Description Syntax

The number of instances of element <definition name of element> in parent <FQN of parent element> is greater than the upper multiplicity of <upper multiplicity value of element> <post build variant name for upper multiplicity>.

3.1.16 BCT016

3.1.16.1 Error Description

When the value provided for the numerical parameter is not within the specified range.

For AR45 schema,

For float parameters in AR45 schema, OPEN and CLOSED interval types are present where:

- OPEN means the value is excluded from the range. It is denoted by '( )'.
- CLOSED means the value is included in the range. It is denoted by '[ ]'.

Ex: If the range is MIN = OPEN: 1 and MAX = CLOSED: 5 .The range is (1, 5] i.e., the value can lie between 1.1 to 5.

3.1.16.2 How To Solve

Provide a value for the numerical parameter which falls in the specified range.

3.1.16.3 Error Description Syntax

The value <Parameter value> of element <FQN of parameter> is not within the specified range of <lower limit value for parameter> to <upper limit value for parameter>.

3.1.17 BCT017

3.1.17.1 Error Description

When the value provided for the textual parameter is not within the specified range.

3.1.17.2 How To Solve

Provide the value for the textual parameter which falls in the specified range.

3.1.17.3 Error Description Syntax

The text <parameter value> of element <FQN of parameter> is not within the specified text length range of <minimum range> to <maximum range>.

3.1.18 BCT018

3.1.18.1 Error Description

When there is an error in system condition evaluation.

3.1.18.2 How To Solve

Configure valid system condition for an element.

3.1.18.3 Error Description Syntax

Error in system constant in value or system condition on element <FQN of element>. For the second case more information is available on opening the Syscond Editor. SystemCondition: <system condition>.

3.1.19 BCT042

3.1.19.1 Error Description

If the short name of the MultipleConfigurationContainer is not a valid C Identifier.

3.1.19.2 How To Solve

Configure a proper C Identifier value as the short name for MultipleConfigurationContainer.

3.1.19.3 Error Description Syntax

The value <element short name> of element <FQN of parent element> is not a valid C Identifier.

3.1.20 BCT047

3.1.20.1 Error Description

When elements of type REQUIRES-INDEX are configured in multiple files under same merged parent.

3.1.20.2 How To Solve

Merge all instances of type REQUIRES-INDEX element parent to one file.

3.1.20.3 Error Description Syntax

The type <Element shortName> is marked with REQUIRES-INDEX and it is not allowed to split instances across several files. Please merge all instances of type <Element definition shortName> in parent <FQN of parent element> into one file. Affected files: '<Files containing split elements>'.

3.1.21 BCT048

3.1.21.1 Error Description

If the project is valid for PB validation and if the element is a PB element, and the configured PB Criterion for the element is not present among the list of available criterions in project.

3.1.21.2 How To Solve

Configure an appropriate PB Criterion for each element from the list of criterions present in the project.

3.1.21.3 Error Description Syntax

PostBuildCriterion <pre-defined variant name> used in <FQN of element> is not existing in project. Please add the criterion to project or correct the variation point.

3.1.22 BCT049

3.1.22.1 Error Description

- If the project is valid for PB validation and if the element is a PB element, then if
- The element configured with PBVP(Post Build Variation Point) matches to the PBVP configured to its parent element.

- The element configured with PBVP matches to the PBVP configuration present in the project if none of its parent is configured with a PBVP.

3.1.22.2 How To Solve

- Configure an appropriate PBVP configuration for the element based on its parent configuration.
- Configure an appropriate PBVP configuration for the element based on its PBVP configuration present in the project.

3.1.22.3 Error Description Syntax

The element <FQN of element> is configured with a PostBuild VariationPoint <Variant name>. Either no TopLevelPredefinedVariant exist, or the condition will not be fulfilled for any variant. Please check if the variation-point and/or the variants are configured correctly.

3.1.23 BCT051

3.1.23.1 Error Description

The parameter/reference in configured with an empty value which is not allowed for this element type.

3.1.23.2 How To Solve

Configure values for parameters/references for the required type.

3.1.23.3 Error Description Syntax

The element <element short name> in <FQN of parent element> is configured without value which is not allowed for this element type. Please configure valid value or remove the element.

3.1.24 BCT053

3.1.24.1 Error Description

- If the project is valid for PB validation.
- If the element is a container and has a PBVP configured even though its PostBuildVariantMultiplicity is set to FALSE.
- If the element is a parameter/reference value and has PBVP configured even though if its PostBuildVariantMultiplicity or PostBuildVariantValue is set to FALSE.

3.1.24.2 How To Solve

- Remove the invalid PBVP for the container element if its PostBuildVariantMultiplicity is set to FALSE.
- Remove the invalid PBVP for the parameter/reference element if its PostBuildVariantMultiplicity or PostBuildVariantValue is set to FALSE.

3.1.24.3 Error Description Syntax

The element <FQN of element> is configured with a PostBuild VariationPoint which is not allowed on elements of type <FQN of element definition>. Please remove the Variation-Point.

3.1.25 BCT054

3.1.25.1 Error Description

If the project is valid for PB validation and if the elements PostBuildVariantValue is set to FALSE, and the element has the different value configured across different PBVP of its parent element.

3.1.25.2 How To Solve

Configure the element with the same value across all variants of its parent when the PostBuildVariantValue is set to FALSE.

3.1.25.3 Error Description Syntax

The value <Element value> of element <FQN of element definition> is inconsistent in the following variant(s) : <Variant name>. Hint: PostBuildVariantValue is set to false.

3.1.26 BCT055

3.1.26.1 Error Description

If the project is valid for PB validation and if the elements PostBuildVariantMultiplicity is set to FALSE, and the element has the different number of its instances configured across different PBVP of its parent element.

3.1.26.2 How To Solve

Configure the element with the same number of its instances across all variants of its parent when the PostBuildVariantMultiplicity is set to FALSE.

3.1.26.3 Error Description Syntax

The element <FQN of element> is inconsistent in the following variant(s): <Variant name>. Hint: PostBuildVariantMultiplicity is set to false.

3.1.27 BCT056

3.1.27.1 Error Description

- For Post Build enabled projects if the referred Post Build Variants exist.
- This validation does not throw an error if the project version in below AR42.

3.1.27.2 How To Solve

Configure the valid post Build variants in a post build enabled project.

3.1.27.3 Error Description Syntax

The element <FQN of element> refers to the <Variant name> that does not exist.

3.1.28 BCT057

3.1.28.1 Error Description

When configuration values of a module are in multiple AR Package structures.

3.1.28.2 How To Solve

Configure module within same package structure.

3.1.28.3 Error Description Syntax

Configuration values for module <Module name> are in multiple AR Package structures and will not be merged. <FQN of module element> package structure is found in <Value file>.Hint: Use the same AR Package structure in all EcucValueFiles. Preferably RB/UBK/Project/EcucModuleConfigurationValuess.

3.1.29 BCT059

3.1.29.1 Error Description

When configuration values of a module are in multiple AR Package structures.

3.1.29.2 How To Solve

Configure module within same package structure.

3.1.29.3 Error Description Syntax

Configuration values for module <Module name> are in multiple AR Package structures and will not be merged. <FQN of module element> package structure is found in <Value file>.Hint: Use the same AR Package structure in all EcucValueFiles. Preferably RB/UBK/Project/EcucModuleConfigurationValuess.

3.1.30 BCT060

3.1.30.1 Error Description

Mandatory long name(s) is not configured for an identifiable.

3.1.30.2 How To Solve

Configure the mandatory LongName(s) for an identifiable.

3.1.30.3 Error Description Syntax

The setting of LONG-NAME <Mandatory long names> is mandatory for the element <FQN of element>.

3.1.31 BCT062

3.1.31.1 Error Description

If the length of linker symbol elements exceeds the specified length.

3.1.31.2 How To Solve

Configure linker symbol elements within the specified length.

3.1.31.3 Error Description Syntax

The value <value of element> of Linker Symbol element <FQN of element> is greater than 255 characters.

3.1.32 BCT063

3.1.32.1 Error Description

If the value of linker symbol elements does not match the regular expression.

3.1.32.2 How To Solve

Configure linker symbol elements which match the regular expression.

3.1.32.3 Error Description Syntax

The value <value of element> of Linker Symbol element <FQN of element> does not match the Regular Expression <Regular expression pattern>.

3.1.33 BCT064

3.1.33.1 Error Description

In a project, there are same AUTOSAR and MSR constants with different values present in multiple files.

3.1.33.2 How To Solve

AUTOSAR and MSR constants should be different for a project.

3.1.33.3 Error Description Syntax

The constant <AR-MSR constant name> is present in multiple files <AUTOSAR file name, MSR file name> with different values. The project should define it once.

3.1.34 BCT065

3.1.34.1 Error Description

If a project has module configuration values without any container value configured. This error is thrown for projects whose version is AR 4.6.

3.1.34.2 How To Solve

The module should be removed or there must be at least one container configured under the module.

3.1.34.3 Error Description Syntax

There are no containers defined under module <module_name>. Please configure container or remove the module.

3.1.35 BCT066

3.1.35.1 Error Description

- For Post Build enabled projects if the PostBuildVariantUsed or PostBuildVariantSupport is set to false.
- This validation does not throw an error if the EcuC Value file version in below 4.4 or if mixed.

3.1.35.2 How To Solve

Set the PostBuildVariantUsed or PostBuildVariantSupport to true in a post build enabled project.

3.1.35.3 Error Description Syntax

PBV is configured for element <Element Name>. Please set PostBuildVariantSupport to true and PostBuildVariantUsed to true for module <Module Name>.

3.1.36 BCT067

3.1.36.1 Error Description

- For Post Build enabled projects if the PostBuildVariantUsed for Module has contradicted values.
- This validation does not throw an error if the EcuC Value file version in below 4.4 or if mixed.

3.1.36.2 How To Solve

Correct the PostBuildVariantUsed to the same value in a post build enabled project.

3.1.36.3 Error Description Syntax

The configured PostBuildVariantUsed for module <Module Short Name> is conflicting. Please evaluate the files <Resource1 name, Resource2 name, …>, and correct the conflict by setting same value.

3.1.37 BCT068

3.1.37.1 Error Description

- For Post Build enabled projects if the PostBuildVariantUsed is true when Post-BuildVariantSupport is false.
- This validation does not throw an error if the version of the EcucValues file is below 4.4 or if it is mixed mode.

3.1.37.2 How To Solve

Correct the PostBuildVariantUsed to false for module value when PostBuildVariantSupport is false in a post build enabled project.

3.1.37.3 Error Description Syntax

PostBuildVariantSupport for Module definition <Module Definition Short Name> is false. Please set PostBuildVariantUsed to false for module value <Module Value Short Name>.

3.1.38 BCT069

3.1.38.1 Error Description

If Parameter under a container is not configured to a value that is recommended or mandated by the supplier, then the error is thrown.

3.1.38.2 How To Solve

Configure the Parameter under the container, to a value that is mandated or recommended by the supplier.

3.1.38.3 Error Description Syntax

<FQN path of Parent Container> does not have <Parameter Short Name> configured to <Parameter Value> as <mandated/recommended> by its supplier.

3.1.39 BCT070

3.1.39.1 Error Description

If Container under a Module or Sub-container under a Container is not configured with a Short Name that is recommended or mandated by the supplier, then the error is thrown.

3.1.39.2 How To Solve

Configure the Container under a module/container, with a Short Name that is mandated or recommended by the supplier.

3.1.39.3 Error Description Syntax

<FQN path of Parent Container or FQN path of Module > does not have <Container Short Name> <Expected Container Short Names> configured as <mandated/recommended> by its supplier.

3.2 Parameter Definition Validations

This section describes about BSW paramdef merge validations.

3.2.1 BCTD01

3.2.1.1 Error Description

There are multiple module definitions with same module name having same or different name spaces. This error is thrown for projects whose version is below 4.2.

3.2.1.2 How To Solve

To have only one module definition with a unique short name.

3.2.1.3 Error Message Syntax

The module "Module_Name" is defined multiple times in different files: ["FQN", ("ResourceURI1", "ResourceURI1")]. Duplicated definition in the project will impact negatively the proper execution of processors (codegenerators). Please check the files and remove the file(s) containing the duplicated definition of the module.

3.2.2 BCTD02

3.2.2.1 Error Description

There are multiple module definitions with same module name in different namespaces. This error is thrown for projects whose version is 4.2 and above and is also applicable for multi-driver modules.

3.2.2.2 How To Solve

To have the module definitions with the same namespace.

3.2.2.3 Error Message Syntax

- For non-Multi Driver Modules: The module "Module_Name" is defined multiple times in different packages: ["FQN","ResourceName"] ["FQN","ResourceName]. The shortnames of the modules have to be globally unique irrespective of the package. Duplicated definition in the project will impact negatively the proper execution of processors(codegenerators). Please check the files and remove the file(s) containing the duplicated definition of the module.
- For Multi Driver Modules: The module "Module_Name" is defined multiple times in different packages: ["FQN","ResourceName"] ["FQN","ResourceName]. The shortnames of the modules have to be globally unique irrespective of the package or must have respective entries in BSWMDT file. Duplicated definition in the project will impact negatively the proper execution of processors(codegenerators). Please check the files and remove the file(s) containing the duplicated definition of the module. If the definitions are picked up from multiple vendors, it must have vendor specific information in BSWMDT file.

3.2.3 BCTD03

3.2.3.1 Error Description

Missing mandatory attributes for the Module/Container/Parameter definitions.

3.2.3.2 How To Solve

Configure the mandatory attributes for Module/Container/Parameter definitions.

3.2.3.3 Error Message Syntax

No attributes defined: There are no attributes defined for “FQN” in any of the files “Resource1, Resource2”. Please contact the owner of the affected Paramdef files.

3.2.4 BCTD04

3.2.4.1 Error Description

Presence of redundant attribute(s) for the same module/container definition.

3.2.4.2 How To Solve

Configure attribute(s) for module/container definitions in any one of the paramdef files.

3.2.4.3 Error Message Syntax

The module "Module_Name" is invalid due to wrong definition of non-splittable attributes "list of attributes" for "FQN" present in paramdef files "Resource1, Resource2". Please contact the owner of the affected paramdef files to resolve this.

3.2.5 BCTD05

3.2.5.1 Error Description

Presence of redundant parameter(s) for the same module/container definition.

3.2.5.2 How To Solve

Configure parameter(s) for module/container definitions in any one of the paramdef files.

3.2.5.3 Error Message Syntax

The complete module "Module_Name" is invalid due to redefinition of parameter for "parameter FQN". The redundancy in paramdef files "Resource1, Resource2" need to be removed. Please contact the owner of the affected paramdef files.

3.2.6 BCTD06

3.2.6.1 Error Description

If a symbolic reference points to a container which contains more than one parameter having SYMBOLIC NAME VALUE defined as true.

3.2.6.2 How To Solve

The container to which symbolic reference points should have exactly one parameter having SYMBOLIC NAME VALUE defined as true.

3.2.6.3 Error Message Syntax

The reference “Reference_Name” destination “container FQN” has more than one parameter with SymbolicNameValue true.

3.2.7 BCTD07

3.2.7.1 Error Description

URI Reference Violation

3.2.7.2 How To Solve

The "Element_Name" "Attribute" value must match the value mentioned in the URI Destination Policy or must be mentioned in the URI Destination Policy is not present in the Paramdef. "TARGET-CONTAINER" must not contain Parameters or References directly defined under the URI Policy.

3.2.7.3 Error Message Syntax

- URI Reference Violation

  The "Element" "Element_Name" "Attribute" value doesn't match the value mentioned in the URI Destination Policy.

- URI Reference Violation

  The "Element" "Element_Name" mentioned in the URI Destination Policy is not present in the Paramdef.

- URI Reference Violation

  Nesting Contract is "TARGET-CONTAINER" and hence cannot contain Parameters or References directly defined under the URI Policy.

3.2.8 BCTD08

3.2.8.1 Error Description

If a project has module definition without any container configured. This error is thrown for projects whose version is AR 4.6.

3.2.8.2 How To Solve

The module should be removed or there must be at least one container configured under the module.

3.2.8.3 Error Message Syntax

There are no containers defined for “Module FQN” in “Resouce1, Resource2”. Please contact the owner of the affected paramdef files.

3.3 Code Generation Validation

3.3.1 BAMF005

3.3.1.1 Error Description

This is a very critical Warning. The name of the Build Action must be unique. This Message is shown if two or more Build Actions have the same action name. There is no 'merge' of actions done. The first found Build Action will be included in configuration. All data of second or other 'instances' are left out.

3.3.1.2 How To Solve

Check all bamf.arxml files for occurrences of this action name.

3.3.1.3 Error Message Syntax

Action '<actionName>': There are n instances found with this action name. Taking first one - Ignoring others!

3.3.2 BCT403

3.3.2.1 Error Description

Triggered during code generation for the BAMF actions in which some data is forwarded.

All forwarded data will be validated against output model references from the corresponding BAMF file.

In case for a forwarded element no matching output model reference could be found, this validation will fail.

3.3.2.2 How To Solve

The responsible of the action must add output model references for missing forwarded elements to the action declaration in the bamf file.

3.3.2.3 Error Message Syntax

Forwarded element(s) not declared in action <Action name>: <Forwarded elements>.

3.4 Domain Validations

These validate the project configuration against the AUTOSAR Domain validations when Live Validation preference is enabled. These validation errors will be logged under the constraint ID “BSWDomainValidations”.

NOTE: Live Validation is a prototype feature, and not visible by default. To use it, select **Window > Preferences > Tool Customization > General Features**. Search for “Live Validation”, select “Live Validation” from the results and click **Apply and Close.** For further details, refer section 11.8.

4 Contact Information

Technical Support

For details of your local sales office as well as your local technical support team and product hotlines, take a look at the website: www.etas.com/hotlines

ETAS Headquarters

ETAS GmbH
Borsigstraße 24
70469 Stuttgart
Germany

Phone: +49 711 3423-0
Fax: +49 711 3423-2106
Internet: www.etas.com

Figures

Tables

Index

No index entries found.

Revision History