

Command/Event	Length	CMD0	CMD1
Device Subgroup			
SNP Power Up	0	0x55 (Async)	0x01
SNP Mask Event	2	0x35 (Sync Req)	0x02
SNP Mask Event Response	2	0x75 (Sync Resp)	0x02
SNP Get Revision	0	0x35 (Sync Req)	0x03
SNP Get Revision Response	13	0x75 (Sync Resp)	0x03
SNP Encapsulated HCI	N	0x55 (Async)	0x04
SNP Encapsulated HCI Response	N	0x55 (Async)	0x04
SNP Event Indication	N	0x55 (Async)	0x05
SNP Get Status	0	0x55 (Async)	0x06
SNP Get Status Response	4	0x55 (Async)	0x06
SNP Invalid Synchronous Command Indication	0	0x75 (Sync Resp)	0x07
SNP Test	0	0x35 (Async Req)	0x10
SNP Test Response	6	0x75 (Async Resp)	0x10
GAP Subgroup			
SNP Start Advertisement	14	0x55 (Async)	0x42
SNP Set Advertisement Data	N	0x55(Async)	0x43
SNP Set Advertisement Data Response	1	0x55 (Async)	0x43
SNP Stop Advertisement	0	0x55 (Async)	0x44
SNP Update Connection Parameters	10	0x55 (Async)	0x45
SNP Update Connection Parameter Response	3	0x55 (Async)	0x45
SNP Terminate Connection	3	0x55 (Async)	0x46
SNP Set GAP Parameter	4	0x35 (Sync Req)	0x48
SNP Set Parameter Response	1	0x75 (Sync Resp)	0x48
SNP Get Gap Parameter	4	0x35 (Sync Req)	0x49
SNP Get Parameter Response	5	0x75 (Sync Resp)	0x49
GATT Subgroup			
SNP Add Service	N	0x35 (Sync Req)	0x81
SNP Add Service Response	1	0x75 (Sync Resp)	0x81
SNP Add Characteristic Value Declaration	N	0x35 (Sync Req)	0x82
SNP Add Characteristic Value Declaration Response	3	0x75 (Sync Resp)	0x82
SNP Add Characteristic Descriptor Declaration	N	0x35 (Sync Req)	0x83
SNP Add Characteristic Descriptor Declaration Response	N	0x75 (Sync Resp)	0x83
SNP Register Service	0	0x35 (Sync Req)	0x84
SNP Register Service Response	5	0x75 (Sync Resp)	0x84

SNP Get Attribute Value	2	0x35 (Sync Req)	0x85
SNP Get Attribute Value Response	N	0x75 (Sync Resp)	0x85
SNP Set Attribute Value	2	0x35 (Sync Req)	0x86
SNP Set Attribute Value Response	3	0x75 (Sync Resp)	0x86
SNP Characteristic Read Confirmation	N	0x55 (Async)	0x87
SNP Characteristic Write Confirmation	N	0x55 (Async)	0x88
SNP Send Notification Indication	N	0x55 (Async)	0x89
SNP Send Notification Indication Response	3	0x55 (Async)	0x89
SNP CCCD Updated Confirmation	N	0x55 (Async)	0x8B
SNP Set GATT Parameter	N	0x35 (Sync Req)	0x8C
SNP Set GATT Parameter Response	N	0x75 (Sync Resp)	0x8C
SNP Get GATT Parameter	N	0x35 (Sync Req)	0x8D
SNP Get GATT Parameter Response	N	0x75 (Sync Resp)	0x8D