

There are four preferred pin combinations for UTMI signals. Chose one based on IO voltage bank and signal routing considerations.

Monahans P - UTMI Pin Mapping, Group 1

GPI010	VCC_I04	CLKOUT
GPI041	VCC_I04	DATA0
GPI042	VCC_I04	DATA1
GPI043	VCC_I04	DATA2
GPI044	VCC_I04	DATA3
GPI045	VCC_I04	DATA4
GPI046	VCC_I04	DATA5
GPI047	VCC_I04	DATA6
GPI048	VCC_I04	DATA7
GPI073	VCC_LCD	TXREADY
GPI039	VCC_I04	TXVALID
GPI035	VCC_I04	RXACTIVE
GPI034	VCC_I04	RXVALID
GPI036	VCC_I04	RXERROR
GPI037	VCC_I04	OPMODE0
GPI038	VCC_I04	OPMODE1
GPI074	VCC_LCD	RESET
GPI065	VCC_LCD	XCVRSELECT
GPI066	VCC_LCD	TERMSELECT
GPI067	VCC_LCD	SUSPENDN
GPI068	VCC_LCD	LINESTATE0
GPI069	VCC_LCD	LINESTATE1
*		VBUSDETECT

* VBUSDETECT can be placed on any available GPIO

Monahans P - UTMI Pin Mapping, Group 2

GPI010	VCC_I04	CLKOUT
GPI049	VCC_CI	DATA0
GPI050	VCC_CI	DATA1
GPI051	VCC_CI	DATA2
GPI052	VCC_CI	DATA3
GPI053	VCC_CI	DATA4
GPI054	VCC_CI	DATA5
GPI055	VCC_CI	DATA6
GPI056	VCC_CI	DATA7
GPI073	VCC_LCD	TXREADY
GPI070	VCC_LCD	TXVALID
GPI059	VCC_CI	RXACTIVE
GPI058	VCC_CI	RXVALID
GPI060	VCC_CI	RXERROR
GPI061	VCC_CI	OPMODE0
GPI062	VCC_CI	OPMODE1
GPI093	VCC_I06	RESET
GPI094	VCC_I06	XCVRSELECT
GPI095	VCC_I06	TERMSELECT
GPI096	VCC_I06	SUSPENDN
GPI090	VCC_I06	LINESTATE0
GPI091	VCC_I06	LINESTATE1
*		VBUSDETECT

* VBUSDETECT can be placed on any available GPIO

Monahans P - UTMI Pin Mapping, Group 3

GPI010	VCC_I04	CLKOUT
GPI049	VCC_CI	DATA0
GPI050	VCC_CI	DATA1
GPI051	VCC_CI	DATA2
GPI052	VCC_CI	DATA3
GPI053	VCC_CI	DATA4
GPI054	VCC_CI	DATA5
GPI055	VCC_CI	DATA6
GPI056	VCC_CI	DATA7
GPI073	VCC_LCD	TXREADY
GPI083	VCC_I06	TXVALID
GPI086	VCC_I06	RXACTIVE
GPI085	VCC_I06	RXVALID
GPI087	VCC_I06	RXERROR
GPI088	VCC_I06	OPMODE0
GPI0104	VCC_I06	OPMODE1
GPI098	VCC_I06	RESET
GPI099	VCC_I06	XCVRSELECT
GPI0100	VCC_I06	TERMSELECT
GPI0101	VCC_I06	SUSPENDN
GPI0102	VCC_I06	LINESTATE0
GPI0103	VCC_I06	LINESTATE1
*		VBUSDETECT

* VBUSDETECT can be placed on any available GPIO

Monahans P - UTMI Pin Mapping, Group 4

GPI010	VCC_I04	CLKOUT
GPI041	VCC_I04	DATA0
GPI042	VCC_I04	DATA1
GPI043	VCC_I04	DATA2
GPI044	VCC_I04	DATA3
GPI045	VCC_I04	DATA4
GPI046	VCC_I04	DATA5
GPI047	VCC_I04	DATA6
GPI048	VCC_I04	DATA7
GPI073	VCC_LCD	TXREADY
GPI039	VCC_I04	TXVALID
GPI030	VCC_I04	RXACTIVE
GPI034	VCC_I04	RXVALID
GPI036	VCC_I04	RXERROR
GPI037	VCC_I04	OPMODE0
GPI0108	VCC_I06	OPMODE1
GPI074	VCC_LCD	RESET
GPI065	VCC_LCD	XCVRSELECT
GPI097	VCC_I06	TERMSELECT
GPI067	VCC_LCD	SUSPENDN
GPI0107	VCC_I06	LINESTATE0
GPI069	VCC_LCD	LINESTATE1
*		VBUSDETECT

* VBUSDETECT can be placed on any available GPIO