

TMS320DM270 Enhanced Function

Rev.1.0

as of Mar/14/2003

No.	Module	Title	Classification	Description
1	DSP Subchip	AMR ROM code	Spec. change	Support AMR ROM code into DSP ROM area.
2	VENC	Synchronize HD/VD	Add'l func.	Enable to synchronize HD/VD with external signal from GIO pin. HD is inputted from GIO30 which is switched by FSEL[29] of GIO register. VD is inputted from GIO33 which is switched by FSEL[29] of GIO register.
3	DSP Sub	External interruption to DSP	Add'l func.	Enable to interrupt to DSP from external host via GIO. The interruption to DSP is intended to input from GIO6 pin.
4	SDRAM I/O	SDRAM I/F pin	Spec. change	Set Hi-Z state when power of SDRAM memory is off. SDR_DQx=pulldn enable, SDR_CLK="L" by register in CLKC. EMIF register BUSRLS (30A18h) SDREL bit=1.
5	VENC	RGB565/666 out	Add'l func.	Support RGB565 (16-bit depth) / RGB666 (18-bit depth) data output.
6	OSD	Interruption	H/W improvement	Enable a interruption to ARM at end of VSYNC signal from VENC, when OSD register VIDEOWIN_MODE (30682h) ACTx bit is "1".
7	SDRC	Refresh counter	H/W improvement	8 bit refresh counter will be cleared by "0" when SDRC register REFCTL (309A8h) REFEN bit is "0".
8	VENC	Initial state of VSYNC and HSYNC	Spec. change	Change initial state of VSYNC and HSYNC to "L".