

Homework Assignment #1 - Theory Problems

September 16, 2020

Instructor: Kyungim Baek

Name: Frendy Lio Can

Problem 1

Let $p = \begin{bmatrix} x \\ y \\ 1 \end{bmatrix}$ and $p' = (S \cdot R \cdot T) \cdot p$.

$$\begin{aligned}
 p' &= \begin{bmatrix} s_x & 0 & 0 \\ 0 & s_y & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} \cos\theta & -\sin\theta & 0 \\ \sin\theta & \cos\theta & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 0 & t_x \\ 0 & 1 & t_y \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix} \\
 &= \begin{bmatrix} s_x & 0 & 0 \\ 0 & s_y & 0 \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} \cos\theta & -\sin\theta & t'_x \\ \sin\theta & \cos\theta & t'_y \\ 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix} \\
 &= \begin{bmatrix} S' & 0 \\ 0 & 1 \end{bmatrix} \begin{bmatrix} R' & t' \\ 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix} \\
 &= \begin{bmatrix} S'R' & S't' \\ 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix}
 \end{aligned}$$

Where

$$\begin{aligned}
 S' &= \begin{bmatrix} S_x & 0 \\ 0 & S_y \end{bmatrix} \\
 R' &= \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix} \\
 t' &= \begin{bmatrix} t_x \cos\theta - t_y \sin\theta \\ t_x \sin\theta + t_y \cos\theta \end{bmatrix}
 \end{aligned}$$

Thus, we can observed that the SRT matrix and the TRS matrix from the lecture are different since:

$$SRT \neq TRS$$

$$\begin{bmatrix} S'R' & S't' \\ 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix} \neq \begin{bmatrix} R'S' & t \\ 0 & 1 \end{bmatrix} \begin{bmatrix} x \\ y \\ 1 \end{bmatrix}, \quad t = \begin{bmatrix} t_x \\ t_y \end{bmatrix}$$

Problem 2

$$\begin{aligned}
 A &= U\Sigma V^T \Rightarrow A^T = V\Sigma U^T \\
 &\therefore \\
 AA^T &= U\Sigma V^T V\Sigma^T U^T \Leftrightarrow \\
 &\Leftrightarrow AA^T = U\Sigma\Sigma^T U^T \\
 &\Leftrightarrow AA^T U = U\Sigma\Sigma^T U \\
 &\Leftrightarrow AA^T U = U\Sigma\Sigma^T
 \end{aligned}$$

Thus, we can observed that $\Sigma\Sigma^T$ must be the eigenvalue matrix of AA^T . Therefore each $\sigma^2 = \lambda(A^T A)$.

Assuming that A is a diagonal Matrix, it implies that the square root of eigenvalues are the singular values since $AA^T = \sigma_i^2 \frac{u_i}{v_i} = \sigma_i^2 \frac{u_i}{u_i}$ where σ_i are the singular value and $u_i = v_i$ for this case.

Finally, we can conclude that AA^T are the columns of U .

Problem 3

A (Total area of sensor) = 512x512 pixels

C (Center) = (256, 256)

$P(1, 2, 8) \rightarrow (356, 456)$ (In meters and pixels) $Q(-3, -1, 16)$

From the projection of P we deduce the following:

$x - axis \rightarrow 1 : 100(356 - 256 = 100)$

$y - axis \rightarrow 2 : 200(456 - 256 = 200)$

We can observe that $Q_z = 16$ is 2 time bigger than $P_z = 8$. This implies that P_x and P_y are 4 time bigger than Q_x and Q_y .

Therefore,

$x - axis \rightarrow -3 : -75 \therefore for P_x 1 : 100 \therefore Q_y 1 : 25 \rightarrow (256 - 75 = 181)$

$y - axis \rightarrow -1 : -25 \therefore for P_y 1 : 100 \therefore Q_y 1 : 25 \rightarrow (256 - 25 = 231)$

Projection of Q is (231, 181)