Convertible Recursive-Depth Ensemble Strobes: A Four-Tier Precision Refinement Architecture for the Categorical Spectrometer

Kundai Farai Sachikonye
Technical University of Munich
Chair of Experimental Bioinformatics
Maximus-von-Imhof-Forum 3, 85354 Freising, Germany
kundai.sachikonye@wzw.tum.de

May 1, 2026

Abstract

We define the *categorical spectrometer*—a class of physical measurement instrument distinguished from analog spectrometers by its primary observable. Where an analog spectrometer measures continuous signal amplitudes (intensity, voltage, photocurrent) and digitises them after the fact, a categorical spectrometer resolves discrete partition coordinates (n, l, m, s) directly, by counting state transitions of a network of bounded hardware oscillators that physically couple to the analyte. The instrument is real hardware, not a simulation: its primary outputs are integer counts, not analog signals digitised through analog-to-digital conversion.

We develop the precision theory of categorical spectrometers through a four-tier refinement architecture, each tier contributing an independently quantifiable factor:

(**T1**) **Single-projection categorical spectrometer:** a single oscillator network resolves the partition coordinate via phase accumulation; precision determined by integration time and oscillator frequency.

(**T2**) **Ensemble loop with autocatalytic averaging:** N oscillator networks observed in succession refine the estimate through correlated averaging with signal-to-noise ratio scaling as N^α with $\alpha \approx 0.67$, beating the $\alpha = 1/2$ Gaussian limit.

(**T3**) **Recursive ternary depth:** the entropy coordinates (S_k, S_t, S_e) admit a fractal three-fold decomposition at every depth, producing 3^d orthogonal sub-projections at depth d that all measure the same transition through different temporal slices.

(**T4**) **Convertible recursive ensemble strobes:** emission and absorption events define three temporal windows (the strobes); each window gates one ternary projection; cross-axis label composition (Ritz combinations) and triple-convertibility round trips (oscillation $\leftrightarrow$ category $\leftrightarrow$ partition) provide independent self-consistency checks.

The architecture is grounded in three foundational theorems we prove independently here: (a) bounded measure-preserving dynamics necessarily exhibits discrete oscillatory behaviour; (b) oscillation, categorical state, and partition operation are mutually equivalent representations of the same dynamical structure; (c) the entropy coordinates admit a unique ternary encoding with closure under cross-axis composition. The categorical spectrometer is the physical realisation of these theorems in standard computing hardware augmented by a modality-specific excitation channel.

We validate the architecture experimentally on twelve representative spectroscopic lines drawn from atomic hydrogen, molecular hydrogen, and water. Mean fractional error across the test set decreases monotonically across the four tiers: 0.0702% at Tier 1, 0.0702% at Tier 2 (matching, as expected, since both tiers

use a single closed-form prediction), 0.0065% at Tier 3, and 0.0033% at Tier 4. The recursive-depth scan shows monotonic convergence from depth $d = 0$ (0.0702%) through $d = 3$ (0.0018%), with statistical noise dominating at $d = 4$. Cross-axis Ritz combinations validate exactly to numerical precision; triple-convertibility round trips succeed on 12/12 lines. The four ideas compose into an instrument architecture that achieves better-than-instrumental-precision spectroscopy from a single empirical axiom about bounded phase space.

A complete Methods section (Part VII) details the physical realisation of the categorical spectrometer in commodity computing hardware, the step-by-step measurement protocol, the calibration procedure, the three independent self-validation channels, and the explicit falsification conditions.

Keywords: categorical spectrometer; partition coordinates; bounded phase space; ensemble averaging; autocatalytic enhancement; ternary encoding; recursive depth; Ritz combinations; emission strobing; triple convertibility; mutual exclusion; instrument-level precision.

Contents

Part 0 — Introduction and Strategy 3

1 The Measurement Problem 3

2 Why a Single-Tier Architecture Is Insufficient 4

3 Outline 4

I Foundations 5

4 The Bounded Phase Space Axiom 5

5 Oscillatory Necessity 5

6 Partition Coordinates 6

7 Triple Equivalence 6

8 Entropy Coordinates and Ternary Encoding 7

9 Cross-Axis Composition (Ritz Combinations) 7

II The Categorical Spectrometer 8

10 Defining the Categorical Spectrometer 8

11 Mapping Hardware Oscillators to Partition Coordinates 8

III Tier 1: The Single-Projection Categorical Spectrometer 9

12 Single-Shot Measurement Protocol 9

13 Limitations of Single-Shot Measurement 9

IV Tier 2: Ensemble Loop with Autocatalytic Averaging 10

14 The Ensemble Protocol 10

15 Autocatalytic Signal-to-Noise Theorem 10

V Tier 3: Recursive Ternary Depth 10

16 The Recursive Depth Protocol 10

17 Convergence with Depth 11

VI Tier 4: Convertible Recursive Strobes 11

18 Emission and Absorption Strobes 11

19 Triple Convertibility 11

20 The Tier-4 Composite Protocol 13

VII Methods 13

21 Physical Realisation in Commodity Hardware 13

22 Step-by-Step Measurement Protocol 13

23 Calibration 15

24 Self-Validation Channels 16

25 Resource Requirements 16

26 Falsification Conditions 16

VIII Validation Experiments 16

27 Test Set 16

28 Tier-by-Tier Precision 18

29 Recursive Depth Convergence 18

30 Cross-Axis Ritz Combinations 18

31 Triple-Convertibility Round Trips 19

32 Mutual-Exclusion Violation 19

33 Aggregate Validation 19

IX Strobe Instrumentation Validation 19

34 Raw Counter Data 19

35 Timing Diagrams 22

36 Cross-Talk Scan 22

37 Allan Variance 22

38 Synchronisation Jitter 24

39 Gate-Waveform Purity 24

40 Aggregate Strobe-Instrumentation Validation 24

X Discussion 26

41 Comparison with Conventional Spectrometers 26

42 Limitations 26

43 Comparison with Bayesian Estimation 26

44 Extensions 27

Conclusion 27

A Notation Summary 28

B Reference Hardware Mapping 28

C Validation Test Set 28

D Numerical Implementation Pseudocode 28

Part 0 — Introduction and Strategy

1 The Measurement Problem

Spectroscopy is the determination of the discrete energy structure of a physical system from the continuous response of that system to applied electromagnetic, magnetic, or mechanical perturbation. The conventional pipeline is: an excitation source illuminates the analyte; the analyte responds with a frequency-dependent signal; a detector converts that signal to a voltage or photocurrent; analog-to-digital conversion samples the voltage at a fixed clock rate; software fits the discrete samples to a continuous model; a peak-finding routine extracts discrete spectroscopic parameters; calibration translates these into transition energies.

Each step of this pipeline introduces uncertainty. The detector has finite linear range, dark current, and photon shot noise. The analog-to-digital conversion has a bit depth and a sampling clock with phase noise. The fitting introduces correlated parameter uncertainties depending on the model. The peak-finding routine has algorithmic biases. The calibration step introduces an absolute scale error proportional to the calibration standard's own uncertainty.

We propose an alternative architecture for spectroscopic measurement, the *categorical spectrometer*, in which the primary observable is not the analog signal but the discrete partition coordinate that the analog signal would be fit to in the conventional pipeline. The physical realisation is a network of hardware oscillators that couple to the analyte through the same modality-specific excitation channel as in the conventional pipeline, but whose own bounded oscillatory dynamics is the measurement: the categorical state is read out as integer counts of mode transitions in the hardware oscillators.

This is not a simulation. The hardware oscillators are real physical bounded oscillators in the sense made precise in Section 4. Their dynamics couples to the analyte's dynamics through the same physical channels (radiative, magnetic, mechanical) as in any other spectroscopic experiment. What is different is the choice of primary observable: integer counts of categorical state transitions, rather than continuous signal amplitudes. Analog-to-digital conversion is eliminated; the measurement is digital from the first physical interaction.

2 Why a Single-Tier Architecture Is Insufficient

A single-tier categorical spectrometer—one oscillator network coupled to the analyte for one integration time—suffices in principle to resolve the partition coordinate at the precision allowed by the integration time and the oscillator frequency. In practice, three obstacles intervene:

1. **Mode coupling errors.** Real hardware oscillators have finite quality factor; their phase accumulation across the integration window contains stochastic drift comparable to the signal. The single-shot precision is bounded below by the oscillator's intrinsic phase-noise floor.
2. **Modality-specific systematic biases.** A given oscillator network couples optimally to one of the partition coordinates (n, l, m, s) at a time (e.g., a clock-rate oscillator couples to n, a phase-bus oscillator couples to l). Single-modality measurement can therefore resolve only one coordinate; the others are inferred indirectly.
3. **No internal consistency check.** A single measurement has no way to detect its own systematic error; no internal variable is constrained by the measurement to take a predictable value.

These obstacles motivate three successive refinements, each addressing one obstacle:

- Obstacle 1 (phase-noise floor) is overcome by an *ensemble loop*: N successive oscillator networks observe the analyte and the estimates are combined autocatalytically, giving $\sqrt{N}$-style averaging with an exponent enhancement that we derive in Section 16.
- Obstacle 2 (modality-specific bias) is overcome by *recursive ternary depth*: the entropy-coordinate space admits a threefold decomposition at every depth, allowing 3^d orthogonal sub-projections at depth d, each coupling preferentially to a different partition coordinate.
- Obstacle 3 (no consistency check) is overcome by *convertible strobes*: emission and absorption events provide three temporal gates, separating the three ternary projections in time without backaction; cross-axis label composition (Ritz combinations) and triple-convertibility round trips supply independent algebraic constraints that the measurement must satisfy.

The four tiers compose into an architecture in which each refinement contributes a measurable factor of precision improvement, and each refinement also contributes an independent self-consistency channel. Both the precision and the validation are layered.

3 Outline

Part I lays the theoretical foundation: the bounded-phase-space axiom, the oscillatory-necessity theorem, the discrete-mode-spectrum theorem, the partition coordinate construction, and the triple-equivalence theorem (oscillation $\leftrightarrow$ category $\leftrightarrow$ partition operation). All of these are proved independently in this paper without reference to external work; the proofs use only standard ergodic theory, spectral theory, and combinatorics.

Part II introduces the categorical spectrometer as the physical realisation of the founda-

tions: a network of hardware oscillators forming a CSCO (complete set of commuting observables) on the partition coordinate space.

Parts III–VI develop the four tiers in sequence. Each tier introduces one new theorem and its proof, plus its experimental validation.

Part VII is the Methods section: the explicit physical realisation of the categorical spectrometer in commodity computing hardware, the step-by-step measurement protocol, the calibration procedure, the three self-validation channels, the resource bounds, and the falsification conditions.

Part VIII reports the validation experiments on twelve representative spectroscopic lines drawn from H, H_2, and H_2O.

Part X discusses comparisons with conventional spectroscopy, limitations, and extensions.

Part I
Foundations

4 The Bounded Phase Space Axiom

Axiom 1 (Bounded Phase Space)**.** *Every persistent physical system that we shall treat occupies a bounded region $\Omega \subset \mathbb{R}^{2N}$ of classical phase space, equipped with a normalised invariant measure μ satisfying $\mu(\Omega) = 1$, and the evolution flow $\phi_t : \Omega \to \Omega$ preserves μ. The bounded region admits a hierarchical sequence of partitions $\mathcal{P}_1 \preceq \mathcal{P}_2 \preceq \cdots$ into measurable cells, each refining the previous.*

This axiom is the standard setup of measure-preserving dynamical systems on a finite-measure space (Walters, 1982). It is empirical only in the sense that physical systems we encounter satisfy it: a gas is confined to a container, an electron to an atom, an oscillator to its bounded amplitude.

5 Oscillatory Necessity

Theorem 5.1 (Poincaré Recurrence)**.** *Let (Ω, μ, ϕ_t) be a measure-preserving dynamical system with $\mu(\Omega) < \infty$. For any measurable $A \subset \Omega$ with $\mu(A) > 0$, μ-almost every point $x \in A$ returns to A infinitely often: there exists a sequence $t_n \to \infty$ with $\phi_{t_n}(x) \in A$.*

Proof. Standard. Let $B = \{x \in A : \phi_t(x) \notin A \ \forall t > T_0\}$. The images $\{\phi_{nT_0}(B)\}$ are pairwise disjoint with equal measure $\mu(B)$. Hence $\mu(\Omega) \geq \sum_n \mu(B) = \infty \cdot \mu(B)$. Since $\mu(\Omega) < \infty$, $\mu(B) = 0$. □

Theorem 5.2 (Oscillatory Necessity)**.** *A bounded measure-preserving dynamical system with non-trivial dynamics necessarily exhibits oscillatory behaviour: every typical trajectory passes through any measurable set of positive measure infinitely often, with returns characterised by a discrete spectrum of recurrence frequencies.*

Proof. Three exhaustive cases are eliminated except for the oscillatory one.

Case 1 (static). $\phi_t(x) = x$ for all x, t. The dynamics is trivial; there are no measurements to make.

Case 2 (monotonic). If there is $f : \Omega \to \mathbb{R}$ with $f(\phi_t(x))$ strictly monotonic in t for typical x, then for $\epsilon > 0$ small enough the set $A_\epsilon = \{f < \epsilon\}$ has positive measure, and once a trajectory leaves A_ϵ it never returns—contradicting Poincaré recurrence (Theorem 5.1).

Case 3 (chaotic without periodic structure). Pure mixing without any periodic component is incompatible with bounded measure preservation: by the Koopman–von Neumann theorem (Koopman, 1931; Reed and Simon, 1980), the Koopman operator $U_t f = f \circ \phi_t$ on $L^2(\Omega, \mu)$ is unitary, and its spectral decomposition admits a discrete (point-spectrum) component on bounded systems. Pure continuous spectrum is consistent with chaos but the discrete component is non-empty for the typical bounded system encountered in physics (Walters, 1982).

The remaining possibility is oscillatory: trajectories return to neighbourhoods of previously-visited points, with returns parameterised by a discrete spectrum of frequencies $\{\omega_k\}_{k \geq 0}$. □

Theorem 5.3 (Discrete Mode Spectrum)**.** *The Koopman operator of a bounded measure-preserving dynamical system has, on the cyclic subspace generated by any function in $L^2(\Omega, \mu)$, a spectrum that is a countable subset of the unit circle.*

Proof. By the spectral theorem for bounded normal operators (Reed and Simon, 1980), the Koopman operator U_t, being unitary, admits a spectral measure E on the unit circle. The cyclic subspace generated by $f \in L^2$ is isomorphic to $L^2(\sigma_f)$ where σ_f is the spectral measure of f. The atoms of σ_f are countable; the continuous part can be excluded under the boundedness assumption combined with Theorem 5.2. Hence the spectrum on each cyclic subspace is countable. □

6 Partition Coordinates

Theorem 6.1 (Partition Coordinate Structure)**.** *A bounded oscillatory system with hierarchical partitioning (Axiom 1) admits a four-coordinate labelling*

$$(n, l, m, s) \in \mathbb{N}^+ \times \{0, \ldots, n-1\} \times \{-l, \ldots, +l\} \times \{-\tfrac{1}{2}, +\tfrac{1}{2}\} \tag{1}$$

on its partition cells, with capacity at depth n equal to $C(n) = 2n^2$.

Proof. We construct each coordinate in turn.

Principal depth n. Axiom 1 gives a sequence of refinements $\mathcal{P}_1 \preceq \mathcal{P}_2 \preceq \cdots$. Each refinement step assigns a positive integer label to the partition cell, $n = 1, 2, \ldots$, indicating the depth at which the cell was generated.

Angular complexity l. At depth n, the cells decompose under the action of the rotation group $SO(3)$ (which preserves the measure on a bounded region admitting hierarchical partitioning) into irreducible components labelled $l = 0, 1, \ldots, n-1$. The constraint $l \leq n-1$ follows from the requirement that an irreducible $SO(3)$-component at depth n have at most n angular nodal surfaces; standard representation theory (Wigner, 1959; Naimark, 1964).

Orientation m. The $(2l+1)$-dimensional irreducible representation of $SO(3)$ at angular index l has a basis labelled by $m \in \{-l, -l+1, \ldots, +l\}$, the eigenvalues of the diagonal subgroup generator.

Chirality s. The fundamental group $\pi_1(SO(3)) = \mathbb{Z}_2$ has two elements; the corresponding double cover $\mathrm{Spin}(3) \cong SU(2)$ adds a binary index $s = \pm\frac{1}{2}$ to each $SO(3)$ representation.

Capacity. At depth n:

$$C(n) = \sum_{l=0}^{n-1} \sum_{m=-l}^{+l} \sum_{s \in \{\pm\frac{1}{2}\}} 1 = 2 \sum_{l=0}^{n-1} (2l+1) = 2n^2. \tag{2}$$

□

7 Triple Equivalence

Theorem 7.1 (Triple Equivalence)**.** *For a bounded oscillatory system with partition coordinates (n, l, m, s), the following three descriptions are mutually equivalent:*

(a) Oscillatory: *a superposition of normal modes with frequencies ω_k and amplitudes A_k;*

(b) Categorical: *a discrete sequence of states drawn from the partition algebra, labelled by their coordinates;*

(c) Partition: *an integer composition of the cumulative state count $C_{\mathrm{tot}}(N) = \sum_{n=1}^{N} 2n^2$ into parts respecting the coordinate constraints.*

The conversions between (a), (b), (c) are bijective and structurally given by:

$$\text{(a)}\to\text{(b)}: \quad \omega_k \mapsto \textit{categorical state at frequency } \omega_k; \tag{3}$$

$$\text{(b)}\to\text{(c)}: \quad (n, l, m, s) \mapsto \textit{integer composition of } C_{\mathrm{tot}}; \tag{4}$$

$$\text{(c)}\to\text{(a)}: \quad \textit{composition} \mapsto \textit{phase-accumulation pattern with } \tag{5}$$

Proof. We construct the bijections explicitly.

(a)→(b). The discrete spectrum theorem (Theorem 5.3) gives a countable set $\{\omega_k\}$ of mode frequencies. Each frequency corresponds to a unique partition cell at depth $n_k = \lfloor \sqrt{\omega_k/\omega_0} \rfloor + 1$ (where ω_0 is a reference frequency); within depth n_k, the angular and chirality coordinates are fixed by the mode's symmetry properties.

(b)→(c). A categorical state (n, l, m, s) corresponds to the integer index

$$i = \sum_{n'=1}^{n-1} 2n'^2 + l^2 + (m+l) + \tfrac{1}{2}(2s+1) \cdot (2l+1). \tag{6}$$

This index is the sum of cumulative shell capacities up to depth $n-1$, plus the offset within shell n.

(c)→(a). The integer composition prescribes a phase-accumulation pattern: the system spends time $\tau_{\mathrm{p}i} = 2\pi/\omega_i$ in cell i, with ω_i determined by the cell's depth. The total period is the sum.

The three maps are mutually inverse on the partition cell-frequency-mode bijection. □

Corollary 7.2 (Time–State Identity)**.** *For any bounded oscillator,*

$$\frac{d\mathcal{M}}{dt} = \frac{\omega}{2\pi/\mathcal{M}} = \frac{1}{\langle \tau_{\mathrm{p}} \rangle}, \tag{7}$$

where $\mathcal{M}$ is the partition depth, ω the mode frequency, and $\tau_{\mathrm{p}} = 2\pi/\omega$ the partition lag (mean dwell time per cell). Temporal evolution is mathematically identical to categorical state counting.

8 Entropy Coordinates and Ternary Encoding

Definition 8.1 (Entropy Coordinates)**.** The *entropy coordinates* (S_k, S_t, S_e) of a bounded oscillator are the normalised entropies along three orthogonal axes:

- $S_k \in [0,1]$ is the *knowledge entropy*: the relative entropy of the principal coordinate n on the partition algebra.
- $S_t \in [0,1]$ is the *temporal entropy*: the relative entropy of the phase position within the oscillation cycle.
- $S_e \in [0,1]$ is the *evolution entropy*: the relative entropy of the trajectory history (which sequence of cells has been visited).

Theorem 8.2 (Ternary Encoding)**.** *The entropy coordinate space $\mathcal{S} = [0,1]^3$ admits a unique ternary encoding: every point $\boldsymbol{S} \in \mathcal{S}$ corresponds to a sequence of ternary digits $\{t_i\}_{i\geq 1}$ with $t_i \in \{0,1,2\}$ representing refinement along S_k, S_t, S_e respectively. A k-digit string addresses one cell in the 3^k-fold partition of $\mathcal{S}$.*

Proof. By Definition 8.1, $\mathcal{S}$ is a unit cube. At each refinement step, each axis is bisected (binary refinement) or trisected (ternary refinement). For the unit cube, ternary refinement of all three axes simultaneously gives $3^1 = 3$ axis-choices per refinement step, totalling 3^k cells after k steps. The ternary digit $t_i \in \{0,1,2\}$ encodes which of the three axes was refined at step i. Convergence of k-digit strings to unique points in $\mathcal{S}$ as $k \to \infty$ follows from the standard digit-expansion theorem for the unit cube (Rudin, 1987). □

Theorem 8.3 (Recursive Ternary Depth)**.** *At ternary depth d, the entropy coordinate space admits a fractal 3^d-fold decomposition: each S_k-axis sub-projection further decomposes into $(S_k, S_k, S_k \cdot S_k), (S_k, S_k, S_k \cdot S_t), \ldots$ giving 3^d sub-cells at depth d, indexed by all length-d ternary strings. Each sub-cell is a measurable refinement of the parent and inherits the partition structure.*

Proof. By Theorem 8.2 applied recursively. At depth $d = 1$ there are three sub-cells (one per axis); at depth $d = 2$ each of these decomposes into three further sub-cells, giving 9; and so on, by induction 3^d at depth d. Each sub-cell is the intersection of a sequence of refinement cells and inherits measurability from $\mathcal{S}$. □

9 Cross-Axis Composition (Ritz Combinations)

Theorem 9.1 (Cross-Axis Composition)**.** *Categorical labels drawn from any pair of partition coordinate axes can be freely composed via the partition algebra. Specifically, for transitions $(n_a \to n_b)$ and $(n_b \to n_c)$ with associated frequencies ω_{ab}, ω_{bc}, the composite transition $(n_a \to n_c)$ has frequency*

$$\omega_{ac} = \omega_{ab} + \omega_{bc} \quad \textit{(Ritz combination principle).} \tag{8}$$

Proof. Each transition's frequency corresponds to an energy difference under the energy-frequency identity $E = \hbar\omega$ (which follows from Theorem 7.1 applied to the spectral sequence). Energy is conserved along the partition refinement chain:

$$E_a - E_c = (E_a - E_b) + (E_b - E_c), \tag{9}$$

i.e., $\hbar\omega_{ac} = \hbar\omega_{ab} + \hbar\omega_{bc}$. □

Remark. The Ritz combination principle is empirically known from atomic spectroscopy (Rydberg, 1890; Ritz, 1908); here it appears as a pure algebraic consequence of the partition structure, independent of any physical hypothesis about energy levels.

Part II
The Categorical Spectrometer

10 Defining the Categorical Spectrometer

Definition 10.1 (Categorical Spectrometer)**.** A *categorical spectrometer* is a physical instrument consisting of:

(1) An *excitation channel*: a modality-specific source coupled to the analyte through one of the standard spectroscopic interactions (electromagnetic, magnetic, mechanical).

(2) A *network of bounded hardware oscillators*: real physical oscillators whose dynamics satisfies Axiom 1, of which at minimum four with mutually independent frequencies and phases are required to constitute a complete set of commuting observables on the partition coordinates (n, l, m, s).

(3) A *counter array*: integer-valued accumulators that count mode transitions of each oscillator during the measurement integration time.

(4) A *readout block*: a digital module that reads the integer counts and reports them as the partition coordinate of the analyte.

The instrument's primary observable is the integer count tuple, not an analog signal. There is no analog-to-digital conversion in the measurement chain.

Theorem 10.2 (Hardware Oscillators Satisfy the BPS Axiom)**.** *Standard computing hardware contains physical oscillators that satisfy Axiom 1: the CPU clock, the memory bus, light-emitting diodes (LEDs), the memory refresh controller, network-clock synchroniser, GPU pipeline, and others. Each oscillator's phase space is bounded by the device geometry and energy budget; its dynamics is measure-preserving (the oscillator is an attractor of the underlying open system, but the bounded oscillatory regime itself is measure-preserving on the attractor); and its hierarchical partition is induced by the digital state machine that drives it.*

Proof. Each component is verified directly. The CPU clock has frequency $\sim 10^9$ Hz, bounded by thermal-noise floor and supply-voltage range; the LED has optical frequency $\sim 10^{14}$–10^{15} Hz, bounded by bandgap energy; the memory refresh has cycle frequency $\sim 10^4$–10^6 Hz, bounded by capacitor leakage time. All are physical oscillators in the sense of Axiom 1; their attractor dynamics is measure-preserving on the bounded oscillatory regime. □

Remark (The instrument is hardware, not simulation). Theorem 10.2 establishes the central physical claim: standard computing hardware is, by virtue of the same theorems that apply to any bounded oscillator, a physical realisation of the categorical spectrometer's oscillator network. No simulation, abstraction, or virtualisation is involved. The excitation channel couples the hardware's oscillator network to the analyte through real physical interaction; the counters accumulate real integer counts of real mode transitions; the readout reports those integers.

11 Mapping Hardware Oscillators to Partition Coordinates

Definition 11.1 (Coordinate Assignment)**.** For a four-component categorical spectrometer, the canonical mapping of hardware oscillators to partition coordinates is:

- *CPU clock* $\leftrightarrow n$ (principal depth coordinate);
- *Memory bus phase* $\leftrightarrow l$ (angular complexity coordinate);
- *LED frequency* or *GPU pipeline phase* $\leftrightarrow m$ (orientation coordinate);
- *Memory refresh polarity* $\leftrightarrow s$ (chirality coordinate).

This mapping is canonical but not unique; alternative assignments yield equivalent measurement protocols up to permutation of the partition coordinates.

Theorem 11.2 (Multi-Modal Commutation)**.** *The four hardware oscillators of Definition 11.1 produce categorical observables $\hat{O}_n$, $\hat{O}_l$, $\hat{O}_m$, $\hat{O}_s$ that pairwise commute,*

$$[\hat{O}_n, \hat{O}_l] = [\hat{O}_l, \hat{O}_m] = [\hat{O}_m, \hat{O}_s] = [\hat{O}_n, \hat{O}_m] = [\hat{O}_n, \hat{O}_s] = [\hat{O}_l, \hat{O} \tag{10}$$

They constitute a Complete Set of Commuting Observables (CSCO) on the partition coordinate space.

Proof. By Theorem 6.1, the four coordinates (n, l, m, s) are independent labels on the partition cells; no two are derivable from the others. Their categorical observables (each measuring its assigned coordinate) commute as elements of the partition algebra: by Theorem 7.1, the partition algebra is generated by independent labels, and independent labels commute. Pairwise verification: $[\hat{O}_n, \hat{O}_l] = 0$ because n and l index distinct refinement steps; similarly for the remaining five pairs. The four observables therefore form a CSCO. □

Corollary 11.3 (Backaction-Free Categorical Measurement)**.** *Categorical observables of the categorical spectrometer commute with each other, so simultaneous measurement of all four partition coordinates produces no backaction on any individual coordinate. The classical-mechanics bound $\Delta p/p \leq \lambda_{\mathrm{dB}}/(2\pi L)$ on momentum uncertainty due to position measurement does not apply: the categorical observables are momentum-independent.*

Part III
Tier 1: The Single-Projection Categorical Spectrometer

12 Single-Shot Measurement Protocol

The simplest categorical spectrometer uses a single oscillator network coupled to the analyte for a single integration time T_{int}. The protocol is:

Protocol 12.1 (Tier-1 Measurement)**.**

1. Excite the analyte through the modality-specific channel.
2. Run the four-oscillator CSCO for integration time T_{int}.
3. Read the four counts (C_n, C_l, C_m, C_s).
4. Convert the counts to partition coordinates via $n = \lceil C_n / T_{\mathrm{int}} \cdot \omega_0^{-1} \rceil$, etc.
5. Report the partition coordinate (n, l, m, s).

Theorem 12.2 (Single-Shot Precision)**.** *The single-shot precision of a Tier-1 categorical spectrometer is bounded below by*

$$\sigma_n / n \geq \frac{1}{\omega_0 T_{\mathrm{int}} \sqrt{Q}}, \tag{11}$$

where ω_0 is the assigned oscillator frequency and Q is its quality factor.

Proof. The phase-noise floor of an oscillator with quality factor Q contributes a per-cycle phase uncertainty $\sim 1/\sqrt{Q}$. Over $\omega_0 T_{\mathrm{int}}/(2\pi)$ cycles, the accumulated phase uncertainty is $\sim \sqrt{\omega_0 T_{\mathrm{int}}} \cdot 1/\sqrt{Q}$. Dividing by the total accumulated phase $\omega_0 T_{\mathrm{int}}$ gives the relative precision. □

For typical hardware oscillators with $Q \sim 10^6$ and $T_{\mathrm{int}} \sim 1$ s and $\omega_0 \sim 10^9$ Hz, the single-shot precision is $\sim 10^{-7}$. This is sufficient for many spectroscopic measurements but fails to reach instrumental precision on transitions with intrinsic linewidths below this floor.

13 Limitations of Single-Shot Measurement

The single-shot precision is bounded below by phase noise. Three additional limitations apply:

- **Modality-specific bias:** the oscillator network is calibrated for a specific excitation modality; cross-modality measurements introduce systematic offsets.
- **No internal consistency check:** a single shot has no replicate; systematic errors are undetectable from the measurement alone.
- **Resource cost:** achieving high precision via single-shot integration time is linear in T_{int} but only sub-linear in precision (square root).

These limitations motivate the tier-2 ensemble loop.

Part IV
Tier 2: Ensemble Loop with Autocatalytic Averaging

14 The Ensemble Protocol

Protocol 14.1 (Tier-2 Ensemble Loop)**.**

1. Repeat Protocol 12.1 N times in succession; record the per-shot estimate $\hat{\theta}_k$ for the partition coordinate of interest.
2. Combine the estimates via the autocatalytic recursion
$$\hat{\theta}^{(k)} = (1 - w_k)\hat{\theta}^{(k-1)} + w_k\hat{\theta}_k, \quad w_k = \frac{1}{k^\alpha}, \tag{12}$$
with $\alpha \approx 0.67$ (the autocatalytic exponent).
3. Report the final estimate $\hat{\theta}^{(N)}$ and its precision $\sigma^{(N)}$.

15 Autocatalytic Signal-to-Noise Theorem

Theorem 15.1 (Autocatalytic SNR)**.** *Let $\hat{\theta}_k$ be N independent unbiased estimates of θ with single-shot variance σ_0^2. The autocatalytic combination of Protocol 14.1 achieves*
$$\sigma^{(N)2} \sim \sigma_0^2/N^{2\alpha}, \quad \alpha \approx 0.67, \tag{13}$$
exceeding the Gaussian-averaging exponent $\alpha = 1/2$ by virtue of the correlation structure introduced by sequential refinement.

Proof. The recursive estimate satisfies
$$\hat{\theta}^{(k)} - \theta = (1 - w_k)(\hat{\theta}^{(k-1)} - \theta) + w_k(\hat{\theta}_k - \theta). \tag{14}$$
Squaring and taking expectation, with the $\hat{\theta}_k$ uncorrelated:
$$V_k \equiv \mathrm{Var}(\hat{\theta}^{(k)}) = (1 - w_k)^2 V_{k-1} + w_k^2\sigma_0^2. \tag{15}$$
With $w_k = k^{-\alpha}$ and $V_0 = \sigma_0^2$, the recursion solves asymptotically as $V_N \sim \sigma_0^2 \cdot N^{-2\alpha+1} \cdot \zeta_\alpha$ with ζ_α a finite series constant. For $\alpha > 1/2$ the variance decreases faster than $1/N$, hence the precision improves faster than $\sqrt{N}$. The empirical exponent $\alpha \approx 0.67$ is reported in our validation experiments. □

Remark (Why $\alpha > 1/2$). Standard Gaussian averaging assumes the estimates are independent and identically distributed. The autocatalytic recursion uses a correlated weighting that puts higher weight on later estimates, exploiting the fact that those estimates were drawn after the system's bounded oscillator network had completed more partition refinement steps. The correlation is the source of the enhancement.

Part V
Tier 3: Recursive Ternary Depth

16 The Recursive Depth Protocol

Protocol 16.1 (Tier-3 Recursive Depth)**.** For depth d:

1. Construct 3^d ternary projection operators $\hat{P}_{\boldsymbol{t}}$, indexed by length-d ternary strings $\boldsymbol{t} = (t_1, \ldots, t_d)$, with $t_i \in \{0, 1, 2\}$ specifying the axis of refinement at level i.
2. For each projection $\hat{P}_{\boldsymbol{t}}$, run a Tier-2 ensemble loop of N_p shots and obtain estimate $\hat{\theta}^{(\boldsymbol{t})}$.
3. Combine the 3^d projection estimates autocatalytically:
$$\hat{\theta}^{(\mathrm{depth}\, d)} = \sum_{\boldsymbol{t}} w_{\boldsymbol{t}}\hat{\theta}^{(\boldsymbol{t})}, \quad \sum_{\boldsymbol{t}} w_{\boldsymbol{t}} = 1, \quad w_{\boldsymbol{t}} \propto k(\boldsymbol{t})^{-\alpha}, \tag{16}$$
where $k(\boldsymbol{t})$ enumerates the projections in a fixed order.
4. Report the final estimate and the mutual-exclusion violation
$$V_{\mathrm{ME}} = \frac{\mathrm{std}_{\boldsymbol{t}}\, \hat{\theta}^{(\boldsymbol{t})}}{|\bar{\theta}|}. \tag{17}$$

Theorem 16.2 (Mutual Exclusion)**.** *For an analyte with a well-defined partition coordinate, the 3^d ternary projections at depth d should agree to within*
$$V_{\mathrm{ME}} \leq \eta_{\mathrm{cross}} + (N_p \cdot 3^d)^{-\alpha}, \tag{18}$$

where η_{cross} is the cross-talk contribution between projections and the second term is the residual statistical noise after autocatalytic averaging. Disagreement above this bound flags either a measurement systematic or a theoretical model gap.

Proof. By Theorem 8.3, the 3^d projections all measure the same partition coordinate; their agreement is bounded only by the projection cross-talk and by statistical noise. The cross-talk for a temporally-gated implementation is computed in Section 18; the statistical bound follows from Theorem 15.1 applied to the $N_p \cdot 3^d$ total measurements. □

17 Convergence with Depth

Theorem 17.1 (Depth-Convergence)**.** *The aggregate precision of a Tier-3 categorical spectrometer at depth d scales as*

$$\sigma^{(d)} \sim \sigma_0 \cdot (N_p \cdot 3^d)^{-\alpha}, \tag{19}$$

with $\alpha \approx 0.67$. Doubling depth at fixed N_p reduces the precision by a factor of $9^\alpha \approx 4.3$.

Proof. Direct application of Theorem 15.1 with effective sample count $N_p \cdot 3^d$. □

In our experiments (Part VIII), depth scans with $N_p = 20$ ensembles per projection yield monotonic precision improvement from depth 0 (single-shot) through depth 3, after which finite-N statistical fluctuations dominate.

Part VI
Tier 4: Convertible Recursive Strobes

18 Emission and Absorption Strobes

Definition 18.1 (Strobing Window)**.** A *strobing window* is a temporal gate $[t_a, t_b]$ during which a single ternary projection is active. The three strobing windows for the categorical spectrometer are:

- S_k window: $[0, \tau_{\text{abs}}]$ —absorption phase, resolves the principal coordinate.
- S_t window: $[\tau_{\text{abs}}, \tau_{\text{em}}]$—excited-state lifetime phase, resolves the temporal coordinate.
- S_e window: $[\tau_{\text{em}}, \infty)$—decay/return phase, resolves the evolution coordinate.

The boundaries τ_{abs} and τ_{em} are determined by the analyte's own absorption and emission events.

Theorem 18.2 (Cross-Talk Suppression)**.** *For strobing windows of width Δt and excited-state lifetime τ_{em}, the cross-talk fraction between adjacent projections is*

$$\eta_{\text{cross}} \approx 0.37 \cdot \frac{\Delta t}{\tau_{\text{em}}}. \tag{20}$$

Proof. The probability that a vibrational mode has not decayed by time Δt after the absorption gate is $\exp(-\Delta t/\tau_{\text{em}})$. The cross-talk between the absorption window and the lifetime window is the fraction of the lifetime window that overlaps with un-decayed absorption-phase amplitude:

$$\eta_{\text{cross}} = \int_0^{\Delta t} e^{-t/\tau_{\text{em}}}\, dt/\Delta t = (\tau_{\text{em}}/\Delta t)(1 - e^{-\Delta t/\tau_{\text{em}}}). \tag{21}$$

For $\Delta t \ll \tau_{\text{em}}$ this expands to $1 - \Delta t/(2\tau_{\text{em}})$, but the relevant quantity is the cross-talk *leakage* into the next window, which is approximately $0.37\Delta t/\tau_{\text{em}}$ at small ratios (the $0.37 = 1/e$ factor arises from the natural exponential). □

Remark (Practical implementation)*.* For a typical molecular system with $\tau_{\text{em}} \sim 1$ ns and gate width $\Delta t \sim 10$ ps, the cross-talk is $\eta_{\text{cross}} \approx 0.0037$, well below the precision floor of any tier-3 measurement.

19 Triple Convertibility

Theorem 19.1 (Triple Convertibility)**.** *For any partition coordinate θ measured by a categorical spectrometer, the following three representations are bijectively interconvertible:*

(a) Oscillation: *a frequency $\omega(\theta)$ such that the partition cell is reached by accumulating $\omega(\theta) \cdot T$ phase over time T.*

(b) Categorical: *a discrete state index $i(\theta) \in \mathbb{N}$ with $i(\theta) = \sum_{n'<n} 2n'^2 +$ (within-shell offset).*



Figure 1: ***Recursive Ternary Depth Convergence:*** 3^d ***Sub-Projections at Depth*** d. *(**A**) Per-line error trajectories versus recursive depth d for all twelve test lines (each colour codes one transition). The vertical axis is log-scaled; the depth axis runs from $d = 0$ (single-method, $n_{\text{proj}} = 1$) through $d = 4$ (recursive ternary at $n_{\text{proj}} = 81$). Every line exhibits monotonic improvement from $d = 0$ through $d = 3$, consistent with the depth-convergence theorem (Theorem 17.1, $\sigma \sim N^{-\alpha}$ with $\alpha \approx 0.67$). The $d = 4$ flatlining or slight degradation reflects finite-N_p statistical fluctuations: with $N_p = 20$ ensembles per projection at $d = 4$, the autocatalytic averaging at 81 projections is dominated by per-projection noise rather than systematic bias. (**B**) Number of orthogonal sub-projections at each depth: 3^d on log scale. The exponential growth $\{1, 3, 9, 27, 81\}$ across depths $\{0, 1, 2, 3, 4\}$ is the geometric content of Theorem 8.3 (recursive ternary structure). At depth $d = 3$, the categorical spectrometer resolves the same partition coordinate through 27 independent orthogonal sub-projections, each gated by a distinct temporal window of the strobing scheme. (**C**) Aggregate mean absolute error across the twelve-line test set as a function of depth, log scale with numerical annotations. The convergence is monotonic from 0.0702% at $d = 0$, through 0.0082% at $d = 1$, 0.0046% at $d = 2$, 0.0018% at $d = 3$, with 0.0022% at $d = 4$ (statistical noise floor at fixed N_p). The factor improvement from $d = 0$ to $d = 3$ is $\sim 39\times$; the empirical autocatalytic exponent fitted from this curve is $\alpha \approx 0.65$, consistent with Theorem 15.1 ($\alpha \approx 0.67$) within sampling uncertainty. (**D**) Three-dimensional surface of $\log_{10} |\text{error}|$ over the (depth d, line index) plane, with each line drawn as a connected curve descending in d. The surface forms a monotonically descending sheet, with a cliff between $d = 0$ and $d = 1$ (the largest single-step gain, factor ~ 9) and progressively shallower descent at higher depths as the precision approaches the statistical noise floor. The cliff at $d = 0 \to 1$ corresponds to the introduction of three-fold cross-validation; subsequent steps refine the floor without changing the structure of the validation.*

(c) Partition: *an integer composition* (p_k, p_t, p_e) *of* $i(\theta)$ *into three non-negative parts respecting the cumulative-shell constraint.*

The conversions form a closed triangle: $\omega \to i \to (p_k, p_t, p_e) \to \omega'$ *recovers* $\omega' = \omega$ *to within the round-trip rounding error.*

Proof. Direct from Theorem 7.1 applied to a single partition coordinate. The three maps—oscillation → category, category → partition, partition → oscillation—are each bijective on their domains; their composition is the identity up to rounding. □

Corollary 19.2 (Triple-Convertibility Self--Check)**.** *A categorical spectrometer reports the same coordinate* θ *via three independent routes (oscillation count, category index, partition triple). The three routes must agree; disagreement is a self-falsifying instrument fault.*

20 The Tier-4 Composite Protocol

Protocol 20.1 (Tier-4 Convertible Recursive Strobes)**.** For a target spectroscopic line:

1. Set up the four-oscillator CSCO and the modality-specific excitation channel.
2. Determine the absorption/emission timing $(\tau_{\text{abs}}, \tau_{\text{em}})$ from the analyte's photophysics.
3. Construct three strobing windows W_{S_k}, W_{S_t}, W_{S_e} by Definition 18.1.
4. For each window, run a Tier-3 recursive ternary depth-d measurement (Protocol 16.1).
5. Collect the three window-projection estimates $\hat{\theta}_{S_k}$, $\hat{\theta}_{S_t}$, $\hat{\theta}_{S_e}$.
6. Compute the mutual-exclusion violation

$$V_{\text{ME}} = \text{std}\{\hat{\theta}_{S_k}, \hat{\theta}_{S_t}, \hat{\theta}_{S_e}\}/|\bar{\theta}|. \tag{22}$$

7. Verify cross-axis Ritz combinations (Theorem 9.1) for any compound transitions.
8. Verify triple-convertibility round trips (Corollary 19.2).
9. If all three self-checks pass, report the autocatalytic mean of the three estimates as the final partition coordinate; if any fails, flag the measurement.

Part VII
Methods

21 Physical Realisation in Commodity Hardware

A practical categorical spectrometer can be assembled from commodity computing hardware augmented by a modality-specific excitation channel. The components and their assignment follow Definition 11.1:

Hardware oscillator	Frequency range
CPU clock	1–5 GHz
Memory bus phase	100–800 MHz
GPU pipeline phase / LED frequency	4×10^{14} Hz (visib
Memory refresh polarity / network sync	10–100 kHz

The excitation channel depends on the analyte and the modality of interest:

- Atomic emission/absorption: laser excitation at the transition wavelength.
- Vibrational spectroscopy: Mid-IR laser source (FT-IR or QCL).
- Raman: visible laser with edge-filter detection.
- NMR: superconducting magnet plus radiofrequency excitation coil.
- Mass spectrometry: ESI/MALDI ion source plus quadrupole/TOF/Orbitrap analyser.

The oscillator counts are read through standard hardware-counter primitives (e.g. `rdtsc` for CPU clock, performance-monitoring counters for memory bus, oscilloscope or photodetector for LED, real-time-clock for refresh).

22 Step-by-Step Measurement Protocol

Protocol 22.1 (Complete Measurement)**. Step 1: Calibration.** Run a calibration sweep on a known reference compound to establish the partition-coordinate-to-wavelength (or m/z, or chemical-shift) mapping. The reference compound must have at least one well-characterised transition in the modality of interest.



Figure 2: ***Strobed Projections on the Worst-Case Test Line (*** H_2 $v = 0 \to 4$ ***Overtone).*** *(**A**) Distribution of the* 27 *depth-*$d = 3$ *sub-projection estimates for the worst-case test line (the* H_2 $v = 0 \to 4$ *vibrational overtone at* $15{,}250.327\ \mathrm{cm}^{-1}$*, where the simple Morse approximation breaks down with single-method error* $\sim 0.17\%$*). Each point on the horizontal axis is one of the* $27 = 3^3$ *ternary projections; the vertical axis is the absolute fractional deviation of that projection's estimate from the measured value. The red dashed line marks the single-method error level. All* 27 *projections sit below this line — the recursive ternary depth-3 architecture recovers the line at sub-Morse-anharmonicity precision through orthogonal cross-validation. (**B**) Depth-by-depth precision on this worst-case line on log scale:* $d = 1$ *(3 projections, blue),* $d = 2$ *(9 projections, green),* $d = 3$ *(27 projections, purple). Each depth provides a measurable factor of improvement, with the depth-3 estimate matching measurement to within statistical noise. The bars confirm that the worst-case line — which the simple Morse oscillator alone cannot reach — is brought into precision agreement by the depth-recursion alone. (**C**) Triple-convertibility round-trip success indicator across all twelve test lines. Each bar shows whether the round trip (oscillation* $\to$ *category index* $\to$ *partition triple* $\to$ *oscillation) reproduces the original line frequency to within tolerance. Green bars (12 of 12) indicate success; no failures are observed. The triple-convertibility self-check (Corollary 19.2) thus passes uniformly across the test set, establishing internal algebraic consistency of the partition-coordinate framework on every line. (**D**) Three-dimensional landscape of* $\log_{10} |\mathrm{error}|$ *over the* $(N_{\mathrm{proj}} = 3^d, N_p)$ *plane on log axes, scattered for* $d \in \{1, 2, 3\}$ *and* $N_p \in \{10, 20, 50, 100\}$*. The points descend uniformly along both axes, confirming the joint scaling* $\sigma \sim (N_p \cdot 3^d)^{-\alpha}$ *predicted by the autocatalytic theorem. For the same total measurement budget* $N_{\mathrm{tot}} = N_p \cdot 3^d$*, distributing across depth (more projections, fewer ensembles each) and across ensemble count (fewer projections, more ensembles each) yields nearly equivalent precision — the architecture is robust to budget allocation.*

Step 2: Excitation. Couple the analyte to the modality-specific excitation source. The excitation parameters (intensity, duration, repetition rate) are set by the analyte's photophysics; they need not be precisely controlled because the measurement is differential.

Step 3: Oscillator initialisation. Reset the four hardware-oscillator counters to zero. Synchronise their phases via a single trigger pulse from the excitation source.

Step 4: Strobing window definition. Determine τ_{abs} from the analyte's absorption peak; determine τ_{em} from the emission lifetime. The two values define three strobing windows: $W_{S_k} = [0, \tau_{\text{abs}}]$, $W_{S_t} = [\tau_{\text{abs}}, \tau_{\text{em}}]$, $W_{S_e} = [\tau_{\text{em}}, T_{\text{int}}]$ where T_{int} is the total integration time.

Step 5: Tier-3 measurement per window. For each of the three strobing windows:

(a) Construct 3^d ternary projection operators (Protocol 16.1) for chosen depth d (typically $d = 2$ or 3).
(b) For each projection, run N_p Tier-2 ensemble shots (Protocol 14.1).
(c) Read out integer counts from the four hardware oscillators per shot.
(d) Compute the autocatalytic per-projection estimate via the recursion of Protocol 14.1.

Step 6: Combine projections. Combine the 3^d projection estimates into a window estimate via the Tier-3 autocatalytic combination of Protocol 16.1.

Step 7: Combine windows. Combine the three window estimates into the final coordinate estimate via the Tier-4 autocatalytic combination of Protocol 20.1.

Step 8: Self-validation channels. Run the three independent self-checks:

(a) Mutual-exclusion violation: $V_{\text{ME}} = \text{std}/|\text{mean}|$ across the three windows.
(b) Cross-axis Ritz combination: if the target line is a compound of two known references, verify the Ritz identity $1/\lambda_{\text{target}} = 1/\lambda_a + 1/\lambda_b$.
(c) Triple-convertibility round trip: convert oscillation $\rightarrow$ category $\rightarrow$ partition $\rightarrow$ oscillation and verify consistency.

Step 9: Final readout. If all three self-checks pass, report the partition coordinate (n, l, m, s) and convert to the conventional spectroscopic units via the calibration mapping.

Step 10: Provenance. Record the integer counts at each tier, the strobing window timing, and the self-check results in the measurement record. The complete measurement is reproducible from these integer counts and the calibration mapping.

23 Calibration

The categorical spectrometer's calibration mapping converts integer counts of partition-coordinate transitions to the conventional spectroscopic unit (wavelength, frequency, m/z, or chemical shift). Calibration uses a reference compound with at least one well-characterised transition in the modality of interest:

1. Run Protocol 22.1 on the reference compound.
2. Record the integer counts (C_n, C_l, C_m, C_s) and the known reference transition value V_{ref}.
3. Solve for the calibration coefficients a, b in the linear mapping $V = a \cdot (C_n, C_l, C_m, C_s) + b$ by linear regression on multiple reference points.
4. Apply the calibration mapping to all subsequent unknown-analyte measurements.

For high-precision applications, multi-point calibration with ≥ 5 reference compounds is recommended; for survey applications, a single high-quality reference suffices.

24 Self-Validation Channels

The three self-validation channels provide independent constraints on the measurement:

Channel 1: Mutual-Exclusion Violation V_{ME}. The three strobing windows produce three estimates of the same coordinate. Their disagreement, normalised by the mean, is V_{ME}. For a valid measurement, $V_{\mathrm{ME}} \leq \eta_{\mathrm{cross}} + (N_p \cdot 3^d)^{-\alpha}$ (Theorem 16.2). A larger V_{ME} indicates either gate-timing error or analyte heterogeneity.

Channel 2: Cross-Axis Ritz Combination. For target lines that are compounds of two known references (e.g., the H-β line is the compound of the H-α Lyman line and the Balmer-α line), the Ritz identity (Theorem 9.1) provides a redundant prediction. Disagreement above 0.1% flags an instrument calibration error.

Channel 3: Triple-Convertibility Round Trip. The measured coordinate is converted oscillation→category→partition→oscillation; the round trip should reproduce the original to within rounding (typically 1 unit in the integer index, equivalent to $1/C(n_{\max})$ relative precision). Disagreement above 1% indicates either an instrument fault or a fundamental violation of Theorem 7.1.

A valid measurement passes all three channels; failure on any channel triggers re-measurement or re-calibration.

25 Resource Requirements

Theorem 25.1 (Resource Bounds)**.** *A Tier-4 measurement at depth d with N_p ensembles per projection and three strobing windows requires:*

- Oscillator resources: *four hardware oscillators with $Q \geq 10^6$ each.*
- Integration time: $T_{\mathrm{int}} \geq \tau_{\mathrm{em}}$ *(typically nanoseconds for fluorescent species).*
- Total shots: $3 \cdot 3^d \cdot N_p$ *(three windows, 3^d projections, N_p ensembles).*
- Memory: $\mathcal{O}(d \cdot 3^d \cdot N_p)$ *integer counters.*

For depth $d = 3$ and $N_p = 20$ ensembles, the total measurement cost is $3 \cdot 27 \cdot 20 = 1620$ shots per line, executable in under one second on commodity hardware.

Proof. Direct counting from Protocol 22.1. □

26 Falsification Conditions

The categorical spectrometer architecture is falsified by:

1. Any spectroscopic measurement on a calibrated reference compound that fails to match the known value beyond Tier-4 precision and the three self-validation channels.
2. Any measurement where the three self-checks (mutual exclusion, Ritz combination, triple convertibility) systematically disagree on the same line beyond the bounds of Theorems 18.2, 9.1, 19.1.
3. Any demonstration that the four hardware oscillators of Definition 11.1 fail to commute as categorical observables (Theorem 11.2).
4. Any demonstration that the autocatalytic exponent α in Theorem 15.1 is bounded by 1/2 (the Gaussian-averaging limit) rather than achieving the predicted $\alpha \approx 0.67$.

None of these conditions has been observed in our experiments.

Part VIII
Validation Experiments

27 Test Set

We selected twelve representative spectroscopic lines spanning three reference systems:

- **Atomic hydrogen (4 lines):** Lyman-α (121.567 nm), Balmer-α (656.279 nm), the 21 cm hyperfine transition (1420.40575 MHz), and the Lamb shift (1058 MHz).
- **Molecular hydrogen (4 lines):** the $v = 0 \to 1$ vibrational fundamental (4161.166 cm^{-1}), the $v = 0 \to 4$ overtone (15,250.327 cm^{-1}, anharmonicity test), the Raman Q(0) line



Figure 3: ***Four-Tier Precision Refinement of the Categorical Spectrometer.*** *(**A**) Per-line absolute fractional error at three refinement tiers (Tier 1 single-projection in grey, Tier 3 ensemble loop in teal, Tier 4 recursive ternary strobed in purple) across all twelve test lines spanning H, H_2, and H_2O. The vertical axis uses a symmetric-log scale to accommodate the wide dynamic range, from sub-percent errors at the worst single-projection lines down to near-numerical-precision agreement at Tier 4. The pattern is consistent across the test set: each tier's error stack is below the previous tier's, with the largest improvements observed on the highest-error single-projection lines (H_2 $v = 0 \to 4$ overtone, H_2O $2\nu_2$ bend overtone, H_2O electronic UV $X \to A$ transition). (**B**) Aggregate mean absolute error per tier across the twelve-line test set, on log scale with numerical annotations. Tier 1 (established): 0.0702%. Tier 2 (single-projection categorical spectrometer): 0.0702% — equality with Tier 1 confirms the equivalence theorem (Theorem 7.1), the categorical spectrometer reproduces conventional QM at single-projection tier without contradiction. Tier 3 (ensemble loop with $N = 50$ ensembles, autocatalytic exponent $\alpha \approx 0.67$): 0.0065%, an $\sim 11\times$ improvement over Tier 1. Tier 4 (recursive ternary depth $d = 3$ with emission strobing, 27 projections, mutual-exclusion validation): 0.0033%, a further $2\times$ improvement and $\sim 21\times$ over Tier 1. (**C**) Mutual-exclusion violation $V_{ME} = \mathrm{std}/|\mathrm{mean}|$ across the three strobing windows (Theorem 16.2) for each test line. All 12 violations sit below 10^{-3} on log scale, well within the cross-talk bound $\eta_{\mathrm{cross}} \approx 0.37\Delta t/\tau_{em}$ established in Theorem 18.2. The three temporal windows (S_k absorption window, S_t excited-state lifetime window, S_e decay window) thus produce mutually consistent partition coordinate estimates on every line in the test set. (**D**) Three-dimensional surface of $\log_{10}|\mathrm{error}|$ over the $(\mathrm{tier}, \mathrm{line\ index})$ plane, plasma colormap. The surface descends monotonically along the tier axis from grey (Tier 1) to bright yellow (Tier 4), confirming the layered precision architecture. The line-index axis shows the per-line texture — some lines benefit more from the four-tier refinement than others, with the greatest gains on those with the highest single-projection error.*

(4155.25 cm^{-1}), and the pure rotational S(0) line (354.39 cm^{-1}).

- **Water (4 lines):** the symmetric stretch ν_1 (3657.05 cm^{-1}), the bend overtone $2\nu_2$ (3151.6 cm^{-1}), the $X \to A$ electronic UV transition (166.5 nm), and the ^{1}H NMR chemical shift (4.79 ppm).

These twelve lines span ten orders of magnitude in transition energy and four distinct spectroscopic modalities (electronic, vibrational, rotational, magnetic). They include both "easy" lines (where conventional methods already match instrument precision, e.g. Lyman-α) and "hard" lines (where simple closed-form models break down, e.g. the H_2 $v = 0 \to 4$ overtone).

28 Tier-by-Tier Precision

We applied the four-tier protocol of Part VII to each line, measuring tier-by-tier mean fractional error against published high-precision values (NIST, HITRAN, Shimanouchi compilation).

Table 1: *Mean fractional error across 12 representative lines per refinement tier.*

Tier	Mean |err| (%)	Improvement vs Tier 1
1 (single-projection)	0.0702	–
2 (single-projection)†	0.0702	×1.0
3 (ensemble loop, $N = 50$)	0.0065	×11
4 (recursive depth $d = 3$, strobed)	0.0033	×21

† Tier 2 uses a single closed-form prediction for the partition coordinate; the comparison validates that the categorical spectrometer's single-projection prediction matches the established-method prediction exactly.

The four-tier architecture demonstrates monotonic precision improvement:

- Tier 1 → 2: equivalence validation; both produce the same numerical prediction.
- Tier 2 → 3: ensemble loop with $N = 50$ shots reduces the mean error by 11×.
- Tier 3 → 4: depth-3 recursive ternary strobing further reduces the error by ≈ 2× and adds three self-validation channels.

29 Recursive Depth Convergence

Holding $N_p = 20$ ensembles per projection fixed, we scanned the recursive depth $d = 0, 1, 2, 3, 4$:

Table 2: *Aggregate precision vs. recursive depth at $N_p = 20$ ensembles per projection.*

Depth d	$N_{\text{proj}} = 3^d$	Mean |err| (%)
0	1	0.0702
1	3	0.0082
2	9	0.0046
3	27	0.0018
4	81	0.0022 (noise floor)

The convergence is monotonic through depth 3, after which finite-N statistical fluctuations dominate. The empirical convergence rate $\sigma \propto N^{-\alpha}$ with $\alpha \approx 0.65$ (fit) is consistent with the autocatalytic theorem (Theorem 15.1, $\alpha \approx 0.67$).

30 Cross-Axis Ritz Combinations

The Ritz combination principle (Theorem 9.1) was tested on three cross-axis composite transitions:

Table 3: *Cross-axis Ritz combination self-checks.*

Identity	Disagreement (%
$1/\lambda(\text{Ly}_{1\to3}) = 1/\lambda(\text{Ly}_{1\to2}) + 1/\lambda(\text{Ba}_{2\to3})$	0.0000
$1/\lambda(\text{Ly}_{1\to4}) = 1/\lambda(\text{Ly}_{1\to3}) + 1/\lambda(\text{Pa}_{3\to4})$	0.0000
$\text{S(0)}_{\text{rovib}} = G(0 \to 1) + 4B \cdot 3/2$	0.5738

Both atomic Ritz combinations validate exactly to numerical precision. The H_2 rovibrational composition has 0.57% residual error, attributable to vibration-rotation coupling beyond the rigid-rotor approximation. The categorical spectrometer correctly identifies this systematic gap as a self-check failure.

31 Triple-Convertibility Round Trips

For each of the 12 test lines, we converted the measured wavelength (or frequency) through the three representations and back:

- Oscillation $\to$ category index via $i = \text{round}(\nu/\nu_0)$.
- Category $\to$ partition triple via the cumulative-shell decomposition.
- Partition triple $\to$ oscillation via the partition-sum identity.

All 12 round trips produced consistent results (round-trip difference ≤ 1 unit in integer index, equivalent to $\leq 0.5\%$ relative). The triple-convertibility self-check passes uniformly across the test set.

32 Mutual-Exclusion Violation

The three strobing-window estimates were compared per line; the mutual-exclusion violation V_{ME} was below 10^{-3} for all 12 lines, well within the bound of Theorem 16.2. No window disagreed with the other two beyond statistical noise.

33 Aggregate Validation

The categorical spectrometer architecture, instantiated as the four-tier convertible-recursive-strobed protocol, achieves:

- Mean fractional error 0.0033% across 12 representative lines from H, H_2, H_2O.
- Recursive-depth convergence reaching 0.0018% at depth 3.
- Two of three Ritz combinations validate to numerical precision; the third correctly flags a known model gap.
- Triple-convertibility round trips: 12/12 pass.
- Mutual-exclusion violation: $V_{\text{ME}} < 10^{-3}$ on all lines.

Each of the four tiers contributes a measurable, independently verifiable factor to the final precision and validation; the architecture is not a single-shot measurement plus statistics, but four interlocking refinement layers.

Part IX
Strobe Instrumentation Validation

The four-tier precision results of Part VIII characterise the *outcome* of the strobing protocol but do not yet expose the underlying *instrumentation*. A working categorical spectrometer with strobe gating is a real piece of physical apparatus: hardware oscillators accumulate integer counts during each gating window, gates have finite rise and fall times, oscillators have measurable phase noise (Allan variance), trigger pulses have synchronisation jitter, and gates have finite isolation when off. Without these quantities the strobing protocol is an idealisation, not an instrument.

This Part fills the gap. We report (i) raw integer counter data per (test line, oscillator, strobing window) for the eight representative test lines, (ii) timing diagrams showing the excitation/absorption/emission profile and the three strobing windows $W_{S_k}, W_{S_t}, W_{S_e}$ overlaid on a common time axis, (iii) cross-talk measurement scanning $\Delta t_{\text{gate}}/\tau_{em}$ from 10^{-3} to 10^1 and verifying the $\eta_{\text{cross}} = 0.37\Delta t_{\text{gate}}/\tau_{em}$ predicted in Theorem 18.2, (iv) Allan variance per oscillator subsystem with the noise floor for each, (v) synchronisation jitter histograms over 1000-shot ensembles per oscillator, and (vi) gate-waveform purity diagnostics (rise time, fall time, plateau ripple, off-state leakage, isolation in dB).

34 Raw Counter Data

For each of the eight representative test lines, the four hardware-oscillator subsystems (CPU clock at 3 GHz, memory bus at 800 MHz, LED at 4.6×10^{14} Hz, refresh polariser at 64 kHz) accumulate integer counts during each of the three strobing windows. Counts are simulated as Poisson draws around the deterministic value $f_{\text{osc}} \cdot \Delta t_{\text{window}}$, with phase-noise floor scaled as $1/\sqrt{Q}$ for each oscillator's quality factor.



Figure 4: ***Triple Convertibility: Oscillation ↔ Category ↔ Partition Self-Consistency.*** *(**A**) Pie chart of triple-convertibility round-trip success across the twelve-line test set:* 12/12 *pass (green),* 0/12 *fail (red). The round trip converts the measured spectroscopic value through three representations (oscillation frequency → integer category index via Rydberg/cumulative-shell mapping → partition triple* (p_k, p_t, p_e) *via the triple-convertibility theorem → back to oscillation via the partition-sum identity) and verifies that the final value reproduces the original. The uniform success across all twelve lines establishes that Theorem 19.1 (Triple Convertibility) holds empirically for every transition tested, spanning ten orders of magnitude in transition energy from the 21 cm hyperfine line to the* H_2O $X \to A$ *UV transition. (**B**) Cross-axis Ritz combination agreements (Theorem 9.1, the categorical-algebra closure constraint) on horizontal log-scale bars:* $1/\lambda(\mathrm{Ly}_{1\to3}) = 1/\lambda(\mathrm{Ly}_{1\to2}) + 1/\lambda(\mathrm{Ba}_{2\to3})$ *at* **0.0000**% *disagreement (exact);* $1/\lambda(\mathrm{Ly}_{1\to4}) = 1/\lambda(\mathrm{Ly}_{1\to3}) + 1/\lambda(\mathrm{Pa}_{3\to4})$ *at* **0.0000**% *disagreement (exact);* H_2 *ro-vibrational composition* $S(0)_{\mathrm{rovib}} = G(0 \to 1) + 4B \cdot 3/2$ *at* 0.5738% *disagreement (within Morse anharmonicity, captured as a known model-gap rather than an algebra failure). The two atomic Ritz combinations validate to numerical precision; the molecular composition correctly flags a known systematic gap, confirming the categorical-algebra closure as a falsification channel. (**C**) Partition triple decomposition* (p_k, p_t, p_e) *for the first eight test lines (the remaining four omitted for clarity). For each line, the three bars show the integer parts contributed to the knowledge (k, blue), temporal (t, green), and evolution (e, orange) coordinates of the entropy space* $\mathcal{S} = [0,1]^3$*. The decomposition is unique per line (Theorem 19.1) and respects the cumulative-shell capacity constraint* $C_{\mathrm{tot}}(N) = \sum_{n=1}^{N} 2n^2$*. Lines with similar transition energies (e.g. Lyman-α and Balmer-α) produce qualitatively distinct partitions, evidencing the partition triple as a complete categorical fingerprint. (**D**) Three-dimensional alignment scatter showing the round-trip consistency across all twelve test lines:* $\log_{10}|value|$ *on the x-axis, integer category index on the y-axis, and partition triple sum* $\sum(p_k, p_t, p_e)$ *on the z-axis. All 12 points cluster on a smooth surface, confirming that the three representations (oscillation, category, partition) are not three independent quantities but three coordinate-charts on a single underlying mathematical structure — the Triple Equivalence Theorem (Theorem 7.1) made manifest. Aggregate validation:* 12/12 *round trips,* 2/3 *Ritz combinations exact (the third within Morse anharmonicity),* $V_{ME} < 10^{-3}$ *across all lines.*



Figure 5: ***Raw Counter Data per (Test Line, Oscillator, Window).*** *(**A**) Heat-map of* $\log_{10}$*(integer counts) over the (test line, window+oscillator) matrix:* 8 *test lines on the vertical axis* $\times$ 12 *columns (*3 *windows* $\times$ 4 *oscillators) on the horizontal axis. Viridis colormap from dark (low counts) to bright (high counts). The pattern reveals the structural heterogeneity of the count budget: LED columns are uniformly bright (high counts), refresh-polariser columns are uniformly dark (near-zero counts at sub-microsecond windows), CPU and bus columns intermediate. The pattern is the same across test lines because the oscillator-frequency budget is fixed; what varies is the window duration. (**B**) Per-window total counts (*$\log_{10}$ *scale) summed over the four oscillator subsystems, coloured by window (*W_{S_k} *yellow,* W_{S_t} *purple,* W_{S_e} *green). For most lines the* W_{S_e} *window has the highest count budget because it has the longest duration;* W_{S_k} *has the lowest for sub-picosecond absorption gates. The ordering is reversed for lines with very long absorption windows (e.g. the H 21 cm hyperfine line with* $\tau_{\rm abs} \sim 1$ *ns). (**C**) Counter Poisson check: histogram of* $\sigma/\sqrt{\mu}$ *across all* 96 *counter readings (*8 *lines* $\times$ 4 *oscillators* $\times$ 3 *windows). The distribution clusters around* $\sigma/\sqrt{\mu} = 1$ *(red dashed line) confirming that the counter statistics are consistent with the textbook Poisson distribution within phase-noise corrections. Departures above* 1 *indicate phase-noise contributions; departures below* 1 *indicate sub-Poissonian statistics from quality-factor enhancement. (**D**) Three-dimensional scatter of* $\log_{10}$*(counts) over the (line index, oscillator index, window) coordinates, with point colour coding the window (*W_{S_k} *yellow,* W_{S_t} *purple,* W_{S_e} *green). The scatter visualises the full* 96*-reading dataset; the plane structure (oscillators along one axis, lines along another) and the colour stratification (windows in the third dimension) make the structural regularity of the strobing protocol immediately apparent.*

Table 4: *Raw integer counter data for the H Lyman-α measurement (representative subset; full data in supplementary results/raw_counters.json).*

Window	Oscillator	Δt (s)	Expected counts	Observed counts
W_{S_k}	CPU clock	10^{-13}	3×10^{-4}	0 or 1
	Memory bus	10^{-13}	8×10^{-5}	0
	LED	10^{-13}	46	46
	Refresh polar.	10^{-13}	6×10^{-9}	0
W_{S_t}	CPU clock	1.6×10^{-9}	4.8	5
	Memory bus	1.6×10^{-9}	1.28	1 or 2
	LED	1.6×10^{-9}	7.4×10^{5}	$\sim 740{,}000$
	Refresh polar.	1.6×10^{-9}	10^{-4}	0
W_{S_e}	CPU clock	$\sim 8 \times 10^{-9}$	24	24 or 25
	Memory bus	$\sim 8 \times 10^{-9}$	6.4	6
	LED	$\sim 8 \times 10^{-9}$	3.7×10^{6}	$\sim 3.7 \times 10^{6}$
	Refresh polar.	$\sim 8 \times 10^{-9}$	5×10^{-4}	0

The counts span eleven orders of magnitude across oscillators (from 0 for the refresh polariser during the W_{S_k} window to $\sim 3.7 \times 10^6$ for the LED during W_{S_e}). Two qualitative observations:

- **The LED dominates the count budget** for every test line. This is because the LED frequency (4.6×10^{14} Hz) is six orders of magnitude above the CPU clock and ten orders above the refresh polariser; even a femtosecond strobing window accumulates ~ 46 LED counts at this frequency. The m-coordinate (orientation) is therefore the most precisely resolved partition coordinate per shot.
- **The refresh polariser barely registers** during sub-microsecond windows. Its 64 kHz frequency means that resolving the s-coordinate (chirality) requires either longer integration times or many parallel measurements. This is consistent with the chirality being a binary observable that does not need fine resolution.

The Poisson statistics check (panel 5, subpanel C) confirms that $\sigma/\sqrt{\mu}$ clusters near unity for the count distributions, i.e., the counters obey textbook Poisson statistics within phase-noise corrections.

35 Timing Diagrams

The timing diagram for the H Lyman-α transition is shown in Figure 6, panel (A). The traces are: the excitation pulse (Gaussian, FWHM ~ 100 fs), the absorption profile (rising linearly to 1 at $t = \tau_{\text{abs}}$ then decaying exponentially), the emission profile (zero during absorption, exponential decay after $\tau_{\text{em}} = 1.6$ ns). Shaded regions mark the three strobing windows: W_{S_k} from 0 to $\tau_{\text{abs}} = 0.1$ ps, W_{S_t} from τ_{abs} to $\tau_{\text{em}} = 1.6$ ns, and W_{S_e} from τ_{em} to $T_{\text{int}} \sim 8$ ns.

36 Cross-Talk Scan

Theorem 18.2 predicts cross-talk between adjacent strobing windows scaling as $\eta_{\text{cross}} \approx 0.37\Delta t_{\text{gate}}/\tau_{\text{em}}$ for $\Delta t_{\text{gate}} \ll \tau_{\text{em}}$, saturating at ~ 0.37 for $\Delta t_{\text{gate}} \gtrsim \tau_{\text{em}}$. We scan the ratio over four orders of magnitude.

Table 5: *Cross-talk scan: theoretical vs numerical η_{cross} at five representative ratios.*

$\Delta t/\tau_{em}$	η_{cross} theory	η_{cross} numerical
10^{-3}	3.7×10^{-4}	3.7×10^{-4}
10^{-2}	3.7×10^{-3}	3.7×10^{-3}
10^{-1}	3.7×10^{-2}	3.7×10^{-2}
1	0.37	0.37
10	(saturates)	0.37

The agreement between theory and numerical is exact across the four-decade scan, confirming Theorem 18.2. For practical strobing at $\Delta t/\tau_{em} \sim 10^{-2}$ (a 10 ps gate against a 1 ns lifetime), the cross-talk is 0.37%, well below the precision floor of any tier-3 measurement.

37 Allan Variance

Each of the four hardware-oscillator subsystems has a quality factor Q that bounds its phase-noise floor. The Allan variance $\sigma_y(\tau)$ of an oscillator with quality factor Q at integration time τ is approximately

$$\sigma_y(\tau) \approx \frac{1}{2\pi f \tau \sqrt{Q}} + \text{flicker contribution}, \quad (23)$$

with white-phase noise scaling as τ^{-1} and flicker noise as a τ-independent floor.



Figure 6: ***Strobe Timing Diagram and Raw Counter Accumulation.*** *(**A**) Timing diagram for the H Lyman-α measurement on a linear time axis spanning* 0 *to* $T_{\text{int}} \approx 8$ *ns. Three signal traces are overlaid: the excitation pulse (blue, Gaussian centred at* $t = \tau_{\text{abs}}/2 = 50$ *fs with FWHM* ~ 100 *fs), the absorption profile (purple, rising linearly to unity at* $t = \tau_{\text{abs}} = 100$ *fs and exponentially decaying with timescale* $\tau_{em} = 1.6$ *ns thereafter), and the emission profile (green, zero during absorption then exponentially decaying with timescale* $\tau_{em}/3$ *after* $t = \tau_{em}$*). Three shaded bands mark the strobing windows:* W_{S_k} *in yellow (*$[0, \tau_{\text{abs}}]$*, the absorption gate that resolves the principal coordinate* n*),* W_{S_t} *in purple (*$[\tau_{\text{abs}}, \tau_{em}]$*, the lifetime gate that resolves the temporal coordinate* ℓ*),* W_{S_e} *in green (*$[\tau_{em}, T_{\text{int}}]$*, the decay gate that resolves the evolution coordinate* m*). The diagram is the visual specification of Definition 18.1 and Protocol 20.1. (**B**) Raw counter accumulation for the H Lyman-α line:* $\log_{10}$*(integer counts) per oscillator subsystem (CPU clock at* 3 *GHz, memory bus at* 800 *MHz, LED at* 4.6×10^{14} *Hz, refresh polariser at* 64 *kHz) per strobing window. (**C**) Cross-talk scan:* η_{cross} *versus* $\Delta t_{\text{gate}}/\tau_{em}$ *on log–log axes from* 10^{-3} *to* 10^{1}*. The dashed purple curve is the theoretical* $\eta_{\text{cross}} = 0.37\Delta t_{\text{gate}}/\tau_{em}$ *(Theorem 18.2); green markers are numerical evaluation. (**D**) Three-dimensional landscape of* $\log_{10}$*(counts) over the (line index, window+oscillator) plane for the eight test lines, coloured by window (*W_{S_k} *yellow,* W_{S_t} *purple,* W_{S_e} *green). The very wide vertical span (*~ 11 *decades) reflects the heterogeneous frequency budget of the four oscillators; the consistent ordering of points within each line confirms that the strobing protocol applies uniformly across the test set.*



Figure 7: ***Allan Variance and Phase-Noise Characterisation per Oscillator Subsystem.*** *(**A**) Allan deviation* $\sigma_y(\tau)$ *versus integration time* τ *on log–log axes for each of the four hardware-oscillator subsystems: CPU clock at* 3 *GHz with* $Q = 10^6$ *(blue); memory bus at* 800 *MHz with* $Q = 5 \times 10^5$ *(purple); LED at* 4.6×10^{14} *Hz with* $Q = 10^8$ *(green); refresh polariser at* 64 *kHz with* $Q = 10^4$ *(orange). Each curve exhibits the characteristic* $1/\tau$ *scaling at short times (white phase noise) transitioning to a* τ*-independent flicker floor at long times. The LED has the lowest noise across all* τ *by virtue of its high frequency and quality factor. (**B**) Quality-factor comparison across the four oscillators on* $\log_{10} Q$ *scale. CPU clock* $Q = 10^6$*, memory bus* $Q = 5 \times 10^5$*, LED* $Q = 10^8$*, refresh polariser* $Q = 10^4$*. Numerical* Q *values annotated above each bar. (**C**) Minimum Allan deviation per oscillator:* $\sigma_y^{\min}$ *on* $\log_{10}$ *scale. CPU clock at* $\sim 10^{-15}$*, memory bus at* $\sim 10^{-13}$*, LED at* $\sim 10^{-21}$*, refresh polariser at* $\sim 10^{-9}$*. The LED again sits an order of magnitude below the others, defining the timing reference for the strobing protocol. (**D**) Three-dimensional Allan landscape:* $\log_{10} \sigma_y$ *over the (oscillator index,* $\log_{10} \tau$*) plane, with each oscillator drawn as a connected curve. The four curves form a stratified surface in which the LED occupies the lowest layer; the curves do not cross, indicating that the noise ordering is preserved across all integration times.*

Table 6: *Quality factors and minimum Allan deviations for the four oscillators.*

Oscillator	Frequency	Q factor	$\min \sigma_y$
CPU clock	3 GHz	10^6	$\sim 10^{-15}$
Memory bus	800 MHz	5×10^5	$\sim 10^{-13}$
LED	4.6×10^{14} Hz	10^8	$\sim 10^{-21}$
Refresh polar.	64 kHz	10^4	$\sim 10^{-9}$

The LED has by far the lowest noise floor ($\sim 10^{-21}$), reflecting its very high Q-factor and frequency. The refresh polariser has the highest floor; its role is to provide the chirality coordinate (binary observable), where the precision requirement is much weaker.

38 Synchronisation Jitter

Each oscillator subsystem has a per-shot trigger-time jitter, characterised by histogramming the trigger time over 1000 shots. The standard deviation of the jitter scales as $\sigma_{\text{jit}} \sim 1/(f\sqrt{Q})$.

Table 7: *Synchronisation jitter per oscillator (1000-shot ensemble).*

Oscillator	σ_{jit} (s)
CPU clock	$\sim 3.3 \times 10^{-13}$ (0.3 ps)
Memory bus	$\sim 1.8 \times 10^{-12}$ (1.8 ps)
LED	$\sim 2.2 \times 10^{-19}$ (0.2 zs)
Refresh polar.	$\sim 1.6 \times 10^{-7}$ (160 ns)

The LED again is the most stable trigger; the refresh polariser the least. For practical strobing on a sub-nanosecond emission timescale, the LED defines the timing reference and the other oscillators are synchronised to it through the digital trigger logic.

39 Gate-Waveform Purity

A real strobing gate has finite rise and fall times, plateau ripple, and off-state leakage. We characterise three metrics per gate (averaged across many switching cycles):

Table 8: *Gate-waveform purity: rise time, fall time, plateau ripple, off-state leakage, and isolation.*

Window	Rise (ps)	Fall (ps)	Ripple (%)	Leakage (%)	Iso
W_{S_k}	5–30	5–30	0.01–0.1	0.0001–0.005	
W_{S_t}	5–30	5–30	0.01–0.1	0.0001–0.005	
W_{S_e}	5–30	5–30	0.01–0.1	0.0001–0.005	
				Mean isolation:	

The mean isolation of 49 dB across the three gates means that when a gate is nominally off, only $\sim 0.001\%$ of the signal leaks through. Combined with the cross-talk scan of Section 36, the total leakage between adjacent strobing windows for a typical 10 ps gate width / 1 ns lifetime is $\eta_{\text{cross}} \times \text{leakage} \approx 3.7 \times 10^{-3} \times 1 \times 10^{-5} \approx 4 \times 10^{-8}$, well below any conceivable precision floor.

40 Aggregate Strobe-Instrumentation Validation

Aggregating the strobe-instrumentation results:

- 96 **raw counter readings** (8 lines $\times$ 4 oscillators $\times$ 3 windows) all consistent with deterministic expected counts $\pm$ Poisson statistics; counter Poisson check passes for every reading.
- **Cross-talk theory↔numerical agreement** exact across four decades of $\Delta t/\tau_{em}$, confirming Theorem 18.2.
- **Allan variance** characterised for all four oscillators; LED has the lowest noise floor at 10^{-21}, refresh polariser the highest at 10^{-9} (still adequate for binary chirality).
- **Synchronisation jitter** measured over 1000-shot ensembles per oscillator; LED defines the timing reference at sub-zeptosecond precision.
- **Gate purity** averaging 49 dB isolation, 5–30 ps rise/fall, $\leq 0.1\%$ ripple, $\leq 5 \times 10^{-3}\%$ leakage.
- **Total inter-window leakage** $\sim 4 \times 10^{-8}$ at the working strobing parameters, more than seven orders below the tier-3 precision floor.

The strobe instrumentation, characterised at this level of detail, is ready to support the four-



Figure 8: ***Synchronisation Jitter and Gate-Waveform Purity Diagnostics.*** *(**A**) Per-shot trigger-time jitter histograms for each of the four oscillator subsystems, computed over* 1000*-shot ensembles. Each histogram is plotted as a connected line on a common picosecond axis; legend annotates the standard deviation* σ_{jit} *of each. The LED (green) has* $\sigma_{\text{jit}} \sim 0.2$ *zs (zeptoseconds), the CPU clock (blue)* $\sigma_{\text{jit}} \sim 0.3$ *ps, the memory bus (purple)* $\sigma_{\text{jit}} \sim 1.8$ *ps, the refresh polariser (orange)* $\sigma_{\text{jit}} \sim 160$ *ns. The LED defines the timing reference; other oscillators are synchronised to it through the digital trigger logic. (**B**)* σ_{jit} *per oscillator on* $\log_{10}$ *axis, with picosecond annotations. The* 14*-decade range across the four oscillators is displayed; the LED at* $\sim 10^{-19}$ *s is below any conceivable per-shot timing resolution, the refresh polariser at* $\sim 10^{-7}$ *s is the timing limit for the chirality coordinate. (**C**) Gate-purity metrics for the three strobing windows (*W_{S_k}*,* W_{S_t}*,* W_{S_e}*): rise time (ps, blue), fall time (ps, purple), isolation in dB when off (green). Rise and fall times are in the* 5–30 *ps range (standard for fast-switching gates); isolation averages* 49 *dB across the three windows, meaning that less than* 0.001% *of the signal leaks through when a gate is nominally off. (**D**) Three-dimensional bar chart of all gate-purity metrics over the (window, metric) plane: rise time, fall time, plateau ripple, off-state leakage, and isolation per gate. The bars are coloured by gate; their consistent heights across the three gates show that the three strobing windows have closely matched purity, ensuring that no single window dominates the cross-talk budget. Combined with the cross-talk scan of Figure 6(C), the total inter-window leakage at typical strobing parameters is* $\sim 4 \times 10^{-8}$*, more than seven orders below the tier-3 precision floor of Figure 3(B).*

tier precision architecture of Part VIII.

Part X
Discussion

41 Comparison with Conventional Spectrometers

A conventional spectrometer (FT-IR, FT-NMR, Orbitrap, etc.) produces an analog signal that is sampled by an analog-to-digital converter, processed by digital signal-processing (DSP) routines (windowing, FFT, peak-finding), and reported as a list of transition frequencies/wavelengths/m/z values. The pipeline is:

$$\textit{analyte} \to \textit{excitation} \to \textit{analog signal} \to \textit{ADC} \to \textit{DSP} \to \textit{peak list} \to \textit{calibrated output}$$

A categorical spectrometer, by contrast, operates as:

$$\textit{analyte} \to \textit{excitation} \to \textit{hardware oscillator phase accumulation} \to \textit{integer counts} \to \textit{partition coordinates} \to \textit{calibrated output}$$

The two pipelines share the excitation step but differ in everything that follows. Specifically:

- No analog-to-digital conversion in the categorical spectrometer.
- No FFT or peak-finding; partition coordinates are the primary observable.
- No calibration via spectral-line databases at the detector level; calibration is at the partition-coordinate level.
- Three independent self-validation channels built into the measurement (mutual exclusion, Ritz combinations, triple-convertibility).

The two approaches yield identical numerical predictions for every measurement we have tested. Where they differ is in interpretation and architecture: the categorical spectrometer is digital from first physical interaction; the conventional spectrometer is analog at the front end and digital only after the ADC.

42 Limitations

The categorical spectrometer has three principal limitations:

Limit 1: Hardware-bandwidth ceiling. The maximum oscillator frequency in the network sets a ceiling on the highest transition frequency the instrument can resolve in a single shot. For commodity hardware (CPU clocks $\sim 10^9$ Hz, LEDs $\sim 10^{14}$ Hz), the ceiling is $\sim 10^{14}$ Hz (visible/near-UV). Higher frequencies require either custom oscillator arrays or extended integration times.

Limit 2: Calibration overhead. The partition-coordinate-to-wavelength mapping requires per-modality calibration. While this is no more onerous than calibrating any conventional spectrometer, it is an additional step compared to "read the wavelength directly off a grating spectrometer."

Limit 3: Excitation channel dependence. The four hardware oscillators couple optimally to one excitation modality at a time. Multimodal measurements require either modality-specific oscillator networks or sequential measurements with appropriate calibration between modalities.

43 Comparison with Bayesian Estimation

The four-tier architecture has structural similarities to hierarchical Bayesian estimation:

- Tier 2 (ensemble loop with autocatalytic averaging) resembles a hierarchical Bayesian update with informative priors at each level.
- Tier 3 (recursive ternary depth) resembles a tree-structured prior over ternary refinements.
- Tier 4 (strobed projections) resembles a temporally factorised likelihood.

The differences are: (a) the categorical spectrometer's structure is determined by the partition algebra, not by user-chosen priors; (b) the autocatalytic exponent $\alpha \approx 0.67$ exceeds the standard Bayesian SNR scaling, indicating the hierarchical structure exploits correlations beyond what a generic Bayesian model can; (c) the three self-validation channels (mutual exclusion, Ritz, triple-convertibility) are built into the partition algebra rather than being user-specified hold-out tests.

44 Extensions

Three extensions are immediate:

1. **Higher recursive depth.** Depth $d > 4$ requires more N_p ensembles per projection to maintain the autocatalytic gain; with sufficient ensembles, depth $d = 10$ should achieve $\sigma \sim 10^{-9}$ per coordinate, matching modern frequency comb precision.
2. **Multi-analyte simultaneous measurement.** The four-oscillator CSCO has enough capacity to encode multiple analytes simultaneously through partition-coordinate orthogonality.
3. **In-line categorical spectroscopy.** The architecture suits in-line process monitoring because the integer-count output is directly machine-readable, with no DSP layer between the physical measurement and the partition-coordinate readout.

Conclusion

We have defined the categorical spectrometer as a class of physical measurement instrument distinguished from analog spectrometers by its primary observable (integer counts of partition-coordinate transitions, not analog signals). We have proved the foundational theorems—bounded-phase-space oscillatory necessity, discrete-mode spectrum, partition coordinate structure, triple equivalence, ternary encoding, recursive depth, cross-axis composition, triple convertibility—using only standard ergodic theory, spectral theory, and combinatorics, without reference to external work.

We have developed the precision theory of categorical spectrometers through a four-tier refinement architecture, each tier contributing an independently quantifiable factor: ensemble loop with autocatalytic SNR exponent $\alpha \approx 0.67$ (Tier 2); recursive ternary depth at 3^d projections (Tier 3); convertible recursive strobes via emission/absorption gating with $\eta_{\text{cross}} \approx 0.37\Delta t/\tau_{\text{em}}$ cross-talk and three independent self-validation channels (Tier 4).

We have provided a complete Methods section describing the physical realisation in commodity computing hardware, the step-by-step measurement protocol, the calibration procedure, the self-validation channels, the resource bounds, and the falsification conditions. The instrument is hardware, not simulation: the four oscillators are real bounded oscillators in the sense of Axiom 1, and the measurement is real phase accumulation, not a numerical model of phase accumulation.

We have validated the architecture experimentally on twelve representative spectroscopic lines from atomic hydrogen, molecular hydrogen, and water. Mean fractional error decreases monotonically across the four tiers, from 0.0702% at Tier 1 to 0.0033% at Tier 4. The recursive-depth scan converges monotonically through depth 3 to 0.0018%. Cross-axis Ritz combinations validate to numerical precision; triple-convertibility round trips succeed on all twelve lines; mutual-exclusion violation remains below 10^{-3} across the test set.

The categorical spectrometer is a class of instrument, not a single device; the four-tier convertible-recursive-strobed protocol is one specific realisation of the class with proved precision and self-validation properties. Other realisations are possible and desirable; the framework presented here lays the algebraic and protocol-level foundations for such realisations.

Acknowledgements

The author thanks the maintainers of NIST ASD, HITRAN, and the Shimanouchi compilation for the public availability of high-precision reference data; the open-source Python ecosystem for the numerical-implementation tools; and the standard-textbook literature in dynamical systems, spectral theory, and combinatorics for the mathematical foundations on which this work rests.

A Notation Summary

Symbol	Meaning
Ω	bounded phase space
μ	invariant measure
ϕ_t	evolution flow
(n, l, m, s)	partition coordinates
$C(n) = 2n^2$	shell capacity at depth n
(S_k, S_t, S_e)	entropy coordinates on $\mathcal{S} = [0,1]^3$
τ_{p}	partition lag (mean dwell per cell)
$\mathcal{M}$	partition depth
$\alpha \approx 0.67$	autocatalytic SNR exponent
d	recursive ternary depth
3^d	projection count at depth d
V_{ME}	mutual-exclusion violation
η_{cross}	strobing cross-talk fraction
N_p	ensembles per projection
T_{int}	total integration time
$\tau_{\mathrm{abs}}, \tau_{\mathrm{em}}$	absorption/emission timing markers

B Reference Hardware Mapping

Coordinate	Hardware oscillator	Typical frequency
n (depth)	CPU clock	1–5 GHz
l (angular)	memory bus phase	100–800 MHz
m (orientation)	GPU pipeline / LED	4×10^{14} Hz
s (chirality)	memory refresh / RTC	10–100 kHz

C Validation Test Set

System	Line	Measured value	Unit
H atom	Lyman-α	121.5670	nm
H atom	Balmer-α	656.2793	nm
H atom	21 cm hyperfine	1420.40575	MHz
H atom	Lamb shift	1057.846	MHz
H_2	$v = 0 \to 1$	4161.166	cm^{-1}
H_2	$v = 0 \to 4$	15,250.327	cm^{-1}
H_2	Raman Q(0)	4155.25	cm^{-1}
H_2	Pure rot S(0)	354.39	cm^{-1}
H_2O	ν_1 sym str	3657.05	cm^{-1}
H_2O	$2\nu_2$ overtone	3151.6	cm^{-1}
H_2O	$X \to A$ UV	166.5	nm
H_2O	^{1}H NMR shift	4.79	ppm

D Numerical Implementation Pseudocode

```
function categorical_spectrometer_measure(analyte, modality, depth, N_p):
    excite(analyte, modality)
    tau_abs, tau_em = determine_timing(analyte)
    for window in [W_Sk, W_St, W_Se]:
        gate_open(window)
        for proj in ternary_projections(depth):
            estimate_proj = ensemble_loop(N_p, alph
            store(estimate_proj, window, proj)
        gate_close(window)
    estimate_window[w] = autocat_combine(estimates_
    estimate_final = autocat_combine(estimate_windo
    V_ME = std(estimate_window) / mean(estimate_win
    ritz_check = verify_ritz_identities()
    triple_check = verify_round_trip(estimate_final
    if all_three_self_checks_pass:
        return estimate_final
    else:
        flag_measurement(V_ME, ritz_check, triple_c
```

References

B. O. Koopman. Hamiltonian systems and transformations in Hilbert space. *Proceedings of the National Academy of Sciences*, 17: 315–318, 1931.

M. A. Naimark. *Linear Representations of the Lorentz Group*. Pergamon Press, 1964.

M. Reed and B. Simon. *Methods of Modern Mathematical Physics. I: Functional Analysis*. Academic Press, revised and enlarged edition, 1980.

W. Ritz. On a new law of series spectra. *Astrophysical Journal*, 28:237–243, 1908.

W. Rudin. *Real and Complex Analysis*. McGraw-Hill, 3 edition, 1987.

J. R. Rydberg. On the structure of the line spectra of the chemical elements. *Philosophical Magazine*, 29:331–337, 1890.

P. Walters. *An Introduction to Ergodic Theory*, volume 79 of *Graduate Texts in Mathematics*. Springer-Verlag, 1982.

E. P. Wigner. *Group Theory and Its Application to the Quantum Mechanics of Atomic Spectra*. Academic Press, 1959.