Exam : NSE4_FGT_AD-7.6

Title : Fortinet NSE 4 - FortiOS 7.6 Administrator

Vendor : Fortinet

Version : V13.95

KOREADUMPS.COM

QUESTION NO: 1
Refer to the exhibit.



An SD-WAN zone configuration on the FortiGate GUI is shown. Based on the exhibit, which statement is true?

A. The Underlay zone contains no member.

B. The virtual-wan-link and overlay zones can be deleted

C. The Underlay zone is the zone by default.

D. port2 and port3 are not assigned to a zone.

Answer: A

Explanation:
According to the FortiOS 7.6 Administrator Guide and the specific behavior of the SD-WAN GUI, here is the technical breakdown:
SD-WAN Zone Hierarchy and UI Elements: In the FortiGate GUI, SD-WAN zones that contain member interfaces are displayed with a plus (+) icon next to the checkbox. This icon allows administrators to expand the zone and view the specific physical or logical interfaces assigned to it.
Analysis of the "Underlay" Zone: In the provided exhibit, the virtual-wan-link and overlay zones both feature the plus (+) expansion icon, indicating they have active members. The Underlay zone, however, lacks this icon and displays a red status icon. This is the visual indicator in FortiOS that the zone is currently empty and contains no member interfaces.
Mandatory Zone Membership: In FortiOS 7.x, every SD-WAN member interface must be assigned to a zone. It is not possible for an interface to be an "SD-WAN member" (as shown in the legend with port2 and port3) without being assigned to a zone. Since port2 and port3 are listed in the legend, they are indeed assigned to one of the other expanded zones (likely virtual-wan-link or overlay), making Option D incorrect.
Default Zone Behavior: While FortiOS 7.6 often creates default zones like virtual-wan-link, underlay, and overlay during certain configuration wizards or by default in newer versions, they are distinct entities. There is no single "default" zone that acts as a global catch-all in the way Option C suggests.
Immutability of System Zones: While certain system-defined zones have restrictions, the primary focus of this specific exhibit is the current membership state, which clearly shows the Underlay zone is empty.

KOREADUMPS.COM

QUESTION NO: 2
You are onboarding an agentless, secure web gateway (SWG) endpoint for secure internet access (SIA). What will happen to the user's nonweb traffic? (Choose one answer)
A. All the nonweb traffic will bypass FortiSASE.
B. FortiSASE will use Firewall-as-a-Service (FWaaS) to redirect nonweb traffic.
C. FortiSASE will use SWG to redirect nonweb traffic to FortiExtender.
D. The endpoint will use split tunneling to redirect nonweb traffic to FortiSASE.
Answer: A

QUESTION NO: 3
When configuring firewall policies which of the following is true regarding the policy ID? (Choose two.)
A. It is mandatory to provide a policy ID while creating a firewall policy regardless of GUI or CLI.
B. A firewall policy ID identifies the order of policy execution in firewall policies.
C. A policy ID cannot be modified once a policy is created.
D. You can create a policy in CLI with policy ID 0
Answer: C,D

QUESTION NO: 4
An administrator has configured a dialup IPsec VPN on FortiGate with add-route enabled.

However, the static route is not showing in the routing table. Which two statements about this scenario are correct? (Choose two.)

A. The administrator must use a policy route instead of a static route for add-route to work properly.

B. The administrator must ensure phase 2 is successfully established

C. The administrator must define the remote network correctly in the phase 2 selectors.

D. The administrator must enable a dynamic routing protocol on the dialup interface.

Answer: B,C

Explanation:

With a dialup IPsec VPN on FortiGate, when add-route is enabled, FortiGate will only install the corresponding route when it has enough negotiated information from the tunnel. In FortiOS 7.6, that means the route is tied to the Phase 2 (Quick Mode) selectors and is created dynamically when the IPsec SA is actually up.

B . The administrator must ensure phase 2 is successfully established

This is required. FortiGate does not install the add-route route just because Phase 1 exists or because the configuration is present. The route is added when the tunnel is effectively usable, which requires Phase 2 (IPsec SA) to be up. If Phase 2 is not established, there is no active SA and FortiGate will not inject the related route into the routing table.

So, if the static route is not showing, one correct explanation is that Phase 2 is not up.

C . The administrator must define the remote network correctly in the phase 2 selectors This is also required. For dialup tunnels, FortiGate derives what route to add from the remote subnet(s) defined in the Phase 2 selector (proxy ID). If the remote network in Phase 2 is missing, incorrect, or too broad/too narrow in a way that prevents negotiation, the tunnel either won't come up (so no route), or the route that would be installed won't match what the administrator expects.

So, another correct explanation is that the Phase 2 remote network is not correctly defined, preventing the correct route from being created.

Why the other options are incorrect

A . Policy route instead of a static route

Add-route does not require policy routes. It is specifically a feature that injects a route (route-table entry) associated with the IPsec tunnel/SA and the Phase 2 selector networks.

D . Enable a dynamic routing protocol

Dynamic routing protocols (OSPF/BGP/RIP) are not required for add-route. Add-route is independent of dynamic routing and works by installing routes locally based on the negotiated selectors.

QUESTION NO: 5

Refer to the exhibit.

A RADIUS server configuration is shown.

KORFADUMPS.COM



An administrator added a configuration for a new RADIUS server While configuring, the administrator enabled Include in every user group What is the impact of enabling Include in every user group in a RADIUS configuration?

A. This option places the RADIUS server, and all users who can authenticate against that server, into every FortiGate user group.

B. This option places all FortiGate users and groups required to authenticate into the RADIUS server, which, in this case, is FortiAuthenticator.

C. This option places the RADIUS server, and all users who can authenticate against that server, into every RADIUS group.

D. This option places all users into every RADIUS user group, including groups that are used for the LDAP server on FortiGate.

Answer: A

Explanation:

Based on the FortiOS 7.6 Authentication and User Group documentation, the correct answer is A.

Meaning of "Include in every user group" (FortiOS 7.6)

When configuring a RADIUS server on FortiGate, enabling Include in every user group has a very specific and documented effect:

The configured RADIUS server object is automatically added to all FortiGate user groups.

YOREADUMPS.COM

As a result, any user who successfully authenticates against that RADIUS server becomes a valid member of every FortiGate user group, unless additional group filtering (such as RADIUS attributes) is applied.
This simplifies configuration when the same external authentication source must be accepted across multiple firewall policies that reference different user groups.
This behavior is explicitly described in the FortiOS 7.6 Administrator Guide under RADIUS authentication servers and user groups.
Why Option A is Correct
FortiGate user groups can include:
Local users
LDAP servers
RADIUS servers
Enabling Include in every user group causes FortiGate to:
Insert the RADIUS server into all existing and future FortiGate user groups Therefore, all users authenticating via this RADIUS server are implicitly allowed in every FortiGate user group.
This is exactly what option A describes.
Why the Other Options Are Incorrect
B: FortiGate does not push users or groups into the RADIUS server. Authentication is always initiated by FortiGate toward RADIUS.
C: FortiGate does not manage or modify RADIUS-side group definitions.
D: LDAP and RADIUS user groups are separate authentication mechanisms; this setting does not merge or affect LDAP groups.

QUESTION NO: 6
You have created a web filter profile named restrictmedia-profile with a daily category usage quota.
When you are adding the profile to the firewall policy, the restrict_media-profile is not listed in the available web profile drop down.
What could be the reason?
A. The web filter profile is already referenced in another firewall policy.
B. The firewall policy is in no-inspection mode instead of deep-inspection.
C. The naming convention used in the web filter profile is restricting it in the firewall policy.
D. The inspection mode in the firewall policy is not matching with web filter profile feature set.
Answer: D
Explanation:
In FortiOS 7.6, web filter profiles are inspection-mode dependent. Certain advanced web filtering features-such as daily category usage quota-are only supported when the firewall policy is operating in proxy-based inspection mode.
Why the profile is not visible
The profile restrictmedia-profile includes a daily category usage quota.
Daily quotas are a proxy-based web filtering feature.
If the firewall policy is configured with:
Inspection mode: Flow-based
Then FortiGate will not display proxy-only web filter profiles in the Web Filter drop-down list.

KOREADUMPS.COM

FortiGate automatically filters the available profiles based on feature compatibility with the policy's inspection mode.
This behavior is explicitly documented in the FortiOS 7.6 Web Filtering and Inspection Mode Compatibility sections.
Why the other options are incorrect
A . Already referenced in another firewall policyWeb filter profiles can be reused across multiple policies. This does not hide them.
B . Firewall policy is in no-inspection mode instead of deep-inspectionSSL inspection depth affects HTTPS visibility, not whether a web filter profile appears in the drop-down list.
C . Naming convention restrictionFortiOS does not restrict profile selection based on naming conventions.

QUESTION NO: 7
Refer to the exhibits.

Network diagram



Dynamic IP pool

KOREADUMPS.COM

Firewall policies

Edit Policy

Name: Internet

Schedule: always

Action: ACCEPT | DENY

Outgoing interface: WAN (port2)

Source & Destination (Show logic)

Source: all

User/group:

Destination: all

Service: ALL

Firewall/Network Options

Firewall/Network Options

Inspection mode: Flow-based | Proxy-based

NAT

IP pool configuration: Use Outgoing Interface Address | Use Dynamic IP Pool

Internet-pool

Preserve source port

Protocol options: default

KOREADUMPS.COM

A diagram of a FortiGate device connected to the network, as well as the firewall policy and IP pool configuration on the FortiGate device are shown.
Two PCs. PC1 and PC2, are connected behind FortiGate and can access the internet successfully. However, when the administrator adds a third PC to the network (PC3), the PC cannot connect to the internet.
Based on the information shown in the exhibit, which two configuration options can the administrator use to fix the connectivity issue for PC3? (Choose two.)

A. In the system settings, set Multiple Interface Policies to enable.

B. in the IP pool configuration, set end ipto 100.65.0.112.

C. In the firewall policy, set match-vip to enable using CLI.

D. In the IP pool configuration, set type to overload.

Answer: B,D

Explanation:
From the exhibits:
The firewall policy has NAT enabled and is configured to Use Dynamic IP Pool.
The selected IP pool (Internet-pool) is configured as:
Type: One-to-One
External IP Range: 100.65.0.110-100.65.0.111 (only two public IPs)
PC1 and PC2 can access the internet because each one-to-one NAT mapping consumes one public IP from the pool. When PC3 is added, there is no third public IP available in the pool, so FortiGate cannot allocate a one-to-one mapping for PC3 and the session fails.
FortiOS behavior here is standard: with one-to-one IP pools, the available pool size limits how many distinct internal sources can be translated concurrently (depending on allocation and sessions), and a pool with only two IPs will not reliably support three separate hosts needing translations.
Therefore, the administrator can fix this in two valid ways:
B . In the IP pool configuration, set end ip to 100.65.0.112.
This expands the pool by adding an additional public IP address, making three public IPs available (.110, .111, .112), so PC3 can be assigned an address for one-to-one NAT.
D . In the IP pool configuration, set type to overload.
Changing the pool type to overload enables PAT (many-to-one), allowing multiple internal hosts (PC1, PC2, PC3) to share the pool address(es) using different source ports. This removes the "one public IP per internal host" limitation inherent to one-to-one pools.
Why the other options are not correct:
A . Multiple Interface Policies is unrelated to IP pool exhaustion and does not solve NAT allocation limits.
C . match-vip affects VIP matching behavior for destination NAT/virtual IP usage and does not address the source NAT pool shortage causing PC3 to fail.

QUESTION NO: 8

Which two statements are correct when the FortiGate device enters conserve mode? (Choose two.)

A. FortiGate refuses to accept configuration changes.

B. FortiGate halts complete system operation and requires a reboot to regain available resources.

KORRADUMPS.COM

C. FortiGate continues to transmit packets without IPS inspection when the fail-open global setting in IPS is enabled.
D. FortiGate continues to run critical security actions, such as quarantine.
Answer: A,C

QUESTION NO: 9
Refer to the exhibits.

FortiGate HA cluster topology



Current HA status

```
HQ-NGFW-1 # get system ha status
 ...
Configuration Status:
    FGVM02TM24013423(updated 0 seconds ago): in-sync
    FGVM02TM24013423 chksum dump: e1 60 2e 42 b8 c1 c6 df 11 34 0c 21 80 79 a4 9f
    FGVM02TM24013501(updated 4 seconds ago): in-sync
    FGVM02TM24013501 chksum dump: e1 60 2e 42 b8 c1 c6 df 11 34 0c 21 80 79 a4 9f
 ...
number of member: 2
HQ-NGFW-1       , FGVM02TM24013423, HA cluster index = 1
HQ-NGFW-2       , FGVM02TM24013501, HA cluster index = 0
number of vcluster: 1
vcluster 1: work 169.254.0.2
Primary: FGVM02TM24013423, HA operating index = 0
Secondary: FGVM02TM24013501, HA operating index = 1
```

KOREADUMPS.COM

New FortiGate HA configuration

```
HQ-NGFW-1
# config system ha
     set group-id 5
     set group-name "Fortinet"
     set mode a-p
     set password *
     set hbdev "port7" 50 "port8" 60
     set session-pick enable
     set override disable
     set priority 90
     set monitor "port3"


HQ-NGFW-2
# config system ha
     set group-id 5
     set group-name "Fortinet"
     set mode a-p
     set password *
     set hbdev "port7" 50 "port8" 60
     set session-pick enable
     set override enable
     set priority 110
     set monitor "port3"
```

KOKEADUMPS.COM

Based on the current HA status, an administrator updates the override and priority parameters on HQ-NGFW-1 and HQ-NGFW-2 as shown in the exhibits.
What would be the expected outcome in the HA cluster?

A. HQ-NGFW-2 will take over as the primary because it has the override enable setting and higher priority than HQ-NGFW-1.

B. HQ-NGFW-1 will remain the primary because HQ-NGFW-2 has lower priority

C. The HA cluster will become out of sync because the override setting must match on all HA members.

D. HQ-NGFW-1 will synchronize the override disable setting with HQ-NGFW-2.

Answer: A

Explanation:

From the current HA status, HQ-NGFW-1 is the primary and HQ-NGFW-2 is the secondary.
The administrator then changes these HA parameters:
HQ-NGFW-1: set override disable, set priority 90
HQ-NGFW-2: set override enable, set priority 110
In FGCP (A-P mode), the override (preemption) feature controls whether a higher-priority unit is allowed to take over the primary role.
When override is enabled, the cluster will prefer (and can re-elect) the unit with the highest device priority to become primary (preempting a lower-priority primary when conditions trigger re-election behavior as defined by FGCP).
Here, HQ-NGFW-2 has:
override enabled
higher priority (110) than HQ-NGFW-1 (90)
Therefore, the expected result is that HQ-NGFW-2 becomes the primary.
Why the other options are incorrect:
B is incorrect because it claims HQ-NGFW-2 has lower priority (it is higher: 110 > 90).
C is incorrect because a mismatch in the override setting is not what causes the "configuration out of sync" condition shown in get system ha status (that is about synchronized configuration databases, not a requirement that override values must match to remain in-sync).
D is incorrect because HA settings like override/priority are not synchronized in the way regular configuration objects are; they are device-level HA parameters.

KODEADUMPS.COM

QUESTION NO: 10
Refer to the exhibit
A firewall policy to enable active authentication is shown.

When attempting to access an external website using an active authentication method, the user is not presented with a login prompt. What is the most likely reason for this situation?
A. No matching user account exists for this user.
B. The Remote-users group must be set up correctly in the FSSO configuration.
C. The Remote-users group is not added to the Destination
D. The Service DNS is required in the firewall policy.
Answer: D
Explanation:
Based on the exhibit and FortiOS 7.6 Active Authentication (captive portal) behavior, the most likely reason the user is not presented with a login prompt is that DNS is missing from the firewall policy.
What the exhibit shows
The firewall policy configured for active authentication includes:
Source: HQ_SUBNET and Remote-users
Destination: all
Services:

HTTP
HTTPS
ALL_ICMP
Security Profiles: Web filter and SSL inspection enabled
Authentication: Active (user group referenced)
DNS is not included as a service in the policy.
Why DNS is required for active authentication
In FortiOS 7.6, active authentication (captive portal) works as follows:
The user attempts to access a website using a URL (for example, www.example.com).
The client must first perform a DNS lookup to resolve the domain name.
FortiGate intercepts the initial HTTP/HTTPS request and redirects the user to the authentication portal.
If DNS traffic is blocked or not allowed:
The hostname cannot be resolved.
The HTTP/HTTPS request never properly occurs.
FortiGate has nothing to intercept, so the login prompt is never triggered.
This is explicitly documented in the FortiOS 7.6 Authentication and Captive Portal requirements, which state that DNS must be permitted for captive portal-based authentication to function correctly.
Why the other options are incorrect
A . No matching user account exists for this user
Incorrect.
If the user account did not exist, the login page would still appear, but authentication would fail after credentials are entered.
B . The Remote-users group must be set up correctly in the FSSO configuration Incorrect.
This policy is using active authentication, not FSSO.
FSSO configuration is irrelevant for active authentication login prompts.
C . The Remote-users group is not added to the Destination
Incorrect.
User groups are applied in the Source field for authentication-based policies.
Destination does not accept user groups.

KOREADUMPS.COM

QUESTION NO: 11
When configuring firewall policies which of the following is true regarding the policy ID? (Choose two.)
A. A firewall policy ID identifies the order of policy execution in firewall policies.
B. A policy ID cannot be modified once a policy is created.
C. You can create a policy in CLI with policy ID 0
D. It is mandatory to provide a policy ID while creating a firewall policy regardless of GUI or CLI.
Answer: B,C
Explanation:
According to the FortiOS 7.6 Administration Guide, the firewall policy ID is a unique numerical identifier assigned to each policy for internal database tracking and management purposes. It is important to distinguish the policy ID from the policy sequence. While the

FortiGate processes traffic based on a top-down approach (the sequence), the policy ID itself does not determine the order of execution (Statement A is incorrect).
In FortiOS, once a policy is committed to the configuration, the policy ID cannot be modified (Statement B). If an administrator needs to change a policy ID, they must either delete and recreate the policy or use the clone command in the CLI to copy the settings to a new ID.
Furthermore, the CLI provides a specific shortcut for policy creation: you can create a policy with ID 0 (Statement C). When the command edit 0 is used within the config firewall policy context, the FortiOS kernel automatically assigns the next available integer as the policy ID. This is a standard practice for efficient configuration via the command line. Statement D is incorrect because, while every policy must have an ID, the GUI automatically generates this value without requiring the user to manually provide or even see it during the initial creation process.

QUESTION NO: 12
Refer to the exhibits.

Network diagram



NAT IP pool configuration

Name	External IP Range	Type	ARP Reply
SNAT-Pool	100.65.0.49 - 100.65.0.49	Overload	Enabled
SNAT-Remote	100.65.0.149 - 100.65.0.149	Overload	Enabled
SNAT-Remote1	100.65.0.99 - 100.65.0.99	Overload	Enabled

Firewall policies

Policy	Source	Destination	Schedule	Service	Action	IP Pool	NAT
LAN (port4) → WAN (port2) 3							
TCP traffic (2)	all	BR1-FGT	always	ALL_TCP	ACCEPT	SNAT-Pool	NAT
PING traffic (3)	all	all	always	PING	ACCEPT	SNAT-Remote1	NAT
IGMP traffic (4)	all	all	always	IGMP	ACCEPT	SNAT-Remote	NAT

The exhibits show a diagram of a FortiGate device connected to the network, as well as the IP pool configuration and firewall policy objects.
The WAN (port2) interface has the IP address

KOREADUMPS.COM

100.65.0.101/24.
The LAN (port4) interface has the IP address
10.0.11.254/24.
Which IP address will be used to source NAT (SNAT) the traffic, if the user on HQ-PC-1 (10.0.11.50) pings the IP address of BR-FGT (100.65.1.111)?

A. 100.65.0.101

B. 100.65.0.49

C. 100.65.0.149

D. 100.65.0.99

Answer: D

Explanation:
From the exhibits, there are three relevant firewall policies from LAN (port4) to WAN (port2), each using a different IP pool for source NAT:
TCP traffic
Service: ALL_TCP
Destination: BR1-FGT
IP Pool: SNAT-Pool → 100.65.0.49
PING traffic
Service: PING
Destination: all
IP Pool: SNAT-Remote1 → 100.65.0.99
IGMP traffic
Service: IGMP
Destination: all
IP Pool: SNAT-Remote → 100.65.0.149
The user on HQ-PC-1 (10.0.11.50) is pinging BR1-FGT (100.65.1.111). In FortiOS, policy matching is based on (among other fields) source, destination, and service, and the first matching policy in top-down order is applied.
Because the traffic is ICMP echo (ping), it matches the policy named PING traffic (service PING, destination all). That policy explicitly uses Use Dynamic IP Pool with SNAT-Remote1, which is configured with external IP 100.65.0.99.
Therefore, the source NAT IP used for this ping is 100.65.0.99.

KOREADUMPS.COM

QUESTION NO: 13

An administrator manages a FortiGate model that supports NTurbo
How does NTurbo acceleration enhance antivirus performance?

A. For flow-based inspection. NTurbo establishes a dedicated data path to redirect traffic between the IPS engine and FortiGate ingress and egress interfaces.

B. For flow-based inspection. NTurbo creates two inspection sessions on the FortiGate device.

C. For proxy-based inspection. NTurbo offloads traffic to the content processor.

D. For proxy-based inspection. NTurbo buffers the whole file and then sends it to the antivirus engine.

Answer: A

Explanation:
According to the FortiOS 7.6 Administration Guide and Fortinet hardware acceleration (NTurbo) documentation, the correct answer is A.
What NTurbo Is (FortiOS 7.6 - Verified)
NTurbo is a hardware-based acceleration feature available on specific FortiGate models. It is designed to improve antivirus and IPS performance when operating in flow-based inspection mode.
NTurbo works by creating a fast, optimized data path between:
FortiGate ingress interface
IPS/AV engine
FortiGate egress interface
This minimizes CPU involvement and reduces packet traversal overhead.
Why Option A Is Correct
A . For flow-based inspection, NTurbo establishes a dedicated data path to redirect traffic between the IPS engine and FortiGate ingress and egress interfaces.
This is exactly how NTurbo works, as documented:
NTurbo applies to flow-based inspection only
It accelerates IPS and antivirus scanning
It creates a dedicated fast path that bypasses unnecessary processing steps This significantly improves throughput and lowers latency This description matches Fortinet's official explanation of NTurbo.
Why the Other Options Are Incorrect
B . NTurbo creates two inspection sessions
Incorrect. NTurbo does not duplicate sessions; it optimizes the packet path.
C . NTurbo offloads traffic to the content processor (proxy-based)
Incorrect. NTurbo does not apply to proxy-based inspection and does not offload to content processors.
D . NTurbo buffers the whole file and then sends it to the antivirus engine Incorrect. Buffering entire files is a proxy-based behavior, not NTurbo.

KOREADUMPS.COM

QUESTION NO: 14
An administrator wants to configure dead peer detection (DPD) on IPsec VPN for detecting dead tunnels. The requirement is that FortiGate sends DPD probes only when there is no inbound traffic.
Which DPD mode on FortiGate meets this requirement?
A. On Demand
B. Enabled
C. On Idle
D. Usabled
Answer: A
Explanation:
Based on the FortiOS 7.6 Infrastructure and IPsec VPN documentation, Dead Peer Detection (DPD) can be configured in three primary modes: On Demand, On Idle, and Disabled.
On Demand (Default Mode): This mode is specifically designed to minimize unnecessary traffic. In this mode, FortiGate sends DPD probes only when there is no inbound traffic but

the FortiGate is attempting to send outbound traffic. Because network communication is typically bidirectional, the absence of inbound traffic while outbound traffic is being sent is a primary indicator of a potentially dead tunnel. This matches the specific requirement described in the question.
On Idle: In this mode, DPD probes are sent if no traffic (neither inbound nor outbound) has been observed in the tunnel for a specific period. It verifies the tunnel status even when the connection is completely idle.
Enabled: In older versions or specific CLI contexts, "Enabled" may refer to periodic DPD, but in the current FortiOS 7.x/7.6 GUI and CLI terminology for Phase 1 settings, the active modes are defined as on-demand or on-idle.
Disabled: In this mode, the FortiGate does not send DPD probes but will still respond to DPD probes sent by the remote peer.
The requirement that the administrator wants probes sent only when there is no inbound traffic (usually implying the FortiGate is sending but not receiving) is the fundamental definition of the On Demand mechanism in the Fortinet curriculum.

QUESTION NO: 15
Refer to the exhibit.

```
HQ-NGFW-1 # diagnose test application ipsmonitor 1
            pid = 2044, engine count = 0 (+1)
            0 - pid:2074:2074 cfg:1 master:0 run:1
```

As an administrator you have created an IPS profile, but it is not performing as expected. While testing you got the output as shown in the exhibit What could be the possible reason of the diagnose output shown in the exhibit?

A. There is a no firewall policy configured with an IPS security profile.

B. Administrator entered the command diagnose test application ipsmonitor 5.

C. FortiGate entered into IPS fail open state.

D. Administrator entered the command diagnose test application ipsmonitor 99.

Answer: A
Explanation:
The exhibit shows the output of the following command:
diagnose test application ipsmonitor 1
pid = 2044, engine count = 0 (+1)
0 - pid:2074:2074 cfg:1 master:0 run:1
How to interpret this output (FortiOS 7.6 - IPS internals)
ipsmonitor displays the status of IPS engines running on the FortiGate.
engine count = 0 means:
No IPS scanning engines are currently active
IPS is not processing any traffic
In FortiOS, IPS engines are started on demand.
Critical documented behavior
IPS processes are only spawned when at least one firewall policy is configured with an IPS

KOREADUMPS.COM

profile and traffic matches that policy.
If no firewall policy references an IPS profile, the IPS engine:
Does not start
Shows engine count = 0
Appears "not working," even though the IPS profile exists
This is exactly what the diagnose output indicates.
Why option A is correct
A . There is no firewall policy configured with an IPS security profile.
Creating an IPS profile alone is not sufficient
IPS must be applied to an active firewall policy
Traffic must match that policy for the IPS engine to run
Otherwise, ipsmonitor will show engine count = 0
This matches FortiOS 7.6 IPS operational behavior.
Why the other options are incorrect
B . Administrator entered the command diagnose test application ipsmonitor 5.
Incorrect.
The exhibit clearly shows ipsmonitor 1
Using a different argument would not explain engine count = 0
C . FortiGate entered into IPS fail open state.
Incorrect.
In fail-open, IPS engines may be bypassed, but they still initialize
engine count = 0 specifically indicates IPS is not in use at all
D . Administrator entered the command diagnose test application ipsmonitor 99.
Incorrect.
The command argument affects debug level, not engine creation
Again, the exhibit shows ipsmonitor 1

QUESTION NO: 16
Refer to the exhibit.

```
date=2025-09-03 time=09:09:57 id=7545895911432388608 itime="2025-09-03 09:10:02" euid=3 epid=3 dsteuid=3 dstepid=101
logflag=0 logver=706003401 type="utm" subtype="app-ctrl" level="warning" action="block" sessionid=510 policyid=1 srcip=
10.0.11.50 dstip=54.146.230.62 srcport=53398 dstport=80 proto=6 logid=1059028705 service="HTTP" eventtime=
1756915797391471958 incidentserialno=116391982 direction="outgoing" apprisk="elevated" appid=30220 srcintfrole="undefined"
dstintfrole="undefined" applist="default" appcat="Video/Audio" app="ABC.Com" hostname="abc.go.com" url="/favicon.ico"
eventtype="signature" srcintf="port4" dstintf="port2" msg="Video/Audio: ABC.Com" tz="-0700" policytype="policy"
srccountry="Reserved" dstcountry="United States" poluuid="b11ac58c-791b-51e7-4600-12f829a689d9" agent="Mozilla/5.0 (X11;
Ubuntu; Linux x86_64; rv:142.0) Gecko/20100101 Firefox/142.0" httpmethod="GET" referralurl="http://abc.go.com/"
devid="FGVM02TM24013423" vd="root" dtime="2025-09-03 09:09:57" itime_t=1756915802 devname="HQ-NGFW-1"
```

Which two ways can you view the log messages shown in the exhibit? (Choose two.)
A. By right clicking the implicit deny policy
B. Using the FortiGate CLI command diagnose log test
C. By filtering by policy universally unique identifier (UUID) and application name in the log entry
D. In the Forward Traffic section
Answer: C,D
Explanation:
The exhibit shows a FortiGate UTM application control log with fields such as:
type="utm"

subtype="app-ctrl"
action="block"
policyid=1
appid=30220
appcat="Video/Audio"
service="HTTP"
apprisk="elevated"
This is a forward traffic security log, generated by Application Control applied to a firewall policy.
Why the correct answers are C and D
C . By filtering by policy universally unique identifier (UUID) and application name in the log entry Correct.
FortiOS logs can be viewed and filtered in:
Log & Report → Forward Traffic
Administrators can filter logs using fields such as:
Policy ID / Policy UUID
Application name (app)
Application ID (appid)
The log entry clearly includes application-related fields, making filtering by policy and application a valid and documented way to view these logs.
D . In the Forward Traffic section
Correct.
The log is a UTM Application Control log for traffic passing through a firewall policy.
Such logs are displayed under:
Log & Report → Forward Traffic
This is the standard and correct location to view application control, web filter, IPS, and other security profile logs related to user traffic.
Why the other options are incorrect
A . By right clicking the implicit deny policy
Incorrect.
Implicit deny policies do not generate UTM forward traffic logs like the one shown.
Application control logs are generated only by explicit firewall policies with security profiles enabled.
B . Using the FortiGate CLI command diagnose log test
Incorrect.
diagnose log test is used to test log connectivity and log settings, not to view historical log entries.
It does not display traffic or UTM logs.

QUESTION NO: 17
Refer to the exhibit.

KOREADUMPS.COM

SD-WAN traffic log

Application Name	Result	Policy ID	Destination Interface	SD-WAN Quality	SD-WAN Rule Name
YouTube	Accept (8.08 kB / 27...	1 (DIA)	port2		
YouTube	Accept (UTM Allowed)	1 (DIA)	port2		
Facebook	Accept (UTM Allowed)	1 (DIA)	port1		
Facebook	Accept (UTM Allowed)	1 (DIA)	port1		
Facebook	Accept (3.33 kB / 10...	1 (DIA)	port1		
YouTube	Accept (44.63 kB / 3....	1 (DIA)	port2		
CNN	Accept (UTM Allowed)	1 (DIA)	port1		
CNN	Accept (UTM Allowed)	1 (DIA)	port2		
CNN	Accept (UTM Allowed)	1 (DIA)	port2		

The administrator configured SD-WAN rules and set the FortiGate traffic log page to display SD-WAN-specific columns: SD-WAN Quality and SD-WAN Rule Name FortiGate allows the traffic according to policy ID 1 placed at the top. This is the policy that allows SD-WAN traffic. Despite these settings, the traffic logs do not show the name of the SD-WAN rule used to steer those traffic flows What could be the reason?

A. SD-WAN rule names do not appear immediately. The administrator must refresh the page.

B. There is no application control profile applied to the firewall policy.

C. Destinations in the SD-WAN rules are configured for each application, but feature visibility is not enabled.

D. FortiGate load balanced the traffic according to the implicit SD-WAN rule.

Answer: D

Explanation:

In FortiOS 7.6, SD-WAN steering decisions are recorded in traffic logs only when traffic matches an explicit SD-WAN rule (SD-WAN service rule). When no configured SD-WAN rule matches a session, FortiGate uses the implicit (default) SD-WAN rule/behavior to select a member (often resulting in load-balancing or default selection based on the configured SD-WAN algorithm).

In the exhibit, traffic is permitted by firewall policy ID 1, and the Destination Interface alternates between port1 and port2, but SD-WAN Rule Name remains empty. This is consistent with the sessions being forwarded by the implicit SD-WAN rule, which does not populate a named rule in the log columns.

Why the other options are not correct:

A: SD-WAN rule name logging is not a "delayed display" behavior requiring refresh; it is populated per-session when an explicit rule matches.

B: Application Control is not required for SD-WAN rule name to appear. Rule name logging depends on SD-WAN rule match, not on whether Application Control is enabled.

C: Feature visibility affects GUI display options, but the exhibit already shows the SD-WAN columns enabled; the issue is that no explicit SD-WAN rule is being hit.

QUESTION NO: 18

Refer to the exhibits.

KOREADUMPS.COM

Network diagram



KOREADUMPS.COM



KOREADUMPS.COM

Firewall policies

Policy	From	To	Source	Destination	Schedule	Service	Action	IP Pool	NAT
Internet (1)	LAN (port4)	WAN (port2)	all	all	always	ALL	ACCEPT		NAT
Web_Server_Access (2)	WAN (port2)	LAN (port4)	all	VIP-WEB-SERVER	always	HTTPS	ACCEPT		Disabled

A diagram of a FortiGate device connected to the network VIP object and firewall policy configurations are shown.
The WAN (port2) interface has the IP address
100.65.0.101/24.
The LAN (port4) interface has the IP address
10.0.11.254/24.
If the host 100.65.1.111 sends a TCP SYN packet on port 443 to 100.65.0.200. what will the

source address, destination address, and destination port of the packet be at the time FortiGate forwards the packet to the destination?

A. 10.0.11.254, 100.65.0.200. and 443, respectively

B. 10.0.11.254, 10.0.15.50, and 4443. respectively

C. 100.65.1. 111, 10.0.11.50, and 4443. respectively

D. 100.65.1.111, 10.0.11.50. and 443. respectively

Answer: C

Explanation:

From the exhibits:

A VIP named VIP-WEB-SERVER is configured on WAN (port2) with:

External IP: 100.65.0.200

Mapped (internal) IP: 10.0.11.50

Port forwarding enabled (TCP)

External service port: 443

Map to IPv4 port: 4443

The inbound firewall policy Web_Server_Access is:

From WAN (port2) to LAN (port4)

Destination: VIP-WEB-SERVER

Service: HTTPS

NAT: Disabled (meaning no source NAT is applied)

What happens to the packet

A host 100.65.1.111 sends TCP SYN dst-port 443 to 100.65.0.200.

When FortiGate matches the VIP and forwards traffic to the internal server, FortiGate performs destination NAT (DNAT) based on the VIP:

Source IP is unchanged because policy NAT is disabled:

Source remains 100.65.1.111

Destination IP is translated by the VIP:

Destination becomes 10.0.11.50

Destination port is translated by the VIP port-forward:

Destination port becomes 4443

Therefore, at the time FortiGate forwards the packet to the destination (internal server), it will be:

Source address: 100.65.1.111

Destination address: 10.0.11.50

Destination port: 4443

QUESTION NO: 19

A network administrator is reviewing firewall policies in both Interface Pair View and By Sequence View. The policies appear in a different order in each view. Why is the policy order different in these two views?

A. By Sequence View groups policies based on rule priority, while Interface Pair View always follows the order of traffic logs.

B. The firewall dynamically reorders policies in Interface Pair View based on recent traffic patterns, but By Sequence View remains static.

C. Interface Pair View sorts policies based on matching interfaces, while By Sequence View

KOREADUMPS.COM

shows the actual processing order of rules.

D. Policies in Interface Pair View are prioritized by security levels, while By Sequence View strictly follows the administrator's manual ordering.

Answer: C

Explanation:

In FortiOS 7.6, firewall policies can be displayed in multiple views to help administrators understand and manage rules more effectively. The difference in ordering between Interface Pair View and By Sequence View is intentional and documented.

Why the policy order is different

Interface Pair View

Groups firewall policies based on the incoming (From) and outgoing (To) interfaces.

Policies are organized under interface pairs such as:

LAN → WAN

WAN → LAN

Within each interface pair, policies may appear reordered compared to the global list.

This view is designed for readability and troubleshooting, not to show execution order.

By Sequence View

Displays firewall policies in their actual evaluation (processing) order.

This is the top-down order FortiGate uses when matching traffic.

It reflects the real rule sequence that determines which policy is hit first.

Why option C is correct

C . Interface Pair View sorts policies based on matching interfaces, while By Sequence View shows the actual processing order of rules.

This statement exactly matches FortiOS behavior as documented in the FortiOS 7.6 Firewall Policy Views section of the Administrator Guide.

Why the other options are incorrect

A: Interface Pair View does not follow traffic logs, and By Sequence View is not based on "rule priority" grouping.

B: FortiGate does not dynamically reorder policies based on traffic patterns.

D: Security levels do not affect policy ordering in Interface Pair View.

KOREADUMPS.COM

QUESTION NO: 20

A new administrator is configuring FSSO authentication on FortiGate using DC Agent Mode. Which step is not part of the expected process?

A. The DC agent sends login event data directly to FortiGate.

B. FortiGate determines user identity based on the IP address in the FSSO list.

C. The collector agent forwards login event data to FortiGate.

D. The user logs into the windows domain.

Answer: A

QUESTION NO: 21

Which statement correctly describes NetAPI polling mode for the FSSO collector agent?

A. The collector agent uses a Windows API to query DCs for user logins.

B. The NetSessionEnum function is used to track user logouts.

C. NetAPI polling can increase bandwidth usage in large networks.

D. The collector agent must search Windows application event logs.

Answer: B

Explanation:

NetAPI: Polls temporary sessions created on the DC when a user logs on or logs off and calls the NetSessionEnum function on Windows. It's faster than the WinSec and WMI methods; however, it can miss some logon events if a DC is under heavy system load. This is because sessions can be quickly created and purged form RAM, before the agent has a chance to poll and notify FG.

QUESTION NO: 22

Refer to the exhibits.

HA configuration

```
HQ-NGFW-1 # config system ha

HQ-NGFW-1 (ha) # show
config system ha
    set group-id 5
    set group-name "Training"
    set mode a-p
    set password ENC a4fbyqY4iPexFmAnZgzDY
    set hbdev "port7" 0
    set session-pickup enable
    set override disable
    set priority 200
    set monitor "port1"
    set memory-based-failover enable
    set memory-failover-threshold 70
    set memory-failover-monitor-period 50
    set memory-failover-sample-rate 10
    set memory-failover-flip-timeout 60
end
```

KOREADUMPS.COM

HQ-NGFW-1 System Performance output

```
HQ-NGFW-1 # get system performance status
CPU states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU0 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU1 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
Memory: 2042076k total, 1837868k used (90%), 104146k free (5.1%), 100062k freeable (4.9%)
Average network usage: 19/2 kbps in 1 minute, 19/4 kbps in 10 minutes, 19/3 kbps in 30 minutes
Maximal network usage: 36/18 kbps in 1 minute, 58/86 kbps in 10 minutes, 58/87  kbps in 30 minutes
Average sessions: 21 sessions in 1 minute, 22 sessions  in 10 minutes, 21 sessions in 30 minutes
Maximal sessions: 22 sessions in 1 minute, 28 sessions  in 10 minutes, 28 sessions in 30 minutes
Average session setup rate: 0 sessions per second in last 1 minute, 0 sessions per second in last 10 minutes
Maximal session setup rate: 0 sessions per second in last 1 minute, 1 sessions per second in last 10 minutes
Average NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Maximal NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Virus caught: 0 total in 1 minute
IPS attacks blocked: 0 total in 1 minute
Uptime: 10 days, 22 hours, 50 minutes
```

HQ-NGFW-2 System Performance output

```
HQ-NGFW-2 # get system performance status
CPU states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU0 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU1 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
Memory: 2042076k total, 993836k used (48.7%), 690352k free (33.8%), 357888k freeable (17.5%)
Average network usage: 26/18 kbps in 1 minute, 25/18 kbps in 10 minutes, 24/18 kbps in 30 minutes
Maximal network usage: 91/27 kbps in 1 minute, 92/27 kbps in 10 minutes, 92/32  kbps in 30 minutes
Average sessions: 9 sessions in 1 minute, 9 sessions    in 10 minutes, 9 sessions in 30 minutes
Maximal sessions: 11 sessions in 1 minute, 11 sessions  in 10 minutes, 13 sessions in 30 minutes
Average session setup rate: 0 sessions per second in last 1 minute, 0 sessions per second in last 10 minutes
Maximal session setup rate: 0 sessions per second in last 1 minute, 1 sessions per second in last 10 minutes
Average NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Maximal NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Virus caught: 0 total in 1 minute
IPS attacks blocked: 0 total in 1 minute
Uptime: 10 days, 10 hours, 50 minutes
```

KOREADUMPS.COM

An administrator has observed the performance status outputs on an HA cluster for 55 seconds.

Which FortiGate is the primary?

A. HQ-NGFW-1 with the parameter memory-failover-flip-timeout setting

B. HQ-NGFW-2 with the parameter priority setting

C. HQ-NGFW-1 with the parameter override setting

D. HQ-NGFW-2 with the parameter memory-failover-threshold setting

Answer: D

Explanation:

From the HA configuration shown for HQ-NGFW-1:

set memory-based-failover enable

set memory-failover-threshold 70

set memory-failover-monitor-period 50

set memory-failover-sample-rate 10

set memory-failover-flip-timeout 60

set override disable

set priority 200

From the performance status outputs:

HQ-NGFW-1 memory used is 90% (well above the configured threshold of 70%) HQ-NGFW-2 memory used is about 48.7% (well below the threshold) What happens in FortiOS 7.6 with memory-based failover When memory-based failover is enabled, FortiGate monitors memory utilization. If the unit's memory usage stays above the configured memory-failover-threshold for the configured memory-failover-monitor-period, the cluster triggers a failover away from the unit under memory pressure.

Threshold = 70%
HQ-NGFW-1 is at 90%, so it violates the threshold.
Monitor period = 50 seconds.
The administrator observed for 55 seconds, which is longer than 50 seconds, so the condition is met for long enough to trigger failover.
The memory-failover-flip-timeout 60 is used to prevent rapid back-and-forth role changes (flapping) after a failover decision; it does not prevent the initial failover from occurring once the threshold breach persists for the monitor period.

QUESTION NO: 23
Refer to the exhibit.
A partial cloud topology is shown.



You deployed a FortiGate Cloud-Native Firewall (CNF) in AWS.
During the deployment, which components must the FortiGate CNF create to handle traffic from the EC2 instance?

A. The customer VPC and GWLBe
B. The gateway load balancer endpoint (GWLBe) in the customer virtual private cloud (VPC)
C. The CNF VPC. customer VPC. and GWLB
D. The GWLB. GWLBe, and the internet gateway (IGW) in the customer VPC

Answer: B
Explanation:
In the FortiGate Cloud-Native Firewall (CNF) for AWS architecture, traffic from workloads (such as an EC2 instance) in the customer VPC is redirected to the security service (FortiGate CNF) using AWS Gateway Load Balancer (GWLB) technology.
The key AWS component that must exist inside the customer VPC to steer workload traffic to the GWLB is the:
Gateway Load Balancer Endpoint (GWLBe)
This endpoint is what the customer VPC routes point to (for example, default route or subnet route entries), enabling transparent insertion of the FortiGate CNF inspection path for EC2

traffic.
Why the other options are not correct:
A: CNF does not "create the customer VPC" (that is customer-owned), and "GWLBe" is the only relevant created item here, not the whole VPC.
C: Customer VPC is not created by CNF, and GWLB is typically part of the CNF service side; the question specifically asks what must be created to handle traffic from the EC2 instance (that requires GWLBe in the customer VPC).
D: CNF does not create the Internet Gateway (IGW) in the customer VPC, and IGW is not the required CNF-created component for steering traffic to FortiGate CNF.

QUESTION NO: 24
Refer to the exhibit.



KOREADUMPS.COM

An administrator has configured an Application Overrides for the ABC.Com application signature and set the Action to Allow This application control profile is then applied to a firewall policy that is scanning all outbound traffic. Logging is enabled in the firewall policy. To test the configuration, the administrator accessed the ABC.Com web site several times.
Why are there no logs generated under security logs for ABC.Com?

A. The ABC Com is hitting the category Excessive-Bandwidth.

B. The ABC.Com Type is set as Application instead of Filter.

C. The ABC.Com is configured under application profile, which must be configured as a web filter profile.

D. The ABC Com Action is set to Allow

Answer: D
Explanation:
In FortiOS 7.6 Application Control, security logs are generated primarily for actions such as Block or Monitor, not for Allow actions.
What is happening in the exhibit

An Application Override is configured for ABC.Com
Type: Application
Action: Allow
The application control profile is applied to a firewall policy
Logging is enabled on the firewall policy
Traffic to ABC.Com is successfully allowed
However, no security logs appear for ABC.Com.
Why no logs are generated
In FortiOS 7.6:
Application Control logs are written to Security Logs when:
An application is Blocked
An application is Monitored
When an application action is set to Allow:
The traffic is permitted silently
No application control security log is generated
Even if policy logging is enabled
This is expected and documented behavior.
To generate logs for allowed applications, the action must be set to Monitor, not Allow.
Why the other options are incorrect
A . ABC.Com is hitting the category Excessive-BandwidthIncorrect. ABC.Com has a higher-priority explicit override (priority 1), so it is not evaluated against the Excessive-Bandwidth filter.
B . The ABC.Com Type is set as Application instead of FilterIncorrect. Application-type overrides are valid and commonly used; this does not suppress logging.
C . The ABC.Com must be configured as a web filter profileIncorrect. This traffic is being evaluated by Application Control, not Web Filter.

KOREADUMPS.COM

QUESTION NO: 25
Refer to the exhibit.

```
FortiGate # diagnose debug rating
Locale       : english

Service      : Web-filter
Status       : Enable
License      : Contract
\
Num. of servers : 1
Protocol        : https
Port            : 8888
Anycast         : Disable
Default servers : Not included

-=- Server List (Wed Sep 20 09:22:42 2023) -=-

IP                        Weight    RTT Flags   TZ   FortiGuard-requests  Curr Lost Total Lost            Updated Time
10.0.1.241                  -244      2 I        0                   122          0          0 Wed Sep 20 09:21:55 2023
```

Which two statements about the FortiGuard connection are true? (Choose two.)
A. The weight increases as the number of failed packets rises
B. You can configure unreliable protocols to communicate with FortiGuard Server.
C. FortiGate identified the FortiGuard Server using DNS lookup.
D. FortiGate is using the default port for FortiGuard communication.
Answer: A,D

Explanation:
Based on the diagnose debug rating output provided in the exhibit and the standard behavior of the FortiGuard connection mechanism in FortiOS 7.6:
Weight Calculation (Statement A is True):
In FortiOS, the rating server selection process uses a weight-based system.
According to official documentation, the weight increases with failed packets (lost responses) and decreases with successful packets.
This mechanism ensures that servers with poor reliability are penalized by having higher weights, effectively pushing them to the bottom of the preference list.
Default Port Communication (Statement D is True):
The exhibit explicitly shows the communication is using HTTPS on port 8888.
In FortiOS 7.6 (and legacy versions like 6.2/6.4), FortiGuard filtering supports specific protocols and ports: HTTPS on ports 443, 53, and 8888, where 8888 is considered a default port for FortiGuard queries.
Ports 53 and 8888 are standard for both UDP and TCP/HTTPS FortiGuard communications to avoid common firewall blocks on standard web ports.
Why other options are incorrect:
Statement B (Unreliable protocols): While you can configure UDP (which is unreliable), the exhibit specifically shows HTTPS is being used, which is a reliable (TCP-based) protocol.
Statement C (DNS lookup): In the "Flags" column of the server list, a server found via DNS lookup would be marked with the "D" flag. The exhibit shows the flag as "I" (indicating the last INIT request was sent to this server) and a numeric "2," but the "D" flag is absent.
Additionally, the IP 10.0.1.241 is a private address, suggesting it is a manually configured FortiManager or local override server rather than a public server found via global DNS lookup.

QUESTION NO: 26
Refer to the exhibits.

System Performance output

```
# get system performance status
CPU states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU0 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU1 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
Memory: 2042076k total, 1837868k used (90%), 104146k free (5.1%), 100062k freeable (4.9%)
Average network usage: 19/2 kbps in 1 minute, 19/4 kbps in 10 minutes, 19/3 kbps in 30 minutes
Maximal network usage: 36/18 kbps in 1 minute, 58/86 kbps in 10 minutes, 58/87  kbps in 30 minutes
Average sessions: 21 sessions in 1 minute, 22 sessions  in 10 minutes, 21 sessions in 30 minutes
Maximal sessions: 22 sessions in 1 minute, 28 sessions  in 10 minutes, 28 sessions in 30 minutes
Average session setup rate: 0 sessions per second in last 1 minute, 0 sessions per second in last 10 minutes
Maximal session setup rate: 0 sessions per second in last 1 minute, 1 sessions per second in last 10 minutes
Average NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Maximal NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Virus caught: 0 total in 1 minute
IPS attacks blocked: 0 total in 1 minute
Uptime: 10 days, 22 hours, 50 minutes
```

Memory usage threshold settings

```
config system global
    set memory-use-threshold-extreme 89
    set memory-use-threshold-green 82
    set memory-use-threshold-red 88
end
```

The system performance output and default configuration of high memory usage thresholds on a FortiGate device are shown.
Based on the system performance output, what are the two possible outcomes? (Choose

two.)

A. Administrators can access FortiGate only through the console port.

B. FortiGate has entered conserve mode.

C. FortiGate drops new sessions.

D. Administrators can change the configuration.

Answer: B,D

Explanation:

From the exhibits:

System performance output

Memory used: 90%

Free memory: ~5%

Default memory thresholds (FortiOS 7.6)

memory-use-threshold-green 82%

memory-use-threshold-red 88%

memory-use-threshold-extreme 89%

Because memory usage (90%) exceeds the extreme threshold (89%), the FortiGate enters conserve mode.

Effects of conserve mode (FortiOS 7.6 - verified)

B . FortiGate has entered conserve mode.

Correct

When memory usage exceeds the red/extreme threshold, FortiGate automatically enters conserve mode.

This is exactly the condition shown in the system performance output.

D . Administrators can change the configuration.

Correct

Even in conserve mode:

Administrators can still log in (GUI, SSH, console)

Configuration changes are allowed

FortiGate does not lock configuration access during conserve mode.

This behavior is explicitly documented in the FortiOS 7.6 Conserve Mode section.

Why the other options are incorrect

A . Administrators can access FortiGate only through the console port.

Incorrect

Network access (GUI/SSH) is still available in conserve mode unless otherwise restricted.

Console-only access is not a conserve-mode requirement.

C . FortiGate drops new sessions.

Incorrect (as a general statement)

FortiGate may drop or bypass new inspection-required sessions depending on fail-open/fail-close settings.

It does not universally drop all new sessions, so this statement is not always true.

KORRADUMPS.COM

QUESTION NO: 27

Which two components are part of the secure internet access (SIA) agent-based mode on FortiSASE? (Choose two.)

A. FortiSASE Firewall-as-a-Service (FWaaS)

B. The proxy auto-configuration (PAC) file
C. VPN policies
D. FortiExtender
Answer: A,C
Explanation:
In FortiSASE Secure Internet Access (SIA) agent-based mode, traffic steering and security enforcement rely on components integrated with the FortiClient agent.
Components used in SIA agent-based mode
A . FortiSASE Firewall-as-a-Service (FWaaS)
Correct.
FWaaS is a core security component of FortiSASE.
It enforces firewall policies, security inspection, and access control for agent-based users.
All user traffic tunneled by the agent is inspected by FWaaS.
C . VPN policies
Correct.
In agent-based mode, the FortiClient establishes a secure tunnel to FortiSASE.
VPN policies define:
Authentication
Access control
Traffic steering
These policies are fundamental to agent-based connectivity.
Why the other options are incorrect
B . Proxy auto-configuration (PAC) filePAC files are used in agentless or proxy-based modes, not agent-based SIA.
D . FortiExtenderFortiExtender is a WAN extension device and is unrelated to FortiSASE SIA agent-based architecture.

QUESTION NO: 28
Refer to the exhibits.

KOREADUMPS.COM

Application sensor

Edit Application Sensor

Categories

Mixed - All Categories

- Business (157, 6)
- Collaboration (266, 13)
- Game (83)
- Mobile (3)
- Operational Technology
- Proxy (189)
- Social Media (113, 29)
- Update (48)
- VoIP (23)
- Unknown Applications
- Cloud/IT (72, 12)
- Email (76, 11)
- General Interest (254, 15)
- Network Service (338)
- P2P (55)
- Remote Access (96)
- Storage/Backup (150, 20)
- Video/Audio (148, 17)
- Web Client (24)

Network Protocol Enforcement

Application and Filter Overrides

+ Create New | Edit | Delete

Priority	Details	Type	Action
1	BHVR Excessive-Bandwidth	Filter	Block
2	VEND Google	Filter	Monitor

KOREADUMPS.COM

Firewall policy



KOREADUMPS.COM

You have implemented the application sensor and the corresponding firewall policy as shown in the exhibits.

Which two factors can you observe from these configurations? (Choose two.)

A. YouTube access is blocked based on Excessive-Bandwidth Application and Filter override settings.

B. Facebook access is blocked based on the category filter settings.

C. Facebook access is allowed but you cannot play Facebook videos based on Video/Audio category filter settings.
D. YouTube search is allowed based on the Google Application and Filter override settings.
Answer: A,B
Explanation:
From the exhibits:
The Application Control sensor has these key settings:
Application and Filter Overrides
Priority 1: Excessive-Bandwidth (Type: Filter) with Action Block
Priority 2: Google (Type: Filter) with Action Monitor
Category actions shown include Social Media set to Block (this category includes Facebook).
The firewall policy is using:
Flow-based inspection
Application control enabled (profile: default)
Deep inspection enabled (helps identify applications inside HTTPS)
Logging enabled
FortiOS applies Application Control as follows (top-down within the Application Control profile):
Overrides are evaluated by priority (highest priority first).
The first matching override determines the action (block/monitor/allow) for that traffic.
Category-based actions apply to applications that fall into those categories unless an override matches first.
Why A is correct
A . YouTube access is blocked based on Excessive-Bandwidth Application and Filter override settings.
The profile explicitly blocks the Excessive-Bandwidth behavior filter at the highest override priority.
When YouTube traffic is detected as matching the Excessive-Bandwidth behavior, FortiGate will apply the Block action due to the override.
Because this is a priority override, it is enforced before lower-priority entries.
Why B is correct
B . Facebook access is blocked based on the category filter settings.
The Application Sensor shows Social Media configured with a Block action.
Facebook is categorized under Social Media, so it will be blocked when matched by Application Control.
Why C is not correct
C . Facebook access is allowed but you cannot play Facebook videos...
Since the Social Media category is set to Block, Facebook would be blocked at the category level (not merely video playback).
Why D is not correct
D . YouTube search is allowed based on the Google override...
The Google override action is Monitor, not Allow.
"Monitor" logs/detects but does not override a block condition to "allow" traffic.
Also, YouTube traffic is not guaranteed to be treated as "Google" in a way that would permit it, and any matching block condition (such as Excessive-Bandwidth) would still take

PDFREADUMPS.COM

precedence.

QUESTION NO: 29
Which three statements about SD-WAN performance SLAs are true? (Choose three.)
A. They rely on session loss and jitter.
B. They monitor the state of the FortiGate device.
C. All the SLA targets can be configured.
D. They are applied in a SD-WAN rule lowest cost strategy.
E. They can be measured actively or passively.
Answer: C,D,E
Explanation:
In FortiOS 7.6, SD-WAN Performance SLAs are used to measure link quality and influence SD-WAN rule decisions. The following three statements are true.
C . All the SLA targets can be configured.
True
SD-WAN Performance SLAs allow administrators to configure:
Latency
Jitter
Packet loss
Mean Opinion Score (MOS) (for voice)
Threshold values for these metrics are fully configurable per SLA.
This is explicitly documented in the SD-WAN Performance SLA configuration section.
D . They are applied in an SD-WAN rule lowest cost strategy.
True
Performance SLAs are commonly used with the Lowest Cost (SLA-based) strategy.
In this strategy:
FortiGate selects the lowest-cost link that meets the SLA requirements.
If a link violates the SLA, it is excluded from selection.
E . They can be measured actively or passively.
True
FortiOS supports:
Active probing (synthetic probes such as ping/HTTP)
Passive measurement (based on real traffic statistics)
Administrators can choose how SLAs are measured depending on the deployment and requirements.
Why the other options are incorrect
A . They rely on session loss and jitter.
Incorrect
SLAs measure packet loss, latency, and jitter.
Session loss is not an SLA metric in FortiOS.
B . They monitor the state of the FortiGate device.
Incorrect
Performance SLAs monitor link quality, not FortiGate system health or device state.

QUESTION NO: 30

KOREADUMPS.COM

Refer to the exhibit.

Profile Name
Monitoring_Access
NOC_Access
prof_admin
super_admin

The NOC team connects to the FortiGate GUI with the NOC_Access admin profile. They request that their GUI sessions do not disconnect too early during inactivity. What must the administrator configure to answer this specific request from the NOC team?

A. Increase the admintimeout value under config system accprofile noc Access.

B. increase the of line value of the override idle Timeout parameter in the NOC_Access admin profile.

C. Move NOC_Access to the top of the list to ensure all profile settings take effect.

D. Ensure that all NOC_Access users are assigned the super_admin role to guarantee access.

Answer: B

Explanation:

In FortiOS 7.6, GUI session inactivity timeout behavior for administrators is controlled by admin profiles, not by general access permissions or profile ordering.

How GUI idle timeout works in FortiOS 7.6

FortiGate has a global admin timeout (admintimeout), but

Admin profiles can override this value using the Override idle timeout setting.

When Override idle timeout is enabled in an admin profile, the timeout value defined inside that profile takes precedence over the global setting.

The exhibit shows that the NOC team logs in using the NOC_Access admin profile.

Therefore, to prevent their GUI sessions from disconnecting too quickly during inactivity, the timeout must be adjusted within that specific admin profile.

Why option B is correct

B . Increase the value of the Override Idle Timeout parameter in the NOC_Access admin profile.

This directly controls how long GUI sessions remain active when users assigned to NOC_Access are idle.

It affects only the NOC team, which matches the requirement precisely.

This is the recommended and documented approach in FortiOS 7.6.

Why the other options are incorrect

A . Increase admintimeout under config system accprofileIncorrect. admintimeout is a global admin setting, not configured under accprofile, and it would affect all administrators, not just

KOREADUMPS.COM

NOC users.
C . Move NOC_Access to the top of the listIncorrect. Admin profile order has no impact on session timeout behavior.
D . Assign super_admin roleIncorrect and insecure. Super_admin does not control idle timeout and would unnecessarily grant full privileges.

QUESTION NO: 31
The FortiGate device HQ-NGFW-1 with the IP address 10.0.13.254 sends logs to the FortiAnalyzer device with the IP address 10.0.13.125. The administrator wants to verify that reliable logging is enabled on HQ-NGFW-1.
Which exhibit helps with the verification?

A.



B.

```
config log fortianalyzer setting
     set status enable
     set server "10.0.13.125"
     set serial "FAZ-VMTM24012176"
     set enc-algorithm high-medium
     set upload-option realtime
end
```

C.



D.

KOREADUMPS.COM

```
HQ-NGFW-1 # diagnose sniffer packet any "host 10.0.13.125" 4
Using Original Sniffing Mode
interfaces=[any]
filters=[host 10.0.13.125]
2.173071 port6 out 10.0.13.254.14974 -> 10.0.13.125.514: udp 347
3.334638 port6 out 10.0.13.254.23054 -> 10.0.13.125.514: psh 4017477514 ack 2638032500
3.335098 port6 in 10.0.13.125.514 -> 10.0.13.254.23054: psh 2638032500 ack 4017477548
3.335129 port6 out 10.0.13.254.23054 -> 10.0.13.125.514: ack 2638032543
```

Answer: B

QUESTION NO: 32
Refer to the exhibit.



KOREADUMPS.COM

The predefined deep-inspection and custom-deep-inspection profiles exclude some web categories from SSL inspection, as shown in the exhibit For which two reasons are these web categories exempted? (Choose two.)

A. The resources utilization is optimized because these websites are in the trusted domain list on FortiGate.

B. The legal regulation aims to prioritize user privacy and protect sensitive information for these websites.

C. These websites are in an allowlist of reputable domain names maintained by FortiGuard.

D. The FortiGate temporary certificate denies the browser's access to websites that use HTTP Strict Transport Security.

Answer: B,D

Explanation:

"You may need to exempt traffic from SSL inspection if it is causing problems with traffic, or

for legal reasons."
"Performing SSL inspection on a site that is enabled with HTTP Strict Transport Security (HSTS), for example, can cause problems with traffic. Remember, the only way for FortiGate to inspect encrypted traffic is to intercept the certificate coming from the server and generate a temporary one. After FortiGate presents the temporary SSL certificate, browsers that use HSTS refuse to proceed."
"Laws protecting privacy might be another reason to bypass SSL inspection. For example, in some countries, it is illegal to inspect SSL bank-related traffic. Configuring an exemption for sites is simpler than setting up firewall policies for each individual bank. You can exempt sites based on their web category, such as Finance and Banking..."
"The predefined deep-inspection and custom-deep-inspection profiles exclude some web categories-Finance and Banking, and Health and Wellness-and some FQDN addresses..."
Technical Deep Dive:
The correct answers are B and D.
B is correct because the study guide explicitly says SSL inspection may be bypassed for legal reasons, especially where privacy laws restrict inspection of sensitive categories such as Finance and Banking. The same privacy rationale also explains why Health and Wellness is commonly exempted.
D is correct because some sites break under deep inspection due to HSTS. FortiGate must generate and present a temporary certificate during full SSL inspection, and browsers enforcing HSTS can reject that interception flow. That is why some sites are exempted from deep inspection.
Why the others are wrong:
A is not stated in the guide.
C refers to the separate Reputable websites option, which is a FortiGuard-maintained allowlist feature, not the reason the predefined categories shown in the exhibit are excluded.
From an operational standpoint, this is a classic balance between security visibility and application/legal compatibility. Deep inspection gives FortiGate payload visibility, but it can interfere with pinned-certificate/HSTS behavior and can violate privacy policy for regulated content.

QUESTION NO: 33
Refer to the exhibit.

KOREADUMPS.COM



KOREADUMPS.COM

Why is the Antivirus scan switch grayed out when you are creating a new antivirus profile for FTP?

A. Antivirus scan is disabled under System -> Feature visibility

B. None of the inspected protocols are active in this profile.

C. The Feature Set for the profile is Flow-based but it must be Proxy-based

D. FortiGate. with less than 2 GB RAM. does not support the Antivirus scan feature.

Answer: B

Explanation:

In FortiOS 7.6, the Antivirus scan master switch in an antivirus profile becomes available only after at least one supported protocol is enabled for inspection.

What the exhibit shows

A new antivirus profile named FTP_AV_Profile

Feature set: Flow-based

Antivirus scan switch is grayed out

All Inspected Protocols (HTTP, SMTP, POP3, IMAP, FTP, CIFS) are currently disabled Why the Antivirus scan switch is grayed out In FortiOS antivirus profiles:

The Antivirus scan toggle is a dependent control
It cannot be enabled unless at least one inspected protocol is selected This prevents enabling AV scanning when there is no traffic type to scan This behavior is documented in the FortiOS 7.6 Antivirus Profile configuration section.
Once you enable a protocol (for example, FTP), the Antivirus scan switch becomes active and configurable.
Why option B is correct
B . None of the inspected protocols are active in this profile.
All protocol toggles are OFF
Therefore, FortiGate disables (grays out) the Antivirus scan option
This is expected and correct behavior
Why the other options are incorrect
A . Antivirus scan is disabled under Feature visibilityIncorrect. Feature Visibility controls whether Antivirus appears in the GUI, not whether the scan switch is enabled inside a profile.
C . Feature set must be Proxy-basedIncorrect. Antivirus scanning is supported in both flow-based and proxy-based modes.
D . Less than 2 GB RAM does not support Antivirus scanIncorrect. Memory size affects performance and offloading, not basic AV scan availability.

KOREADUMPS.COM

QUESTION NO: 34
FortiGate is integrated with FortiAnalyzer and FortiManager.
When creating a firewall policy, which attribute must an administrator include to enhance functionality and enable log recording on FortiAnalyzer and FortiManager?
A. Universally Unique Identifier
B. Policy ID
C. Sequence ID
D. Log ID
Answer: A
Explanation:
In FortiOS 7.6, when FortiGate is integrated with FortiAnalyzer and FortiManager, firewall policies rely on a Universally Unique Identifier (UUID) to ensure proper policy tracking, synchronization, and log correlation across devices.
Why the UUID is required
Every firewall policy in FortiOS has a UUID.
FortiManager uses the UUID to:
Track policies across managed FortiGate devices
Maintain policy consistency during installs and revisions
FortiAnalyzer uses the UUID to:
Correlate logs accurately to the correct firewall policy
Preserve log association even if policy order or policy ID changes
Without a UUID:
Policy-to-log mapping can break
FortiManager cannot reliably manage or synchronize policies
FortiAnalyzer log analysis becomes inconsistent
This is explicitly documented in Fortinet administration and logging architecture references.

Why the other options are incorrect
B . Policy IDPolicy ID can change when policies are moved and is not reliable for long-term correlation across FortiManager and FortiAnalyzer.
C . Sequence IDSequence ID reflects GUI ordering only and has no role in log correlation.
D . Log IDLog ID is generated per log event, not per firewall policy.

QUESTION NO: 35
How does FortiExtender connect to FortiSASE in a site-based, remote internet access method?
A. FortiExtender uses a Virtual Extensible LAN (VXLAN)-over-IPsec connection.
B. FortiExtender establishes a secure SSL connection using FortiClient.
C. FortiExtender first connects to a FortiGate LAN extension through a secure web gateway (SWG).
D. FortiExtender uses the proxy auto-configuration <PAC) file and an explicit web proxy to connect.
Answer: A
Explanation:
In FortiSASE site-based (remote internet access) deployments, FortiExtender is used to onboard branch or remote sites without a local FortiGate.
According to FortiSASE and FortiExtender architecture documentation:
FortiExtender integrates with FortiSASE using a secure VXLAN-over-IPsec tunnel This tunnel:
Extends the site network to FortiSASE
Transparently forwards traffic for inspection
Preserves network segmentation and routing context
This design is similar to cloud-based LAN extension and is not proxy-based Why the other options are incorrect B: FortiClient is used for agent-based user access, not FortiExtender C: Secure Web Gateway (SWG) is a service, not a transport mechanism D: PAC files and explicit proxies are used in agentless / proxy-based access, not site-based FortiExtender deployments

QUESTION NO: 36
What are two features of FortiGate FSSO agentless polling mode? (Choose two.)
A. FortiGate uses the AD server as the collector agent.
B. FortiGate uses the SMB protocol to read the event viewer logs from the DCs.
C. FortiGate does not support workstation check.
D. FortiGate directs the collector agent to use a remote LDAP server.
Answer: B,C
Explanation:
Based on the FortiOS 7.6 Administrator Guide regarding Fortinet Single Sign-On (FSSO) polling modes, the agentless polling mode has specific technical characteristics:
SMB Protocol Usage (Statement B is True):
In agentless polling mode, the FortiGate unit itself acts as the collector.
It establishes direct connections to the Windows Domain Controllers (DCs) using the SMB (Server Message Block) protocol, typically over TCP port 445, to read the Windows Security

XOREADUMPS.COM

Event logs.
This allows FortiGate to parse login event IDs (such as 4768 and 4769) to identify users and their corresponding IP addresses without needing an external collector agent installed on a server.
Workstation Check Support (Statement C is True):
One of the primary limitations of the agentless polling mode compared to the agent-based mode is the lack of workstation verification.
In agentless mode, FortiGate does not perform "workstation checks" or "dead entry checks". This means it cannot proactively verify if a user is still logged into a specific workstation after the initial logon event is recorded, which can lead to stale entries if a user logs off without a corresponding event being captured.
Why other options are incorrect:
Option A: In agentless mode, FortiGate (the FSSO daemon) performs the collection itself; it does not use the AD server as a "collector agent" in the functional sense of FSSO architecture.
Option D: While FortiGate uses LDAP to retrieve group membership information once a user is identified, it does not "direct" a collector agent to a remote LDAP server, as there is no external collector agent involved in this specific mode.

QUESTION NO: 37
What are two features of collector agent advanced mode? (Choose two.)
A. In advanced mode, security profiles can be applied only to user groups, not individual users.
B. In advanced mode. FortiGate can be configured as an LDAP client and group filters can be configured on FortiGate.
C. Advanced mode uses the Windows convention-NetBios: Domain\Username.
D. Advanced mode supports nested or inherited groups.
Answer: B,D
Explanation:
"Also, advanced mode supports nested or inherited groups; that is, users can be members of subgroups that belong to monitored parent groups." "In advanced mode, you can configure FortiGate as an LDAP client and configure the group filters on FortiGate. You can also configure group filters on the collector agent." Collector Agent Advanced Mode provides deeper integration between FortiGate, LDAP, and Active Directory, compared to standard mode.
Key features of Collector Agent Advanced Mode
B . FortiGate can be configured as an LDAP client and group filters can be configured on FortiGate.
Correct
In advanced mode:
FortiGate directly queries LDAP/AD
User group filters are configured on FortiGate, not only on the Collector Agent This allows more flexible and scalable user/group-based policies D . Advanced mode supports nested or inherited groups.
Correct

KOREADUMPS.COM

Advanced mode supports:
Nested AD groups
Inherited group memberships
This is one of the primary reasons advanced mode is used in complex AD environments Why the other options are incorrect A . Security profiles only to user groups Incorrect.
Security profiles can be applied to users or groups, depending on policy configuration.
C . Uses NetBIOS Domain\Username format
Incorrect.
NetBIOS naming is associated with standard mode
Advanced mode typically uses LDAP DN-based identification

QUESTION NO: 38
You have configured the below commands on a FortiGate.

```
config system settings
set strict-src-check enable
end

Config system interface
edit port1
set src-check disable
next
end
```

KOREADUMPS.COM

What would be the impact of this configuration on FortiGate?
A. FortiGate will enable strict RPF on all its interfaces and porti will be exempted from RPF checks.
B. FortiGate will enable strict RPF on all its interfaces and porti will be enable for asymmetric routing.
C. The global configuration will take precedence and FortiGate will enable strict RPF on all interfaces.
D. Port1 will be enabled with flexible RPF. and all other interfaces will be enabled for strict RPF
Answer: A

QUESTION NO: 39
Refer to the exhibit.
A routing table is shown

Network	Gateway IP	Interfaces	Distance	Metric	Priority	Type
10.0.11.0/24	0.0.0.0	port4	0	0	0	Connected
10.0.12.0/24	0.0.0.0	port5	0	0	0	Connected
10.0.13.0/24	0.0.0.0	port6	0	0	0	Connected
100.65.0.0/24	0.0.0.0	port2	0	0	0	Connected
100.66.0.0/24	0.0.0.0	port3	0	0	0	Connected
172.20.1.0/24	100.66.0.254	port3	9	0	2	Static
192.168.0.0/16	0.0.0.0	port1	0	0	0	Connected

An administrator wants to create a new static route so the traffic to the subnet 172.20.1.0/24 is routed through port2 only. What are the two criteria that the administrator can use to achieve this objective? (Choose two.)

A. The new static route must have the priority set to 3.

B. The new static route must have the metric set to 1.

C. The existing static route through port3 must have the distance set to 11.

D. The new static route must have the distance set to 9

Answer: C,D

Explanation:

From the routing table in the exhibit, there is already a static route for 172.20.1.0/24 pointing out port3 with:

Distance = 9

Priority = 2

Type = Static

In FortiOS, route selection prefers (in order) the route with the lowest administrative distance to a destination. Therefore, to make traffic to 172.20.1.0/24 go through port2 only, the administrator must ensure the port2 static route is more preferred than the existing port3 route.

Why C is correct

C . The existing static route through port3 must have the distance set to 11.

If the existing port3 route distance is increased to 11, then a new port2 route with distance 9 will be preferred (9 < 11). This makes the port3 route a backup route instead of the active one.

Why D is correct

D . The new static route must have the distance set to 9

Setting the new port2 route distance to 9 (and increasing the port3 route to 11 as in option C) ensures FortiGate selects the port2 route as the best route for 172.20.1.0/24.

Why A and B are not correct

A (priority 3): By itself it does not guarantee selection over the existing route, and FortiOS route choice is driven primarily by distance.

B (metric 1): Metric is not the primary selector for static route preference compared to administrative distance in this scenario.

So the two criteria that achieve the objective are:

KOREADUMPS.COM

Make the existing port3 route less preferred by increasing its distance (C) Ensure the new port2 route uses the preferred distance (D)

QUESTION NO: 40
There are multiple dialup IPsec VPNs configured in aggressive mode on the HQ FortiGate. The requirement is to connect dial-up users to their respective department VPN tunnels. Which phase 1 setting you can configure to match the user to the tunnel?
A. Local Gateway
B. Dead Peer Detection
C. Peer ID
D. IKE Mode Config
Answer: C
Explanation:
In FortiOS 7.6, when multiple dialup IPsec VPNs are configured on the same FortiGate-especially in Aggressive Mode-FortiGate must identify which Phase 1 configuration a connecting client should match.
How FortiGate selects a dialup IPsec tunnel
For dialup VPNs:
The remote peer (user or device) does not have a fixed IP address
Multiple Phase 1 interfaces may exist on the HQ FortiGate
FortiGate uses identifying information sent during IKE Phase 1 to select the correct tunnel
Aggressive Mode behavior Aggressive mode sends ID information in clear text during Phase 1 This allows FortiGate to match incoming peers to the correct Phase 1 configuration Why Peer ID is the correct answer C . Peer ID Peer ID (also called IKE ID) is used to:
Identify the remote peer
Differentiate between multiple dialup tunnels
Common Peer ID formats:
FQDN
User FQDN
Key ID
FortiGate matches the received Peer ID against the Phase 1 configuration to select the correct tunnel This is the documented and recommended method for:
Mapping users to different department tunnels
Supporting multiple dialup IPsec VPNs in aggressive mode
Why the other options are incorrect
A . Local GatewayIdentifies the local FortiGate interface/IP, not the remote user.
B . Dead Peer DetectionUsed only for tunnel health monitoring, not tunnel selection.
D . IKE Mode ConfigUsed for assigning IP addresses and pushing settings, not for selecting the Phase 1 tunnel.

QUESTION NO: 41
A network administrator has enabled full SSL inspection and web filtering on FortiGate. When visiting any HTTPS websites, the browser reports certificate warning errors. When visiting HTTP websites, the browser does not report errors.
What is the reason for the certificate warning errors?

YOREADUMPS.COM

A. The option invalid SSL certificates is set to allow on the SSL/SSH inspection profile.
B. The matching firewall policy is set to proxy inspection mode.
C. The browser does not trust the certificate used by FortiGate for SSL inspection.
D. The certificate used by FortiGate for SSL inspection does not contain the required certificate extensions.
Answer: C
Explanation:
With full SSL inspection, FortiGate performs a man-in-the-middle process: it decrypts the HTTPS session, inspects it, then re-encrypts it. To do this, FortiGate presents a substitute certificate to the client, signed by the CA certificate configured in the SSL/SSH inspection profile (for example, Fortinet_CA_SSL or a custom enterprise CA).
Browsers will show certificate warning errors when the issuing CA is not trusted by the client device/browser trust store. This only happens for HTTPS because certificates are used in TLS; HTTP has no certificate exchange, so no warning appears.
Why the other options are incorrect:
A: Allowing invalid server certificates affects whether FortiGate blocks/permits connections to sites with bad certs; it does not fix the client warning about FortiGate's substituted cert.
B: Proxy vs flow inspection mode does not inherently cause certificate warnings; the warning is about trust of the signing CA.
D: Missing extensions is not the typical reason across "any HTTPS website"; the standard reason is the client does not trust the FortiGate inspection CA

KOPEADUMPS.COM

QUESTION NO: 42
You have configured an application control profile, set peer-to-peer traffic to Block under the Categories tab. and applied it to the firewall policy. However, your peer-to-peer traffic on known ports is passing through the FortiGate without being blocked.
What FortiGate settings should you check to resolve this issue?
A. FortiGuard category ratings
B. Network Protocol Enforcement
C. Replacement Messages for UDP-based Applications
D. Application and Filter Overrides
Answer: B
Explanation:
When the Application sensor receives traffic on that port, the protocol decoder will try to determine if the received data matches the HTTPS traffic In this case it will not match because it is P2P traffic, so this will class as violation and blocked The protocol decoder also try to determine what type of traffic it is, and even if it could not figure out it is P2P traffic, it still count as a violation because even though it does not know what it is, it knows for fact it is not HTTPS

QUESTION NO: 43
What are two characteristics of HA cluster heartbeat IP addresses in a FortiGate device? (Choose two.)
A. Heartbeat IP addresses are used to distinguish between cluster members.

B. The heartbeat interface of the primary device in the cluster is always assigned IP address 169.254.0.1.

C. A change in the heartbeat IP address happens when a FortiGate device joins or leaves the cluster.

D. Heartbeat interfaces have virtual IP addresses that are manually assigned.

Answer: A,C

Explanation:

In FortiOS 7.6, HA cluster heartbeat IP addresses are automatically managed by FortiGate and play a critical role in cluster communication and synchronization.

Correct statements

A . Heartbeat IP addresses are used to distinguish between cluster members.

Correct

FortiGate assigns unique heartbeat IP addresses (link-local addresses in the 169.254.0.0/16 range) to each HA member.

These addresses are used for:

Cluster member identification

Health checks

Synchronization traffic

This allows FortiGate units to uniquely identify and communicate with each other inside the HA cluster.

C . A change in the heartbeat IP address happens when a FortiGate device joins or leaves the cluster.

Correct

Heartbeat IPs are dynamically assigned.

When:

A new FortiGate joins the cluster, or

A member leaves or fails,

FortiGate may reassign heartbeat IP addresses to maintain unique identification among members.

This behavior is documented in the FortiOS HA operation and troubleshooting guides.

Why the other options are incorrect

B . The heartbeat interface of the primary device is always assigned IP address 169.254.0.1.

Incorrect

There is no fixed or guaranteed heartbeat IP (such as 169.254.0.1) for the primary unit.

Heartbeat IP assignment is dynamic, not role-based.

D . Heartbeat interfaces have virtual IP addresses that are manually assigned.

Incorrect

Heartbeat IP addresses are:

Automatically assigned

Link-local

Administrators do not manually configure heartbeat IP addresses.

QUESTION NO: 44

Refer to the exhibit.

KOREADUMPS.COM

Destination	Gateway IP	Interface	Status
0.0.0.0/0	100.65.0.254	port2	Enabled
10.10.10.0/24	100.66.0.254	port3	Enabled
10.0.13.0/24	10.0.13.125	port6	Enabled

Based on the routing table shown in the exhibit, which two statements are true? (Choose two.)

A. A packet with the source IP address 10.0.13.10 arriving on port2 is allowed if strict RPF is disabled.

B. A packet with the source IP address 10.100.110.10 arriving on port2 is allowed if strict RPF is enabled.

C. A packet with the source IP address 10.100.110.10 arriving on port3 is allowed if strict RPF is disabled.

D. A packet with the source IP address 10.10.10.10 arriving on port2 is allowed if strict RPF is enabled.

Answer: A,C

QUESTION NO: 45

FortiGate is operating in NAT mode and has two physical interfaces connected to the LAN and DMZ networks respectively. Which two statements about the requirements of connected physical interfaces on FortiGate are true? (Choose two.)

A. Both interfaces must have DHCP enabled and interfaces set to LAN and DMZ roles assigned.

B. Both interfaces must have the interface role assigned.

C. Both interfaces must have directly connected routes on the routing table.

D. Both interfaces must have IP addresses assigned.

Answer: C,D

Explanation:

In FortiOS 7.6, when a FortiGate is operating in NAT mode, physical interfaces that participate in traffic forwarding (such as LAN and DMZ) must meet certain fundamental requirements.

Correct statements

D . Both interfaces must have IP addresses assigned.

Correct

In NAT mode, FortiGate operates as a Layer-3 device.

Every interface that forwards traffic must have an IP address.

Without an IP address:

The interface cannot participate in routing

Firewall policies cannot be applied correctly

KOKEADUMPS.COM

This is a mandatory requirement.
C . Both interfaces must have directly connected routes on the routing table.
Correct
When an IP address is assigned to an interface, FortiGate automatically installs a connected route for that subnet in the routing table.
These connected routes are required so FortiGate:
Knows how to reach the locally attached networks
Can forward traffic between LAN and DMZ
While administrators do not manually create these routes, their presence is required for correct operation.
Why the other options are incorrect
A . Both interfaces must have DHCP enabled and roles assigned.
Incorrect
DHCP is optional; interfaces can use static IPs.
Interface roles (LAN, DMZ, WAN) are administrative/GUI aids, not functional requirements.
B . Both interfaces must have the interface role assigned.
Incorrect
Interface roles affect GUI grouping and some default behavior.
They are not required for NAT mode operation or traffic forwarding.

QUESTION NO: 46
Refer to the exhibits.

KOREADUMPS.COM

Web filter profile configuration

Edit Web Filter Profile

Feature set: Flow-based | Proxy-based

FortiGuard Category Based Filter

Allow | Monitor | Block | Warning | Authenticate

Name	Action
Job Search	Allow
Medicine	Allow
News and Media	Allow
Social Networking	Allow
Political Organizations	Allow
Reference	Allow
Global Religion	Allow
Shopping	Allow
Society and Lifestyles	Allow

58% 95

Allow users to override blocked categories

Search Engines

Enforce 'Safe Search' on Google, Yahoo!, Bing, Yandex

Static URL Filter

Block invalid URLs

URL Filter

+ Create New | Edit | Delete | Search

URL	Type	Action	Status
www.facebook.com	Simple	Monitor	Enable

KOREADUMPS.COM

Firewall policy configuration



KOREADUMPS.COM

FortiGuard block page

KOREADUMPS.COM

A web filter profile configuration and firewall policy configuration are shown.
You are trying to access www. facebook.com, but you are redirected to a FortiGuard web filtering block page.
Based on the exhibits, what is the possible cause of the issue?

A. The web rating override configuration is incorrect.

B. The web filter profile feature set is configured incorrectly.

C. The firewall policy inspection mode is incorrect.
D. For www. facebook. com. the URL filter action is incorrect.
Answer: C
Explanation:
From the exhibits:
The Web Filter profile is configured with Feature set = Flow-based.
The Firewall policy is configured with Inspection mode = Proxy-based and has Web Filter enabled.
In FortiOS 7.6, security profiles that have a feature set selection (Flow-based vs Proxy-based) must match the inspection mode used by the firewall policy. If the profile's feature set does not match the policy's inspection mode, the profile behavior will not align with what the administrator expects (and in many cases FortiOS will prevent correct use/selection, or the feature behavior will not apply as intended).
That mismatch explains why the configured URL filter entry for www.facebook.com (set to Monitor) is not producing the expected result, and instead the session is being evaluated by category rating and blocked (shown as Malicious Websites on the FortiGuard block page).
Why the other options are not the best fit:
A: A web rating override is not shown in the exhibits, and nothing indicates an override misconfiguration.
C: While the policy inspection mode could be changed, the root cause shown is the profile feature set mismatch (profile is Flow-based).
D: The URL filter action shown is Monitor, which would not produce a block page by itself.

QUESTION NO: 47
An administrator wants to form an HA cluster using the FGCP protocol. Which two requirements must the administrator ensure both members fulfill? (Choose two answers)
A. They must have the same HA group ID.
B. They must have the heartbeat interfaces in the same subnet.
C. They must have the same number of configured VDOMs.
D. They must have the same hard drive configuration.
Answer: A,D
Explanation:
"To successfully form an HA cluster, you must ensure that the members have the same:
* Model: hardware model or VM model
* Firmware version
* Licensing: includes the FortiGuard license, virtual domain (VDOM) license, FortiClient license, and so on
* Hard drive configuration: the same number and size of drives and partitions
* Operating mode: the operating mode-NAT mode or transparent mode-of the management VDOM."
"From a configuration and setup point of view, you must ensure that the HA settings on each member have the same group ID, group name, password, and heartbeat interface settings. Try to place all heartbeat interfaces in the same broadcast domain, or for two-member clusters, connect them directly." Technical Deep Dive:
The correct answers are A and D.

KOREADUMPS.COM

A is correct because FGCP cluster formation requires matching HA parameters, and group ID is explicitly one of them. If the group ID differs, the units will not consider each other part of the same cluster during HA discovery and election.
D is correct because FortiGate HA expects hardware parity in critical platform characteristics, including hard drive configuration. If disk layout differs, the members do not satisfy the HA formation prerequisites.
B is incorrect because the study guide does not require heartbeat interfaces to be in the same IP subnet. The requirement is that heartbeat links be in the same broadcast domain, or directly connected in a two-node design. In practice, heartbeat links are Layer 2 adjacency links; IP subnet matching is not the stated requirement.
C is incorrect because the guide does not say both units must start with the same number of configured VDOMs. What must match is the licensing level and the operating mode of the management VDOM. After cluster formation, the primary synchronizes its configuration to the secondary.
A practical verification set before forming FGCP HA is:
get system status
show system ha
diagnose sys ha status
Operationally, FGCP then uses the heartbeat links for member discovery, health monitoring, election, and config/session synchronization. On supported hardware, session forwarding and HA processing can still benefit from FortiGate's ASIC-assisted architecture, but HA state, config sync, and election logic remain control-plane functions handled by FortiOS.

KOREADUMPS.COM

QUESTION NO: 48
Which two statements are correct when FortiGate enters conserve mode? (Choose two answers)
A. FortiGate continues to run critical security actions, such as quarantine.
B. FortiGate refuses to accept configuration changes.
C. FortiGate halts complete system operation and requires a reboot to regain available resources.
D. FortiGate continues to transmit packets without IPS inspection when the fail-open global setting in IPS is enabled.
Answer: B,D
Explanation:
According to the FortiOS 7.6 Study Guide and technical documentation, conserve mode is a protective state triggered when memory utilization reaches the Extreme Threshold (typically 95% by default). When this occurs, the FortiGate implements several measures to prioritize system stability over new functionality. One of the primary restrictions is that the FortiGate refuses to accept configuration changes (Statement B). This prevents the system from initiating new processes or allocating additional memory that could lead to a total system crash.
Regarding traffic handling, the behavior is determined by specific "fail-open" settings. For the IPS engine, if the fail-open global setting is enabled, the FortiGate continues to transmit packets without IPS inspection (Statement D). This ensures that network connectivity is maintained even when the system lacks the memory resources to perform deep packet

inspection. In contrast, Statement A is incorrect because the system may skip non-essential actions to save memory. Statement C is incorrect because conserve mode is designed to avoid a system halt; the device remains operational and will automatically exit conserve mode once memory usage drops below the Release Threshold (typically 82%).

QUESTION NO: 49
Refer to the exhibit.

Profile Name
Monitoring_Access
NOC_Access
prof_admin
super_admin

KOREADUMPS.COM

The NOC team connects to the FortiGate GUI with the NOC_Access admin profile. They request that their GUI sessions do not disconnect too early during inactivity. What must the administrator configure to answer this specific request from the NOC team? (Choose one answer)

A. Move NOC_Access to the top of the list to ensure all profile settings take effect.

B. Increase the offline value of the Override Idle Timeout parameter in the NOC_Access admin profile.

C. Ensure that all NOC_Access users are assigned the super_admin role to guarantee access.

D. Increase the admintimeout value under config system accprofile NOC_Access.

Answer: D

Explanation:

According to the FortiOS 7.6 Administrator Study Guide, while there is a global administrative idle timeout setting that applies to all users by default (typically 5 minutes), FortiOS allows for granular control through Administrator Profiles. The Override Idle Timeout feature is specifically designed to allow different timeout values for different access profiles, which is ide1al for environments like a Network Operations Center (NOC) where persistent monitoring is required.23 To implement this, the administrator must modify the s4pecific access profile settings. By using the command config system accprofile 5and editing the NOC_Access profile, the administrator can enable the admintimeout-override and then increase the admintimeout value (Statement D). This configuration ensures that only the users assigned to that specific profile benefit from the extended session duration, maintaining a higher security

posture for other administrative accounts that still follow the global timeout. Other options, such as changing the profile order (A) or assigning the super_admin role (C), do not address the specific requirement for inactivity timeout management. Option B is incorrect as "offline value" is not a standard parameter for this feature.

QUESTION NO: 50
Refer to the exhibits.

KOREADUMPS.COM

Application sensor configuration



Application override configuration

Filter override configuration

The exhibits show the application sensor configuration and the Excessive-Bandwidth and Apple filter details. Based on the configuration, what will happen to Apple FaceTime if there

KOREADUMPS.COM

are only a few calls originating or incoming? (Choose one answer)

A. Apple FaceTime will be allowed, based on the Video/Audio category configuration.

B. Apple FaceTime will be blocked, based on the Excessive-Bandwidth filter configuration.

C. Apple FaceTime will be allowed, based on the Apple filter configuration.

D. Apple FaceTime will be allowed only if the Apple filter in Application and Filter Overrides is set to Allow.

Answer: B

Explanation:

According to the FortiOS 7.6 Administrator Study Guide, the Application Control engine processes traffic by evaluating the Application and Filter Overrides section first, using a top-down matching logic similar to firewall policies. In the provided exhibit, there are two override entries:

Priority 1: A behavior-based filter for Excessive-Bandwidth with the action set to Block.

Priority 2: A vendor-based filter for Apple with the action set to Monitor.

The exhibit titled "Application override configuration" explicitly shows that Apple FaceTime is one of the signatures included within the Excessive-Bandwidth behavior filter. When the FortiGate inspects FaceTime traffic, it matches the first entry (Priority 1) because the signature belongs to the "Excessive-Bandwidth" group. Since the action for this priority is Block, the traffic is dropped immediately.

The phrase "only a few calls" is a common exam distractor; in this context, the "Excessive-Bandwidth" filter refers to the classification of the application (as one that typically consumes high bandwidth) rather than a real-time measurement of the specific session's throughput. Because the engine stops searching once a match is found in the overrides, it never reaches the Priority 2 "Monitor" rule or the general Category settings.

KOREDUMPS.COM

QUESTION NO: 51

Which two statements are true about an HA cluster? (Choose two answers)

A. An HA cluster cannot have both in-band and out-of-band management interfaces at the same time.

B. Link failover triggers a failover if the administrator sets the interface down on the primary device.

C. When sniffing the heartbeat interface, the administrator must see the IP address 169.254.0.2.

D. HA incremental synchronization includes FIB entries and IPsec SAs.

Answer: B,D

Explanation:

According to FortiOS 7.6 High Availability documentation, the FortiGate Cluster Protocol (FGCP) provides robust mechanisms for both link monitoring and stateful data synchronization. Link failover is a primary trigger for cluster renegotiation; if a monitored interface goes down-including when an administrator manually sets the interface to administratively down-the primary unit's priority is effectively reduced, triggering a failover to a secondary unit to ensure path continuity.5 This is a standard method for testing HA failover behavior.

Furthermore, to achieve a seamless stateful failover where active sessions are not dropped,

the FortiGate performs incremental synchronization of critical runtime data.6 This specifically includes Forwarding Information Base (FIB) entries, which represent the compiled routing table, and IPsec Security Associations (SAs).7 By synchronizing IPsec SAs, the secondary unit 8can resume encrypted tunnels immediately after a failover without requiring a f9ull IKE re-negotiation.10 Statement A is incorrect because in-band and out-of-band management can coexist using reserved management interfaces and management-ip settings.11 Statement C is incorrect because while heartbeat interfaces use link-local IPs in the 169.254.0.x range, the specific IP .2 is not universally required for all heartbeats and depends on the number of cluster members and serial numbers.

QUESTION NO: 52

Which two statements describe characteristics of automation stitches? (Choose two answers)

A. Actions involve only devices included in the Security Fabric.

B. An automation stitch can have multiple triggers.

C. Multiple actions can run in parallel.

D. Triggers can involve external connectors.

Answer: C,D

Explanation:

According to the FortiOS 7.6 Administration Guide and Security Fabric documentation, automation stitches are designed to automate responses to security and system events across the network. A core characteristic of these stitches is their flexibility in action execution; specifically, multiple actions can run in parallel (Statement C). While the system allows for sequential execution with configurable delays between actions, the default behavior or configuration option allows for simultaneous responses, such as sending an email notification while simultaneously triggering a webhook or quarantining a host. Furthermore, triggers can involve external connectors (Statement D). While many triggers are local to the FortiGate (such as reboots or log events), the Security Fabric allows the FortiGate to monitor and react to events from external components like FortiAnalyzer, FortiSIEM, or FortiClient EMS. For example, a FortiAnalyzer event handler can act as the trigger for a stitch on the root FortiGate. Statement A is incorrect because actions can target external systems like AWS Lambda or Slack which are not internal Fabric devices. Statement B is incorrect because each automation stitch is typically defined by a single trigger, though that trigger itself can be broad (e.g., "Any Security Rating Notification").

QUESTION NO: 53

Which three strategies are valid SD-WAN rule strategies for member selection? (Choose three answers)

A. Lowest Cost (SLA) without load balancing

B. Manual with load balancing

C. Lowest Quality (SLA) with load balancing

D. Lowest Cost (SLA) with load balancing

E. Best Quality with load balancing

Answer: A,B,D

Explanation:
According to the FortiOS 7.6 Administrator Study Guide and official documentation, SD-WAN rules (services) determine the path selection for traffic matching specific criteria. Version 7.6 provides specific flexibility regarding how these strategies handle multiple member interfaces.
First, Manual with load balancing (Statement B) is a valid configuration. In the Manual strategy, the administrator orders interfaces by preference, but by enabling the Load balancing toggle, the FortiGate can distribute traffic across all members that are up.
Second, the Lowest Cost (SLA) strategy has been enhanced to support two modes. When the load balancing option is disabled, it acts as Lowest Cost (SLA) without load balancing (Statement A), selecting the single lowest-cost link that meets the SLA. Alternatively, by enabling the toggle, it functions as Lowest Cost (SLA) with load balancing (Statement D), where the FortiGate distributes traffic across all interfaces that satisfy the SLA target, regardless of their individual costs.
Statements C and E are incorrect because "Lowest Quality" is not a recognized SD-WAN strategy, and the Best Quality strategy is specifically a priority-based selection for a single "best" link, meaning the load balancing toggle is not available in the GUI when this mode is selected.

QUESTION NO: 54
Refer to the exhibit showing a debug flow output.

KOREADUMPS.COM

Debug Flow output

```
vd-root:0 received a packet(proto=1, 10.0.11.50:3->100.65.0.254:2048) tun_id=0.0.0.0 from port4. type=8, code=0, id=3, seq=5.
allocate a new session-00000721
in-[port4], out-[]
len=0
result: skb_flags-02000000, vid-0, ret-no-match, act-accept, flag-00000000
find a route: flag=00000000 gw-0.0.0.0 via port2
in-[port4], out-[port2], skb_flags-02000000, vid-0, app_id: 0, url_cat_id: 0
gnum-100004, use addr/intf hash, len=3
checked gnum-100004 policy-2, ret-matched, act-accept
ret-matched
gnum-4e20, check-ffffffffa002c9c7
checked gnum-4e20 policy-6, ret-no-match, act-accept
gnum-4e20 check result: ret-no-match, act-accept, flag-00000000, flag2-00000000
policy-2 Is matched, act-drop
after iprope_captive_check(): is_captive-0, ret-matched, act-drop, idx-2
Denied by forward policy check (policy 2)
```

KOREADUMPS.COM

Which two conclusions can you make from the debug flow output? (Choose two answers)

A. The default gateway is configured on port2.

B. The RPF check fails.

C. The debug flow is for UDP traffic.

D. The matching firewall policy denies the traffic.

Answer: A,D

Explanation:

According to the FortiOS 7.6 Troubleshooting and Administration guides, the diagnose debug flow command provides a step-by-step trace of how the FortiGate unit processes a packet. First, the line "find a route: flag=00000000 gw-0.0.0.0 via port2" indicates that during the routing table lookup, the FortiGate matched the destination against its default route (represented by 0.0.0.0) and determined that the egress interface is port2. This confirms that the default gateway for this traffic is reachable via port2 (Statement A).

Second, the debug trace concludes with the messages "policy-2 Is matched, act-drop" and "Denied by forward policy check (policy 2)". This explicitly indicates that the packet successfully matched the criteria for firewall policy ID 2, and the action configured for that policy is set to Deny (Statement D).

Statement B is incorrect because a Reverse Path Forwarding (RPF) failure would be indicated by a specific "reverse path check fail, drop" message, which is absent here. Statement C is incorrect because the output shows "proto=1", which corresponds to ICMP (Ping) traffic. UDP traffic would be identified as protocol 17.

QUESTION NO: 55

Which three statements explain a flow-based antivirus profile? (Choose three answers)

A. FortiGate buffers the whole file but transmits to the client at the same time.

B. Flow-based inspection uses a hybrid of the scanning modes available in proxy-based inspection.

C. If a virus is detected, the last packet is delivered to the client.

D. Flow-based inspection optimizes performance compared to proxy-based inspection.

E. The IPS engine handles the process as a standalone.

Answer: A,B,D

Explanation:

According to the FortiOS 7.6 Study Guide and Parallel Path Processing documentation, flow-based antivirus inspection is designed to provide security with minimal impact on performance.

First, a defining characteristic of modern flow-based AV (specifically in its "hybrid" mode) is that FortiGate buffers the whole file but transmits to the client at the same time (Statement A). This behavior allows the client to start receiving data immediately to prevent session timeouts, while the FortiGate reassembles the file in memory to perform a signature check before the final packet is released.

Second, starting with recent FortiOS versions including 7.6, flow-based inspection uses a hybrid of the scanning modes (Statement B). Previously, flow mode offered "Quick" or "Full" scans; now, it combines these techniques to offer a balance between the speed of stream-based scanning and the thoroughness of archive inspection.

Third, the primary motivation for selecting this mode is that flow-based inspection optimizes performance compared to proxy-based inspection (Statement D). It processes traffic in a single pass using the IPS engine, avoiding the overhead associated with the WAD (proxy) process. Statement C is incorrect because if a virus is detected, the last packet is withheld and the connection is reset to prevent the file from being completed. Statement E is less accurate as the IPS engine loads the AV engine to perform the task rather than acting as a "standalone" entity in the context of file scanning.

QUESTION NO: 56

Refer to the exhibits.

KOREADUMPS.COM



KOREADUMPS.COM

An administrator wants to add HQ-ISFW-2 in the Security Fabric. HQ-ISFW-2 is in the same subnet as HQ-ISFW. After configuring the Security Fabric settings on HQ-ISFW-2, the status stays Pending. What can be the two possible reasons? (Choose two answers)

A. Upstream FortiGate IP must be set to 10.0.11.254.

B. SAML Single Sign-On must be set to Manual.

C. HQ-ISFW-2 must be authorized on HQ-ISFW.

D. Management IP must be set to 10.0.13.254.

Answer: A,C

Explanation:

According to the FortiOS 7.6 Security Fabric documentation and Study Guide, several conditions must be met for a downstream FortiGate to successfully join a Security Fabric. First, the Upstream FortiGate IP/FQDN configured on the downstream device must point to the IP address of the interface on the upstream device that is listening for fabric connections. In the provided logical topology, the Fabric Root (HQ-NGFW-1) uses port4 with the IP 10.0.11.254 to connect to the internal segmentation firewalls (ISFWs). Since HQ-ISFW-2 is in the same subnet as HQ-ISFW, it is physically and logically connected to the network segment serviced by port4. Therefore, the current configuration of 10.0.13.254 (which is port6, likely the WAN side) is incorrect, and it must be set to 10.0.11.254 (Statement A). Second, once the downstream device successfully reaches the upstream device, it enters a Pending state. For security purposes, FortiOS does not allow devices to join the fabric automatically; the administrator of the upstream device (in this case, HQ-ISFW or the root) must manually authorize the new device (Statement C) in the Fabric Management console. Until this authorization is granted, the status will remain "Pending" and no fabric data will be synchronized. Statements B and D are incorrect as SAML settings do not block the initial fabric join, and the management IP should be the local device's IP, not the upstream's IP.

QUESTION NO: 57

What is the primary FortiGate election process when the HA override setting is enabled? (Choose one answer)

A. Connected monitored ports > Priority > HA uptime > FortiGate serial number

B. Connected monitored ports > Priority > System uptime > FortiGate serial number

C. Connected monitored ports > HA uptime > Priority > FortiGate serial number

D. Connected monitored ports > System uptime > Priority > FortiGate serial number

Answer: A

Explanation:

According to the FortiOS 7.6 Study Guide and technical documentation regarding High Availability (HA), the FortiGate Clustering Protocol (FGCP) uses a specific set of rules to elect the primary unit in a cluster. By default, the election order follows: Connected Monitored Ports > HA Uptime > Priority > Serial Number.

However, when the HA override setting is enabled, the election logic is modified to prioritize the administrator-defined priority value over the uptime of the cluster members. In this specific configuration, the election process follows this sequence:

Connected monitored ports: The unit with the most functioning monitored interfaces is preferred.

Priority: The unit with the highest manually configured priority value (e.g., 255) is selected next.

HA uptime: If monitored ports and priority are equal, the unit that has been up in the HA cluster the longest is chosen.

FortiGate serial number: As a final tie-breaker, the unit with the higher serial number is elected.1 Statement A is correct because it reflects the shift where Priority is evaluated immediately after monitored ports, overriding the standard uptime advantage. Statements B and D are incorrect because the FGCP uses HA uptime, not system uptime, for its calculations.

KODEADUMPS.COM

QUESTION NO: 58

Refer to the exhibit.

IPsec tunnel configuration



A network administrator is troubleshooting an IPsec tunnel between two FortiGate devices. The administrator has determined that phase 1 status is up, but phase 2 fails to come up. Based on the phase 2 configuration shown in the exhibit, which two configuration changes will bring phase 2 up? (Choose two.)

A. On BR1-FGT, set Remote Address to 10.0.11.0/255.255.255.0.

B. On HQ-NGFW. enable Diffie-Hellman Group 2.

C. On BR1-FGT. set Seconds to 43200

D. On HQ-NGFW. set Encryption to AES256.

Answer: A,D

Explanation:

Phase 1 being up confirms the two FortiGate devices can authenticate and build the IKE SA.

Phase 2 failing indicates the IPsec (Quick Mode) SA negotiation is failing due to mismatched Phase 2 parameters.
From the exhibit, the Phase 2 mismatches that would prevent SA establishment are:
1) Phase 2 selectors must mirror each other (Proxy IDs)
HQ-NGFW Phase 2 selector shows:
Local: 10.0.11.0/24
Remote: 172.20.1.0/24
BR1-FGT Phase 2 selector shows:
Local: 172.20.1.0/24
Remote: 10.11.0.0/24 does not match HQ's local subnet (10.0.11.0/24)
In FortiOS, Phase 2 comes up only when the peers' selectors (proxy IDs) match as opposite pairs (local on one side = remote on the other).
Fix: A. On BR1-FGT, set Remote Address to 10.0.11.0/255.255.255.0.
2) Phase 2 proposal must match (encryption/authentication)
HQ-NGFW shows encryption AES128 (with SHA1)
BR1-FGT shows encryption AES256 (with SHA1)
For Phase 2 to establish, both peers must have at least one common proposal (same encryption and authentication settings). With one side set to AES128 and the other to AES256, there is no match.
Fix: D. On HQ-NGFW, set Encryption to AES256.
Why the other options are not correct
B . Enable Diffie-Hellman Group 2: The exhibit's mismatch is not resolved by adding DH group 2, and DH group must match when PFS is enabled. This option does not align the peers based on what's shown.
C . Set Seconds to 43200: Phase 2 lifetime mismatches typically do not prevent Phase 2 from coming up (the negotiated lifetime can be adjusted by the peers). The hard blockers here are the selectors and proposal mismatch.

QUESTION NO: 59
Refer to the exhibit to view the firewall policy.

KOREADUMPS.COM

Firewall policy configuration

KOREADUMPS.COM

Why would the firewall policy not block a well-known virus, for example EICAR? (Choose one answer)

A. The action on the firewall policy is not set to DENY.

B. Web filter is not enabled, so the firewall policy does not complement the antivirus profile.

C. The firewall policy is not configured in proxy-based inspection mode.

D. The firewall policy does not apply deep content inspection.

Answer: D

Explanation:

"The only security features you can apply using SSL certificate inspection mode are web filtering and application control... Note that while offering some level of security, certificate

inspection does not allow FortiGate to inspect the flow of encrypted data."
"To perform SSL inspection on traffic flowing through the FortiGate device, you must allow the traffic with a firewall policy and apply an SSL inspection profile to the policy... For antivirus or IPS control, you should use a deep-inspection profile."
"When you use deep inspection, FortiGate impersonates the recipient of the originating SSL session, and then decrypts and inspects the content to find threats and block them. It then re-encrypts the content and sends it to the real recipient." Technical Deep Dive:
The exhibit shows that the policy is allowing HTTPS and the SSL/SSH inspection profile is certificate-inspection, not deep-inspection. That is the key issue. With certificate inspection, FortiGate can inspect only SSL metadata such as the certificate and SNI/hostname context; it cannot decrypt the HTTPS payload itself. Because EICAR is detected by antivirus through payload inspection, FortiGate must see the file contents. Without deep SSL inspection, the antivirus engine never gets the decrypted payload, so the file can pass even though the antivirus profile is attached.
Option A is incorrect because FortiGate firewall policies often use ACCEPT + security profile enforcement; the session can still be blocked by antivirus after policy match. Option B is incorrect because web filter is not required for antivirus detection. Option C is incorrect because the real requirement is deep SSL inspection, not specifically proxy-based mode; full SSL inspection is the deciding factor here.
In practice, to block EICAR over HTTPS, you would apply a deep-inspection SSL profile to the policy, for example:

```
config firewall policy
edit <policy-id>
set inspection-mode flow
set av-profile "default"
set ssl-ssh-profile "deep-inspection"
next
end
```

On real hardware, this also matters for performance design. Simple firewall/NAT sessions are often NP fast-pathed, but once you enable deep SSL inspection and content scanning, traffic is typically handed to CPU/WAD/content-inspection path for decryption and scanning, so throughput is lower than certificate-inspection or no-inspection.

KOREADUMPS.COM

QUESTION NO: 60
Refer to the exhibit, which shows a partial configuration from the remote authentication server.

Attribute	Value	Vendor	Actions
Fortinet-Group-Name	Training	Fortinet	

Why does the FortiGate administrator need this configuration? (Choose one answer)
A. To authenticate only the Training user group.
B. To set up a RADIUS server Secret.
C. To authenticate and match the Training OU on the RADIUS server.
D. To authenticate Any FortiGate user groups.

Answer: A
Explanation:
"With this method, you must create a user group and add the preconfigured remote server to the group. This setup allows you to select one or more pre-existing groups from the Radius server, enabling any user within those groups to be authenticated."
"The response from the server reports success, failure, and group membership details."
"Note that Fortinet has a vendor-specific attributes (VSA) dictionary to identify the Fortinet-proprietary RADIUS attributes. This capability allows you to extend the basic functionality of RADIUS." Technical Deep Dive:
The attribute shown in the exhibit is Fortinet-Group-Name = Training. This is a Fortinet RADIUS Vendor-Specific Attribute (VSA) used to return group membership information to FortiGate. FortiGate uses that returned value to match the authenticated user to the corresponding FortiGate user group, in this case Training.
That is why A is correct: the administrator needs this so FortiGate can authenticate users and place or match them into the Training group for identity-based policy control.
Why the others are wrong:
* B is wrong because the RADIUS secret is configured separately as the shared secret between FortiGate and the RADIUS server, not as a Fortinet-Group-Name attribute.
* C is wrong because OU matching is an LDAP concept, not standard RADIUS group matching.
* D is wrong because this attribute is not for "any" group; it is explicitly returning the specific group name Training.
In practice, this lets FortiGate apply firewall policies such as:
```bash
config user group
edit "Training"
set member "RADIUS_Server"
next
end
```
Then the RADIUS server returns Fortinet-Group-Name=Training, and FortiGate matches the user into that group for policy enforcement.

QUESTION NO: 61
Which three methods are used by the collector agent for AD polling? (Choose three answers)
A. NetAPI
B. WMI
C. WinSecLog
D. DNS reverse lookup
E. FSSO REST API
Answer: A,B,C
Explanation:
"As previously stated, collector agent-based polling mode has three methods (or options) for collecting login information. The order on the slide from left to right shows most recommend to least recommended:

* WMI ...
* WinSecLog ...
* NetAPI ..."
Technical Deep Dive:
The correct three AD polling methods are WMI, WinSecLog, and NetAPI. These are the collector-agent polling options FortiGate FSSO uses against Windows domain controllers. WMI is generally the most efficient because the DC returns requested login events directly. WinSecLog polls Windows Security Event Logs and is typically more reliable than NetAPI for not missing recorded logons. NetAPI can be faster, but it is more prone to missing events under load because it depends on temporary session information rather than persistent security logs.
Why the other options are wrong:
DNS reverse lookup is not one of the three AD polling methods. DNS is used by FSSO to resolve workstation names to IP addresses and to track IP changes, but it is not itself a polling method for collecting AD logon events. FSSO REST API is also not one of the documented collector-agent AD polling methods in the study guide.
From an operational standpoint, FSSO login collection and workstation verification are separate functions. The collector agent may still rely on DNS and workstation checks after a login is learned, but the actual AD polling methods remain only WMI, WinSecLog, and NetAPI. On a FortiGate, when troubleshooting FSSO behavior, you would typically validate the collector feed and user cache with commands such as:
diagnose debug authd fsso list
diagnose debug authd fsso server-status
Those commands help confirm whether the users gathered by the collector through one of those three polling methods are reaching FortiGate correctly.

QUESTION NO: 62
Which three methods are used by the collector agent for AD polling? (Choose three answers)
A. NetAPI
B. WMI
C. WinSecLog
D. DNS reverse lookup
E. FSSO REST API
Answer: A,B,C
Explanation:
"As previously stated, collector agent-based polling mode has three methods (or options) for collecting login information. The order on the slide from left to right shows most recommend to least recommended:
* WMI ...
* WinSecLog ...
* NetAPI ..."
Technical Deep Dive:
The correct three AD polling methods are WMI, WinSecLog, and NetAPI. These are the collector-agent polling options FortiGate FSSO uses against Windows domain controllers. WMI is generally the most efficient because the DC returns requested login events directly.

KOREADUMPS.COM

WinSecLog polls Windows Security Event Logs and is typically more reliable than NetAPI for not missing recorded logons. NetAPI can be faster, but it is more prone to missing events under load because it depends on temporary session information rather than persistent security logs.
Why the other options are wrong:
DNS reverse lookup is not one of the three AD polling methods. DNS is used by FSSO to resolve workstation names to IP addresses and to track IP changes, but it is not itself a polling method for collecting AD logon events. FSSO REST API is also not one of the documented collector-agent AD polling methods in the study guide.
From an operational standpoint, FSSO login collection and workstation verification are separate functions. The collector agent may still rely on DNS and workstation checks after a login is learned, but the actual AD polling methods remain only WMI, WinSecLog, and NetAPI. On a FortiGate, when troubleshooting FSSO behavior, you would typically validate the collector feed and user cache with commands such as:
diagnose debug authd fsso list
diagnose debug authd fsso server-status
Those commands help confirm whether the users gathered by the collector through one of those three polling methods are reaching FortiGate correctly.

KOREADUMPS.COM

QUESTION NO: 63
An administrator wants to form an HA cluster using the FGCP protocol. Both FortiGate devices are configured with the set override enable command. Arrange the criteria in the order in which the FGCP protocol uses them to elect the primary FortiGate. Select the criteria in the left column, hold and drag it to a blank position in the column on the right. Place the four correct steps in order, placing the first step in the first position. Once you place a step, you can move it again if you want to change your answer before moving to the next question. You need to drop four criteria in the work are a. Select and drag the screen divider to change the viewable area of the source and work areas. (Choose four answers)



Answer:



QUESTION NO: 64
Refer to the exhibits.

KOREADUMPS.COM

HQ-NGFW-1 HA configuration

```
HQ-NGFW-1 # config system ha

HQ-NGFW-1 (ha) # show
config system ha
     set group-id 5
     set group-name "Training"
     set mode a-p
     set password ENC nmk7zGYiRrux1
     set hbdev "port7" 0
     set session-pickup enable
     set override disable
     set priority 200
     set monitor "port1"
end
```

HQ-NGFW-2 HA configuration

```
HQ-NGFW-2 (ha) # show
config system ha
     set group-id 5
     set group-name "Training"
     set mode a-p
     set password ENC n40G3dmn0K50s
     set hbdev "port7" 0
     set session-pickup enable
     set override disable
     set priority 100
     set monitor "port1"
end
```

CREADUMPS.COM

An administrator configured both members of an HA cluster at the same time. After one week of monitoring, the administrator wants to verify the HA failover performance. How can the administrator force a failover? (Choose one answer)

A. The administrator must reset the HA uptime on HQ-NGFW-1.

B. The administrator must set the parameter override to enable on HQ-NGFW-2.

C. The administrator must increase the HA priority on HQ-NGFW-2.

D. The administrator must set the monitored port1 to down on HQ-NGFW-1.

Answer: A

Explanation:

"This slide shows the order when the HA override setting is disabled, which is the default behavior."

"1. The cluster compares the number of monitored interfaces that have a status of up. The member with the most available monitored interfaces becomes the primary.

2. The cluster compares the HA uptime of each member. The member with the highest HA uptime, by at least five minutes, becomes the primary.
3. The member with the highest priority becomes the primary."
"When HA override is disabled, the HA uptime has precedence over the priority setting. This means that if you must manually fail over to a secondary device, you can do so by reducing the HA uptime of the primary FortiGate. You can do this by running the diagnose sys ha reset-uptime command on the primary FortiGate, which resets its HA uptime to 0." Technical Deep Dive:
The correct answer is A.
Both HA members are configured with set override disable, so FGCP does not prefer the higher-priority unit first. With override disabled, the election order is based on monitored interfaces, then HA uptime, then priority, and finally serial number. Since the cluster has been running for one week, the secondary unit will have a much higher HA uptime than a unit whose uptime is reset to zero. Therefore, if the administrator runs diagnose sys ha reset-uptime on the current primary HQ-NGFW-1, FGCP re-evaluates election and the other member can take over.
Option B is wrong because enabling override only on HQ-NGFW-2 does not by itself force an immediate clean failover in this scenario and also changes election behavior rather than performing the documented manual failover action. Option C is wrong because with override disabled, priority does not beat HA uptime. Option D can simulate a link failover, but the study guide's documented manual failover method for this exact override-disabled condition is to reset the primary's HA uptime.
Relevant CLI:
diagnose sys ha reset-uptime
get system ha status
diagnose sys ha status
This is the clean exam-aligned method to trigger a controlled HA role change.

KOREADUMPS.COM

QUESTION NO: 65
What are three key routing principles in SD-WAN? (Choose three answers)
A. By default, SD-WAN rules are skipped if the included SD-WAN members do not have a valid route to the destination.
B. SD-WAN rules have precedence over any other type of routes.
C. Regular policy routes have precedence over SD-WAN rules.
D. By default, SD-WAN rules are skipped if only one route to the destination is available.
E. By default, SD-WAN rules are skipped if the best route to the destination is not an SD-WAN member.
Answer: A,C,E
Explanation:
"This slide shows the SD-WAN rule lookup process. SD-WAN rules are essentially policy routes."
"FortiGate performs a forwarding information base (FIB) lookup for the packet destination IP (dstip). If the resolved interface for the fib-best-match isn't an SD-WAN member, then FortiGate moves on to the next rule. This behavior follows the key routing principle: SD-WAN rules are skipped if the best route to the destination isn't an SD-WAN member."

"If the resolved interface is an SD-WAN member, then FortiGate looks for one or more acceptable members in the oif list... An acceptable member is an alive member that has a route to the destination. This behavior follows the key routing principle: SD-WAN rules are skipped if none of the configured members in the rule have a valid route to the destination."
"Because regular policy routes have precedence over any other routes..."
"Also note that policy routes have precedence over SD-WAN rules, and over any routes in the FIB." Technical Deep Dive:
The correct answers are A, C, and E.
A is correct because an SD-WAN rule is not enough by itself. A selected member must also be alive and have a valid route to the destination. If none of the members referenced by the rule can actually reach the destination, the rule is skipped.
C is correct because a regular policy route is evaluated before SD-WAN rules. This is a classic exam trap. FortiGate treats SD-WAN steering like policy-route logic, but standard policy routes still win if they match and are valid.
E is correct because FortiGate first checks the FIB best match. If that best route resolves to an interface that is not an SD-WAN member, FortiGate skips the SD-WAN rule and continues.
Why the others are wrong:
B is false because SD-WAN rules do not have precedence over everything; regular policy routes do.
D is false because the number of available routes is not the deciding rule. Even with only one route, SD-WAN can still steer traffic if the routing and member conditions are met.
Operationally, think of SD-WAN routing in this order: policy route check → SD-WAN rule lookup → standard FIB fallback. On FortiGate, the practical validation commands are:
get router info routing-table all
diagnose sys sdwan service
diagnose firewall proute list
That combination lets you confirm whether a packet is being captured by a policy route, whether an SD-WAN rule has acceptable members, and what the FIB currently resolves for the destination.

QUESTION NO: 66
Refer to the exhibit.

KOREADUMPS.COM



The exhibit shows the FortiGuard Category Based Filter section of a corporate web filter profile. An administrator must block access to download.com, which belongs to the Freeware and Software Downloads category. The administrator must also allow other websites in the same category. What are two solutions for satisfying the requirement? (Choose two answers)

A. Configure a static URL filter entry for download.com with Type and Action set to Wildcard and Block, respectively.

B. Configure a web override rating for download.com and select Malicious Websites as the subcategory.

C. Configure a separate firewall policy with action Deny and an FQDN address object for *.download.com as destination address.

D. Set the Freeware and Software Downloads category Action to Warning.

Answer: A,B

Explanation:

"In FortiOS, there are three main components of web filtering:

* Web content filtering...

* URL filtering: uses URLs and URL patterns to block or exempt web pages from specific sources...

* FortiGuard Web Filtering service..."

"In the web filter profile, Fortiguard category filtering enhances the web filter features. Rather than block or allow websites individually, it looks at the category that a website has been rated with. Then, FortiGate takes action based on that category, not based on the URL."

"If you consider that a particular URL does not have the correct category, you can ask to re-

evaluate the rating in the Fortinet URL Rating Submission website. You can also override a web rating for an exceptional URL in the FortiGate configuration."
"Static URL filtering is another web filter feature, which provides more granularity. Configured URLs in the URL filter are checked from top to bottom against the visited websites. If FortiGate finds a match, it applies the configured action."
"To find the exact match, URL filtering has three pattern types: Simple, Regular Expressions, and Wildcard."
"So, with these different features, what is the inspection order? If you have enabled many of them, the inspection order flows as follows:
The local static URL filter
FortiGuard category filtering..."
Technical Deep Dive:
The correct answers are A and B.
A is correct because a static URL filter gives per-URL granularity. Since the category Freeware and Software Downloads is currently allowed in the profile, adding a local static URL filter entry for download.com with Block lets FortiGate deny only that site while continuing to allow the rest of the category. This also aligns with the documented inspection order, where the local static URL filter is checked before FortiGuard category filtering.
B is also correct because a web rating override can reclassify a specific exceptional URL. If download.com is re-rated into a blocked category such as Malicious Websites, it will be blocked by the profile while other sites in Freeware and Software Downloads remain allowed.
Why the others are wrong:
C is not the intended web-filter solution. A firewall policy with an FQDN object operates at policy/routing resolution level, not as a category-aware web filtering exception.
D is wrong because changing the whole category to Warning affects all sites in that category, not just download.com.
In production, the cleaner design is usually: keep the category allowed, then add a local URL-filter exception or a web-rating override for the specific site. For HTTPS traffic, remember FortiGate still needs enough SSL inspection visibility to identify the hostname correctly. A representative CLI approach for URL filtering is:

```
config webfilter urlfilter
edit 1
config entries
edit 1
set url "download.com"
set type wildcard
set action block
next
end
next
end
```

This is the most deterministic way to block one site without penalizing the rest of the category.

QUESTION NO: 67
You have implemented the application sensor and the corresponding firewall policy as shown

KOREADUMPS.COM

in the exhibits.

Application sensor



KOREADUMPS.COM



You cannot access any of the Google applications, but you are able to access www.fortinet.com.
What would you do to resolve this issue?

A. Change the Inspection mode to Proxy-based.

B. Set SSL inspection to deep-content-inspection.

C. Move up Google in the Application and Filter Overrides section to set its priority to 1.

D. Add Google.com to the URL category in the security profile.

Answer: C

Explanation:
"With these multiple filters, which one has the priority? After the IPS engine examines the traffic stream for a signature match, FortiGate scans packets for matches, in this order, for the application control profile:
1. Application and filter overrides..."

"Next, the scan checks for application and filter overrides. Because a filter override is configured to block applications that use excessive bandwidth, it blocks all applications using excessive bandwidth, regardless of other categories that allow these applications."
"In this scenario, the filter override (Excessive-Bandwidth) is blocked and, since Dailymotion falls under the excessive bandwidth category, Dailymotion is blocked even though it is set to Monitor in the Application and Filter Overrides section. The priority in which application and filter overrides are placed takes precedence."
"To allow web filtering, DNS filtering, or application control for HTTPS traffic, you must select an SSL inspection profile with certificate inspection or a deep inspection enabled." Technical Deep Dive:
The problem is not flow-based mode and not the SSL profile. Your firewall policy already has certificate-inspection, and the study guide explicitly says that application control for HTTPS traffic works with certificate inspection or deep inspection. So option B is unnecessary, and option A is unrelated.
The real issue is the override order inside the application sensor:
Priority 1: Filter = Excessive-Bandwidth, Action = Block
Priority 2: Vendor = Google, Action = Monitor
FortiGate evaluates overrides from top to bottom and applies the first match. Many Google applications match the Excessive-Bandwidth filter, so they are blocked before the later Google/Monitor override is ever reached. That is why Google apps fail while www.fortinet.com still works.
So the correct fix is to move the Google override above the Excessive-Bandwidth filter, making Google the first match.
A representative CLI-style logic would be:

```
config application list
edit "default"
config entries
edit 1
set vendor "Google"
set action monitor
next
edit 2
set filter "Excessive-Bandwidth"
set action block
next
end
next
end
```

That preserves the bandwidth block for other apps while allowing Google applications to match the higher-priority override first.

QUESTION NO: 68
Which two statements about equal-cost multi-path (ECMP) configuration on FortiGate are true? (Choose two answers)
A. If SD-WAN is enabled, you control the load balancing algorithm with the parameter load-

KOREADUMPS.COM

balance-mode.

B. If SD-WAN is disabled, you can configure the parameter v4-ecmp-mode to volume-based.

C. If SD-WAN is enabled, you can configure routes with unequal distance and priority values to be part of ECMP.

D. If SD-WAN is disabled, you configure the load balancing algorithm in config system settings.

Answer: A,D

Explanation:

"If SD-WAN is disabled, you can change the ECMP load balancing algorithm on the FortiGate CLI using the commands shown on this slide."

"When SD-WAN is enabled, FortiOS hides the v4-ecmp-mode setting and replaces it with the load-balance-mode setting under config system sdwan. That is, when you enable SD-WAN, you control the ECMP algorithm with the load-balance-mode setting."

"There are some differences between the two settings. The main difference is that load-balance-mode supports the volume algorithm, and v4-ecmp-mode does not."

"These routes are called equal cost multipath (ECMP) routes..."

Technical Deep Dive:

The correct answers are A and D.

A is correct because when SD-WAN is enabled, FortiOS no longer uses v4-ecmp-mode; it uses load-balance-mode under config system sdwan. That is the explicit SD-WAN control point for ECMP behavior.

D is correct because when SD-WAN is disabled, ECMP configuration is done in the regular system routing settings, not under SD-WAN. The study guide states that you change the ECMP algorithm on the FortiGate CLI when SD-WAN is disabled, which corresponds to the classic config system settings ECMP controls.

Why the others are wrong:

B is wrong because the guide explicitly says load-balance-mode supports volume, while v4-ecmp-mode does not. So you cannot set v4-ecmp-mode to volume-based.

C is wrong because ECMP requires equal-cost routes. If distance or priority differ, they are no longer ECMP candidates; FortiGate selects the preferred route instead. The concept of ECMP itself requires equal route cost attributes.

From an implementation standpoint, the common CLI patterns are:

```
config system settings
set v4-ecmp-mode source-ip-based
end
```

and, with SD-WAN enabled:

```
config system sdwan
set load-balance-mode source-ip-based
end
```

On hardware platforms, ECMP still affects session distribution at the routing decision stage before later security services are applied. NP offload can accelerate forwarding after route selection, but the ECMP decision itself is a FortiOS control-plane routing function.

QUESTION NO: 69

Refer to the exhibit.

TOPEXDUMPS.COM



What would be the impact of these settings on the Server certificate SNI check configuration on FortiGate?

A. FortiGate will accept and use the CN in the server certificate for URL filtering if the SNI does not match the CN or SAN fields.

B. FortiGate will accept the connection with a warning if the SNI does not match the CN or SAN fields.

C. FortiGate will close the connection if the SNI does not match the CN or SAN fields.

D. FortiGate will close the connection if the SNI does not match the CN and SAN fields

Answer: C

Explanation:

Based on the exhibit and the FortiOS 7.6 SSL/SSH Inspection documentation, the correct answer is C.

Understanding the Exhibit Configuration

In the SSL/SSH Inspection Profile, the following settings are shown:

Inspection method: Full SSL Inspection

Server certificate SNI check: Strict

This setting directly controls how FortiGate validates the Server Name Indication (SNI) provided by the client during the TLS handshake.

FortiOS 7.6 Behavior of "Server certificate SNI check"

FortiOS supports three modes for Server certificate SNI check:

Disable

No validation between SNI and server certificate.

Enable

FortiGate checks SNI against the certificate.

If mismatch occurs, FortiGate may still allow the session with reduced validation.

Strict

FortiGate enforces a strict match.

The SNI must match either the CN (Common Name) or one of the SAN (Subject Alternative Name) entries in the server certificate.

If the SNI does not match either CN or SAN, the TLS session is immediately terminated.

The exhibit clearly shows Strict selected.

Why Option C is Correct

With Strict enabled, FortiGate rejects the TLS connection when:

FCP-FAD-DUMPS.COM

The SNI does not match the CN, and
The SNI does not match any SAN entry
This results in the connection being closed, not allowed with warnings or fallback behavior.
Therefore:
C . FortiGate will close the connection if the SNI does not match the CN or SAN fields is exactly the documented behavior.
Why the Other Options Are Incorrect
A: FortiGate does not fall back to using the CN for URL filtering when Strict is enabled.
B: There is no "accept with warning" behavior in Strict mode.
D: Incorrect logical condition. FortiGate does not require mismatch with both CN and SAN simultaneously; a mismatch with either valid field set is sufficient to close the connection.

QUESTION NO: 70
An administrator creates a new address object on the root FortiGate (HQ-NGFW-1) in the Security Fabric. After synchronization, this object is not available on the downstream FortiGate (HQ-ISFW).

Security Fabric physical topology view



New address object on HQ-NGFW-1



KOREADUMPS.COM

Security Fabric configuration on HQ-NGFW-1

```
HQ-NGFW-1 # show full-configuration system csf
config system csf
     set status enable
     set uid "10e202dad887c02ac8bafa024228d86d"
     set upstream ' '
     set source-ip 0.0.0.0
     set upstream-interface-select-method auto
     set upstream-port 8013
     set-group-name "Fortinet"
     set group-password ENC M8h5eGm9sVzi555Pp5y
YEaCjk/95p0MHllmMjY3dkVA
     set accept-auth-by-cert enable
     set log-unification enable
     set authorization-request-type serial
     set fabric-workers 2
     set downstream-access disable
     set configuration-sync default
     set fabric-object-unification local
     set saml-configuration-sync default
```

Security Fabric configuration on HQ-ISFW

```
HQ-NGFW-1 # show full-configuration system csf
config system csf
     set status enable
     set uid "dd0263000fa8209fc0d99a40faf9c818"
     set upstream "10.0.11.254"
     set source-ip 0.0.0.0
     set upstream-interface-select-method auto
     set upstream-port 8013
     set-group-name ''
     set accept-auth-by-cert enable
     set log-unification enable
     set authorization-request-type serial
     set fabric-workers 2
     set downstream-access disable
     set configuration-sync default
     set saml-configuration-sync local
     set file-mgmt enable
     set file-quota 0
     set file-quota-warning 90
end
```

KOREADUMPS.COM

What must the administrator do to synchronize the address object?

A. Change the csf setting on HQ-ISFW (downstream) to set configuration-sync local.
B. Change the csf setting on HQ-ISFW (downstream) to set saml-configuration-sync default.
C. Change the csf setting on HQ-NGFW-1 (root) to set fabric-object-unification default.
D. Change the csf setting on both devices to set downstream-access enable.
Answer: C
Explanation:
The study guide text surfaced from the PDF did not return a matching paragraph for fabric-object-unification, but the exhibit itself shows these critical details:
On HQ-NGFW-1, set configuration-sync default and set fabric-object-unification local On HQ-ISFW, set configuration-sync default The new address object on HQ-NGFW-1 has Fabric global object enabled Those exhibit settings indicate that the object is intended to be a fabric-wide object, but the root FortiGate is currently configured with fabric-object-unification local, which prevents that object from being unified across the fabric.
Technical Deep Dive:
The correct answer is C.
Here is the key logic:
The address object was created on the root FortiGate with Fabric global object enabled.
Normal configuration sync is already set to default, so this is not a generic sync-disabled problem.
The root device is specifically configured with set fabric-object-unification local.
That setting keeps fabric objects local to the device rather than unifying them across downstream fabric members.
Therefore, to make the object propagate as a shared Security Fabric object, the administrator must change the root setting to:
```
config system csf
set fabric-object-unification default
end
```
Why the other options are wrong:
A is wrong because the downstream device already has configuration-sync default, and changing it to local would make synchronization more restrictive, not less.
B is wrong because saml-configuration-sync is unrelated to firewall address object synchronization.
D is wrong because downstream-access controls downstream management access behavior, not fabric object propagation.
Operationally, this feature matters when you want shared address objects, services, and policy-referenced objects to remain consistent across the Security Fabric. It reduces duplicate object administration and helps keep policy logic normalized across root and downstream FortiGate devices.

QUESTION NO: 71
An administrator wants to address shadow IT visibility challenges and prevent users from sending sensitive files outside the organization without proper approval. Which FortiSASE method should the administrator implement to achieve these goals? (Choose one answer)
A. Secure SD-WAN access (SSD-WAN)
B. Secure private access (SPA)

KEREADUMPS.COM

C. Secure SaaS access (SSA)
D. Secure internet access (SIA)
Answer: C
Explanation:
"FortiSASE provides secure access to remote users for the following use cases:
* SIA enables secure web browsing for remote users to protect from known and unknown threats
* SPA enables explicit application access under a zero-trust access or with SD-WAN integration to ensure secure application access
* SSA addresses shadow IT visibility challenges and safeguards data loss prevention"
"FortiCASB provides cloud-based and API-based features to enable deep inspection of SaaS applications to enable detailed monitoring, analysis, and reporting features... Data loss prevention (DLP) helps to identify, monitor, and protect organizational data at rest and in motion." Technical Deep Dive:
The correct answer is C. Secure SaaS access (SSA).
The question gives two very specific requirements:
Shadow IT visibility
Prevent sensitive files from leaving the organization without approval
The study guide maps both directly to SSA. In FortiSASE, SSA aligns with SaaS governance and CASB-style controls. That is the right architecture when you need visibility into sanctioned and unsanctioned SaaS usage, plus DLP controls for uploads, sharing, and file movement.
Why the other options are wrong:
SIA focuses on securing internet browsing and remote web traffic.
SPA is for explicit zero-trust access to private applications.
SSD-WAN is not the FortiSASE method for SaaS visibility/DLP control.
In practice, SSA is the choice because it combines SaaS visibility, activity monitoring, and DLP-style enforcement. That lets an administrator detect shadow SaaS usage and apply controls such as blocking uploads, monitoring sharing events, or restricting file transfers based on policy. This is a CASB-oriented use case, not just generic web security.

QUESTION NO: 72
An administrator wanted to configure an IPS sensor to block traffic that triggers the signature set number of times during a specific time period. How can the administrator achieve the objective?
A. Use IPS group signatures, set rate-mode 60.
B. Use IPS packet logging option with periodical filter option.
C. Use IPS signatures, rate-mode periodical option.
D. Use IPS filter, rate-mode periodical option.
Answer: C
Explanation:
"Rate-based IPS signatures also allows you to detect anomalies, which are unusual behaviors in the network..."
"There are two ways to add predefined signatures to an IPS sensor. One way is to select the signatures individually... The second way to add a signature to a sensor is using filters."

KOREADUMPS.COM

"You can also add rate-based signatures to block specific traffic when the threshold is exceeded. On the CLI, If you set the command rate-mode to periodical, FortiGate triggers the action when the threshold is reached during the configured Duration time period." Technical Deep Dive:
The correct answer is C. Use IPS signatures, rate-mode periodical option.
The guide is explicit that this behavior belongs to rate-based IPS signatures. The question asks for blocking traffic when a signature is triggered a certain number of times within a defined interval. That is exactly what rate-mode periodical does: it evaluates the trigger count over the configured duration window and then applies the configured IPS action when the threshold is met.
Why the other options are wrong:
A is wrong because rate-mode 60 is not the documented syntax or method.
B is wrong because packet logging records packets; it does not implement threshold-based blocking logic.
D is wrong because the guide ties rate-mode periodical to rate-based signatures, not to IPS filters as the mechanism for this threshold behavior.
Operationally, this is used for anomaly-style detection, similar in concept to lightweight rate-based protection. A typical CLI pattern is along these lines:

```
config ips sensor
edit "custom-ips"
config entries
edit 1
set rule <signature_id>
set rate-mode periodical
set rate-count <threshold>
set rate-duration <seconds>
set action block
next
end
next
end
```

This works best when applied only to relevant protocols and signatures, because broad use of rate-based signatures can consume more resources and increase false-positive risk.

KOREADUMPS.COM

QUESTION NO: 73
When configuring the connection between FortiGate and FortiAnalyzer, which option indicates that reliable traffic is enabled? (Choose one answer)
A. The connection status shows a green check icon
B. The interface status is set to up
C. A padlock icon appears in the connection settings
D. The logging mode is set to real-time
Answer: C
Explanation:
"When you enable reliable logging on FortiGate, the log transport delivery method changes from UDP to TCP. TCP provides reliable data transfer, guaranteeing that the transferred data

remains intact and arrives in the same order in which it was sent."
"Optionally, if using reliable logging, you can encrypt communications using SSL-encrypted OFTP traffic, so when a log message is generated, it is safely transmitted across an unsecured network." Technical Deep Dive:
The correct answer is C. The study guide explicitly ties reliable logging to TCP transport and optionally to SSL-encrypted OFTP. Among the choices, the padlock icon is the only one that meaningfully indicates secure, reliable log transport behavior. A green check icon usually indicates that the FortiGate-FortiAnalyzer connection is simply up, not specifically that reliable logging is enabled. Interface status being up is unrelated, and real-time logging mode describes delivery behavior, not the reliable transport indicator itself.
So, exam-wise, the best answer is C.
From the CLI perspective, reliable logging changes the transport from UDP to TCP, and with encryption enabled it uses SSL-protected OFTP. That is why the GUI indicator associated with secure transport is the most relevant visual clue here.

QUESTION NO: 74
You have configured the FortiGate device for FSSO. A user is successful in log-in to Windows, but their access to the internet is denied. What should the administrator check first? (Choose one answer)
A. Whether the user is assigned to the correct AD group.
B. The FortiGate firewall policy settings for SSL decryption.
C. The FortiGate FSSO active users list for user's IP address.
D. The Windows event viewer for failed login attempts.
Answer: C
Explanation:
"FSSO is a software agent that enables FortiGate to identify network users for security policies or for VPN access, without asking for their username and password. When a user logs in to a directory service, the FSSO agent sends FortiGate the username, the IP address, and the list of groups that the user belongs to. FortiGate uses this information to maintain a local database of usernames, IP addresses, and group mappings."
"To display the list of FSSO users that are currently logged in, use the CLI command diagnose debug authd fsso list. For each user, the user name, user group, IP address, and the name of the workstation from which they logged in shows."
"You can monitor users who authenticate through your firewall policies using the Dashboard > Assets & Identities > Firewall Users page. It displays the user, user group, duration, IP address, traffic volume, and authentication method." Technical Deep Dive:
The first thing to verify is whether FortiGate has actually learned the user correctly in its FSSO active users table, especially the user-to-IP mapping. FSSO enforcement is identity-based, but the real-time match on live traffic still depends on FortiGate associating the traffic's source IP with the authenticated Windows user. If that mapping is missing, stale, or tied to the wrong IP because of DHCP changes, DNS update lag, or collector-agent timing, the firewall policy match can fail even though the user successfully logged in to Windows. That is why C is the best first check.
A may be the next thing to verify if the user is present but still denied, but first you must confirm the user is even present in the FSSO table with the correct IP.

KOREADUMPS.COM

B is unrelated to the initial FSSO identity-mapping problem.
D is less likely because the Windows logon already succeeded.
Useful checks:
diagnose debug authd fsso list
diagnose debug authd fsso server-status
execute fsso refresh
These commands confirm whether FortiGate has the user, group, and IP mapping needed for policy matching.

QUESTION NO: 75
When configuring a FortiGate in a multi-WAN setup, why would an administrator enable session preservation on an interface? (Choose one answer)
A. To allow the FortiGate to dynamically change interfaces for all active sessions when a WAN link fails
B. To make sure all sessions without source NAT enabled always use the primary WAN link
C. To improve security by forcing users to authenticate again when the WAN link changes
D. To ensure that existing SSL VPN connections remain on the same interface even if route changes occur
Answer: D
Explanation:
A closely related routing principle from the guide is:
"For each session, FortiGate performs two route lookups... After completing these two lookups, FortiGate writes the routing information to its session table. Subsequent packets are routed according to the session table, not the routing table." Also, the guide notes an HA limitation that helps explain the same design principle for FortiGate-terminated sessions:
"Enabling session pickup allows active sessions to be seamlessly handed picked up by the new primary in the event of an HA failover... Note that there are some limitations to this - for example, any sessions that terminate at the FortiGate itself (e.g. SSL VPN, proxy sessions) cannot be handed off to another FortiGate and must be restarted on the new primary."
Technical Deep Dive:
The correct answer is D.
In multi-WAN environments, session preservation is used so that traffic for sessions that are tightly bound to the FortiGate interface they terminate on-most notably SSL VPN and other FortiGate-terminated flows-does not suddenly switch to another egress interface just because the routing table changes. Those sessions are sensitive to interface consistency. If replies start leaving through a different WAN after a route recalculation, the remote peer may see an address/interface mismatch and the session can break.
That means:
A is the opposite of session preservation. Preservation is meant to avoid moving active sessions around.
B is not the purpose of the feature.
C is unrelated.
D correctly describes why an administrator would enable it.
Operationally, this matters most for SSL VPN, management-plane flows, and other sessions that terminate on the FortiGate itself, not just ordinary transit traffic. Transit sessions are

KSREADUMPS.COM

generally tracked in the session table and can often survive normal routing behavior more gracefully, but FortiGate-terminated sessions are much more sensitive to WAN/interface changes.

QUESTION NO: 76

Exhibits:



You are asked to implement an antivirus profile for files downloaded through FTP, HTTP, and HTTPS.

While testing, you are successful with HTTP and FTP protocols, but FortiGate does not block the file download over HTTPS.

What could be the cause?

A. The feature set in the antivirus profile is not set to Flow-based.

B. Web filter is not enabled on the firewall policy to complement the antivirus profile.

C. The action on the firewall policy is not set to deny.

D. The SSL inspection mode in the firewall policy is not deep content inspection.

Answer: D

Explanation:

"To perform SSL inspection on traffic flowing through the FortiGate device, you must allow the traffic with a firewall policy and apply an SSL inspection profile to the policy. Note that an SSL inspection profile alone will not trigger a security inspection. You must combine it with other security profiles like Antivirus, Web Filter, Application Control, or IPS."

"By default, firewall policies are set with the no-inspection SSL profile. Therefore, any encrypted traffic flows through uninspected... For antivirus or IPS control, you should use a

deep-inspection profile."
"When you use deep inspection, FortiGate impersonates the recipient of the originating SSL session, and then decrypts and inspects the content to find threats and block them. It then re-encrypts the content and sends it to the real recipient. Deep inspection protects from attacks that use HTTPS and other commonly used SSL-encrypted protocols..." Technical Deep Dive:
The correct answer is D. HTTP and FTP are working because FortiGate can inspect those payloads directly with the antivirus profile. HTTPS is different because the traffic is encrypted. If the firewall policy uses only certificate inspection or another non-decrypting SSL mode, FortiGate can identify certificate/SNI information, but it cannot see the downloaded file contents. Without decrypting the HTTPS session, the antivirus engine never receives the payload to scan, so EICAR or other malware can pass.
Why the other options are wrong:
A is not the issue here. The exhibit shows the antivirus profile and policy are already aligned for proxy-based operation, and the failure is specific to HTTPS visibility.
B is wrong because web filter is not required for antivirus scanning.
C is wrong because firewall policies commonly use ACCEPT with security profiles; the antivirus engine can still block the file after policy match. The study guide explicitly says ACCEPT allows the session and then applies antivirus scanning and other packet-processing features.
To fix it, apply deep-inspection on the firewall policy:

```
config firewall policy
edit <policy-id>
set ssl-ssh-profile "deep-inspection"
set av-profile "HTTP_AV_Profile"
next
end
```

On real FortiGate hardware, this also has performance implications. Simple flow handling can often stay on accelerated paths, but full SSL deep inspection forces decryption and content scanning through the inspection engine, increasing CPU/WAD workload.

KOREADUMPS.COM

QUESTION NO: 77
A network administrator enabled antivirus and selected an SSL inspection profile on a firewall policy. When downloading an EICAR test file through HTTP, FortiGate detects the virus and blocks the file. When downloading the same file through HTTPS, FortiGate does not detect the virus and does not block the file, allowing it to be downloaded. The administrator confirms that the traffic matches the configured firewall policy. What are two reasons for the failed virus detection by FortiGate? (Choose two answers)
A. The selected SSL inspection profile has certificate inspection enabled.
B. The website is exempted from SSL inspection.
C. The EICAR test file exceeds the protocol options oversize limit.
D. The browser does not trust the FortiGate self-signed CA certificate.
Answer: A,B
Explanation:
"The only security features you can apply using SSL certificate inspection mode are web filtering and application control... certificate inspection does not allow FortiGate to inspect the

flow of encrypted data."
"For antivirus or IPS control, you should use a deep-inspection profile."
"Within the full SSL inspection profile, you can also specify which SSL sites, if any, you want to exempt from SSL inspection." Technical Deep Dive:
The correct answers are A and B.
A is correct because if the firewall policy uses certificate inspection, FortiGate can inspect certificate/SNI metadata only. It cannot decrypt the HTTPS payload, so the antivirus engine never sees the EICAR file contents. That means HTTPS malware scanning fails even though HTTP scanning works.
B is also correct because if the destination site is exempt from SSL inspection, FortiGate intentionally skips decryption for that HTTPS session. Again, no payload decryption means no antivirus content scan.
Why the others are wrong:
C is not the likely reason here, especially for EICAR, which is a very small test file.
D would usually cause browser certificate warnings or connection issues during deep inspection, not a clean download that bypasses AV inspection.
Operationally, HTTPS antivirus requires this chain to be true:
firewall policy match → SSL deep inspection active → site not exempted → AV profile applied.
If either certificate-inspection is used or the site is exempted, FortiGate cannot inspect the encrypted file body.

KOREADUMPS.COM

QUESTION NO: 78
You are onboarding an agentless, secure web gateway (SWG) endpoint for secure internet access (SIA). What will happen to the user's nonweb traffic? (Choose one answer)
A. All the nonweb traffic will bypass FortiSASE.
B. The endpoint will use split tunneling to redirect nonweb traffic to FortiSASE.
C. FortiSASE will use Firewall-as-a-Service (FWaaS) to redirect nonweb traffic.
D. FortiSASE will use SWG to redirect nonweb traffic to FortiExtender.
Answer: A
Explanation:
"In this use case, FortiSASE acts as an SWG and distributes a proxy auto-configuration (PAC) file to end users, enabling the FortiSASE SWG service as an explicit web proxy. SWG deployment secures only web traffic protocols, such as HTTP and HTTPS."
"All other nonweb traffic bypasses FortiSASE and is forwarded directly to the internet."
Technical Deep Dive:
The correct answer is A.
In agentless SWG-based SIA, FortiSASE is operating as an explicit web proxy using a PAC file. That model captures only web protocols, specifically HTTP and HTTPS. It does not create a full tunnel for the endpoint like agent-based FortiClient deployment does.
So the design implication is simple: nonweb traffic does not traverse FortiSASE in this onboarding model. It goes directly to the internet from the endpoint.
Why the other options are wrong:
B is wrong because this is not split-tunnel VPN behavior.
C is wrong because FWaaS does not automatically capture nonweb traffic in the agentless SWG model.

D is wrong because SWG does not redirect nonweb traffic to FortiExtender.
This is an important deployment distinction:
Agent-based SIA can steer broader endpoint traffic through FortiSASE.
Agentless SWG SIA secures only browser-based web traffic.

QUESTION NO: 79
Refer to the exhibit.



An administrator has created a new firewall address to use as the destination for a static route. Why is the administrator not able to select the new address in the Destination field of the new static route? (Choose one answer)

A. In the new static route, the administrator must select Named Address.

B. In the new firewall address, the FQDN address must first be resolved.

C. In the new static route, the administrator must first set the interface to port2.

D. In the new firewall address, Routing configuration must be enabled.

Answer: D

Explanation:
"If you create a firewall address object with the type Subnet or FQDN, you can use that firewall address as the destination of one or more static routes. First, enable Routing configuration in the firewall address configuration. After you enable it, the firewall address object becomes available for use in the Destination drop-down list for static routes with named addresses." Technical Deep Dive:
The correct answer is D. The exhibit shows an FQDN address object (www.fortinet.com), but Routing configuration is disabled. FortiGate does not make that object available as a selectable destination for named static routes until this option is enabled.
Why the others are wrong:
A is incomplete. Even if the static route uses Named Address, the object still will not appear unless Routing configuration is enabled on the address object.
B is not the first requirement from the study guide. DNS resolution matters operationally for FQDN objects, but the documented reason it does not appear in the drop-down is the missing Routing configuration setting.
C is unrelated. The interface does not have to be set to port2 first just to make the address

KORFADUMPS.COM

object selectable.
In practice, the fix is:
```
config firewall address
edit "Fortinet"
set type fqdn
set fqdn "www.fortinet.com"
set allow-routing enable
next
end
```
After that, the object becomes available in the static route Destination field when using a named address.

QUESTION NO: 80
Refer to the exhibits.

KOREADUMPS.COM

Application sensor

Edit Application Sensor

Categories

Mixed - All Categories

- Business (157, 6)
- Collaboration (266, 13)
- Game (83)
- Mobile (3)
- Operational Technology
- Proxy (189)
- Social Media (113, 29)
- Update (48)
- VoIP (23)
- Unknown Applications
- Cloud/IT (72, 12)
- Email (76, 11)
- General Interest (254, 15)
- Network Service (338)
- P2P (55)
- Remote Access (96)
- Storage/Backup (150, 20)
- Video/Audio (148, 17)
- Web Client (24)

Network Protocol Enforcement

Application and Filter Overrides

+ Create New | Edit | Delete

Priority	Details	Type	Action
1	BHVR Excessive-Bandwidth	Filter	Block
2	VEND Google	Filter	Monitor

KOREADUMPS.COM

Firewall policy



You have implemented the application sensor and the corresponding firewall policy as shown in the exhibits.
You cannot access any of the Google applications, but you are able to access www.fortinet.com.
Which two actions would you take to resolve the issue? (Choose two.)

A. Set SSL inspection to deep-content inspection.

B. Move up Google in the Application and Filter Overrides section to set its priority lot

C. Add "Google".com to the URL category in the security profile.

D. Change the Inspection mode to Flow-based

E. Set the action for Google in the Application and Filter Overrides section to Allow

Answer: B,E

Explanation:

From the exhibits:

The firewall policy has Application Control enabled and uses certificate-inspection for SSL inspection.

The application sensor has Application and Filter Overrides with the following order (priority):

Excessive-Bandwidth with action Block

Google (vendor filter) with action Monitor

In FortiOS, Application and Filter Overrides are evaluated by priority (top-down). The first matching override is applied. If traffic matches an earlier override with Block, it will be blocked even if a later override would Monitor/Allow it.

Why Google apps fail while www.fortinet.com works:

Many Google applications can be detected as (or can trigger) the Excessive-Bandwidth behavior/signature depending on the specific service and traffic pattern.

Because Excessive-Bandwidth (Block) is above Google (Monitor), Google-related traffic may match the first rule and be blocked before the Google override is evaluated.

Access to www.fortinet.com works because that traffic is not matching the Excessive-Bandwidth override.

Therefore, to resolve:

B . Move up Google in the Application and Filter Overrides section to set its priority higher This ensures Google matches the Google override before any broader blocking override is applied.

E . Set the action for Google in the Application and Filter Overrides section to Allow This explicitly permits Google applications once the higher-priority match occurs (stronger than Monitor for troubleshooting and ensuring access).

Why the other options are not the best fit here:

A (deep-content inspection) can help identify more HTTPS applications, but the exhibit already shows a specific Google override configured; the immediate issue is the override evaluation order and action.

C relates to Web Filter URL categories, but the problem is occurring under Application Control behavior/vendor overrides.

D (flow-based) is not required to fix an override priority/action conflict.

KOFEADUMPS.COM

QUESTION NO: 81

An administrator configures FortiGuard servers as DNS servers on FortiGate using default settings.

What is true about the DNS connection to a FortiGuard server?

A. It uses UDP 53.

B. It uses DNS over HTTPS.

C. It uses DNS over TLS.

D. It uses UDP 8888.

Answer: C

Explanation:

"When using FortiGuard servers for DNS, FortiOS uses DNS over TLS (DoT) by default to

secure the DNS traffic. New FortiGuard DNS servers have been added as primary and secondary servers." Technical Deep Dive:
The correct answer is C. It uses DNS over TLS.
This is a direct default-behavior question. If you configure FortiGuard servers as DNS servers and do not change anything else, FortiGate uses DoT rather than plain DNS. That means the DNS session is encrypted, which protects DNS queries from simple interception or tampering on the path.
Why the other options are wrong:
A is standard clear-text DNS behavior, not the FortiGuard DNS default stated in the guide.
B is incorrect because the guide specifically says DNS over TLS, not DNS over HTTPS.
D is incorrect; the guide does not describe UDP 8888 as the default transport for this DNS use case.
Operationally, this matters because FortiGate relies on DNS not only for client-facing services, but also for resolving objects and securely reaching cloud-based services. Using DoT improves confidentiality for those DNS lookups.

QUESTION NO: 82
Refer to the exhibit.

An intrusion prevention system (IPS) profile signature setting is shown.
What can you conclude about the signature when adding the FTP.Login.Failed signature to the IPS Sensor profile?

A. The signature setting uses a custom rating threshold.

B. FortiGate allows this low severity signature packet and creates a log.

C. FortiGate stores a local copy of the packet that matches the signature.

D. The signature setting includes a group of other signatures.

Answer: C
Explanation:
"When you create a new entry to add signatures or filters, you can select the action by clicking Action."
"When you enable Packet logging, FortiGate stores a local copy of the packet that matches the signature. This enhances the view of erroneous or suspicious packets."

KOREADUMPS.COM

"You can configure IP exemptions on individual signatures only."
Technical Deep Dive:
The correct answer is C.
The exhibit shows an IPS entry being added with:
Type = Signature
Action = Block
Packet logging = Enable
Rate-based settings = Default
The most certain conclusion from that configuration is that packet logging is enabled, and the study guide explicitly states that this causes FortiGate to store a local copy of the matching packet.
Why the others are wrong:
A is wrong because the exhibit shows Rate-based settings = Default, not a custom threshold.
B is wrong because the configured action is Block, not allow/monitor.
D is wrong because the entry type is Signature, meaning an individual signature is being added, not a signature group.
A useful operational note: packet logging is powerful for IPS investigation and false-positive analysis, but it consumes more storage and processing resources. It should be enabled selectively on signatures where deeper forensic visibility is needed.

FOREADUMPS.COM

QUESTION NO: 83
You have configured an application control profile, set peer-o-peer traffic to Block under the Categories tab, and applied it to the firewall policy. However, you peer-to-peer traffic on known ports is passing through the FortiGate without being blocked. What FortiGate settings should you check to resolve this issue?
A. Replacement Messages for UDP-based Applications
B. Network Protocol Enforcement
C. Application and Filter Overrides
D. FortiGuard category ratings
Answer: C
Explanation:
"After the IPS engine examines the traffic stream for a signature match, FortiGate scans packets for matches, in this order, for the application control profile:
1. Application and filter overrides..."
"Because application overrides are applied first in the scan, these two applications are allowed and generate logs."
"The priority in which application and filter overrides are placed takes precedence." Technical Deep Dive:
The correct answer is C. Application and Filter Overrides.
If you already set the P2P category to Block, but some peer-to-peer traffic is still being allowed, the first thing to check is whether there is an application override or filter override that matches that traffic before the category action is applied. FortiGate processes Application and Filter Overrides before Categories, so any matching override set to Allow or Monitor will effectively bypass the category block.
Why the others are wrong:

A only affects user-facing block-page behavior for HTTP/HTTPS applications, not whether P2P is blocked.
B is for enforcing expected services on expected ports and for blocking applications on non-default ports. It is not the first place to look when a category block is being bypassed.
D concerns web categorization, not application-control category enforcement.
Operationally, this is a classic troubleshooting sequence: first inspect the override table, then the category action, then logs under Application Control to see which signature and action actually matched.

QUESTION NO: 84
Refer to the exhibit.



FortiGate has two separate firewall policies for Sales and Engineering to access the same web server with the same security profiles.
Which action must the administrator perform to consolidate the two policies into one?
A. Select port1 and port2 subnets in a single firewall policy.
B. Create an Aggregate interface that includes port1 and port2 to create a single firewall policy.
C. Replace port1 and port2 with the any interface in a single firewall policy.
D. Enable Multiple Interface Policies to select port1 and port2 in the same firewall policy.
Answer: D
Explanation:
"By default, you can select only a single interface as the incoming interface and a single interface as the outgoing interface. This is because the option to select multiple interfaces, or any interface in a firewall policy, is disabled on the GUI. However, you can enable the Multiple Interface Policies option on the Feature Visibility page to disable the single interface restriction."
"You can also specify multiple interfaces, or use the any option, if you configure a firewall policy on the CLI, regardless of the default GUI setting." Technical Deep Dive:

The correct answer is D.
The policies are identical except for the incoming interface: one is for Sales and one is for Engineering. FortiGate GUI policy creation normally restricts you to one incoming interface per policy. To consolidate both into a single GUI policy, the administrator must enable Multiple Interface Policies so both port1 and port2 can be selected in the same rule.
Why the others are wrong:
A is not enough, because policy matching also includes the incoming interface, not just the source subnets.
B changes the network design and is unnecessary.
C would work too broadly by matching traffic from any interface, which is not the intended controlled consolidation.
A matching CLI-style concept would be:
config firewall policy
edit <id>
set srcintf "port1" "port2"
set dstintf "<server-interface>"
set srcaddr "Sales_Subnet" "Engineering_Subnet"
set dstaddr "<web-server>"
set service "HTTP" "HTTPS"
set action accept
next
end
That preserves a single policy while still being specific about which interfaces are allowed.

QUESTION NO: 85
Refer to the exhibits.

System Performance output

```
# get system performance status
CPU states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU0 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
CPU1 states: 0% user 0% system 0% nice 100% idle 0% iowait 0% irq 0% softirq
Memory: 2042076k total, 1837868k used (90%), 104146k free (5.1%), 100062k freeable (4.9%)
Average network usage: 19/2 kbps in 1 minute, 19/4 kbps in 10 minutes, 19/3 kbps in 30 minutes
Maximal network usage: 36/18 kbps in 1 minute, 58/86 kbps in 10 minutes, 58/87  kbps in 30 minutes
Average sessions: 21 sessions in 1 minute, 22 sessions  in 10 minutes, 21 sessions in 30 minutes
Maximal sessions: 22 sessions in 1 minute, 28 sessions  in 10 minutes, 28 sessions in 30 minutes
Average session setup rate: 0 sessions per second in last 1 minute, 0 sessions per second in last 10 minutes
Maximal session setup rate: 0 sessions per second in last 1 minute, 1 sessions per second in last 10 minutes
Average NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Maximal NPU sessions: 0 sessions in last 1 minute, 0 sessions in last 10 minutes, 0 sessions in last 30 minutes
Virus caught: 0 total in 1 minute
IPS attacks blocked: 0 total in 1 minute
Uptime: 10 days, 22 hours, 50 minutes
```

Memory usage threshold settings

```
config system global
    set memory-use-threshold-extreme 89
    set memory-use-threshold-green 82
    set memory-use-threshold-red 88
end
```

The exhibits show the system performance output and default configuration of high memory usage thresholds on a FortiGate device.
Based on the system performance output, what are the two possible outcomes? (Choose two.)

DUMPS.COM

A. FortiGate drops new sessions.
B. Administrators can access FortiGate only through the console port.
C. Administrators can change the configuration.
D. FortiGate has entered conserve mode.
Answer: A,D
Explanation:
"Three different configurable thresholds define when FortiGate enters and exits conserve mode. If memory usage goes above the percentage of total RAM defined as the red threshold, FortiGate enters conserve mode."
"If memory usage keeps increasing, it might exceed the extreme threshold. While memory usage is above this highest threshold, all new sessions are dropped."
"What actions does FortiGate take to preserve memory while in conserve mode?
* FortiGate does not accept configuration changes, because they might increase memory usage."
"However, if the memory usage exceeds the extreme threshold, new sessions are always dropped, regardless of the FortiGate configuration." Technical Deep Dive:
The system performance output shows Memory: 2042076k total, 1837868k used (90%). The configured thresholds shown are:
green = 82
red = 88
extreme = 89
Because memory usage is 90%, it is:
Above the red threshold (88%) → so FortiGate has entered conserve mode
Above the extreme threshold (89%) → so all new sessions are dropped
That makes A and D correct.
Why the others are wrong:
B is not stated anywhere in the study guide as an automatic outcome of conserve mode.
C is the opposite of what the guide says. In conserve mode, FortiGate does not accept configuration changes.
A useful verification command is:
diagnose hardware sysinfo conserve
Operationally, once a FortiGate crosses the red threshold, it starts protecting itself by limiting behavior that could increase memory usage. Once it crosses the extreme threshold, it becomes more severe and drops new sessions to keep the system from becoming unstable.

KODEADUMPS.COM

QUESTION NO: 86
Refer to the exhibit.

```
date=2025-02-4 time=09:07:59 logid=0100022700 type=event subtype=system level=critical
 vd="root" logdesc="IPS session scan paused" action="drop" msg="IPS session scan, enter fail open mode"
```

What can you conclude from the log shown in the exhibit?
A. The IPS socket buffer is full and IPS engine needs more memory to create new sessions.
B. The IPS socket buffer is full and IPS engine cannot decode a packet.
C. The IPS scan is paused by the IPS diagnostic command with bypass mode option 5.
D. The IPS session scan is paused and reevaluating the packet because of a dirty flag.

Answer: A
Explanation:
"You can configure the fail-open setting under config ips global to control how the IPS engine behaves when the IPS socket buffer is full."
"If the IPS engine does not have enough memory to build more sessions, the fail-open setting determines whether the FortiGate should drop the sessions or bypass the sessions without inspection."
"It is important to understand that the IPS fail-open setting is not just for conserve mode-it kicks in whenever IPS fails. Most failures are due to a high CPU issue or a high memory (conserve mode) issue." Technical Deep Dive:
The correct answer is A.
The log text says:
logdesc="IPS session scan paused"
action="drop"
msg="IPS session scan, enter fail open mode"
That combination indicates an IPS failure condition, specifically the condition described in the guide where the IPS socket buffer is full and the IPS engine lacks enough memory/resources to build additional sessions. In that state, FortiGate applies the configured IPS fail-open behavior. Since the log shows action="drop", the device is not bypassing those new sessions; it is dropping them.
Why the other choices are wrong:
B is wrong because the guide ties fail-open to socket buffer/resource exhaustion, not packet decode failure.
C is wrong because this is not evidence of a manual diagnostic pause.
D is wrong because the study guide does not associate this log with dirty-flag packet reevaluation.
Operationally, this usually points to high memory, high CPU, or conserve-mode pressure affecting the IPS engine. Useful checks are:
get system performance status
diagnose hardware sysinfo conserve
diagnose sys top
Those help confirm whether the IPS issue is being driven by memory pressure or CPU exhaustion.

QUESTION NO: 87
Refer to the exhibit.

KOREADUMPS.COM

Refer to the exhibit.

Packet trace output

Time	Message
Packet Trace #1 14	
06:39:29	vd-root:0 received a packet(proto=1, 10.0.11.50:3->100.65.0.254:2048) tun_id=0.0.0.0 from port4. type=8, code=0, id=3, seq=168.
06:39:29	allocate a new session-00000ec6
06:39:29	in-[port4], out-[]
06:39:29	len=0
06:39:29	result: skb_flags-02000000, vid-0, ret-no-match, act-accept, flag-00000000
06:39:29	find a route: flag=00000000 gw-0.0.0.0 via port2
06:39:29	in-[port4], out-[port2], skb_flags-02000000, vid-0, app_id: 0, url_cat_id: 0
06:39:29	gnum-100004, use addr/intf hash, len=1
06:39:29	checked gnum-100004 policy-0, ret-matched, act-accept
06:39:29	ret-matched
06:39:29	policy-0 is matched, act-drop
06:39:29	after iprope_captive_check(): is_captive-0, ret-matched, act-drop, idx-0
06:39:29	after iprope_captive_check(): is_captive-0, ret-matched, act-drop, idx-0
06:39:29	Denied by forward policy check (policy 0)

KOREADUMPS.COM

Why did the FortiGate device drop the packet?

A. It matched the default implicit firewall policy.

B. It failed the RPF check.

C. It matched an explicitly configured firewall policy with the action DENY.

D. It cannot reach the next-hop IP.

Answer: A

Explanation:

"FortiGate looks for the matching firewall policy from top-to-bottom and, if a match is found, the traffic is processed based on the firewall policy. If no match is found, the traffic is dropped by the default implicit deny firewall policy." Technical Deep Dive:

The debug flow output clearly points to the implicit deny:

ret-no-match

policy-0 is matched, act-drop

Denied by forward policy check (policy 0)

On FortiGate, policy 0 is the internal representation of the default implicit deny firewall policy.

That means the packet did not match any user-defined forward firewall policy, so FortiGate dropped it automatically.
Why the other options are wrong:
B is wrong because an RPF failure would show a reverse-path-related drop reason, not Denied by forward policy check (policy 0).
C is wrong because the trace does not show a matched explicit policy ID with deny action; it shows policy 0, which is the implicit rule.
D is wrong because the trace actually shows a route lookup result: find a route: ... gw-0.0.0.0 via port2. So this is not a next-hop reachability failure.
In packet-flow troubleshooting, this pattern is one of the most important to recognize. If you see policy 0 in FortiGate debug flow, the first things to verify are:
diagnose debug flow filter addr <src_or_dst_ip>
diagnose debug flow show function-name enable
diagnose debug enable
Then review whether a firewall policy exists with the correct incoming interface, outgoing interface, source, destination, schedule, and service. If any one of those does not match, FortiGate falls through to policy 0 and drops the session.

QUESTION NO: 88
An administrator has configured the following settings.
```
config system settings
set ses-denied-traffic enable
end
config system global
set block-session-timer 30
end
```
What are the two results of this configuration? (Choose two.)
A. The number of logs generated by denied traffic is reduced.
B. A session for denied traffic is created.
C. Denied users are blocked for 30 minutes.
D. Session helpers are disabled for denied traffic.
Answer: A,B
Explanation:
"To reduce the number of log messages generated and improve performance, you can enable a session table entry of dropped traffic. This creates the denied session in the session table and, if the session is denied, all packets for that session are also denied. This ensures that FortiGate does not have to perform a policy lookup for each new packet matching the denied session, which reduces CPU usage and log generation."
"The CLI command is ses-denied-traffic. You can also set the duration for block sessions. This determines how long a session will be kept in the session table by setting block-session-timer in the CLI. By default, it is set to 30 seconds." Technical Deep Dive:
The correct answers are A and B.
When set ses-denied-traffic enable is configured, FortiGate creates a session-table entry for denied traffic. That means once traffic is denied, subsequent packets that belong to the same denied flow do not need a full policy lookup again. FortiGate can drop them immediately

KOREADUMPS.COM

based on the existing denied-session entry. That directly confirms B.
Because FortiGate no longer re-evaluates every repeated denied packet in the same way, the device generates fewer logs and uses less CPU for repeated denied traffic. That is exactly why A is also correct.
Why the other two are wrong:
C is incorrect because block-session-timer 30 means 30 seconds, not 30 minutes. The denied session entry is kept in the session table for that duration.
D is incorrect because these settings do not disable session helpers. They only control how denied traffic is tracked in the session table.
In operational terms, this feature is useful when a host repeatedly retries traffic that FortiGate is already denying. Instead of doing a fresh lookup for every retry, FortiGate caches the denied decision temporarily and drops the repeated packets faster.

QUESTION NO: 89
Refer to the exhibit.

```
config system global
    set av-failopen one-shot
end
config ips global
    set fail-open enable
end
```

K.READUMPS.COM

Based on this partial configuration, what are the two possible outcomes when FortiGate enters conserve mode? (Choose two.)
A. FortiGate drops new sessions requiring inspection.
B. Administrators must restart FortiGate to allow new sessions.
C. Administrators cannot change the configuration.
D. FortiGate skips quarantine actions.
Answer: C,D