



TXOne Edge Series Event Log Formats and Definitions

Version 2.1
December 18, 2024

Copyright © 2023 TXOne Networks Incorporated. All rights reserved. No part of this publication may be reproduced, photocopied, stored in a retrieval system, or transmitted without the express prior written consent of TXOne Networks Incorporated.

TXOne Networks Incorporated reserves the right to make changes to this document and to the product described herein without notice. Before installing and using the product, review the readme files, release notes, and/or the latest version of the applicable documentation, which are available at <https://download-center.cs.txone.com/>.

TXOne Networks is a registered trademark of TXOne Networks Incorporated. All other product names may be trademarks or registered trademarks of their owners.

In order to protect the value of TXOne Networks' logos and marks, it is very important that they be used appropriately and only by TXOne Networks and Partners with a current and valid partnership agreement.

The following marks are owned exclusively by TXOne Networks and may be registered in the U.S. or other countries. TXOne Networks reserves the right in its sole discretion to add additional marks to or remove marks from this list at any time and the failure of a TXOne trademark or logo to appear on this list shall not be construed as a waiver of any of TXOne Networks' rights in such trademark or logo.

- EdgeIPS
- EdgeIPS Pro
- EdgeIPS LE
- EdgeFire
- EdgeOne
- OT Defense Console

Trademark ownership is attributed in two ways, with the use of a trademark symbol (such as [™] or ®) after the trademark, and with a trademark legend, usually found at the end of a document in legible text following the copyright notice. Whenever you use one of TXOne trademarks, you must also include a proper trademark attribution statement somewhere on the same document or webpage, such as the following: "The TXOne Networks® and EdgeIPS[™] trademarks are owned by TXOne Networks, Inc. and is used with permission." Remember, mere inclusion of a trademark symbol and legend does not entitle you to use a TXOne trademark.

Table of Contents

1	Introduction	5
2	CEF Log Fields	6
2.1	Cyber Security Event Logs	6
2.1.1	Headers	6
2.1.2	Event Attributes.....	7
2.1.3	Examples	9
2.2	Protocol Filter Event Logs	11
2.2.1	Headers	11
2.2.2	Event Attributes.....	11
2.2.3	Examples	13
2.3	Policy Enforcement Event Logs	15
2.3.1	Headers	15
2.3.2	Event Attributes.....	16
2.3.3	Examples	18
2.4	Asset Event Logs.....	19
2.4.1	Headers	19
2.4.2	Event Attributes.....	19
2.4.3	Examples	20
2.5	System Event Logs.....	21
2.5.1	Headers	21
2.5.2	Event Attributes.....	21
2.5.3	Examples	22
2.6	Audit Event Logs	23
2.6.1	Headers	23
2.6.2	Event Attributes.....	24
2.6.3	Examples	24
2.7	File Filter Event Logs.....	25
2.7.1	Headers	25
2.7.2	Event Attributes.....	26
2.7.3	Examples	28
2.8	Suspicious Object Event Logs.....	29
2.8.1	Headers	29
2.8.2	Event Attributes.....	30
2.8.3	Examples	32
2.9	VPN Event Logs	33
2.9.1	Headers	33
2.9.2	Event Attributes.....	33
2.9.3	Examples	34
2.10	Domain Name Filter Event Logs	34
2.10.1	Headers	34
2.10.2	Event Attributes.....	35
2.10.3	Examples	36
2.11	CPSPDR Event Logs	37
2.11.1	Headers	37
2.11.2	Event Attributes.....	37
2.11.3	Examples	39
3	LEEF Log Fields	40
3.1	Cyber Security Event Logs	40
3.1.1	Headers	40
3.1.2	Event Attributes.....	41
3.1.3	Examples	43
3.2	Protocol Filter Event Logs	45
3.2.1	Headers	45
3.2.2	Event Attributes.....	45
3.2.3	Examples	47
3.3	Policy Enforcement Event Logs	48
3.3.1	Headers	48
3.3.2	Event Attributes.....	49
3.3.3	Examples	50
3.4	Asset Event Logs.....	52

3.4.1	Headers	52
3.4.2	Event Attributes.....	52
3.4.3	Examples	53
3.5	System Event Logs.....	54
3.5.1	Headers	54
3.5.2	Event Attributes.....	54
3.5.3	Examples	55
3.6	Audit Event Logs	56
3.6.1	Headers	56
3.6.2	Event Attributes.....	57
3.6.3	Examples	57
3.7	File Filter Event Logs.....	58
3.7.1	Headers	58
3.7.2	Event Attributes.....	59
3.7.3	Examples	60
3.8	Suspicious Object Event Logs.....	62
3.8.1	Headers	62
3.8.2	Event Attributes.....	62
3.8.3	Examples	64
3.9	VPN Event Logs	65
3.9.1	Headers	65
3.9.2	Event Attributes.....	65
3.9.3	Examples	66
3.10	Domain Name Filter Event Logs	67
3.10.1	Headers	67
3.10.2	Event Attributes.....	67
3.10.3	Examples	68
3.11	CPSDR Event Logs	69
3.11.1	Headers	69
3.11.2	Event Attributes.....	69
3.11.3	Examples	71
4	Appendix A: System Event IDs and Messages	72
5	Appendix B: Audit Event IDs and Messages.....	77

1 Introduction

We have defined 10 different types of event logs for the TXOne Edge series v2.1 event logs as follows:

No.	Log Type	Description
1	Cyber Security Event Log	Issued when a cyber security event, such as IPS event or DoS event, is detected.
2	Protocol Filter Event Log	Issued when the traffic flow matches a user-defined protocol filter.
3	Policy Enforcement Event Log	Issued when the traffic flow violates a user-defined Policy Enforcement rule.
4	Asset Event Log	Issued when a new asset is detected in the protected area or when an existing asset is lost (idle timeout).
5	System Event Log	Issued when a system event, such as NTP synchronization, DPI pattern update, firmware update, occurs.
6	Audit Event Log	Issued when a user changed the system configuration.
7	File Filter Event Log	Issued when a file transferred via the network matches a user-defined file filter.
8	Suspicious Object Event Log	Issued when a suspicious object is detected or blocked.
9	VPN Event Log	Issued when a new VPN connection is established or an existing VPN connection is terminated.
10	Domain Name Filter Event Log	Issued when a DNS query matches a user-defined domain name filter.
11	CPSDR Event Log	Issued when an abnormal or suspicious event is detected, indicating a potential threat in the CPS environment.

The format of these event logs can be either the Common Event Format (CEF) or the Log Event Extended Format (LEEF) based on administrator's configuration.

Chapter 2 *CEF Log Fields* provides detailed descriptions of log fields of each log event displayed in the CEF format. Chapter 3 *LEEF Log Fields* provides detailed descriptions of log fields in the LEEF format.

Appendices A and B list the pre-defined event IDs of the system and audit events as well as the corresponding messages.

2 CEF Log Fields

When event logs are in the CEF format, the CEF extension field “cat” can be used to distinguish the log types.

No.	Log Type	Value in “cat” Field
1	Cyber Security Event Log	0
2	Protocol Filter Event Log	1
3	Policy Enforcement Event Log	2
4	Asset Event Log	3
5	System Event Log	4
6	Audit Event Log	5
7	File Filter Event Log	6
8	Suspicious Object Event Log	7
9	VPN Event Log	8
10	Domain Name Filter Event Log	9
11	CPSDR Event Log	10

Please refer to the next sections for detailed descriptions of each log field.

2.1 Cyber Security Event Logs

2.1.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to “CEF:0”.
Device Vendor	<String>	Vendor name. Fixed to “TXOne”.
Device Product	<String>	Product name. Possible values are: • “EdgeOne” – EdgeOne Server • “IPS” – EdgeIPS • “IEF” – EdgeFire • “IPSP” – EdgeIPS Pro • “IPSLE” – EdgeIPS Lite
Device Version	<String>	Product version. For example, “2.0.1”.
Signature ID	<Integer>	The Signature ID related to the cyber security event.
Event Name	<String>	The Signature name related to the cyber security event.

Field Name	Value Type	Description
Severity	<Integer>	The severity of the cyber security event. Possible values are 2, 4, 6, 8, or 10. 2 → Information 4 → Low 6 → Medium 8 → High 10 → Critical

2.1.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 0 for the Cyber Security Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cn1Label	<String>	Label "etherType" – the key for "Ether Type"
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
spt	<Integer>	(Optional) The source port, ranging from 0 to 65535.
smac	<String>	(Optional) The source MAC address
dst	<String>	(Optional) The destination IP address
dpt	<Integer>	(Optional) The destination port, ranging from 0 to 65535.

Field Name	Value Type	Description
dmac	<String>	(Optional) The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
cs1Label	<String>	Label "sigCategory" – the key for “Signature Category”
cs1	<String>	The Signature Category of the cyber security event. Currently, 11 categories are defined: • File vulnerabilities • Buffer Overflow • DoS attacks • Exploits • Malware traffic • Reconnaissance • Web threats • ICS threats • Flooding & Scan • Protocol Attack Protection • IP Spoofing
cs2Label	<String>	(Optional) Label "attacker" – the key for “Attacker”
cs2	<String>	(Optional) The attacker of the cyber security event. It could be the source IP (or MAC) address or the destination IP (or MAC) address of the cyber security event.
cs3Label	<String>	(Optional) Label "direction" – the key for “Direction”
cs3	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN

Field Name	Value Type	Description
		- DMZ to VPN - VPN to DMZ - VPN to VPN - WAN to WAN - DMZ to DMZ - WAN to VPN
cs4Label	<String>	(Optional) Label "profileName" – the key for the "IPS Profile Name"
cs4	<String>	(Optional) The name of the IPS profile.
cs5Label	<String>	(Optional) Label "ruleName" – the key for the "Policy Enforcement Rule Name"
cs5	<String>	(Optional) The name of the Policy Enforcement rule in which this protocol filter is triggered. For example, "xyz" or "abc:xyz", where "abc" is the rule set name (if available), and "xyz" is the rule name.
cs6Label	<String>	(Optional) Label "mitreTechniqueId" – the key for the "MITRE Technique ID"
cs6	<String>	(Optional) The MITRE Technique IDs related to the event.
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".
moduleType	<String>	The type of the module that triggered the cyber security event. Possible values are: "Cyber Security" – for data port protection "System Security" – for self-protection

2.1.3 Examples

```
2020-01-06T17:10:19+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.3|1054837|WEB Remote File Inclusion
/etc/passwd|10|start=2020-01-06T09:25:28Z cat=0 dvchost=ips_2
deviceExternalId=TMG011900000003 cn1Label=etherType cn1=2048
cn2Label=vlanId cn2=87 proto=TCP deviceInboundInterface=PORT2
src=10.24.33.100 spt=45042 smac=00:0c:29:da:14:1c dst=213.211.198.62
dpt=80 dmac=64:00:6a:cd:04:a2 act=Deny cnt=1 cs1Label=sigCategory
cs1=Flooding & Scan cs2Label=attacker cs2=10.24.33.100
```

```
2020-01-06T17:13:54+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.3|1051723|VIRUS Eicar test string -
1|10|start=2020-01-06T09:13:51Z cat=0 dvchost=ips_1 deviceExternalId=
TMG011900000002 cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=PORT1 src=213.211.198.62 spt=80
smac=64:00:6a:cd:04:a2 dst=10.24.8.76 dpt=51697 dmac=00:0c:29:04:3c:42
act=Allow cnt=1 cs1Label=sigCategory cs1= Malware traffic
```

2020-11-13T03:09:16Z EdgeIPS-Pro

CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|1051680|RPC Linux statd
overflow|8|start=2020-11-13T03:09:16Z cat=0 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cn1Label=etherType cn1=2048
cn2Label=vlanId cn2=0 proto=UDP deviceInboundInterface=SLOT1:PORT16
src=151.225.137.144 spt=3045 smac=78:a2:19:c4:5c:3a dst=138.106.15.37
dpt=16079 dmac=52:2f:b1:5d:4c:48 act=Deny cnt=1 cs1Label=sigCategory
cs1=Buffer Overflow cs2Label=attacker cs2=151.225.137.144
cs4Label=profileName cs4=IPSPProfTestLog cs5Label=ruleName
cs5=RuleSet:ACLTestLog

2022-04-06T14:42:16+08:00 EdgeIPS-Pro

CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|1137431|FILE Microsoft PE file
transfer possible -1|6|start=2022-04-06T14:42:16+08:00 cat=0
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cn1Label=etherType
cn1=2048 proto=TCP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67
spt=445 smac=00:0c:29:c2:89:c1 dst=10.24.8.177 dpt=57809
dmac=00:0c:29:04:3c:42 act=Allow cnt=1 cs1Label=sigCategory cs1=File
vulnerabilities cs4Label=profileName cs4=Default_IPS_Profile
cs5Label=ruleName cs5=TEST_IPSP:Test_IPSP_PF_FF_AV
cs6Label=mitreTechniqueId cs6=T0843;T0857;T1105;T1059;T1059.001;

2022-04-06T14:42:16+08:00 EdgeIPS-Pro

CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|1137431|FILE Microsoft PE file
transfer possible -1|6|start=2022-04-06T14:42:16+08:00 cat=0
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cn1Label=etherType
cn1=2048 proto=TCP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67
spt=445 smac=00:0c:29:c2:89:c1 dst=10.24.8.177 dpt=57813
dmac=00:0c:29:04:3c:42 act=Allow cnt=1 cs1Label=sigCategory cs1=File
vulnerabilities cs4Label=profileName cs4=Default_IPS_Profile
cs5Label=ruleName cs5=TEST_IPSP:Test_IPSP_PF_FF_AV
cs6Label=mitreTechniqueId cs6=T0843;T0857;T1105;T1059;T1059.001;

2022-04-06T14:42:21+08:00 EdgeOne

CEF:0|TXOne|EdgeOne|1.5.7|1137431|FILE Microsoft PE file transfer
possible -1|6|start=2022-04-06T14:42:16+08:00 cat=0 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 cn1Label=etherType cn1=2048
proto=TCP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 spt=445
smac=00:0c:29:c2:89:c1 dst=10.24.8.177 dpt=57809
dmac=00:0c:29:04:3c:42 act=Allow cnt=1 cs1Label=sigCategory cs1=File
vulnerabilities cs4Label=profileName cs4=Default_IPS_Profile
cs5Label=ruleName cs5=TEST_IPSP:Test_IPSP_PF_FF_AV
cs6Label=mitreTechniqueId cs6=T0843;T0857;T1105;T1059;T1059.001;

2022-04-06T14:42:21+08:00 EdgeOne

CEF:0|TXOne|EdgeOne|1.5.7|1137431|FILE Microsoft PE file transfer
possible -1|6|start=2022-04-06T14:42:16+08:00 cat=0 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 cn1Label=etherType cn1=2048
proto=TCP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 spt=445
smac=00:0c:29:c2:89:c1 dst=10.24.8.177 dpt=57813
dmac=00:0c:29:04:3c:42 act=Allow cnt=1 cs1Label=sigCategory cs1=File
vulnerabilities cs4Label=profileName cs4=Default_IPS_Profile
cs5Label=ruleName cs5=TEST_IPSP:Test_IPSP_PF_FF_AV
cs6Label=mitreTechniqueId cs6=T0843;T0857;T1105;T1059;T1059.001;

```
2022-04-06T14:42:06+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|1051723|VIRUS Eicar test string -
1|10|start=2022-04-06T14:42:06+08:00 cat=0 dvchost=EdgeIPS-Pro
deviceExternalId=TMG022000000001 cnlLabel=etherType cnl=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 spt=445
smac=00:0c:29:c2:89:c1 dst=10.24.8.177 dpt=57807
dmac=00:0c:29:04:3c:42 act=Deny cnt=1 cs1Label=sigCategory cs1=Malware
traffic cs2Label=attacker cs2=10.24.8.67 cs4Label=profileName
cs4=Default_IPS_Profile cs5Label=ruleName
cs5=TEST_IPSP:Test_IPSP_PF_FF_AV cs6Label=mitreTechniqueId cs6=T1105;
```

2.2 Protocol Filter Event Logs

2.2.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Protocol Filter Event Logs.
Event Name	<String>	Fixed to "PF_EVENT" for the Protocol Filter Event Logs.
Severity	<Integer>	The severity of the protocol filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

2.2.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 1 for the Protocol Filter Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve

Field Name	Value Type	Description
		the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cs1Label	<String>	Label "filterName" – the key for the "Protocol Filter Name"
cs1	<String>	The name of the Protocol Filter.
cs2Label	<String>	Label "ruleName" – the key for the "Policy Enforcement Rule Name"
cs2	<String>	The name of the Policy Enforcement rule in which this protocol filter is triggered. For example, "xyz" or "abc:xyz", where "abc" is the rule set name (if available), and "xyz" is the rule name.
cn1Label	<String>	Label "etherType" – the key for "Ether Type"
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
spt	<Integer>	(Optional) The source port, ranging from 0 to 65535.
smac	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dpt	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dmac	<String>	The destination MAC address
cs3Label	<String>	Label "protoName" – the key for "Protocol Name"
cs3	<String>	The ICS/OT protocol name related to the event. For example, "Modbus", "FTP", "SMB", etc.
cn3Label	<String>	(Optional) Label "funcType" – the key "Function Type"
cn3	<Integer>	(Optional) The function type related to the event. Currently, four function types are defined: 1 - Read Only

Field Name	Value Type	Description
		2 - Read/Write 3 - Admin Config 4 - Others
cs4Label	<String>	(Optional) Label "extraInfo" – the key for "Extra Information"
cs4	<String>	(Optional) Extra information related to the event.
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
cs5Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs5	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".

2.2.3 Examples

```

2020-01-06T17:08:45+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|PF_EVENT|6|start=2020-01-06T09:23:57Z
cat=1 dvchost=ips_2 deviceExternalId=TMG01190000003 cn1Label=etherType
cn1=2048 cn2Label=vlanId cn2=87 proto=TCP deviceInboundInterface=PORT2
src=10.24.33.100 spt=57432 smac=00:0c:29:da:14:1c dst=10.24.34.100
dpt=502 dmac=00:0c:29:f5:08:f1 act=Deny cs1Label=filterName
cs1=ModbusProfessionalSetting-3 cs2Label=ruleName cs2=ModbusAdvanced-3
cs3Label=protoName cs3=Modbus cs4Label=extraInfo cs4=UnitID: 254,
FunctionCode: 0x7f, Address: 0 cn3Label=funcType cn3=4 cnt=1

```

2020-01-06T17:08:55+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|PF_EVENT|6|start=2020-01-06T09:24:08Z
cat=1 dvchost=ips_2 deviceExternalId=TMG011900000003 cn1Label=etherType
cn1=2048 cn2Label=vlanId cn2=87 proto=TCP deviceInboundInterface=PORT2
src=10.24.33.100 spt=36950 smac=00:0c:29:da:14:1c dst=10.24.34.100
dpt=502 dmac=00:0c:29:f5:08:f1 act=Deny cs1Label=filterName
cs1=ModbusCategories-1 cs2Label=ruleName cs2=ModbusCategories-1
cs3Label=protoName cs3=Modbus cn3Label=funcType cn3=2 cnt=1

2020-11-13T03:15:16Z EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|PF_EVENT|6| start=2020-11-
13T03:15:14Z cat=1 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=filterName cs1=PFProfTestLog cs2Label=ruleName
cs2=RuleSet:ACLTestLog cn1Label=etherType cn1=2048 cn2Label=vlanId
cn2=0 proto=TCP deviceInboundInterface=SLOT1:PORT21
src=140.225.223.216 spt=28309 smac=f3:bc:2e:5d:51:15
dst=136.119.140.33 dpt=21305 dmac=e9:7a:1f:35:7b:aa cs3Label=protoName
cs3=CIP cn3Label=funcType cn3=1 cs4Label=extraInfo cs4=ClassID:
0x9E05, ServiceCode: 0xF3 act=Deny cnt=1

2022-04-06T14:19:55+08:00 EdgeIPS-
Pro CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PF_EVENT|6|start=2022-04-
06T14:19:54+08:00 cat=1 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 cs1Label=filterName
cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=UDP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 spt=59328
smac=00:0c:29:04:3c:42 dst=8.8.8.8 dpt=53 dmac=64:00:6a:cd:00:a2
cs3Label=protoName cs3=DNS act=Deny cnt=1

2022-04-06T14:19:57+08:00 EdgeIPS-
Pro CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PF_EVENT|2|start=2022-04-
06T14:19:55+08:00 cat=1 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 cs1Label=filterName
cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 spt=57363
smac=00:0c:29:04:3c:42 dst=40.100.2.82 dpt=25 dmac=64:00:6a:cd:00:a2
cs3Label=protoName cs3=SMTP act=Allow cnt=1

2022-04-06T14:20:01+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PF_EVENT|6|start=2022-04-06T14:19:54+08:00
cat=1 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=UDP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 spt=59328
smac=00:0c:29:04:3c:42 dst=8.8.8.8 dpt=53 dmac=64:00:6a:cd:00:a2
act=Deny cs1Label=filterName cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=DNS cnt=1

2022-04-06T14:20:01+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PF_EVENT|2|start=2022-04-06T14:19:55+08:00
cat=1 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 spt=57363

```
smac=00:0c:29:04:3c:42 dst=40.100.2.82 dpt=25 dmac=64:00:6a:cd:00:a2
act=Allow cs1Label=filterName cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=SMTP cnt=1
```

```
2022-04-06T14:20:37+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PF_EVENT|2|start=2022-04-
06T14:20:36+08:00 cat=1 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=filterName
cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.177 spt=57364
smac=00:0c:29:04:3c:42 dst=10.24.8.67 dpt=445 dmac=00:0c:29:c2:89:c1
cs3Label=protoName cs3=SMB cs4Label=extraInfo cs4=SMB v2 act=Allow
cnt=1
```

```
2022-04-06T14:20:37+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PF_EVENT|2|start=2022-04-
06T14:20:36+08:00 cat=1 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=filterName
cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.177 spt=57364
smac=00:0c:29:04:3c:42 dst=10.24.8.67 dpt=445 dmac=00:0c:29:c2:89:c1
cs3Label=protoName cs3=SMB cn3Label=funcType cn3=1 cs4Label=extraInfo
cs4=SMB v2: read access act=Allow cnt=1
```

```
2022-04-06T14:20:41+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PF_EVENT|2|start=2022-04-06T14:20:36+08:00
cat=1 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.177 spt=57364
smac=00:0c:29:04:3c:42 dst=10.24.8.67 dpt=445 dmac=00:0c:29:c2:89:c1
act=Allow cs1Label=filterName cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=SMB
cs4Label=extraInfo cs4=SMB v2 cnt=1
```

```
2022-04-06T14:20:41+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PF_EVENT|2|start=2022-04-06T14:20:36+08:00
cat=1 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.177 spt=57364
smac=00:0c:29:04:3c:42 dst=10.24.8.67 dpt=445 dmac=00:0c:29:c2:89:c1
act=Allow cs1Label=filterName cs1=Enable_IT_protocol cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=SMB
cs4Label=extraInfo cs4=SMB v2: read access cn3Label=funcType cn3=1
cnt=1
```

2.3 Policy Enforcement Event Logs

2.3.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".

Field Name	Value Type	Description
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Policy Enforcement Event Logs.
Event Name	<String>	Fixed to "PE_EVENT" for the Policy Enforcement Event Logs.
Severity	<Integer>	The severity of the Policy Enforcement event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

2.3.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 2 for the Policy Enforcement Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cs1Label	<String>	Label "ruleName" – the key for the "Policy Enforcement Rule Name"
cs1	<String>	The name of the Policy Enforcement rule in which this protocol filter is triggered. For example, "xyz" or "abc:xyz", where "abc" is the rule set name (if available), and "xyz" is the rule name.
cn1Label	<String>	Label "etherType" – the key for "Ether Type"

Field Name	Value Type	Description
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
spt	<Integer>	(Optional) The source port, ranging from 0 to 65535.
smac	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dpt	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dmac	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cs2Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs2	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ

Field Name	Value Type	Description
		WAN to VPN
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".

2.3.3 Examples

```
2022-04-06T12:59:51+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PE_EVENT|2|start=2022-04-06T12:59:45+08:00
cat=2 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=ruleName cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType
cn1=2048 proto=UDP deviceInboundInterface=SL0T2:PORT2 src=10.24.2.66
spt=59957 smac=00:05:1b:c2:7e:4b dst=239.255.255.250 dpt=1900
dmac=01:00:5e:7f:ff:fa act=Allow
```

```
2022-04-06T12:59:51+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PE_EVENT|2|start=2022-04-06T12:59:46+08:00
cat=2 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=ruleName cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType
cn1=2048 proto=UDP deviceInboundInterface=SL0T2:PORT2 src=10.24.8.191
spt=138 smac=00:0c:29:25:1a:3e dst=10.24.255.255 dpt=138
dmac=ff:ff:ff:ff:ff:ff act=Allow
```

```
2022-04-06T12:59:51+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PE_EVENT|2|start=2022-04-
06T12:59:49+08:00 cat=2 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=ruleName
cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=UDP
deviceInboundInterface=SL0T2:PORT2 src=10.24.200.107 spt=138
smac=a4:bb:6d:d0:f5:d3 dst=10.24.255.255 dpt=138
dmac=ff:ff:ff:ff:ff:ff act=Allow
```

```
2022-04-06T12:59:51+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PE_EVENT|2|start=2022-04-
06T12:59:49+08:00 cat=2 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=ruleName
cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=UDP
deviceInboundInterface=SL0T2:PORT2 src=10.24.0.19 spt=138
smac=a4:bb:6d:d0:f5:d3 dst=10.24.255.255 dpt=138
dmac=ff:ff:ff:ff:ff:ff act=Allow
```

```
2022-04-06T13:00:31+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|PE_EVENT|2|start=2022-04-06T13:00:23+08:00
cat=2 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=ruleName cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType
cn1=2048 proto=IGMP deviceInboundInterface=SL0T2:PORT1 src=10.24.8.40
spt=0 smac=00:0c:29:6c:a1:1b dst=224.0.0.251 dpt=0
dmac=01:00:5e:00:00:fb act=Allow
```

```
2022-04-06T13:00:25+08:00 EdgeIPS-
Pro CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|PE_EVENT|2|start=2022-04-
06T13:00:23+08:00 cat=2 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=ruleName
```

```
cs1=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048
proto=IGMP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.40 spt=0
smac=00:0c:29:6c:a1:1b dst=224.0.0.251 dpt=0 dmac=01:00:5e:00:00:fb
act=Allow
```

2.4 Asset Event Logs

2.4.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Asset Event Logs.
Event Name	<String>	Fixed to "ASSET_EVENT" for the Asset Event Logs.
Severity	<Integer>	The severity of the asset event. Possible value is 2 (information).

2.4.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 3 for the Asset Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
eventId	<Long>	The asset event ID. Currently, four asset event IDs are defined: 0 - Unknown

Field Name	Value Type	Description
		1 - New asset detected 2 - Asset idle timeout 3 - Asset changed
cs1Label	<String>	Label "assetIpAddress" – the key for "asset IP address"
cs1	<String>	The asset IP address (IPv4 or IPv6).
cs2Label	<String>	Label "assetMacAddress" – the key for "asset MAC address"
cs2	<String>	The asset MAC address.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).

2.4.3 Examples

```
2020-01-06T17:44:27+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|ASSET_EVENT|2|start=2020-01-06T09:44:27Z
cat=3 dvchost=ips_1 deviceExternalId=TMG01190000002 eventId=3
cs1Label=assetIpAddress cs1=10.24.253.220 cs2Label=assetMacAddress
cs2=00:0c:29:a7:83:be deviceInboundInterface=PORT2
```

```
2020-01-06T17:44:27+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|ASSET_EVENT|2|start=2020-01-06T09:44:26Z
cat=3 dvchost=ips_1 deviceExternalId=TMG01190000002 eventId=1
cs1Label=assetIpAddress cs1=0.0.0.0 cs2Label=assetMacAddress
cs2=00:0c:29:a7:83:be deviceInboundInterface=PORT2
```

```
2020-11-13T05:45:24Z EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|ASSET_EVENT|2|start=2020-11-
13T05:45:24Z cat=3 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
eventId=1 cs1Label=assetIpAddress cs1=0.0.0.0 cs2Label=assetMacAddress
cs2=00:0c:29:2a:b3:e0 deviceInboundInterface=SLOT1:PORT2
```

```
2022-04-06T14:00:17+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|ASSET_EVENT|2|start=2022-04-
06T14:00:17+08:00 cat=3 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=2 cs1Label=assetIpAddress
cs1=122.117.253.246 cs2Label=assetMacAddress cs2=64:00:6a:cd:00:a2
deviceInboundInterface=SLOT2:PORT2
```

```
2022-04-06T14:00:17+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|ASSET_EVENT|2|start=2022-04-
06T14:00:17+08:00 cat=3 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=2 cs1Label=assetIpAddress
cs1=122.117.253.246 cs2Label=assetMacAddress cs2=64:00:6a:cd:00:a2
deviceInboundInterface=SLOT2:PORT2
```

```
2022-04-06T14:02:17+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|ASSET_EVENT|2|start=2022-04-
06T14:02:17+08:00 cat=3 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=2 cs1Label=assetIpAddress
cs1=220.132.100.157 cs2Label=assetMacAddress cs2=64:00:6a:cd:00:a2
deviceInboundInterface=SLOT2:PORT2
```

```
2022-04-06T14:02:17+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|ASSET_EVENT|2|start=2022-04-
06T14:02:17+08:00 cat=3 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=2 cs1Label=assetIpAddress
cs1=220.132.100.157 cs2Label=assetMacAddress cs2=64:00:6a:cd:00:a2
deviceInboundInterface=SLOT2:PORT2
```

2.5 System Event Logs

2.5.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the System Event Logs.
Event Name	<String>	Fixed to "SYSTEM_EVENT" for the System Event Logs.
Severity	<Integer>	The severity of the system event. Possible values are 2, 4, 6, or 7. 2 → Information 4 → Notice 6 → Warning 7 → Error

2.5.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".

Field Name	Value Type	Description
cat	<Integer>	Device event category. Fixed to 4 for the System Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
eventId	<Integer>	The system event ID. Please refer to Appendix A for the defined system event IDs and the corresponding messages.
msg	<String>	The message of the system event. Please refer to Appendix A for the defined system event IDs and the corresponding messages.

2.5.3 Examples

```
2019-12-30T11:26:23+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|SYSTEM_EVENT|4|start=2019-12-30T03:26:22Z
cat=4 dvchost=ips_1 deviceExternalId=TMG01190000002 eventId=26
msg=Pattern updated successfully via (EdgeOne)
```

```
2019-12-30T11:26:25+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|SYSTEM_EVENT|2|start=2019-12-30T03:26:22Z
cat=4 dvchost=EdgeOne deviceExternalId=01fd3cc2-25fa-11ea-800d-
000c293fb1c5 eventId=12547 msg=Sync (EdgeIPS) device group (R2D2)
settings to device (ips_1) successful
```

```
2019-12-30T11:27:42+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|SYSTEM_EVENT|4|start=2019-12-30T03:27:42Z
cat=4 dvchost=ips_1 deviceExternalId=TMG01190000002 eventId=5 msg=Sync
with NTP server (10.24.254.56) successful
```

```
2020-11-13T03:42:11Z EdgeIPS-Pro CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|
SYSTEM_EVENT|4|start=2020-11-13T03:42:11Z cat=4 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=5 msg=Sync with NTP server
(192.168.127.100) successful
```

```
2022-04-06T11:01:58+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|SYSTEM_EVENT|4|start=2022-04-
06T11:01:58+08:00 cat=4 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=40 msg=HA Peer un-synced
```

```
2022-04-06T11:01:58+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|SYSTEM_EVENT|4|start=2022-04-
06T11:01:58+08:00 cat=4 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=40 msg=HA Peer un-synced
```

```
2022-04-06T10:27:46+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|SYSTEM_EVENT|4|start=2022-04-
06T10:27:46+08:00 cat=4 dvchost=Wendy-EdgeFire-113
deviceExternalId=TMF0220NS25419 eventId=5 msg=Sync with NTP server
(10.24.19.141) successful
```

```
2022-04-06T10:27:46+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T10:27:46+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=Wendy-EdgeFire-113 deviceExternalId=TMF0220NS25419 cat=5
msg=Sync with NTP server (10.24.19.141) successful
```

```
2022-04-06T10:27:46+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T10:27:46+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=Wendy-EdgeFire-113 deviceExternalId=TMF0220NS25419 cat=28
msg=System time adjusted (34 ms)
```

```
2022-04-06T10:27:46+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|SYSTEM_EVENT|4|start=2022-04-
06T10:27:46+08:00 cat=4 dvchost=Wendy-EdgeFire-113
deviceExternalId=TMF0220NS25419 eventId=28 msg=System time adjusted
(34 ms)
```

2.6 Audit Event Logs

2.6.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Audit Event Logs.
Event Name	<String>	Fixed to "AUDIT_EVENT" for the Audit Event Logs.
Severity	<Integer>	The severity of the audit event. Possible values are 2, 4, 6, or 7. 2 → Information 4 → Notice

Field Name	Value Type	Description
		6 → Warning 7 → Error

2.6.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 5 for the Audit Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
eventId	<Long>	The audit event ID. Please refer to Appendix B for the defined audit event IDs and the corresponding messages.
suser	<String>	The username of the user who triggers the audit event.
cs1Label	<String>	Label "clientIpAddress" – the key for "client IP address"
cs1	<String>	The client IP address from which the user logs in and executes commands.
msg	<String>	The message of the audit event. Please refer to Appendix B for the defined audit event IDs and the corresponding messages.

2.6.3 Examples

```
2019-12-30T11:25:17+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|AUDIT_EVENT|4|start=2019-12-30T03:25:16Z
cat=5 dvchost=EdgeOne deviceExternalId=01fd3cc2-25fa-11ea-800d-
000c293fb1c5 eventId=8193 suser=jdoe cs1Label=clientIpAddress
cs1=10.24.8.8 msg=User (jdoe) login
```

```
2019-12-30T11:27:43+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|AUDIT_EVENT|4|start=2019-12-30T03:27:41Z
cat=5 dvchost=EdgeOne deviceExternalId=01fd3cc2-25fa-11ea-800d-
000c293fb1c5 eventId=8195 suser=jdoe cs1Label=clientIpAddress
cs1=10.24.8.8 msg=User (jdoe) logout
```

```

2020-01-06T17:08:50+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|AUDIT_EVENT|4|start=2020-01-06T09:24:07Z
cat=5 dvchost=ips_2 deviceExternalId=TMG01190000003 eventId=135
suser=WasiAdmin cs1Label=clientIpAddress cs1=10.24.253.108 msg=User
(WasiAdmin) deleted protocol filter profile (Schneider-1)

2020-01-06T17:08:50+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|0.9.2|0|AUDIT_EVENT|4|start=2020-01-06T09:24:07Z
cat=5 dvchost=ips_2 deviceExternalId=TMG01190000003 eventId=131
suser=WasiAdmin cs1Label=clientIpAddress cs1=10.24.253.108 msg=User
(WasiAdmin) added service object (ModbusService)

2020-11-13T03:47:00Z EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|AUDIT_EVENT|4|start=2020-11-
13T03:47:00Z cat=5 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
eventId=128 suser=admin1 cs1Label=clientIpAddress cs1=192.168.127.1
msg=User (admin1) added IP object (XServers)

2022-04-06T12:46:04+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|AUDIT_EVENT|4|start=2022-04-
06T12:46:04+08:00 cat=5 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=82 suser=Jimmy
cs1Label=clientIpAddress cs1=10.24.8.211 msg=User (Jimmy) changed
syslog settings

2022-04-06T13:31:46+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|AUDIT_EVENT|4|start=2022-04-
06T13:31:46+08:00 cat=5 dvchost=EdgeOne deviceExternalId=0d9bc16e-
a8bd-11ec-aa00-000c29e111dd eventId=8196 suser=Jimmy
cs1Label=clientIpAddress cs1=10.24.8.211 msg=User (Jimmy) timeout,
force logout

2022-04-06T14:24:13+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|AUDIT_EVENT|4|start=2022-04-
06T14:24:13+08:00 cat=5 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 eventId=82 suser=Jimmy
cs1Label=clientIpAddress cs1=10.24.8.211 msg=User (Jimmy) changed
syslog settings

```

2.7 File Filter Event Logs

2.7.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS

Field Name	Value Type	Description
		"IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the File Filter Event Logs.
Event Name	<String>	Fixed to "FF_EVENT" for the File Filter Event Logs.
Severity	<Integer>	The severity of the file filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

2.7.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 6 for the File Filter Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cs1Label	<String>	Label "filterName" – the key for the "File Filter Name"
cs1	<String>	The name of the file filter.
cs2Label	<String>	Label "ruleName" – the key for the "Policy Enforcement Rule Name"
cs2	<String>	The name of the Policy Enforcement rule in which this protocol filter is triggered. For example, "xyz" or "abc:xyz", where "abc" is the rule set name (if available), and "xyz" is the rule name.
cn1Label	<String>	Label "etherType" – the key for "Ether Type"
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"

Field Name	Value Type	Description
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	The source IP address
spt	<Integer>	The source port, ranging from 0 to 65535.
smac	<String>	The source MAC address
dst	<String>	The destination IP address
dpt	<Integer>	The destination port, ranging from 0 to 65535.
dmac	<String>	The destination MAC address
cs3Label	<String>	Label "protoName" – the key for "Protocol Name"
cs3	<String>	The ICS/OT protocol name related to the event. For example, "Modbus", "FTP", "SMB", etc.
cs4Label	<String>	(Optional) Label "extraInfo" – the key for "Extra Information"
cs4	<String>	(Optional) Extra information related to the event.
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cs5Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs5	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ

Field Name	Value Type	Description
		- VPN to VPN - WAN to WAN - DMZ to DMZ - WAN to VPN
cs6Label	<String>	(Optional) Label "profileType" – the key for "Profile Type"
cs6	<String>	(Optional) The profile type by which this event was detected. Possible values are: - File Filter - Antivirus
virusName	<String>	(Optional) The name of the virus detected in the event.

2.7.3 Examples

```
2020-11-13T06:53:39Z EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|FF_EVENT|6| start=2020-11-
13T06:53:37Z cat=6 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=filterName cs1=FileFilterTestLog cs2Label=ruleName
cs2=RuleSet:ACLTestLog cn1Label=etherType cn1=2048 cn2Label=vlanId
cn2=0 proto=ICMP deviceInboundInterface=MR src=221.43.119.153 spt=115
smac=67:66:c0:f0:49:2a dst=247.88.237.196 dpt=204
dmac=6a:3f:e9:97:3d:21 cs3Label=protoName cs3=Others
cs4Label=extraInfo cs4=File Type: Windows PE, Filename: Fakefile.exe
act=Deny
```

```
2020-11-13T06:53:43Z EdgeIPS
CEF:0|TXOne|IPSP|IPSP_T01_1.1.0|0|FF_EVENT|6| start=2020-11-
13T06:53:41Z cat=6 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cs1Label=filterName cs1=FileFilterTestLog cs2Label=ruleName
cs2=RuleSet:ACLTestLog cn1Label=etherType cn1=2048 cn2Label=vlanId
cn2=0 proto=ICMP deviceInboundInterface=SL0T2:PORT3 src=218.132.99.213
spt=184 smac=c4:22:45:5e:06:e4 dst=53.62.119.25 dpt=237
dmac=78:dd:69:b7:07:ef cs3Label=protoName cs3=Others
cs4Label=extraInfo cs4=GPO: Yes, Filename:
Machine\Preferences\Registry\Registry.xml act=Deny
```

```
2022-04-06T11:16:40+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|FF_EVENT|6|start=2022-04-
06T11:16:39+08:00 cat=6 dvchost=EdgeIPS-Pro
deviceExternalId=TMG022000000001 cs1Label=filterName cs1=Enable_FF_SMB
cs2Label=ruleName cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType
cn1=2048 proto=TCP deviceInboundInterface=SL0T2:PORT1 src=10.24.8.10
spt=50105 smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=445
dmac=00:0c:29:66:52:72 cs3Label=protoName cs3=SMB cs4Label=extraInfo
cs4=File Type: Windows PE, Filename: SecConfig.efi act=Deny
cs6Label=profileType cs6=File Filter
```

```
2022-04-06T11:16:50+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|FF_EVENT|6|start=2022-04-06T11:16:39+08:00
cat=6 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.10 spt=50103
smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=445 dmac=00:0c:29:66:52:72
act=Deny cs1Label=filterName cs1=Enable_FF_SMB cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=SMB
cs4Label=extraInfo cs4=File Type: Windows PE, Filename: SecConfig.efi
cs6Label=profileType cs6=File Filter
```

```
2022-04-06T11:16:38+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|FF_EVENT|6|start=2022-04-
06T11:16:37+08:00 cat=6 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cs1Label=filterName
cs1=Default_AV_Profile cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.10 spt=50095
smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=445 dmac=00:0c:29:66:52:72
cs3Label=protoName cs3=SMB cs4Label=extraInfo cs4=SHA1:
556a25208824efd585cb211ba1951a46da97127e, File Type: Linux ELF,
Filename: qemu-ppc64abi32-static act=Deny cs6Label=profileType
cs6=Antivirus virusName=TXONE_TEST_qemu-ppc64abi32-static
```

```
2022-04-06T11:16:40+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|FF_EVENT|6|start=2022-04-06T11:16:37+08:00
cat=6 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT1 src=10.24.8.10 spt=50092
smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=445 dmac=00:0c:29:66:52:72
act=Deny cs1Label=filterName cs1=Default_AV_Profile cs2Label=ruleName
cs2=TEST_IPSP:Test_IPSP_PF_FF_AV cs3Label=protoName cs3=SMB
cs4Label=extraInfo cs4=SHA1: 556a25208824efd585cb211ba1951a46da97127e,
File Type: Linux ELF, Filename: qemu-ppc64abi32-static
cs6Label=profileType cs6=Antivirus virusName=TXONE_TEST_qemu-
ppc64abi32-static
```

2.8 Suspicious Object Event Logs

2.8.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite

Field Name	Value Type	Description
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Suspicious Object Event Logs.
Event Name	<String>	Fixed to "SO_EVENT" for the Suspicious Object Event Logs.
Severity	<Integer>	The severity of the suspicious object event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

2.8.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 7 for the Suspicious Object Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cn1Label	<String>	Label "etherType" – the key for "Ether Type"
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
spt	<Integer>	(Optional) The source port, ranging from 0 to 65535.
smac	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address

Field Name	Value Type	Description
dpt	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dmac	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
cs1Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs1	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
cs2Label	<String>	Label "sold" – the key for "Suspicious Object ID"
cs2	<String>	A unique identifier of the suspicious object
cs3Label	<String>	Label "soSource" – the key for "Suspicious Object Source"
cs3	<String>	The original source where the suspicious object is defined
cs4Label	<String>	Label "soType" – the key for "Suspicious Object Type"
cs4	<String>	The type of the suspicious object. Possible values are: • Node • Link

Field Name	Value Type	Description
		File
cs5Label	<String>	(Optional) Label "soExpiration" – the key for "Suspicious Object Expiration"
cs5	<DateTime>	(Optional) The expiration of the suspicious object displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'" (ISO 8601 format).
cn3Label	<String>	Label "soRiskLevel" – the key for "Suspicious Object Risk Level"
cn3	<Integer>	The risk level of the suspicious object. Possible values are: 1 – Low 2 – Medium 3 – High

2.8.3 Examples

```
2021-02-25T02:33:12Z EdgeIPS CEF:0|TXOne
|IPS|IPS_G02_1.2.0|0|SO_EVENT|2| start=2021-02-25T02:33:11Z cat=7
dvchost=EdgeIPS deviceExternalId=TMG02200000001 cn1Label=etherType
cn1=2048 proto=TCP deviceInboundInterface=PORT1 src=10.7.19.57
spt=54430 smac=24:f5:a2:8d:12:9d dst=10.7.19.55 dpt=443
dmac=ea:2c:93:98:72:c1 act=Allow cnt=1 cs2Label=soId
cs2=473004f59dda7db25b30cb4e3d6d004e cs3Label=soSource cs3=DDI
cs4Label=soType cs4=Node cn3Label=soRiskLevel cn3=1
```

```
2021-02-25T02:34:42Z EdgeIPS CEF:0|TXOne
|IPS|IPS_G02_1.2.0|0|SO_EVENT|6| start=2021-02-25T02:33:11Z cat=7
dvchost=EdgeIPS deviceExternalId=TMG02200000001 cn1Label=etherType
cn1=2048 proto=TCP deviceInboundInterface=PORT1 src=10.7.19.57
spt=54431 smac=24:f5:a2:8d:12:9d dst=10.7.19.55 dpt=80
dmac=ea:2c:93:98:72:c1 act=Deny cnt=1 cs2Label=soId
cs2=afc27f96c844f89012225deb46b0e641 cs3Label=soSource cs3=DDI
cs4Label=soType cs4=Link cn3Label=soRiskLevel cn3=2
```

```
2022-04-06T11:02:02+08:00 EdgeIPS-Pro
CEF:0|TXOne|IPSP|IPSP_T01_1.3.7|0|SO_EVENT|2|start=2022-04-
06T11:02:01+08:00 cat=7 dvchost=EdgeIPS-Pro
deviceExternalId=TMG02200000001 cn1Label=etherType cn1=2048 proto=ICMP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 spt=8
smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=0 dmac=00:0c:29:66:52:72
act=Allow cnt=1 cs2Label=soId cs2=89964e32c524d123b8c671909e4dd269
cs3Label=soSource cs3=IPSP_SO cs4Label=soType cs4=Node
cn3Label=soRiskLevel cn3=3
```

```
2022-04-06T11:02:10+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|1.5.7|0|SO_EVENT|2|start=2022-04-06T11:02:01+08:00
cat=7 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cn1Label=etherType cn1=2048 proto=ICMP
deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 spt=8
smac=00:0c:29:43:24:05 dst=10.24.8.111 dpt=0 dmac=00:0c:29:66:52:72
```

```
act=Allow cnt=1 cs2Label=soId cs2=89964e32c524d123b8c671909e4dd269
cs3Label=soSource cs3=IPSP_SO cs4Label=soType cs4=Node
cn3Label=soRiskLevel cn3=3
```

2.9 VPN Event Logs

2.9.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IEF" – EdgeFire
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the VPN Event Logs.
Event Name	<String>	Fixed to "VPN_EVENT" for the VPN Event Logs.
Severity	<Integer>	The severity of the VPN events. Possible value is 2 (information).

2.9.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 8 for the VPN Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cs1Label	<String>	Label "profileName" – the key for the "VPN Profile Name"
cs1	<String>	The name of the VPN profile.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP" or "UDP".
src	<String>	The source IP address
spt	<Integer>	The source port, ranging from 0 to 65535.

Field Name	Value Type	Description
dst	<String>	The destination IP address
dpt	<Integer>	The destination port, ranging from 0 to 65535.
cs2Label	<String>	Label "vpnProfileType" – the key for "VPN Profile Type"
cs2	<String>	The VPN profile type of this event. Possible values are: - IPSec - L2TP/IPSec
cs3Label	<String>	Label "vpnEvent" – the key for "VPN Event"
cs3	<String>	The type of this event. Possible values are: - Connected - Disconnected

2.9.3 Examples

```
2023-03-29T11:08:45+08:00 IEF-gateway
CEF:0|TXOne|IEF|IEF_T01_2.0.8|0|VPN_EVENT|2| start=2023-03-
29T11:08:45+08:00 cat=8 dvchost=IEF-gateway
deviceExternalId=TMF02220000492 cs1Label=profileName cs1=VPN_test
proto=UDP src=10.24.200.180 spt=500 dst=10.24.8.138 dpt=500
cs2Label=vpnProfileType cs2=IPSec vpnEvent=Connected
```

```
2023-03-29T11:08:46+08:00 EdgeOne
CEF:0|TXOne|EdgeOne|2.1.4|0|VPN_EVENT|2| start=2023-03-
29T03:08:45+08:00 cat=8 dvchost=IEF-gateway
deviceExternalId=TMF02220000492 cs1Label=profileName
cs1=VPN_test proto=(17) UDP src=10.24.200.180 spt=500 dst=10.24.8.138
dpt=500 cs2Label=vpnProfileType cs2=IPSec cs3Label=vpnEvent
cs3=Connected
```

2.10 Domain Name Filter Event Logs

2.10.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro

Field Name	Value Type	Description
		"IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
Signature ID	<Integer>	Fixed to 0 for the Domain Name Filter Event Logs.
Event Name	<String>	Fixed to "DF_EVENT" for the Domain Name Filter Event Logs.
Severity	<Integer>	The severity of the domain name filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

2.10.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 9 for the Domain Name Filter Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cs1Label	<String>	Label "ruleName" – the key for the "Domain Name Filter Rule Name"
cs1	<String>	The name of the domain name filter rule in which the domain name filter is triggered.
cn1Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn1	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
deviceInboundInterface	<String>	The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	The source IP address
spt	<Integer>	The source port, ranging from 0 to 65535.
smac	<String>	The source MAC address
dst	<String>	The destination IP address

Field Name	Value Type	Description
dpt	<Integer>	The destination port, ranging from 0 to 65535.
dmac	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cs2Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs2	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
cs3Label	<String>	Label "domainName" – the key for "Domain Name"
cs3	<String>	The domain name related to the event

2.10.3 Examples

```
2023-07-03T10:51:32+08:00 EdgeIPSP-2016
CEF:0|TXOne|IPSP|IPSP_T01_2.0.4|0|DF_EVENT|2| start=2023-07-
03T10:51:31+08:00 cat=9 dvchost=EdgeIPSP-2016 deviceExternalId=
TMG02200000001 cs1Label=ruleName cs1=Default Rule
deviceInboundInterface=PORT2 src=10.24.8.131 spt=43829
smac=40:60:5a:02:b6:8a dst=8.8.8.8 dpt=53 dmac=5c:26:0a:f6:92:62
act=Allow cs3Label=domainName cs3=syslog.txone.com
```

```
2023-07-03T10:51:32+08:00 EdgeIPSP-2016
CEF:0|TXOne|IPSP|IPSP_T01_2.0.4|0|DF_EVENT|2| start=2023-07-
03T10:51:31+08:00 cat=9 dvchost=EdgeIPSP-2016 deviceExternalId=
TMG02200000001 cs1Label=ruleName cs1=Default Rule
```

```
deviceInboundInterface=PORT2 src=10.24.8.131 spt=53296
smac=40:60:5a:02:b6:8a dst=8.8.8.8 dpt=53 dmac=5c:26:0a:f6:92:62
act=Allow cs3Label=domainName cs3=syslog.txone.com
```

2.11 CPSDR Event Logs

2.11.1 Headers

Field Name	Value Type	Description
CEF:Version	<String>	CEF version. Fixed to "CEF:0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.1.1".
Signature ID	<Integer>	The Signature ID related to the CPSDR event.
Event Name	<String>	The Signature name related to the CPSDR event.
Severity	<Integer>	The severity of the CPSDR event. Possible values are 4, 6, or 8. 4 → Low 6 → Medium 8 → High

2.11.2 Event Attributes

Field Name	Value Type	Description
start	<DateTime>	The UTC time when the event log is generated. The format is ISO 8601 format displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
cat	<Integer>	Device event category. Fixed to 0 for the CPSDR Event Logs.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.

Field Name	Value Type	Description
cn1Label	<String>	Label "etherType" – the key for "Ether Type"
cn1	<Integer>	The Ether Type data, ranging from 0 to 65535.
cn2Label	<String>	(Optional) Label "vlanId" – the key for "VLAN ID"
cn2	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The inbound interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
spt	<Integer>	(Optional) The source port, ranging from 0 to 65535.
smac	<String>	(Optional) The source MAC address
dst	<String>	(Optional) The destination IP address
dpt	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dmac	<String>	(Optional) The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
cs1Label	<String>	(Optional) Label "attacker" – the key for "Attacker"
cs1	<String>	(Optional) The attacker of the cyber security event. It could be the source IP address or the destination IP address of the CPSDR event.
cs2Label	<String>	(Optional) Label "direction" – the key for "Direction"
cs2	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN

Field Name	Value Type	Description
		• LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
cs3Label	<String>	(Optional) Label "riskLevel" – the key for “Risk Level”
cs3	<String>	(Optional) The risk level of the CPSPDR event.
cs4Label	<String>	(Optional) Label "mitreTechniqueId" – the key for “MITRE Technique ID”
cs4	<String>	(Optional) The MITRE Technique IDs related to the event.
cs5Label	<String>	(Optional) Label "mitreTacticsId" – the key for “MITRE Tactics ID”
cs5	<String>	(Optional) The MITRE Tactics IDs related to the event.
cs6Label	<String>	(Optional) Label "extraInfo" – the key for “Extra Information”
cs6	<String>	(Optional) The extra information related to the event.

2.11.3 Examples

```

2024-08-30T11:20:21+08:00 EdgeIPS-Pro-212F-77
CEF:0|TXOne|IPSP|IPSP_T01_2.1.22|3010005|BabyShark Agent
Pattern|8|start=2024-08-30T11:20:21+08:00 cat=0 dvchost=EdgeIPS-Pro-
212F-77 deviceExternalId=TXP1024S000011 cn1Label=etherType cn1=2048
proto=TCP deviceInboundInterface=PORT6 src=192.168.70.216 spt=54662
smac=00:0c:29:f7:76:73 dst=192.168.70.197 dpt=8080
dmac=00:0c:29:3f:08:4e act=Deny cnt=1 cs1Label=attacker
cs1=192.168.70.216 cs3Label=riskLevel cs3=critical
cs4Label=mitreTechniqueId cs4=T0869, T1071, T1071.001
cs4Label=mitreTacticsId cs4=TA0011, TA0101

```

3 LEEF Log Fields

When event logs are in the LEEF format, the LEEF header field "EventID" can be used to distinguish the log types.

No.	Log Type	EventID
1	Cyber Security Event Log	CS_EVENT
2	Protocol Filter Event Log	PF_EVENT
3	Policy Enforcement Event Log	PE_EVENT
4	Asset Event Log	ASSET_EVENT
5	System Event Log	SYSTEM_EVENT
6	Audit Event Log	AUDIT_EVENT
7	File Filter Event Log	FF_EVENT
8	Suspicious Object Event Log	SO_EVENT
9	VPN Event Log	VPN_EVENT
10	Domain Name Filter Event Log	DF_EVENT
11	CPSDR Event Log	CPSDR_EVENT

Please refer to the next sections for detailed descriptions of each log field.

3.1 Cyber Security Event Logs

3.1.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "CS_EVENT" for Cyber Security Event Logs.

3.1.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the cyber security event. Possible values are 2, 4, 6, 8, or 10. 2 → Information 4 → Low 6 → Medium 8 → High 10 → Critical
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
sigName	<String>	The Signature name related to the cyber security event.
sigId	<Integer>	The Signature ID related to the cyber security event.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	(Optional) The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	(Optional) The destination MAC address

Field Name	Value Type	Description
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
sigCategory	<String>	The Signature Category of the cyber security event. Currently, 11 categories are defined: • File vulnerabilities • Buffer Overflow • DoS attacks • Exploits • Malware traffic • Reconnaissance • Web threats • ICS threats • Flooding & Scan • Protocol Attack Protection • IP Spoofing
attacker	<String>	(Optional) The attacker of the cyber security event. It could be the source IP (or MAC) address or the destination IP (or MAC) address of the cyber security event.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN

Field Name	Value Type	Description
profileName	<String>	(Optional) The user-defined IPS protocol name.
ruleName	<String>	(Optional) The user-defined Policy Enforcement rule name.
mitreTechniqueId	<String>	(Optional) The MITRE Technique IDs related to the event.
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".
moduleType	<String>	The type of the module that triggered the cyber security event. Possible values are: "Cyber Security" – for data port protection "System Security" – for self-protection

3.1.3 Examples

```
2020-07-08T18:07:09+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|CS_EVENT|sev=10 devTime=2020-07-
08T10:07:03Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=WEB
Generic File Upload Directory Traversal -2 sigId=1132620
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 etherType=2048
proto=TCP deviceInboundInterface=PORT1 src=192.168.127.155
srcPort=6839 srcMAC=02:1a:c5:03:00:1c dst=192.168.127.38 dstPort=8080
dstMAC=02:1a:c5:04:00:25 act=Allow cnt=1 sigCategory=Web threats
attacker=192.168.127.155
```

```
2020-07-08T18:07:09+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|CS_EVENT|sev=8 devTime=2020-07-
08T10:07:04Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=ICS
WellinTech KingSCADA kxNetDispose.dll Stack Buffer Overflow -1 (CVE-
2014-0787) sigId=1059710 dvchost=EdgeIPS-126
deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=PORT1 src=192.168.127.164 srcPort=30246
srcMAC=02:1a:c5:03:00:25 dst=192.168.127.13 dstPort=12401
dstMAC=02:1a:c5:04:00:0c act=Allow cnt=11059710 sigCategory=Buffer
Overflow attacker=192.168.127.164
```

```
2020-07-08T10:06:21Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|CS_EVENT| sev=8 devTime=2020-07-
08T10:06:20Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=WEB Zavio
IP Camera Firmware 1.6.03 Authentication Bypass -1 (CVE-2013-2567)
sigId=1059633 dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001
etherType=2048 proto=TCP deviceInboundInterface=PORT1
src=192.168.127.177 srcPort=5975 srcMAC=02:1a:c5:03:00:32
dst=192.168.127.47 dstPort=80 dstMAC=02:1a:c5:04:00:2e act=Allow cnt=1
sigCategory=Web threats attacker=192.168.127.177
```

```
2020-07-08T10:06:22Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|CS_EVENT| sev=8 devTime=2020-07-
08T10:06:21Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=SIP Digium
Asterisk SIP Invalid SDP Media Descriptions Denial of Service (CVE-
```

```
2013-5642) sigId=1058190 dvchost=EdgeIPS-126
deviceExternalId=TMG02200000001 etherType=2048 proto=UDP
deviceInboundInterface=PORT1 src=192.168.127.138 srcPort=22812
srcMAC=02:1a:c5:03:00:0b dst=192.168.127.57 dstPort=5060
dstMAC=02:1a:c5:04:00:38 act=Allow cnt=1 sigCategory=DoS attacks
attacker=192.168.127.138
```

```
2020-11-13T03:10:46Z EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|CS_EVENT|sev=10 devTime=2020-11-
13T03:10:46Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=DB
Firebird Database Remote Database Name Overflow (CVE-2004-2043)
sigId=1051231 dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
etherType=2048 vlanId=0 proto=TCP deviceInboundInterface=SLOT2:PORT9
src=145.136.24.89 srcPort=63004 srcMAC=15:dd:51:7b:b1:7e
dst=151.11.176.174 dstPort=35278 dstMAC=98:23:67:d0:e6:00 act=Deny
cnt=1 sigCategory=Buffer Overflow profileName=IPSPProfTestLog
ruleName=RuleSet:ACLTestLog
```

```
2022-04-06T14:31:43+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|CS_EVENT|sev=6 devTime=2022-04-
06T14:31:43+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=FILE
Microsoft PE file transfer possible -1 sigId=1137431 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 srcPort=445
srcMAC=00:0c:29:c2:89:c1 dst=10.24.8.177 dstPort=57594
dstMAC=00:0c:29:04:3c:42 act=Allow cnt=1 sigCategory=File
vulnerabilities profileName=Default_IPS_Profile
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
mitreTechniqueId=T0843;T0857;T1105;T1059;T1059.001;
```

```
2022-04-06T14:31:43+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|CS_EVENT|sev=6 devTime=2022-04-
06T14:31:43+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=FILE
Microsoft PE file transfer possible -1 sigId=1137431 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 srcPort=445
srcMAC=00:0c:29:c2:89:c1 dst=10.24.8.177 dstPort=57602
dstMAC=00:0c:29:04:3c:42 act=Allow cnt=1 sigCategory=File
vulnerabilities profileName=Default_IPS_Profile
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
mitreTechniqueId=T0843;T0857;T1105;T1059;T1059.001;
```

```
2022-04-06T14:31:41+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|CS_EVENT|sev=6 devTime=2022-04-
06T14:31:39+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=FILE
Microsoft PE file transfer possible -1 sigId=1137431 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=SLOT2:PORT2 src=10.24.8.67 srcPort=445
srcMAC=00:0c:29:c2:89:c1 dst=10.24.8.177 dstPort=57458
dstMAC=00:0c:29:04:3c:42 act=Allow cnt=1 sigCategory=File
vulnerabilities profileName=Default_IPS_Profile
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
mitreTechniqueId=T0843;T0857;T1105;T1059;T1059.001;
```

```
2022-04-06T14:31:41+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|CS_EVENT|sev=6 devTime=2022-04-
```

```
06T14:31:40+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' sigName=FILE
Microsoft PE file transfer possible -1 sigId=1137431 dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=SL0T2:PORT2 src=10.24.8.67 srcPort=445
srcMAC=00:0c:29:c2:89:c1 dst=10.24.8.177 dstPort=57498
dstMAC=00:0c:29:04:3c:42 act=Allow cnt=1 sigCategory=File
vulnerabilities profileName=Default_IPS_Profile
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
mitreTechniqueId=T0843;T0857;T1105;T1059;T1059.001;
```

```
2022-04-06T14:37:51+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|CS_EVENT|sev=10 devTime=2022-04-
06T14:37:50+08:00 devTimeFormat=yyyy-MM-
dd'T'HH:mm:ss'Z' sigName=VIRUS Eicar test string -1 sigId=1051723
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 etherType=2048
proto=TCP deviceInboundInterface=SL0T2:PORT2 src=10.24.8.67
srcPort=445 srcMAC=00:0c:29:c2:89:c1 dst=10.24.8.177 dstPort=57714
dstMAC=00:0c:29:04:3c:42 act=Deny cnt=1 sigCategory=Malware traffic
attacker=10.24.8.67 profileName=Default_IPS_Profile
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV mitreTechniqueId=T1105;
```

3.2 Protocol Filter Event Logs

3.2.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "PF_EVENT" for Protocol Filter Event Logs.

3.2.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the protocol filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)

Field Name	Value Type	Description
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
filterName	<String>	The user-defined protocol filter name.
ruleName	<String>	The user-defined Policy Enforcement rule name.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	The destination MAC address
protoName	<String>	The ICS/OT protocol name related to the event. For example, "Modbus", "FTP", "SMB", etc.
funcType	<Integer>	(Optional) The function type related to the event. Currently, four function types are defined: 1 - Read Only 2 - Read/Write 3 - Admin Config 4 - Others
extraInfo	<String>	(Optional) Extra information related to the event.

Field Name	Value Type	Description
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".

3.2.3 Examples

```
2020-07-08T14:50:25+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|PF_EVENT|sev=2 devTime=2020-07-
08T06:50:24Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 filterName=abc ruleName=IPS
etherType=2048 proto=TCP deviceInboundInterface=PORT1
src=192.168.127.13 srcPort=52595 srcMAC=00:0c:29:04:3c:4c
dst=10.24.99.166 dstPort=21 dstMAC=5a:c1:88:39:cf:4c protoName=FTP
funcType=2 act=Deny cnt=1
```

```
2020-07-08T14:55:08+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|PF_EVENT|sev=2 devTime=2020-07-
08T06:54:57Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 filterName=abc ruleName=IPS
etherType=2048 proto=TCP deviceInboundInterface=PORT2
src=192.168.127.14 srcPort=52602 srcMAC=00:0c:29:04:3c:4c
dst=10.24.99.166 dstPort=80 dstMAC=5a:c1:88:39:cf:4c protoName=HTTP
act=Deny cnt=1
```

```
2020-07-08T03:08:17Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|PF_EVENT| sev=2 devTime=2020-07-
08T03:08:16Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG022000000001 filterName=abc
ruleName=ModbusCategories-1 etherType=2048 proto=TCP
deviceInboundInterface=PORT2 src=192.168.127.13 srcPort=52539
srcMAC=00:0c:29:04:3c:4c dst=117.18.237.29 dstPort=502
dstMAC=5a:c1:88:39:cf:4c protoName=Modbus funcType=2 act=Deny cnt=1
```

```
2020-11-13T03:14:23Z EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|PF_EVENT| sev=6 devTime=2020-11-
13T03:14:21Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
Pro deviceExternalId=TMG022000000001 filterName=PFProfTestLog
ruleName=RuleSet:ACLTestLog etherType=2048 vlanId=0 proto=ICMP
deviceInboundInterface=SLOT1:PORT2 src=95.121.176.161 srcPort=21
srcMAC=7a:62:77:55:05:da dst=235.254.30.170 dstPort=143
dstMAC=fb:0e:92:22:a6:69 protoName=S7COMM_PLUS funcType=3
extraInfo=FunctionCode: 0x574D act=Deny cnt=1
```

```
2022-04-06T14:24:47+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|PF_EVENT|sev=6 devTime=2022-04-
06T14:24:46+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001
filterName=Enable_IT_protocol ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
etherType=2048 proto=UDP deviceInboundInterface=SLOT2:PORT1
src=10.24.8.126 srcPort=54902 srcMAC=1a:82:fa:a9:60:f5 dst=8.8.8.8
dstPort=53 dstMAC=64:00:6a:cd:00:a2 protoName=DNS act=Deny cnt=1
```

```
2022-04-06T14:24:50+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|PF_EVENT|sev=2 devTime=2022-04-
06T14:24:49+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001
filterName=Enable_IT_protocol ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT2
src=52.98.37.34 srcPort=25 srcMAC=64:00:6a:cd:00:a2 dst=10.24.8.177
dstPort=57365 dstMAC=00:0c:29:04:3c:42 protoName=SMTP act=Allow cnt=1
```

```
2022-04-06T14:28:21+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|PF_EVENT|sev=2 devTime=2022-04-
06T14:28:14+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001
filterName=Enable_IT_protocol ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV
etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT1
src=10.24.8.177 srcPort=57372 srcMAC=00:0c:29:04:3c:42 dst=10.24.8.67
dstPort=445 dstMAC=00:0c:29:c2:89:c1 protoName=SMB extraInfo=SMB v2
act=Allow cnt=1
```

3.3 Policy Enforcement Event Logs

3.3.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".

Field Name	Value Type	Description
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "PE_EVENT" for Policy Enforcement Event Logs.

3.3.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the Policy Enforcement event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
ruleName	<String>	The user-defined Policy Enforcement rule name.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).

Field Name	Value Type	Description
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
protoLayer	<String>	The layer of the network traffic in the OSI model. Possible values are "Layer2" or "Layer3".

3.3.3 Examples

```

2020-07-08T15:34:59+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|PE_EVENT|sev=2 devTime=2020-07-
08T07:34:46Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 ruleName=IPS etherType=2048
proto=UDP deviceInboundInterface=PORT2 src=192.168.127.14
srcPort=54538 srcMAC=00:0c:29:04:3c:4c dst=8.8.8.8 dstPort=53
dstMAC=5a:c1:88:39:cf:4c act=Allow

```

2020-07-08T07:34:59Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|PE_EVENT|sev=2 devTime=2020-07-08T07:34:58Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 ruleName=IPS etherType=2048 proto=UDP deviceInboundInterface=PORT2 src=192.168.127.14 srcPort=62024 srcMAC=00:0c:29:04:3c:4c dst=8.8.8.8 dstPort=53 dstMAC=5a:c1:88:39:cf:4c act=Allow

2020-11-13T03:44:41Z EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|PE_EVENT|sev=6 devTime=2020-11-13T03:44:39Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 ruleName=RuleSet:ACLTestLog etherType=2048 vlanId=0 proto=UDP deviceInboundInterface=SLOT2:PORT4 src=95.44.120.196 srcPort=42380 srcMAC=f9:86:bc:56:f9:57 dst=204.56.126.88 dstPort=1925 dstMAC=02:79:23:09:e2:8b act=Deny

2022-04-06T12:43:30+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|PE_EVENT|sev=2 devTime=2022-04-06T12:43:26+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=UDP deviceInboundInterface=SLOT2:PORT2 src=10.24.10.188 srcPort=61544 srcMAC=00:50:56:b8:40:e5 dst=239.255.255.250 dstPort=1900 dstMAC=01:00:5e:7f:ff:fa act=Allow

2022-04-06T12:43:31+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|PE_EVENT|sev=2 devTime=2022-04-06T12:43:29+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=IGMP deviceInboundInterface=SLOT2:PORT2 src=172.16.1.27 srcPort=0 srcMAC=00:04:96:20:c7:cf dst=224.0.0.1 dstPort=0 dstMAC=01:00:5e:00:00:01 act=Allow

2022-04-06T12:43:40+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|PE_EVENT|sev=2 devTime=2022-04-06T12:43:38+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=IGMP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 srcPort=0 srcMAC=00:0c:29:04:3c:42 dst=224.0.0.252 dstPort=0 dstMAC=01:00:5e:00:00:fc act=Allow

2022-04-06T12:43:40+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|PE_EVENT|sev=2 devTime=2022-04-06T12:43:38+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=IGMP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.177 srcPort=0 srcMAC=00:0c:29:04:3c:42 dst=239.255.255.250 dstPort=0 dstMAC=01:00:5e:7f:ff:fa act=Allow

2022-04-06T12:43:40+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|PE_EVENT|sev=2 devTime=2022-04-06T12:43:29+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'

```
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=IGMP
deviceInboundInterface=SL0T2:PORT2 src=172.16.1.27 srcPort=0
srcMAC=00:04:96:20:c7:cf dst=224.0.0.1 dstPort=0
dstMAC=01:00:5e:00:00:01 act=Allow
```

```
2022-04-06T12:43:40+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|PE_EVENT|sev=2 devTime=2022-04-
06T12:43:29+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001
ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=UDP
deviceInboundInterface=SL0T2:PORT2 src=10.24.7.12 srcPort=54592
srcMAC=f0:bf:97:df:13:b1 dst=239.255.255.250 dstPort=1900
dstMAC=01:00:5e:7f:ff:fa act=Allow
```

3.4 Asset Event Logs

3.4.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "ASSET_EVENT" for Asset Event Logs.

3.4.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the asset event. Possible value is 2 (information).
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the

Field Name	Value Type	Description
		event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cat	<Integer>	The asset event ID. Currently, four asset event IDs are defined: 0 - Unknown 1 - New asset detected 2 - Asset idle timeout 3 - Asset changed
assetIpAddress	<String>	The asset IP address.
assetMacAddress	<Integer>	The asset MAC address.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).

3.4.3 Examples

```
2020-07-07T17:02:12Z EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|ASSET_EVENT|sev=2 devTime=2020-07-
07T17:02:12Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 cat=3 assetIpAddress=13.35.153.42
assetMacAddress=5a:c1:88:39:cf:4c deviceInboundInterface=PORT2
```

```
2020-07-08T03:04:02Z EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.1.1|ASSET_EVENT|sev=2 devTime=2020-07-
08T03:04:02Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 cat=1 assetIpAddress=0.0.0.0
assetMacAddress=00:0c:29:c9:85:d1 deviceInboundInterface=PORT2
```

```
2020-07-07T16:37:12Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|ASSET_EVENT| sev=2 devTime=2020-07-
07T16:37:12Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 cat=3 assetIpAddress=10.1.1.20
assetMacAddress=5a:c1:88:39:cf:4c deviceInboundInterface=PORT2
```

```
2020-07-07T16:47:11Z EdgeIPS-126
LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|ASSET_EVENT| sev=2 devTime=2020-07-
07T16:47:11Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
126 deviceExternalId=TMG02200000001 cat=3 assetIpAddress=13.35.153.42
assetMacAddress=5a:c1:88:39:cf:4c deviceInboundInterface=PORT2
```

```
2020-11-13T06:09:33Z EdgeIPS-Pro LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|
ASSET_EVENT|sev=2 devTime=2020-11-13T06:09:33Z devTimeFormat=yyyy-MM-
dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cat=1 assetIpAddress=0.0.0.0 assetMacAddress=00:0c:29:2a:b3:ea
deviceInboundInterface=SLOT1:PORT2
```

```
2022-04-06T14:30:19+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|ASSET_EVENT|sev=2 devTime=2022-04-
06T14:30:19+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001 cat=2
assetIpAddress=10.24.8.216 assetMacAddress=24:6e:96:24:99:90
deviceInboundInterface=SLOT2:PORT2
```

```
2022-04-06T14:30:19+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|ASSET_EVENT|sev=2 devTime=2022-04-
06T14:30:19+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG022000000001 cat=2
assetIpAddress=10.24.8.216 assetMacAddress=24:6e:96:24:99:90
deviceInboundInterface=SLOT2:PORT2
```

3.5 System Event Logs

3.5.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "SYSTEM_EVENT" for System Event Logs.

3.5.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the system event. Possible values are 2, 4, 6, or 7. 2 → Information 4 → Notice 6 → Warning 7 → Error
devTime	<DateTime>	The UTC time (ISO 8601 format) when the event is generated.

Field Name	Value Type	Description
devTimeFormat	<String>	The date-time format of the field "devTime", "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event. It is used to preserve the information of the device generating the event when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cat	<Integer>	The system event ID (category ID). Please refer to Appendix A for the defined system event IDs and the corresponding messages.
msg	<String>	The message of the system event. Please refer to Appendix A for the defined system event IDs and the corresponding messages.

3.5.3 Examples

```
2020-07-08 10:22:55 Local1.Notice 10.24.253.216 2020-07-08T02:19:17Z
EdgeOne LEEF:1.0|TXOne|EdgeOne|1.1.1|SYSTEM_EVENT|sev=4 devTime=2020-
07-08T02:19:17Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=28 msg=System
time adjusted (-120 ms)
```

```
2020-07-08 10:22:55 Local1.Notice 10.24.253.216 2020-07-08T02:19:17Z
EdgeOne LEEF:1.0|TXOne|EdgeOne|1.1.1|SYSTEM_EVENT|sev=4 devTime=2020-
07-08T02:19:17Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=5 msg=Sync
with NTP server (10.24.253.216) successful
```

```
2020-07-08 11:07:39 Local0.Warning 10.24.220.220 2020-07-08T03:03:53Z
EdgeIPS-126 LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|SYSTEM_EVENT|sev=6
devTime=2020-07-08T03:03:53Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=4 msg=Port
(PORT2) link down
```

```
2020-07-08 11:07:39 Local0.Warning 10.24.220.220 2020-07-08T03:03:58Z
EdgeIPS-126 LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|SYSTEM_EVENT|sev=6
devTime=2020-07-08T03:03:58Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=3 msg=Port
(PORT1) link up
```

```
2020-11-13T03:43:25Z EdgeIPS-Pro LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|
SYSTEM_EVENT|sev=4 devTime=2020-11-13T03:43:25Z devTimeFormat=yyyy-MM-
dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cat=5 msg=Sync with NTP server (192.168.127.100) successful
```

```
2022-04-06T10:24:48+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T10:24:48+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
```

```
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=23 msg=Updated
configurations via EdgeOne
```

```
2022-04-06T11:25:36+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T11:25:36+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=40 msg=HA Peer
un-synced
```

```
2022-04-06T11:25:36+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T11:25:36+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=40 msg=HA Peer
un-synced
```

```
2022-04-06T11:25:47+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T11:25:46+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro-VM130 deviceExternalId=godzellagogogo cat=28
msg=System time adjusted (4 ms)
```

```
2022-04-06T11:25:56+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T11:25:56+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=41 msg=HA Peer
synced
```

```
2022-04-06T11:25:56+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SYSTEM_EVENT|sev=4 devTime=2022-04-
06T11:25:56+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=41 msg=HA Peer
synced
```

3.6 Audit Event Logs

3.6.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".

Field Name	Value Type	Description
EventID	<String>	The Event ID of the event. Fixed to "AUDIT_EVENT" for Audit Event Logs.

3.6.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the audit event. Possible values are 2, 4, 6, or 7. 2 → Information 4 → Notice 6 → Warning 7 → Error
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
cat	<Integer>	The audit event ID (category ID). Please refer to Appendix B for the defined audit event IDs and the corresponding messages.
suser	<String>	The username of the user who triggers the audit event.
clientIpAddress	<String>	The client IP address from which the user logs in and executes commands.
msg	<String>	The message of the audit event. Please refer to Appendix B for the defined audit event IDs and the corresponding messages.

3.6.3 Examples

```
2020-07-08 10:23:02 Local1.Notice 10.24.253.216 2020-07-08T02:19:24Z
EdgeOne LEEF:1.0|TXOne|EdgeOne|1.1.1|AUDIT_EVENT|sev=4 devTime=2020-
07-08T02:19:24Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeOne
cat=8465 suser=Jimmy clientIpAddress=10.24.8.211 msg=User (Jimmy)
created (EdgeIPS) device group (IPS_126)
```

```
2020-07-08 10:23:14 Local1.Notice 10.24.253.216 2020-07-08T02:19:36Z
EdgeOne LEEF:1.0|TXOne|EdgeOne|1.1.1|AUDIT_EVENT|sev=4 devTime=2020-
07-08T02:19:36Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeOne
```

```
cat=8467 suser=Jimmy clientIpAddress=10.24.8.211 msg=User (Jimmy)
changed (EdgeIPS) device group (IPS_126) settings
```

```
2020-07-08 10:42:31 Local0.Notice 10.24.220.220 2020-07-08T02:38:53Z
EdgeIPS-126 LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|AUDIT_EVENT|sev=4
devTime=2020-07-08T02:38:53Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=82 suser=Jimmy
clientIpAddress=10.24.8.211 msg=User (Jimmy) changed syslog settings
```

```
2020-07-08 10:48:01 Local0.Notice 10.24.220.220 2020-07-08T02:44:23Z
EdgeIPS-126 LEEF:1.0|TXOne|IPS|IPS_G02_1.1.1|AUDIT_EVENT|sev=4
devTime=2020-07-08T02:44:23Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-126 deviceExternalId=TMG02200000001 cat=87 suser=Jimmy
clientIpAddress=10.24.8.211 msg=User (Jimmy) changed time zone to
(Asia/Taipei)
```

```
2020-11-13T03:48:32Z EdgeIPS-Pro LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|
AUDIT_EVENT|sev=4 devTime=2020-11-13T03:48:32Z devTimeFormat=yyyy-MM-
dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001
cat=128 suser=admin1 clientIpAddress=192.168.127.1 msg=User (admin1)
added IP object (XServers)
```

```
2022-04-06T10:31:10+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|AUDIT_EVENT|sev=4 devTime=2022-04-
06T10:31:10+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=82 suser=Jimmy
clientIpAddress=10.24.8.211 msg=User (Jimmy) changed syslog settings
```

```
2022-04-06T10:31:10+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|AUDIT_EVENT|sev=4 devTime=2022-04-
06T10:31:10+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 cat=82 suser=Jimmy
clientIpAddress=10.24.8.211 msg=User (Jimmy) changed syslog settings
```

3.7 File Filter Event Logs

3.7.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite

Field Name	Value Type	Description
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "FF_EVENT" for File Filter Event Logs.

3.7.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the file filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
filterName	<String>	The user-defined file filter name.
ruleName	<String>	The user-defined Policy Enforcement rule name.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	The source IP address
srcPort	<Integer>	The source port, ranging from 0 to 65535.
srcMAC	<String>	The source MAC address
dst	<String>	The destination IP address
dstPort	<Integer>	The destination port, ranging from 0 to 65535.
dstMAC	<String>	The destination MAC address

Field Name	Value Type	Description
protoName	<String>	The ICS/OT protocol name related to the event. For example, "Modbus", "FTP", "SMB", etc.
extraInfo	<String>	(Optional) Extra information related to the event.
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
profileType	<String>	(Optional) The profile type by which this event was detected. Possible values are: • File Filter • Antivirus
virusName	<String>	(Optional) The name of the virus detected in the event.

3.7.3 Examples

```

2020-11-13T06:52:46Z EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|FF_EVENT| sev=6 devTime=2020-11-
13T06:52:44Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-
Pro deviceExternalId=TMG02200000001 filterName=FileFilterTestLog
ruleName=RuleSet:ACLTestLog etherType=2048 vlanId=0 proto=TCP
deviceInboundInterface=SLOT2:PORT15 src=201.134.62.33 srcPort=49921
srcMAC=a4:56:99:72:6a:88 dst=115.75.57.225 dstPort=50910
dstMAC=10:27:e8:cc:a2:ed protoName=Others extraInfo=File Type: Windows
PE, Filename: Fakefile.exe act=Deny

```

2020-11-13T06:52:47Z EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.1.0|FF_EVENT|sev=6 devTime=2020-11-13T06:52:45Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 filterName=FileFilterTestLog ruleName=RuleSet:ACLTestLog etherType=2048 vlanId=0 proto=UDP deviceInboundInterface=SLOT1:PORT20 src=135.137.187.139 srcPort=46153 srcMAC=b4:a5:ed:a6:35:a7 dst=154.160.103.46 dstPort=13309 dstMAC=5f:38:1a:67:d4:7f protoName=Others extraInfo=GPO: Yes, Filename: Machine\Preferences\Registry\Registry.xml act=Deny

2022-04-06T11:27:16+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|FF_EVENT|sev=6 devTime=2022-04-06T11:27:14+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 filterName=Default_AV_Profile ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=50174 srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=445 dstMAC=00:0c:29:66:52:72 protoName=SMB extraInfo=SHA1:556a25208824efd585cb211ba1951a46da97127e, File Type: Linux ELF, Filename: qemu-ppc64abi32-static act=Deny profileType=Antivirus virusName=TXONE_TEST_qemu-ppc64abi32-static

2022-04-06T11:27:20+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|FF_EVENT|sev=6 devTime=2022-04-06T11:27:14+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 filterName=Default_AV_Profile ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=50168 srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=445 dstMAC=00:0c:29:66:52:72 protoName=SMB extraInfo=SHA1:556a25208824efd585cb211ba1951a46da97127e, File Type: Linux ELF, Filename: qemu-ppc64abi32-static act=Deny profileType=Antivirus virusName=TXONE_TEST_qemu-ppc64abi32-static

2022-04-06T11:25:53+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|FF_EVENT|sev=6 devTime=2022-04-06T11:25:51+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 filterName=Enable_FF_SMB ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=50151 srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=445 dstMAC=00:0c:29:66:52:72 protoName=SMB extraInfo=File Type: Windows PE, Filename: helloWorld.exe act=Deny profileType=File Filter

2022-04-06T11:26:00+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|FF_EVENT|sev=6 devTime=2022-04-06T11:25:51+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 filterName=Enable_FF_SMB ruleName=TEST_IPSP:Test_IPSP_PF_FF_AV etherType=2048 proto=TCP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=50145 srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=445 dstMAC=00:0c:29:66:52

3.8 Suspicious Object Event Logs

3.8.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "SO_EVENT" for Suspicious Object Event Logs.

3.8.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the file filter event. Possible values are 2 or 6. 2 → Information (associated to the case when the suspicious objects are allowed) 6 → Warning (associated to the case when suspicious objects are denied)
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	(Optional) The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.

Field Name	Value Type	Description
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
sold	<String>	A unique identifier of the suspicious object.
soSource	<String>	The original source where the suspicious object is defined
soType	<String>	The type of the suspicious object. Possible values are: • Node

Field Name	Value Type	Description
		• Link • File
soExpiration	<DateTime>	(Optional) The expiration of the suspicious object displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'" (ISO 8601 format).
soRiskLevel	<Integer>	The risk level of the suspicious object. Possible values are: • 1 – Low • 2 – Medium • 3 – High

3.8.3 Examples

```
2021-02-25T02:35:19Z EdgeIPS
LEEF:1.0|TXOne|IPS|IPS_G02_1.2.0|SO_EVENT|sev=2 devTime=2021-02-
25T02:35:18Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS
deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=PORT1 src=10.7.19.57 srcPort=54444
srcMAC=24:f5:a2:8d:12:9d dst=10.7.19.55 dstPort=22
dstMAC=ea:2c:93:98:72:c1 act=Allow cnt=1
soId=473004f59dda7db25b30cb4e3d6d004e soSource=DDI soType=Node
soRiskLevel=1
```

```
2021-02-25T02:35:27Z EdgeIPS
LEEF:1.0|TXOne|IPS|IPS_G02_1.2.0|SO_EVENT|sev=6 devTime=2021-02-
25T02:35:18Z devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=EdgeIPS
deviceExternalId=TMG02200000001 etherType=2048 proto=TCP
deviceInboundInterface=PORT1 src=10.7.19.57 srcPort=54445
srcMAC=24:f5:a2:8d:12:9d dst=10.7.19.55 dstPort=80
dstMAC=ea:2c:93:98:72:c1 act=Deny cnt=1
soId=afc27f96c844f89012225deb46b0e641 soSource=DDI soType=Link
soRiskLevel=2
```

```
2022-04-06T10:31:31+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|SO_EVENT|sev=2 devTime=2022-04-
06T10:31:30+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 etherType=2048
proto=ICMP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=8
srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=0
dstMAC=00:0c:29:66:52:72 act=Allow cnt=1
soId=14e17417b3e0608f295cdc8a408583e3 soSource=IPSP_SO soType=Link
soExpiration=2022-04-06T10:33:18+08:00 soRiskLevel=1
```

```
2022-04-06T10:31:40+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SO_EVENT|sev=2 devTime=2022-04-
06T10:31:30+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 etherType=2048
proto=ICMP deviceInboundInterface=SLOT2:PORT1 src=10.24.8.10 srcPort=8
srcMAC=00:0c:29:43:24:05 dst=10.24.8.111 dstPort=0
dstMAC=00:0c:29:66:52:72 act=Allow cnt=1
```

```
soId=14e17417b3e0608f295cdc8a408583e3 soSource=IPSP_SO soType=Link
soExpiration=2022-04-06T10:33:18+08:00 soRiskLevel=1
```

```
2022-04-06T10:39:21+08:00 EdgeIPS-Pro
LEEF:1.0|TXOne|IPSP|IPSP_T01_1.3.7|SO_EVENT|sev=2 devTime=2022-04-
06T10:39:19+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 etherType=2048
proto=UDP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.111
srcPort=61305 srcMAC=00:0c:29:66:52:72 dst=239.255.255.250
dstPort=1900 dstMAC=01:00:5e:7f:ff:fa act=Allow cnt=1
soId=89964e32c524d123b8c671909e4dd269 soSource=IPSP_SO soType=Node
soRiskLevel=3
```

```
2022-04-06T10:39:30+08:00 EdgeOne
LEEF:1.0|TXOne|EdgeOne|1.5.7|SO_EVENT|sev=2 devTime=2022-04-
06T10:39:19+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPS-Pro deviceExternalId=TMG02200000001 etherType=2048
proto=UDP deviceInboundInterface=SLOT2:PORT2 src=10.24.8.111
srcPort=61305 srcMAC=00:0c:29:66:52:72 dst=239.255.255.250
dstPort=1900 dstMAC=01:00:5e:7f:ff:fa act=Allow cnt=1
soId=89964e32c524d123b8c671909e4dd269 soSource=IPSP_SO soType=Node
soRiskLevel=3
```

3.9 VPN Event Logs

3.9.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IEF" – EdgeFire
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "VPN_EVENT" for VPN Event Logs.

3.9.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the asset event. Possible value is 2 (information).
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".

Field Name	Value Type	Description
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
profileName	<String>	The user-defined VPN profile name.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP" or "UDP".
src	<String>	The source IP address
srcPort	<Integer>	The source port, ranging from 0 to 65535.
dst	<String>	The destination IP address
dstPort	<Integer>	The destination port, ranging from 0 to 65535.
vpnProfileType	<string>	The VPN profile type of this event. Possible values are: - IPSec - L2TP/IPSec
vpnEvent	<String>	The type of this event. Possible values are: - Connected - Disconnected

3.9.3 Examples

```
2023-03-29T11:08:45+08:00 IEF-gateway
LEEF:1.0|TXOne|IEF|IEF_T01_2.0.8|VPN_EVENT|sev=2 devTime=2023-03-
29T11:08:45+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=IEF-
gateway deviceExternalId=TMF02220000492 profileName=VPN_test proto=UDP
src=10.24.200.180 srcPort=500 dst=10.24.8.138 dstPort=500
vpnProfileType=IPSec vpnEvent=Connected
```

```
2023-03-29T11:08:45+08:00 IEF-gateway
LEEF:1.0|TXOne|EdgeOne|IEF_T01_2.0.8|VPN_EVENT|sev=2 devTime=2023-03-
29T11:08:45+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z' dvchost=IEF-
gateway deviceExternalId=TMF02220000492 profileName=VPN_test
proto=(17) UDP src=10.24.200.180 srcPort=500 dst=10.24.8.138
dstPort=500 vpnProfileType=IPSec vpnEvent=Connected
```

3.10 Domain Name Filter Event Logs

3.10.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.0.1".
EventID	<String>	The Event ID of the event. Fixed to "DF_EVENT" for Domain Name Filter Event Logs.

3.10.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the domain name filter event. Possible values are 2 or 6. 2 → Information (associated to the case when packets are allowed) 6 → Warning (associated to the case when packets are denied)
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
ruleName	<Integer>	The user-defined domain name filter rule name.
valnId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).

Field Name	Value Type	Description
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN • DMZ to VPN • VPN to DMZ • VPN to VPN • WAN to WAN • DMZ to DMZ • WAN to VPN
domainName	<String>	The domain name related to the event.

3.10.3 Examples

```

2023-07-03T11:16:26+08:00 EdgeIPSP-2016
LEEF:1.0|TXOne|IPSP|IPSP_T01_2.0.4|DF_EVENT|sev=2 devTime=2023-07-
03T11:16:24+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPSP-2016 deviceExternalId= TMG02200000001
ruleName=Default Rule deviceInboundInterface=PORT2 src=10.24.8.131
spt=33448 smac=40:60:5a:02:b6:8a dst=8.8.8.8 dpt=53
dstMAC=5c:26:0a:f6:92:62 act=Allow domainName=syslog.txone.com

```

```
2023-07-03T11:16:26+08:00 EdgeIPSP-2016
LEEF:1.0|TXOne|IPSP|IPSP_T01_2.0.4|DF_EVENT|sev=2 devTime=2023-07-
03T11:16:24+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
dvchost=EdgeIPSP-2016 deviceExternalId= TMG022000000001
ruleName=Default Rule deviceInboundInterface=PORT2 src=10.24.8.131
spt=58208 smac=40:60:5a:02:b6:8a dst=8.8.8.8 dpt=53
dstMAC=5c:26:0a:f6:92:62 act=Allow domainName=syslog.txone.com
```

3.11 CPSDR Event Logs

3.11.1 Headers

Field Name	Value Type	Description
LEEF:Version	<String>	LEEF version. Fixed to "LEEF:1.0".
Device Vendor	<String>	Vendor name. Fixed to "TXOne".
Device Product	<String>	Product name. Possible values are: "EdgeOne" – EdgeOne Server "IPS" – EdgeIPS "IEF" – EdgeFire "IPSP" – EdgeIPS Pro "IPSLE" – EdgeIPS Lite
Device Version	<String>	Product version. For example, "2.1.1".
EventID	<String>	The Event ID of the event. Fixed to "CPSDR_EVENT" for CPSDR Event Logs.

3.11.2 Event Attributes

Field Name	Value Type	Description
sev	<Integer>	The severity of the CPSDR event. Possible values are 4, 6, or 8. 4 → Low 6 → Medium 8 → High
devTime	<DateTime>	The UTC time when the event log is generated.
devTimeFormat	<String>	The date-time format (ISO 8601 format) of the field "devTime" displayed as "yyyy-MM-dd'T'HH:mm:ss'Z'".
sigName	<String>	The Signature name related to the CPSDR event.
sigId	<Integer>	The Signature ID related to the CPSDR event.
dvchost	<String>	(Optional) The hostname of the device generating the event log. It is used to preserve the information of the device generating the

Field Name	Value Type	Description
		event log when it is not the same device sending the syslog.
deviceExternalId	<String>	(Optional) The serial number of the device generating the event log.
etherType	<Integer>	The Ether Type data, ranging from 0 to 65535.
valId	<Integer>	(Optional) The VLAN ID data, ranging from 0 to 4095.
proto	<String>	The IP protocol name or number (if name is not available). Possible values are "TCP", "UDP", or "143", etc.
deviceInboundInterface	<String>	(Optional) The interface where this event is detected. For example, "PORT1" or "SLOT1:PORT1" (if the slot number is available).
src	<String>	(Optional) The source IP address
srcPort	<Integer>	(Optional) The source port, ranging from 0 to 65535.
srcMAC	<String>	(Optional) The source MAC address
dst	<String>	(Optional) The destination IP address
dstPort	<Integer>	(Optional) The destination port, ranging from 0 to 65535.
dstMAC	<String>	(Optional) The destination MAC address
act	<String>	The action taken by the device. Possible values are "Allow", "Deny", etc.
cnt	<Integer>	The event counts.
attacker	<String>	(Optional) The attacker of the cyber security event. It could be the source IP address or the destination IP address of the CPSDR event.
direction	<String>	(Optional) The direction of the initial connection of this event. Possible values are: • WAN to LAN • LAN to WAN • WAN to DMZ • DMZ to WAN • LAN to DMZ • DMZ to LAN • WAN to VPN • VPN to WAN • LAN to VPN • VPN to LAN

Field Name	Value Type	Description
		- DMZ to VPN - VPN to DMZ - VPN to VPN - WAN to WAN - DMZ to DMZ - WAN to VPN
riskLevel	<String>	(Optional) The risk level of the CPSDR event.
mitreTechniqueId	<String>	(Optional) The MITRE Technique IDs related to the event.
mitreTacticsId	<String>	(Optional) The MITRE Tactics IDs related to the event.
extraInfo	<String>	(Optional) The extra information related to the event.

3.11.3 Examples

```

2024-08-30T11:47:09+08:00 EdgeIPS-Pro-212F-77
LEEF:1.0|TXOne|IPSP|IPSP_T01_2.1.23|CPSDR_EVENT|sev=4 devTime=2024-08-
30T11:47:09+08:00 devTimeFormat=yyyy-MM-dd'T'HH:mm:ss'Z'
sigName=Potential Port Scan Detected sigId=3010043 dvchost=EdgeIPS-
Pro-212F-77 deviceExternalId=TXP1024S000011 etherType=2048 proto=UDP
deviceInboundInterface=PORT6 src=168.95.192.1 srcPort=53
srcMAC=00:1b:17:00:01:30 dst=10.7.16.15 dstPort=60726
dstMAC=f8:32:e4:9b:c2:99 act=Allow cnt=13 attacker=168.95.192.1
riskLevel=medium mitreTechniqueId=T1046 mitreTacticsId=TA0008

```

4 Appendix A: System Event IDs and Messages

The pre-defined system event IDs and the corresponding messages are listed in the following table.

ID	Message	Arguments	Products
1	System started	None	IPS/IEF/IPSP
2	System reboot via (\$0)	\$0: EdgeOne Reset button	IPS/IEF/IPSP
3	Port (\$0) link up	\$0: port number	IPS/IEF/IPSP
4	Port (\$0) link down	\$0: port number	IPS/IEF/IPSP
5	Sync with NTP server (\$0) successful	\$0: NTP server	IPS/IEF/IPSP
6	Sync with NTP server (\$0) failed	\$0: NTP server	IPS/IEF/IPSP
7	Connect with EdgeOne (\$0)	\$0: EdgeOne IP address (or DN)	IPS/IEF/IPSP
8	Disconnected from EdgeOne (\$0)	\$0: EdgeOne IP address (or DN)	IPS/IEF/IPSP
9	Firmware upgraded successfully	None	IPS/IEF/IPSP
10	Firmware upgrade failed - (\$0)	\$0: error code	IPS/IEF/IPSP
11	Pattern updated successfully	None	IPS/IEF/IPSP
12	Pattern update failed - (\$0)	\$0: error code	IPS/IEF/IPSP
13	The total number of event logs exceeds the capacity of the device - (\$0) logs dropped	\$0: number of event logs being dropped	IPS/IEF/IPSP
14	Invalid address (\$0) tried to access device service port (\$1) (retries (\$2))	\$0: IP address; \$1: service port; \$2: retries count	IPS/IEF/IPSP
15	Maximum number of sessions exceeded	None	IPS/IEF/IPSP
16	USB Device plugged in	None	IPS/IEF/IPSP
17	USB Device plugged out	None	IPS/IEF/IPSP
18	Saved config file to "USB Device" successfully	None	IPS/IEF/IPSP
19	Saved config file to "USB Device" failed - (\$0)	\$0: error code error string	IPS/IEF/IPSP
20	Configuration restore succeeded via USB	None	IPS/IEF/IPSP
21	Configuration restore failed via USB - (\$0)	\$0: error code error string	IPS/IEF/IPSP
22	Switched boot partition to (\$0) via EdgeOne	\$0: Partition Name	IPS/IEF/IPSP
23	Updated configurations via EdgeOne	None	IPS/IEF/IPSP

24	Firmware upgraded successfully via (\$0)	\$0: USB EdgeOne	IPS/IEF/IPSP
25	Firmware upgrade failed via (\$0) - (\$1)	\$0: USB EdgeOne; \$1: error code	IPS/IEF/IPSP
26	IPS pattern updated successfully via (\$0)	\$0: USB EdgeOne	IPS/IEF/IPSP
27	IPS Pattern update failed via (\$0) - (\$1)	\$0: USB EdgeOne; \$1: error code error string	IPS/IEF/IPSP
28	System time adjusted (\$0 ms)	\$0: delta in ms	IPS/IEF/IPSP
29	Boot partition (\$0) failed	\$0: partition name, "boot1" or "boot2"	IPS/IEF/IPSP
30	Antivirus pattern updated successfully via (\$0)	\$0: USB EdgeOne	IPSP
31	Antivirus pattern update failed via (\$0) - (\$1)	\$0: USB EdgeOne; \$1: error code error string	IPSP
32	Port (\$0) link down by LFPT	\$0: port number	IPSP
33	System started the auto-learning task	None	IPS/IEF
34	System stopped the auto-learning task	None	IPS/IEF
35	System canceled the auto-learning task	None	IPS/IEF
36	Port (\$0) resumes the traffic	\$0: port number	IEF
37	Port (\$0) blocked the traffic	\$0: port number	IEF
38	HA Peer disconnected	None	IEF
39	HA Peer connected	None	IEF
40	HA Peer un-synced	None	IEF
41	HA Peer synced	None	IEF
42	Slot card (\$0) is missing	\$0: slot number	IPSP
43	Slot card (\$0) is changed	\$0: slot number	IPSP
44	Slot card combination is changed	None	IPSP
45	PPPoE Connection established on (\$0)	\$0: WAN interface name	IEF
46	PPPoE Connection dropped on (\$0)	\$0: WAN interface name	IEF
47	DDNS profile (\$0) with host name (\$1) provider (\$2) ip(\$3) connect successfully	\$0: profile name \$1: host name \$2: provider \$3: ip	IEF

48	DDNS profile (\$0) with host name (\$1) provider (\$2) ip(\$3) connect failed	\$0: profile name \$1: host name \$2: provider \$3: ip	IEF
8192	EdgeOne started	None	EdgeOne
8193	EdgeOne stopped	None	EdgeOne
8208	Web server started	None	EdgeOne
8209	Web server stopped	None	EdgeOne
8210	Web server initialized using user-defined certificate	None	EdgeOne
8211	Unable to initialize web server using user-defined certificate - (\$0)	\$0: error code	EdgeOne
8212	Web server initialized using default certificate	None	EdgeOne
8224	NTP server (\$0) synchronized	\$0: NTP server	EdgeOne
8225	Unable to synchronize NTP server (\$0)	\$0: NTP server	EdgeOne
8226	System time adjusted (\$0 ms)	\$0: delta in ms	EdgeOne
8227	Sent the event notification to the SMTP server failed	None	EdgeOne
8449	Scheduled update for component (\$0) started	\$0: component name	EdgeOne
8450	Scheduled update for component (\$0) finished	\$0: component name	EdgeOne
8452	No new version available for component (\$0)	\$0: component name	EdgeOne
8454	Component (\$0) version (\$1) downloaded from update server	\$0: component name \$1: version number	EdgeOne
8456	Unable to download component (\$0) from update server - Internal error, error code (\$1)	\$0: component name \$1: error code	EdgeOne
8457	Unable to download component (%s) from update server - License unavailable	\$0: component name	EdgeOne
8464	Unable to download component (\$1) from update server - Maximum number of file exceeded	\$0: component name	EdgeOne
8465	Unable to download component (\$1) from update server - Network unavailable, error code (\$2)	\$0: component name \$1: error code	EdgeOne
8705	Node (Type: \$0, ID: \$1) added	\$0: node type (IPS or IEF)	EdgeOne

		\$1: device S/N or endpoint UUID	
8706	Node (Type: \$0, ID: \$1) removed	\$0: node type (IPS or IEF) \$1: device S/N or endpoint UUID	EdgeOne
9473	Report task (\$0) started	\$0: report task name	EdgeOne
9474	Report task (\$0) completed	\$0: report task name	EdgeOne
9475	Scheduled report task (\$0) started	\$0: report task name	EdgeOne
9476	Scheduled report task (\$0) completed	\$0: report task name	EdgeOne
9477	Report generated successfully (\$0)	\$0: report task name	EdgeOne
9478	Report generated failed (\$0) - (\$1)	\$0: report task name \$1: error code	EdgeOne
9479	Report sent successfully via email (\$0)	\$0: report task name	EdgeOne
9480	Report sent failed via email (\$0) - (\$1)	\$0: report task name \$1: error code	EdgeOne
12289	DPI pattern metadata updated	None	EdgeOne
12290	Unable to update DPI pattern metadata - (\$0)	\$0: error code	EdgeOne
12291	System pattern metadata updated	None	EdgeOne
12292	Unable to update system pattern metadata - (\$0)	\$0: error code	EdgeOne
12545	Device (\$0) connected	\$0: device S/N	EdgeOne
12546	Device (\$0) disconnected	\$0: device S/N	EdgeOne
12547	Sync (\$0) device group (\$1) settings to device (\$2) successful	\$0: Product name, e.g., "EdgeFire" \$1: device group name \$2: device S/N	EdgeOne
12548	Unable to sync (\$0) device group (\$1) settings to device (\$2) - (\$3)	\$0: Product name, e.g., "EdgeFire" \$1: device group name \$2: device S/N \$3: error code	EdgeOne
12549	Device \$0 deactivated	\$0: device S/N	EdgeOne
12550	Device \$0 activated	\$0: device S/N	EdgeOne
12801	System firmware upgrade started	None	EdgeOne
12802	System pattern upgrade started	None	EdgeOne
12803	System pattern upgraded successfully	None	EdgeOne

12804	System pattern upgraded failed	None	EdgeOne
12805	System firmware upgrade failed	\$0: the upgrade step	EdgeOne
12806	System firmware upgrade successfully	None	EdgeOne
13057	SNMP agent started at port \$0	\$0: the snmp port number	EdgeOne
13058	SNMP agent stopped	None	EdgeOne
13059	Unable to decode SNMP v3 USM user (\$0) settings. Please delete the current settings and configure new ones.	\$0: the SNMP USM user	EdgeOne
13060	Legacy SNMP settings migrated successfully	None	EdgeOne
13061	Failed to migrate legacy SNMP settings	None	EdgeOne
13313	Suspicious objects have been purged by scheduled job	None	EdgeOne
13314	Suspicious objects have been purged	None	EdgeOne
13315	Reload port security settings of Slot (\$0) from device (\$1) (\$2) - Slot card is changed	\$0: slot name, e.g., "SLOT1" \$1: Product name, e.g., "EdgeIPS Pro" \$2: device S/N	EdgeOne
13316	Reload port security settings from device (\$0) (\$1) - Offline mode unsupported	\$0: Product name, e.g., "EdgeIPS Pro" \$1: device S/N	EdgeOne
13569	Logs of (\$0) before (\$1) has been purged	\$0: table name \$1: hour(s)	EdgeOne
13570	All logs in (\$0) has been purged	\$0: table name	EdgeOne
13571	Reindex continuous aggregate view of table (\$0)	\$0: table name	EdgeOne
14081	The API key named is changed from (\$0) to (\$1) after preparation for restoring config	\$0: original API key name \$1: new API key name	EdgeOne

5 Appendix B: Audit Event IDs and Messages

The pre-defined audit event IDs and the corresponding messages are listed in the following table.

ID	Message	Arguments	Products
1	User (\$0) login	\$0: Account ID	IPS/IEF/IPSP
2	User (\$0) logout	\$0: Account ID	IPS/IEF/IPSP
3	User (\$0) timeout, force logout	\$0: Account ID	IPS/IEF/IPSP
42	User (\$0) login failed	\$0: Account ID	IPS/IEF/IPSP
43	User (\$0) changed password	\$0: Account ID	IPS/IEF/IPSP
48	User (\$0) added user account (\$1)	\$0: Account ID \$1: the user account ID being created	IPS/IEF/IPSP
49	User (\$0) deleted user account (\$1)	\$0: Account ID \$1: the user account ID being deleted	IPS/IEF/IPSP
50	User (\$0) modified user account (\$1)	\$0: Account ID \$1: the user account ID being modified	IPS/IEF/IPSP
51	User (\$0) changed password policy	\$0: Account ID	IPS/IEF/IPSP
52	User (\$0) changed user account (\$1) to (\$2)	\$0: Account ID \$1: the original user account ID \$2: the new user account ID	IPS/IEF/IPSP
53	User (\$0) changed user account (\$1) password	\$0: Account ID \$1: the user account ID being changed	IPS/IEF/IPSP
54	User (\$0) changed user account (\$1) authentication type (\$2)	\$0: Account ID \$1: the user account ID being modified \$2: local, tacacs+, local and tacacs+	IPS/IEF/IPSP
55	User (\$0) enabled tacacs+ setting	\$0: Account ID	IPS/IEF/IPSP
56	User (\$0) disabled tacacs+ setting	\$0: Account ID	IPS/IEF/IPSP
57	User (\$0) changed tacacs+ setting	\$0: Account ID	IPS/IEF/IPSP
58	User (\$0) enabled radius setting	\$0: Account ID	IPS/IEF/IPSP
59	User (\$0) disabled radius setting	\$0: Account ID	IPS/IEF/IPSP
60	User (\$0) changed radius setting	\$0: Account ID	IPS/IEF/IPSP

64	User (\$0) changed device name to (\$1)	\$0: Account ID \$1: Device Name	IPS/IEF/IPSP
65	User (\$0) enabled Access Control List	\$0: Account ID	IPS/IEF/IPSP
66	User (\$0) disabled Access Control List	\$0: Account ID	IPS/IEF/IPSP
67	User (\$0) modified Access Control List	\$0: Account ID	IPS/IEF/IPSP
68	User (\$0) changed Web service to (\$1)	\$0: Account ID \$1: New web service (HTTP/80, or HTTPS/443)	IPS/IEF/IPSP
69	User (\$0) enabled SSH service - (\$1)	\$0: Account ID \$1: SSH port	IPS/IEF/IPSP
70	User (\$0) disabled SSH service	\$0: Account ID	IPS/IEF/IPSP
71	User (\$0) enabled Telnet service - (\$1)	\$0: Account ID \$1: Telnet port	IPS/IEF/IPSP
72	User (\$0) disabled Telnet service	\$0: Account ID	IPS/IEF/IPSP
73	User (\$0) enabled allow ping to management interface	\$0: Account ID	IPS/IEF/IPSP
74	User (\$0) disabled allow ping to management interface	\$0: Account ID	IPS/IEF/IPSP
75	User (\$0) enabled access from WAN	\$0: Account ID	IEF
76	User (\$0) disabled access from WAN	\$0: Account ID	IEF
77	User (\$0) changed device location to (\$1)	\$0: Account ID \$1: Location	IPS/IEF/IPSP
78	User (\$0) purged EdgeOne rules and profiles	\$0: Account ID	IPS/IEF/IPSP
79	User (\$0) changed EdgeOne server to (\$1) with authentication method (\$2)	\$0: Account ID \$1: EdgeOne Address \$2: Edge Authentication Method	IPS/IEF/IPSP
81	User (\$0) disabled EdgeOne management	\$0: Account ID	IPS/IEF/IPSP
82	User (\$0) changed syslog settings	\$0: Account ID	IPS/IEF/IPSP
83	User (\$0) changed system time (\$1)	\$0: Account ID \$1: new system time in ISO 8601, e.g., "2019-11-11T18:12:14Z"	IPS/IEF/IPSP

84	User (\$0) enabled NTP synchronization (\$1)	\$0: Account ID \$1: NTP server	IPS/IEF/IPSP
85	User (\$0) disabled NTP synchronization	\$0: Account ID	IPS/IEF/IPSP
86	User (\$0) synchronized system time with NTP server (\$0)	\$0: Account ID \$1: NTP server	IPS/IEF/IPSP
87	User (\$0) changed time zone to (\$1)	\$0: Account ID \$1: new time zone ID, e.g., "(GMT+08:00) Asia/Taipei"	IPS/IEF/IPSP
88	User (\$0) upgraded firmware to (\$1)	\$0: Account ID \$1: Firmware Version	IPS/IEF/IPSP
89	User (\$0) switched boot partition to (\$1)	\$0: Account ID \$1: Partition Name	IPS/IEF/IPSP
90	User (\$0) updated IPS pattern to (\$1)	\$0: Account ID \$1: Pattern Version	IPS/IEF/IPSP
91	User (\$0) has backed up system settings to local file	\$0: Account ID	IPS/IEF/IPSP
92	User (\$0) restored system settings from local file	\$0: Account ID	IPS/IEF/IPSP
93	User (\$0) rebooted system	\$0: Account ID	IPS/IEF/IPSP
94	User (\$0) powered off system	\$0: Account ID	IPS/IEF/IPSP
95	User (\$0) updated antivirus pattern to (\$1)	\$0: Account ID \$1: Antivirus Pattern Version	IPSP
96	User (\$0) enabled IPS Profile (\$1) for system self protection	\$0: Account ID \$1: Profile Name	IPS/IEF/IPS
97	User (\$0) disabled IPS Profile for system self protection	\$0: Account ID	IPS/IEF/IPS
98	User (\$0) enabled DoS Prevention Mode for system self protection	\$0: Account ID	IPS/IEF/IPS
99	User (\$0) disabled DoS Prevention Mode for system self protection	\$0: Account ID	IPS/IEF/IPS
100	User (\$0) enabled DoS Prevention for (\$1) - Threshold (\$2) for system self protection	\$0: Account ID \$1: Rule Name \$2: Threshold Value	IPS/IEF/IPS
101	User (\$0) disabled DoS Prevention for (\$1) for system self protection	\$0: Account ID \$1: Rule Name	IPS/IEF/IPS
102	User (\$0) created api key (\$1)	\$0: Account ID \$1: API Key ID	IPS/IEF/IPS

103	User (\$0) modified api key (\$1)	\$0: Account ID \$1: API Key ID	IPS/IEF/IPS
104	User (\$0) deleted api key (\$1)	\$0: Account ID \$1: API Key ID	IPS/IEF/IPS
105	User (\$0) renewed secret of api key (\$1)	\$0: Account ID \$1: API Key ID	IPS/IEF/IPS
112	User (\$0) changed device IP to (\$1)	\$0: Account ID \$1: New device IP address	IPS/IPSP
113	User (\$0) changed device Netmask to (\$1)	\$0: Account ID \$1: New device netmask	IPS/IPSP
114	User (\$0) changed device gateway to (\$1)	\$0: Account ID \$1: New device gateway	IPS/IPSP
115	User (\$0) changed DNS to (\$1)	\$0: Account ID \$1: New DNS	IPS/IPSP
116	User (\$0) changed VLAN ID to (\$1)	\$0: Account ID \$1: VLAN ID (0 indicates VLAN ID disabled)	IPS/IPSP
117	User (\$0) changed port (\$1) link mode to (\$2)	\$0: Account ID \$1: Port number \$2: New link mode	IPS/IEF
118	User (\$0) enabled LLDP transmit	\$0: Account ID	IPSP
119	User (\$0) disabled LLDP transmit	\$0: Account ID	IPSP
120	User (\$0) enabled Independent MGMT Port	\$0: Account ID	IEF
121	User (\$0) disabled Independent MGMT Port	\$0: Account ID	IEF
128	User (\$0) added IP object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP
129	User (\$0) modified IP object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP
130	User (\$0) deleted IP object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP
131	User (\$0) added service object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP
132	User (\$0) deleted service object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP

133	User (\$0) modified service object (\$1)	\$0: Account ID \$1: Object name	IPS/IEF/IPSP
134	User (\$0) added protocol filter profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IEF/IPSP
135	User (\$0) deleted protocol filter profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IEF/IPSP
136	User (\$0) modified protocol filter profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IEF/IPSP
137	User (\$0) added ips profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IPSP
138	User (\$0) deleted ips profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IPSP
139	User (\$0) modified ips profile (\$1)	\$0: Account ID \$1: Profile name	IPS/IPSP
140	User (\$0) added Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPS/IPSP
141	User (\$0) deleted Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPS/IPSP
142	User (\$0) modified Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPS/IPSP
144	User (\$0) changed Security Operation Mode to (\$1)	\$0: Account ID \$1: Inline Mode or Offline Mode	IPS
145	User (\$0) enabled Intrusion Prevention - (\$1)	\$0: Account ID \$1: Monitor Mode or Prevention Mode	IPS/IEF
146	User (\$0) disabled Intrusion Prevention	\$0: Account ID	IPS/IEF
147	User (\$0) enabled DoS Prevention - (\$1)	\$0: Account ID \$1: Monitor Mode or Prevention Mode	IPS/IEF
148	User (\$0) disabled DoS Prevention	\$0: Account ID	IPS/IEF
149	User (\$0) enabled Policy Enforcement - (\$1)	\$0: Account ID \$1: Monitor Mode or Prevention Mode	IPS/IEF
150	User (\$0) disabled Policy Enforcement	\$0: Account ID	IPS/IEF
151	User (\$0) enabled DoS Prevention for (\$1) - Threshold (\$2)	\$0: Account ID	IPS/IEF

		\$1: Rule name \$2: Threshold	
152	User (\$0) disabled DoS Prevention for (\$1)	\$0: Account ID \$1: Rule name	IPS/IEF
153	User (\$0) added Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule name	IPS/IEF
154	User (\$0) deleted Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule name	IPS/IEF
155	User (\$0) modified Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule name	IPS/IEF
156	User (\$0) changed Policy Enforcement rules priorities	\$0: Account ID	IPS/IEF
157	User (\$0) enabled Policy Enforcement - (\$1) default action (\$2)	\$0: Account ID; \$1: Monitor Mode or Prevention Mode; \$2: Deny or Accept	IPS/IEF
160	User (\$0) enabled active query	\$0: Account ID	IPS/IEF
161	User (\$0) disabled active query	\$0: Account ID	IPS/IEF
162	User (\$0) reset asset information	\$0: Account ID	IPSP
163	API user (\$0) enabled Policy Enforcement - (\$1) default action (\$2)	\$0: The name of the API Key \$1: Monitor Mode or Prevention Mode \$2: Deny or Accept	IPS/IEF
163	API user (\$0) enabled Policy Enforcement - (\$1) default action (\$2)	\$0: The name of the API Key \$1: Rule Name	IPS/IEF
164	API user (\$0) disabled Policy Enforcement	\$0: The name of the API Key	IPS/IEF
165	API user (\$0) enabled Policy Enforcement Rule (\$1)	\$0: The name of the API Key \$1: Rule Name	IPS/IEF
166	API user (\$0) disabled Policy Enforcement Rule (\$1)	\$0: The name of the API Key \$1: Rule Name	IPS/IEF
167	User (\$0) added L2 Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPSP
168	User (\$0) deleted L2 Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPSP
169	User (\$0) modified L2 Policy Enforcement rule set (\$1)	\$0: Account ID \$1: Rule set name	IPSP
170	User (\$0) enabled Domain Name Filter - (\$1) default action (\$2)	\$0: Account ID \$1: Monitor Mode or Prevention	IPSP

		Mode \$2: Accept, AcceptAndLog, Deny	
171	User (\$0) disabled Domain Name Filter	\$0: Account ID	IPSP
172	User (\$0) added Domain Name Filter rule (\$1)	\$0: Account ID \$1: Rule Name	IPSP
173	User (\$0) deleted Domain Name Filter rule (\$1)	\$0: Account ID \$1: Rule Name	IPSP
174	User (\$0) modified Domain Name Filter rule (\$1)	\$0: Account ID \$1: Rule Name	IPSP
175	User (\$0) changed Domain Name Filter rule priorities	\$0: Account ID	IPSP
176	User (\$0) added file filter profile (\$1)	\$0:Account ID \$1: Profile name	IPSP/IPS/IEF
177	User (\$0) deleted file filter profile (\$1)	\$0:Account ID \$1: Profile name	IPSP/IPS/IEF
178	User (\$0) modified file filter profile (\$1)	\$0:Account ID \$1: Profile name	IPSP/IPS/IEF
179	User (\$0) added antivirus profile (\$1)	\$0: Account ID \$1: Profile name	IPSP
180	User (\$0) deleted antivirus profile (\$1)	\$0: Account ID \$1: Profile name	IPSP
181	User (\$0) modified antivirus profile (\$1)	\$0: Account ID \$1: Profile name	IPSP
182	User (\$0) changed file exceptions of antivirus.	\$0: Account ID	IPSP
183	User (\$0) changed file exclusions of file filter.	\$0: Account ID	IPSP/IPS/IEF/IP SLE
184	User (\$0) added MAC Object (\$1)	\$0: Account ID \$1: Object name	IPS
185	User (\$0) deleted MAC Object (\$1)	\$0: Account ID \$1: Object name	IPS
186	User (\$0) modified MAC Object (\$1)	\$0: Account ID \$1: Object name	IPS
187	User (\$0) added Domain Name Object (\$1)	\$0: Account ID \$1: Object name	(IPSP)
188	User (\$0) deleted Domain Name Object (\$1)	\$0: Account ID \$1: Object name	(IPSP)

189	User (\$0) modified Domain Name Object (\$1)	\$0: Account ID \$1: Object name	(IPSP)
256	User (\$0) enabled port (\$1)	\$0: Account ID \$1: Port number	IEF
257	User (\$0) disabled port (\$1)	\$0: Account ID \$1: Port number	IEF
258	User (\$0) mapped port (\$1) to interface (\$2)	\$0: Account ID \$1: Port number \$2: interface name	IEF
272	User (\$0) enabled interface (\$1)	\$0: Account ID \$1: interface name	IEF
273	User (\$0) disabled interface (\$1)	\$0: Account ID \$1: interface name	IEF
274	User (\$0) changed interface (\$1) connection type to (\$2)	\$0: Account ID \$1: interface name \$2: Static / DHCP Client / PPPoE	IEF
275	User (\$0) changed interface (\$1) DHCP service to (\$2)	\$0: Account ID \$1: interface name \$2: DHCP Server / DHCP Relay	IEF
276	User (\$0) disabled interface (\$1) DHCP service	\$0: Account ID \$1: interface name	IEF
277	User (\$0) changed interface (\$1) IP to (\$2)	\$0: Account ID \$1: interface name \$2: New device IP address	IEF
278	User (\$0) changed interface (\$1) netmask to (\$2)	\$0: Account ID \$1: interface name \$1: New device netmask	IEF
279	User (\$0) changed interface (\$1) gateway to (\$2)	\$0: Account ID \$1: interface name \$2: New device gateway	IEF
280	User (\$0) changed interface (\$1) DNS to (\$2)	\$0: Account ID \$1: interface name \$2: New DNS	IEF
281	User (\$0) changed interface (\$1) VLAN ID to (\$2)	\$0: Account ID \$1: interface name \$2: VLAN ID (0 indicates VLAN ID disabled)	IEF

282	User (\$0) changed management port to (\$1)	\$0: Account ID \$1: port number	IPS
283	User (\$0) changed Network Operation Mode to (\$1)	\$0: Account ID \$1: Gateway Mode or Bridge Mode	IEF
284	User (\$0) enabled Spanning Tree Protocol	\$0: Account ID	IEF (bridge mode)
285	User (\$0) disabled Spanning Tree Protocol	\$0: Account ID	IEF (bridge mode)
288	User (\$0) added Static Route (\$1)	\$0: Account ID \$1: Name	IEF
289	User (\$0) deleted Static Route (\$1)	\$0: Account ID \$1: Name	IEF
290	User (\$0) modified Static Route (\$1)	\$0: Account ID \$1: Name	IEF
304	User (\$0) enabled ALG (\$1)	\$0: Account ID \$1: service name	IEF
305	User (\$0) disabled ALG (\$1)	\$0: Account ID \$1: service name	IEF
306	User (\$0) added NAT Rule (\$1)	\$0: Account ID \$1: Rule Name	IEF
307	User (\$0) deleted NAT Rule (\$1)	\$0: Account ID \$1: Rule Name	IEF
308	User (\$0) modified NAT Rule (\$1)	\$0: Account ID \$1: Rule Name	IEF
309	User (\$0) changed NAT rules priorities	\$0: Account ID	IEF
320	User (\$0) changed Security Mode to (\$1) for port (\$2)	\$0: Account ID \$1: Security Operation Mode \$2: Slot Name:Port Name	IPSP
322	User (\$0) enabled policy enforcement (\$1) for port (\$2)	\$0: Account ID \$1: Policy Enforcement Rule Set Name \$2: Slot Name:Port Name	IPSP
323	User (\$0) disabled policy enforcement for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
324	User (\$0) enabled DoS prevention setting for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
325	User (\$0) disabled DoS prevention setting for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP

326	User (\$0) changed rules of DoS prevention setting for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
327	User (\$0) changed hardware bypass mode to (\$1) for port (\$2)	\$0: Account ID \$1: HW Bypass Mode \$2: Slot Name:Port Name	IPSP
328	User (\$0) enabled port mirror	\$0: Account ID	IPSP
329	User (\$0) disabled port mirror	\$0: Account ID	IPSP
330	User (\$0) changed port mirror setting	\$0: Account ID	IPSP
331	User (\$0) enabled HA setting	\$0: Account ID	IPSP
332	User (\$0) disabled HA setting	\$0: Account ID	IPSP
333	User (\$0) changed HA setting	\$0: Account ID	IPSP
334	User (\$0) enabled LFPT for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
335	User (\$0) disabled LFPT for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
339	User (\$0) enabled bandwidth control on port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
340	User (\$0) disabled bandwidth control on port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
341	User (\$0) changed port (\$1) egress rate limit to (\$2)	\$0: Account ID \$1: Slot Name:Port Name \$2: new rate limit	IPSP
352	User (\$0) enabled USB application setting	\$0: Account ID	IPS/IEF/IPSP
353	User (\$0) disabled USB application setting	\$0: Account ID	IPS/IEF/IPSP
354	User (\$0) changed USB application setting	\$0: Account ID	IPS/IEF/IPSP
355	User (\$0) enabled packet capture setting	\$0: Account ID	IPSP
356	User (\$0) disabled packet capture setting	\$0: Account ID	IPSP
357	User (\$0) changed packet capture setting	\$0: Account ID	IPSP
368	User (\$0) enabled SNMP setting on port (\$1)	\$0: Account ID \$1: port number	IPS/IEF/IPSP

369	User (\$0) disabled SNMP setting	\$0: Account ID	IPS/IEF/IPSP
370	User (\$0) changed SNMP setting version (\$1)	\$0: Account ID \$1: v1/v2c and/or v3	IPS/IEF/IPSP
371	User (\$0) changed SNMP trap messages	\$0: Account ID	IPS/IEF/IPSP
372	User (\$0) enabled vlan trunk setting	\$0: Account ID	IEF
373	User (\$0) disabled vlan trunk setting	\$0: Account ID	IEF
374	User (\$0) changed vlan trunk setting	\$0: Account ID	IEF
375	User (\$0) added ddns setting profile (\$1)	\$0: Account ID \$1: Profile name	IEF
376	User (\$0) modified ddns setting profile (\$1)	\$0: Account ID \$1: Profile name	IEF
377	User (\$0) deleted ddns setting profile (\$1)	\$0: Account ID \$1: Profile name	IEF
384	User (\$0) enabled suspicious object setting	\$0: Account ID	IPS
385	User (\$0) disabled suspicious object setting	\$0: Account ID	IPS
386	User (\$0) changed suspicious object operation mode to (\$1)	\$0: Account ID \$1: Mode	IPS
387	User (\$0) changed actions of suspicious object list	\$0: Account ID	IPS
388	User (\$0) created the auto-learning task	\$0: Account ID	IPS/IEF
389	User (\$0) stopped the auto-learning task	\$0: Account ID	IPS/IEF
390	User (\$0) canceled the auto-learning task	\$0: Account ID	IPS/IEF
391	User (\$0) deleted the auto-learning result	\$0: Account ID	IPS/IEF
392	User (\$0) generated the policy enforcement rules and the protocol filter profiles via auto-learning	\$0: Account ID	IPS/IEF
400	User (\$0) requested sync-up and sent the configuration to the Peer.	\$0: Account ID	IEF
416	User (\$0) enabled L2 Policy Enforcement - (\$1) default action (\$2)	\$0: Account ID	IPS

		\$1: Monitor Mode or Prevention Mode \$2: Deny or Accept	
417	User (\$0) disabled L2 Policy Enforcement	\$0: Account ID	IPS
418	User (\$0) added L2 Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule Name	IPS
419	User (\$0) deleted L2 Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule Name	IPS
420	User (\$0) modified L2 Policy Enforcement Rule (\$1)	\$0: Account ID \$1: Rule Name	IPS
421	User (\$0) changed L2 Policy Enforcement rules priorities	\$0: Account ID	IPS
422	User (\$0) updated logout timer to (\$1) minutes.	\$0: Account ID \$1: New timeout duration	IPS/IEF/IPSP
423	User (\$0) added IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF
424	User (\$0) deleted IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF
425	User (\$0) modified IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF
426	User (\$0) renamed IPsec VPN profile (\$1) to (\$2)	\$0:Account ID \$1: The old profile name \$2: The new profile name	IEF
427	User (\$0) enabled IPsec VPN profile- (\$1)	\$0:Account ID \$1: Profile name	IEF
428	User (\$0) disabled IPsec VPN profile- (\$1)	\$0:Account ID \$1: Profile name	IEF
429	User (\$0) set IPsec VPN default gateway to (\$1)	\$0:Account ID \$1: Profile name (if user set to empty \$1= disabled)	IEF
430	User (\$0) added L2TP/IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF
431	User (\$0) deleted L2TP/IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF
432	User (\$0) modified L2TP/IPsec VPN profile (\$1)	\$0:Account ID \$1: Profile name	IEF

433	User (\$0) renamed IPSec VPN profile (\$1) to (\$2)	\$0:Account ID \$1: The old profile name \$2: The new profile name	IEF
434	User (\$0) enabled L2TP/IPSec VPN profile- (\$1)	\$0:Account ID \$1: Profile name	IEF
435	User (\$0) disabled L2TP/IPSec VPN profile- (\$1)	\$0:Account ID \$1: Profile name	IEF
436	User (\$0) changed L2TP/IPSec VPN settings	\$0:Account ID	IEF
437	User (\$0) activated (\$1) VPN Profile (\$2)	\$0:Account ID \$1: VPN type(IPSec, L2TP/IPSec) \$2 : Profile name	IEF
438	User (\$0) dropped (\$1) VPN Profile (\$2)	\$0:Account ID \$1: VPN type(IPSec, L2TP/IPSec) \$2 : Profile name	IEF
439	User (\$0) triggered PPPoE connection activation on (\$1)	\$0: Account ID \$1: WAN interface name	IEF
440	User (\$0) triggered PPPoE connection drop on (\$1)	\$0: Account ID \$1: WAN interface name	IEF
441	User (\$0) changed (\$1) PPPoE username to (\$2)	\$0: Account ID \$1: WAN interface name \$2: New PPPoE connect username	IEF
442	User (\$0) changed (\$1) PPPoE password	\$0: Account ID \$1: WAN interface name	IEF
443	User (\$0) changed (\$1) PPPoE DNS to (\$2)	\$0: Account ID \$1: WAN interface name \$2: New DNS	
444	User (\$0) changed (\$1) PPPoE MTU to (\$2)	\$0: Account ID \$1: WAN interface name \$2: MTU value	IEF
445	User (\$0) changed (\$1) PPPoE reconnection mode to (\$2)	\$0: Account ID \$1: WAN interface name \$2: Reconnection mode	IEF
446	User (\$0) changed (\$1) PPPoE retry interval to (\$2)	\$0: Account ID \$1: WAN interface name	IEF

		\$2: Retry interval	
447	User (\$0) changed (\$1) PPPoE idle timeout to (\$2)	\$0: Account ID \$1: WAN interface name \$2: Idle timeout	IEF
449	User (\$0) enabled L2TP/IPSec VPN settings	\$0:Account ID	IEF
450	User (\$0) disabled L2TP/IPSec VPN settings	\$0:Account ID	IEF
451	User (\$0) changed Policy Enforcement Operation Mode to (\$1) for port (\$2)	\$0: Account ID \$1: Operation Mode \$2: Slot Name:Port Name	IPSP
452	User (\$0) changed L2 Policy Enforcement Operation Mode to (\$1) for port (\$2)	\$0: Account ID \$1: Operation Mode \$2: Slot Name:Port Name	IPSP
453	User (\$0) changed DoS Prevention Operation Mode to (\$1) for port (\$2)	\$0: Account ID \$1: Operation Mode \$2: Slot Name:Port Name	IPSP
454	User (\$0) enabled L2 policy enforcement (\$1) for port (\$2)	\$0: Account ID \$1: L2 Policy Enforcement Rule Set Name \$2: Slot Name:Port Name	IPSP
455	User (\$0) disabled L2 policy enforcement for port (\$1)	\$0: Account ID \$1: Slot Name:Port Name	IPSP
456	User (\$0) changed port (\$1) Port Pair Mode to (\$2)	\$0: Account ID \$1: Slot Name:Port Name \$2: New Port Pair Mode	IPSP
8193	User (\$0) login	\$0: Account ID	EdgeOne
8194	User (\$0) login failed	\$0: Account ID	EdgeOne
8195	User (\$0) logout	\$0: Account ID	EdgeOne
8196	User (\$0) timeout, force logout	\$0: Account ID	EdgeOne
8197	User (\$0) changed password	\$0: Account ID	EdgeOne
8198	User (\$0) SSO login	\$0: Account ID	EdgeOne
8199	User (\$0) SSO login failed	\$0: Account ID	EdgeOne
8200	User (\$0) changed logout timer to (\$1) minutes	\$0: Account ID \$1: Minutes	EdgeOne
8208	Reset admin account from vshell	None	EdgeOne

8209	User (\$0) created user account (\$1)	\$0: Account ID \$1: User account ID being created	EdgeOne
8210	Add user account (\$0) failed -- (\$1)	\$0: Account ID	EdgeOne
8211	User (\$0) deleted user account (\$1)	\$0: Account ID \$1: User account ID being deleted	EdgeOne
8212	User (\$0) modified user account (\$1)	\$0: Account ID \$1: User account ID being modified	EdgeOne
8213	User (\$0) changed user account (\$1) to (\$2)	\$0: Account ID \$1: Original user account ID \$2: New user account ID	EdgeOne
8214	User (\$0) changed user account (\$1) password	\$0: Account ID \$1: User account ID being changed	EdgeOne
8215	User (\$0) changed password policy	\$0: Account ID	EdgeOne
8216	User (\$0) changed password expiration settings	\$0: Account ID	EdgeOne
8217	User (\$0) changed brute-force login prevention settings	\$0: Account ID	EdgeOne
8224	User (\$0) changed user account (\$1) authentication type (\$2)	\$0: Account ID \$1: User account ID being changed \$2: Authenticate Type	EdgeOne
8225	User (\$0) changed system time (\$1)	\$0: Account ID \$1: new system time in ISO 8601, e.g., "2019-11-11T18:12:14Z"	EdgeOne
8226	User (\$0) enabled NTP synchronization (\$1)	\$0: Account ID \$1: NTP server	EdgeOne
8227	User (\$0) disabled NTP synchronization	\$0: Account ID	EdgeOne
8228	User (\$0) synchronized system time with NTP server (\$0)	\$0: Account ID \$1: NTP server	EdgeOne
8229	User (\$0) changed time zone to (\$1)	\$0: Account ID \$1: new time zone ID, e.g., "(GMT+08:00) Asia/Taipei"	EdgeOne
8230	User (\$0) enable SSO SAML	\$0: Account ID	EdgeOne
8231	User (\$0) disable SSO SAML	\$0: Account ID	EdgeOne

8232	User (\$0) changed SSO SAML settings	\$0: Account ID	EdgeOne
8241	User (\$0) changed syslog settings	\$0: Account ID	EdgeOne
8242	User (\$0) created the syslog setting (\$1)	\$0: Account ID \$1: Setting Name	EdgeOne
8243	User (\$0) changed the syslog setting (\$1)	\$0: Account ID \$1: Setting Name	EdgeOne
8244	User (\$0) deleted the syslog setting (\$1)0x2129	\$0: Account ID \$1: Setting Name	EdgeOne
8245	User (\$0) updated the proxy setting	\$0: Account ID	EdgeOne
8257	User (\$0) changed (\$1) scheduled update settings	\$0: Account ID \$1: component name, e.g., "Trend Micro DPI Pattern"	EdgeOne
8258	User (\$0) updated (\$1) version (\$2) from update server	\$0: Account ID \$1: component name, e.g., "Trend Micro DPI Pattern" \$2: component version	EdgeOne
8259	User (\$0) imported (\$1) version (\$2) from local file	\$0: Account ID \$1: component name, e.g., "Trend Micro DPI Pattern" \$2: component version	EdgeOne
8260	User (\$0) deleted (\$1) version (\$2)	\$0: Account ID \$1: component name, e.g., "Trend Micro DPI Pattern" \$2: component version	EdgeOne
8273	User (\$0) changed SSL certificate	\$0: Account ID	EdgeOne
8289	User (\$0) executed "Purge Now"	\$0: Account ID	EdgeOne
8290	User (\$0) changed auto-purge settings	\$0: Account ID	EdgeOne
8305	User (\$0) has backed up system settings to local file	\$0: Account ID	EdgeOne
8306	User (\$0) restored system settings from local file	\$0: Account ID	EdgeOne
8321	User (\$0) applied firmware upgrade	\$0:Account ID	EdgeOne
8322	User (\$0) canceled firmware upgrade	\$0:Account ID	EdgeOne
8337	User (\$0) changed smtp server settings	\$0:Account ID	EdgeOne

8338	User (\$0) sent a test email	\$0: Account ID	EdgeOne
8339	User (\$0) changed event notification settings	\$0: Account ID	EdgeOne
8465	User (\$0) created (\$1) device group (\$2)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Group name	EdgeOne
8466	User (\$0) deleted (\$1) device group (\$2)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Group name	EdgeOne
8467	User (\$0) changed (\$1) device group (\$2) settings	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Group name	EdgeOne
8468	User (\$0) changed (\$1) device group (\$2) permissions	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Group name	EdgeOne
8469	User (\$0) changed device (\$1) port (\$2-\$3) security settings	\$0: Account ID \$1: Device SN \$2: slot \$3: port	EdgeOne
8470	User (\$0) updated Cyber Security Settings for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8471	User (\$0) created (\$1) in the Policy Enforcement Settings for device group (\$2)	\$0: Account ID \$1: Profile name \$2: Group name	EdgeOne
8472	User (\$0) updated Policy Enforcement Settings for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8473	User (\$0) deleted (\$1) in the Policy Enforcement Settings for device group (\$2)	\$0: Account ID \$1: Profile name \$2: Group name	EdgeOne
8480	User (\$0) created (\$1) in the IP Object Settings for device group (\$2)	\$0: Account ID \$1: IP object name \$2: Group name	EdgeOne
8481	User (\$0) updated (\$1) in the IP Object Settings for device group (\$2)	\$0: Account ID \$1: IP object name \$2: Group name	EdgeOne

8482	User (\$0) deleted (\$1) in the IP Object Settings for device group (\$2)	\$0: Account ID \$1: IP object name \$2: Group name	EdgeOne
8483	User (\$0) created (\$1) in the Service Object Settings for device group (\$2)	\$0: Account ID \$1: Service object name \$2: Group name	EdgeOne
8484	User (\$0) updated (\$1) in the Service Object Settings for device group (\$2)	\$0: Account ID \$1: Service object name \$2: Group name	EdgeOne
8485	User (\$0) deleted (\$1) in the Service Object Settings for device group (\$2)	\$0: Account ID \$1: Service object name \$2: Group name	EdgeOne
8486	User (\$0) created (\$1) in the Protocol Filter Settings for device group (\$2)	\$0: Account ID \$1: Protocol Filter name \$2: Group name	EdgeOne
8487	User (\$0) updated (\$1) in the Protocol Filter Settings for device group (\$2)	\$0: Account ID \$1: Protocol Filter name \$2: Group name	EdgeOne
8488	User (\$0) deleted (\$1) in the Protocol Filter Settings for device group (\$2)	\$0: Account ID \$1: Protocol Filter name \$2: Group name	EdgeOne
8489	User (\$0) created (\$1) in the IPS Profile Settings for device group (\$2)	\$0: Account ID \$1: IPS profile name \$2: Group name	EdgeOne
8496	User (\$0) updated (\$1) in the IPS Profile Settings for device group (\$2)	\$0: Account ID \$1: IPS profile name \$2: Group name	EdgeOne
8497	User (\$0) deleted (\$1) in the IPS Profile Settings for device group (\$2)	\$0: Account ID \$1: IPS profile name \$2: Group name	EdgeOne
8498	User (\$0) updated Pattern Settings for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8499	User (\$0) updated (\$1) in the Policy Enforcement Settings for device group (\$2)	\$0: Account ID \$1: Policy enforcement rule name \$2: Group name	EdgeOne

8500	User (\$0) created (\$1) in the File Filter Settings for device group (\$2)	\$0: Account ID \$1: File filter name \$2: Group name	EdgeOne
8501	User (\$0) updated (\$1) in the File Filter Settings for device group (\$2)	\$0: Account ID \$1: File filter name \$2: Group name	EdgeOne
8502	User (\$0) deleted (\$1) in the File Filter Settings for device group (\$2)	\$0: Account ID \$1: File filter name \$2: Group name	EdgeOne
8503	User (\$0) updated the Packet Capture Settings for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8504	User (\$0) updated the Suspicious Object Filter for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8505	User (\$0) updated the Suspicious Object Priority for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8512	User (\$0) updated the Suspicious Object Settings for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8513	User (\$0) created (\$1) in the AntiVirus Profile for device group (\$2)	\$0: Account ID \$1: Profile name \$2: Group name	EdgeOne
8514	User (\$0) updated (\$1) in the AntiVirus Profile for device group (\$2)	\$0: Account ID \$1: Profile name \$2: Group name	EdgeOne
8515	User (\$0) deleted (\$1) in the AntiVirus Profile for device group (\$2)	\$0: Account ID \$1: Profile name \$2: Group name	EdgeOne
8516	User (\$0) updated AntiVirus Pattern to (\$1) for device group (\$2)	\$0: Account ID \$1: Pattern version \$2: Group name	EdgeOne
8517	User (\$0) enabled DoS Prevention - (\$1) for device group (\$2)	\$0: Account ID \$1: Action mode \$2: Group name	EdgeOne
8518	User (\$0) disabled DoS Prevention for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8519	User (\$0) enabled DoS Prevention for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number	EdgeOne

		\$2: Slot name \$3: Port Name	
8520	User (\$0) disabled DoS Prevention for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number \$2: Slot name \$3: Port Name	EdgeOne
8521	User (\$1) enabled Policy Enforcement - (\$1) default action (\$2) for device group (\$3)	\$0: Account ID \$1: Monitor mode or Prevention Mode \$2: Action \$3: Group name	EdgeOne
8528	User (\$0) disabled Policy Enforcement for device group (\$1)	\$0: Account ID \$1: Group name	EdgeOne
8529	User (\$0) enabled Policy Enforcement - (\$1) for device (\$2) port (\$3:\$4)	\$0: Account ID \$1: Rule set name \$2: Device serial number \$3: Slot name \$4: Port name	EdgeOne
8530	User (\$0) disabled Policy Enforcement for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number \$2: Slot name \$3: Port name	EdgeOne
8532	User (\$0) changed rules of DoS prevention setting for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number \$2: Slot name \$3: Port name	EdgeOne
8533	User (\$0) changed hardware bypass mode to (\$1) for device (\$2) port (\$3:\$4)	\$0: Account ID \$1: Mode name \$2: Device serial number \$3: Slot name \$4: Port name	EdgeOne
8534	User (\$0) enabled LFPT for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number \$2: Slot name \$3: Port name	EdgeOne
8535	User (\$0) disabled LFPT for device (\$1) port (\$2:\$3)	\$0: Account ID \$1: Device serial number \$2: Slot name	EdgeOne

		\$3: Port name	
8549	User (\$0) changed device (\$1) port (\$2) security settings	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8550	User (\$0) enabled DoS Prevention for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8551	User (\$0) disabled DoS Prevention for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8552	User (\$0) enabled Policy Enforcement - (\$1) for device (\$2) port (\$3)	\$0: Account ID \$1: Rule set name \$2: Device serial number \$3: Port name	EdgeOne
8553	User (\$0) disabled Policy Enforcement for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8560	User (\$0) changed rules of DoS prevention setting for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8561	User (\$0) changed hardware bypass mode to (\$1) for device (\$2) port (\$3)	\$0: Account ID \$1: Mode name \$2: Device serial number \$3: Port name	EdgeOne
8562	User (\$0) enabled LFPT for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8563	User (\$0) disabled LFPT for device (\$1) port (\$2)	\$0: Account ID \$1: Device serial number \$2: Port name	EdgeOne
8564	User (\$0) enabled device authentication passcode for selected node (\$1)	\$0: Account ID \$1: Product Name	EdgeOne
8565	User (\$0) disabled device authentication passcode	\$0: Account ID	EdgeOne
8566	User (\$0) updated File Exclusion Settings for device group (\$1)	\$0: Account ID \$1: Group Name	EdgeOne

8567	User (\$0) created (\$1) in the Domain Name Object Settings for device group (\$2)	\$0: Account ID \$1: Profile Name \$2: Group Name	EdgeOne
8568	User (\$0) updated (\$1) in the Domain Name Object Settings for device group (\$2)	\$0: Account ID \$1: Profile Name \$2: Group Name	EdgeOne
8569	User (\$0) deleted (\$1) in the Domain Name Object Settings for device group (\$2)	\$0: Account ID \$1: Profile Name \$2: Group Name	EdgeOne
8576	User (\$0) updated Domain Name Filter for device group (\$1)	\$0: Account ID \$1: Group Name	EdgeOne
8577	User (\$0) enabled Domain Name Filter - (\$1) default action (\$2) for device group (\$3)	\$0: Account ID \$1: Monitor mod or Prevention mode \$2: Action \$3: Group Name	EdgeOne
8578	User (\$0) disabled Domain Name Filter for device group (\$1)	\$0: Account ID \$1: Group Name	EdgeOne
8705	User (\$0) changed (\$1) device (\$2) name (\$3)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number \$3: Device name	EdgeOne
8706	User (\$0) changed (\$1) device (\$2) location (\$3)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number \$3: Device location	EdgeOne
8707	User (\$0) upgraded (\$1) device (\$2) firmware (\$3)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number \$3: Firmware version	EdgeOne
8708	User (\$0) moved (\$1) device (\$2) to device group (\$3)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number \$3: Group name	EdgeOne
8709	User (\$0) rebooted (\$1) device (\$2)	\$0: Account ID	EdgeOne

		\$1: Product name, e.g., "EdgeFire" \$2: Device serial number	
8710	User (\$0) deleted (\$1) device (\$2)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number	EdgeOne
8711	User (\$0) switched boot partition (\$1) device (\$2)	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number	EdgeOne
8775	User (\$0) enabled radius setting	\$0: Account ID	EdgeOne
8776	User (\$0) disabled radius setting	\$0: Account ID	EdgeOne
8777	User (\$0) changed radius setting	\$0: Account ID	EdgeOne
8784	User (\$0) enabled tacacs+ setting	\$0: Account ID	EdgeOne
8785	User (\$0) disabled tacacs+ setting	\$0: Account ID	EdgeOne
8786	User (\$0) changed tacacs+ setting	\$0: Account ID	EdgeOne
8787	User (\$0) created api key (\$1)	\$0: Account ID \$1: API Key ID	EdgeOne
8788	User (\$0) modified api key (\$1)	\$0: Account ID \$1: API Key ID	EdgeOne
8789	User (\$0) deleted api key (\$1)	\$0: Account ID \$1: API Key ID	EdgeOne
8790	User (\$0) renewed secret of api key (\$1)	\$0: Account ID \$1: API Key ID	EdgeOne
8791	User (\$0) forced user account (\$1) password to expire	\$0: Account ID \$1: Account ID	EdgeOne
8800	Converted device relay temp token from source ip (\$0)	\$0: source IP	EdgeOne
8801	Converted device relay temp token failed from source ip (\$0)	\$0: source IP	EdgeOne
8802	User (\$0) access remote device console (\$1) successfully	\$0: Account ID \$1: Device serial number	EdgeOne
8803	User (\$0) access remote device console (\$1) failed	\$0: Account ID \$1: Device serial number	EdgeOne
8816	User (\$0) accepted EULA	\$0: Account ID	EdgeOne
8817	User (\$0) accepted OT Intelligent Trust	\$0: Account ID	EdgeOne
8818	User (\$0) declined OT Intelligent Trust	\$0: Account ID	EdgeOne

8832	User (\$0) updated Vision One settings	\$0: Account ID	EdgeOne
8961	User (\$0) changed SNMP settings	\$0: Account ID	EdgeOne
8962	User (\$0) changed SNMP trap receivers	\$0: Account ID	EdgeOne
9217	User (\$0) enabled receiving suspicious objects	\$0: Account ID	EdgeOne
9218	User (\$0) disabled receiving suspicious objects	\$0: Account ID	EdgeOne
9219	User (\$0) updated the retention policy setting	\$0: Account ID	EdgeOne
9220	User (\$0) updated suspicious objects	\$0: Account ID	EdgeOne
9221	User (\$0) deleted suspicious objects	\$0: Account ID	EdgeOne
9222	User (\$0) accessed (\$1) device (\$2) web remotely	\$0: Account ID \$1: Product name, e.g., "EdgeFire" \$2: Device serial number	EdgeOne
9473	User (\$0) created the report task (\$1)	\$0: Account ID \$1: Report task	EdgeOne
9474	User (\$0) deleted the report task (\$1)	\$0: Account ID \$1: Report task	EdgeOne
9475	User (\$0) ran the report task (\$1)	\$0: Account ID \$1: Report task	EdgeOne
9476	User (\$0) canceled the report task (\$1)	\$0: Account ID \$1: Report task	EdgeOne
9477	User (\$0) deleted the report file (\$1)	\$0: Account ID \$1: Report file name	EdgeOne
9478	User (\$0) downloaded the report file (\$1)	\$0: Account ID \$1: Report file name	EdgeOne