

Closed Loop Architecture

A Complete OS in Four Flat Lists

Registry: [\[HOWL-COMP-12-2026\]](#)

Series Path: [\[HOWL-COMP-1-2026\]](#) → [\[HOWL-COMP-2-2026\]](#) → [\[HOWL-COMP-3-2026\]](#) → [\[HOWL-COMP-4-2026\]](#) → [\[HOWL-COMP-5-2026\]](#) → [\[HOWL-COMP-6-2026\]](#) → [\[HOWL-COMP-7-2026\]](#) → [\[HOWL-COMP-8-2026\]](#) → [\[HOWL-COMP-9-2026\]](#) → [\[HOWL-COMP-10-2026\]](#) → [\[HOWL-COMP-11-2026\]](#) → [\[HOWL-COMP-12-2026\]](#)

DOI: 10.5281/zenodo.20615398

Date: June 2026

Domain: Software Architecture / Systems Engineering

AI Usage Disclosure: Only the top metadata, figures, refs and final copyright sections were edited by the author. All paper content was LLM-generated using Anthropic's Claude 4.5 Sonnet.

1. The Problem With Partial Views

Most software design methods produce partial views of a system. A class diagram shows structure but not behavior. A sequence diagram shows one interaction path but not all of them. A state diagram shows one component's lifecycle but not how it connects to others. Each diagram is a projection — it takes the full system and flattens it onto one plane, discarding information in the process. Understanding the system means mentally reassembling these projections into a coherent whole. This reassembly is where designs break, where assumptions diverge between team members, and where implicit dependencies hide until they surface as bugs in production.

The root cause is that projection-based methods divide the system by *view type* rather than by *what the system contains*. You get a structural view, a behavioral view, a data view — each cutting across every component. No single artifact tells you everything about one component, and no single artifact tells you everything about the system from any one angle.

Closed Loop Architecture takes a different approach. Instead of projecting a system onto multiple partial views, it slices the system into four flat lists. Each list is complete from its own angle. The union of all four lists is the complete system. Adding a new slice — a new component, a new feature — means adding entries to the four lists. The existing entries do not change. The new entries interact with existing ones only through declared references, never through implicit coupling. The specification is closed under addition: you can grow it without opening it up.

This paper describes the method, demonstrates it by specifying a complete operating system, and examines what the specification reveals about OS design that was not previously

visible.

2. The Four Lists

Closed Loop Architecture specifies a system using four data structures, written in order, each building on the previous one. They are flat lists — not trees, not graphs, not diagrams. Each entry in each list is a small record with a few fields. The entire specification of a non-trivial system fits in a single document readable in an afternoon.

List 1: EntityGroups. Every noun in the system, with a cardinality. The cardinality has three values. Zero means the noun exists as a concept in the system's vocabulary but has no runtime representation — it is named so the specification is complete, but no code manages it. One means exactly one instance exists at runtime — a singleton. Infinity means a population of instances exists at runtime, with members created and destroyed dynamically. An EntityGroup entry is a name and a cardinality. Nothing more. The full set of EntityGroups is the system's ontology — every thing the system knows about, categorized by how many of that thing exist.

List 2: EventSets. Every verb in the system, tied to the EntityGroup it belongs to. An event is something that happens to or within a specific kind of thing. Each event carries custom data — whatever information the event needs to deliver. The events belonging to an EntityGroup form that group's lifecycle: how instances of that kind of thing come into existence, change state, interact with other things, and cease to exist. The full set of events across all groups is everything that can happen in the system.

List 3: EventFlows. The ordering relationships between events. A flow is a record saying: after this event, that event can follow. Flows can be linear (A then B), branching (A then either B or C), parallel (A enables both B and C simultaneously), fan-out (one event triggers many instances of another), convergence (many instances of one event enable a single other event), or cyclic (A and B repeat). Flows exist within a single EntityGroup (intra-group) and between different EntityGroups (inter-group). The full set of flows is the system's complete behavior — every possible sequence of events, readable by walking the flow declarations.

List 4: EventConstraints. The conditions under which each event is allowed to fire. A constraint is a set of logical conditions evaluated against the data of the entities involved. If the conditions pass, the event can fire. If they fail, the event is blocked. Constraints reference entity data — the fields and states of the things in the system. For a singleton (One cardinality), the constraint reads the one instance's data directly. For a population (Infinity cardinality), the constraint binds a variable to a specific member and tests that member's data, functioning as a filter over the population. For a concept with no runtime instance (Zero cardinality), the constraint can only test whether other events have fired — there is no entity data to read.

These four lists — what exists, what happens, in what order, under what conditions — are the complete specification. Every behavior of the system is traceable through them. Every gap is visible by inspection: an EntityGroup with no events has no lifecycle. An

event with no flows is disconnected. An event with no constraint fires unconditionally, which is either intentional or a specification error.

3. Cardinality as Architecture

The three cardinalities — Zero, One, Infinity — appear to be a minor bookkeeping detail. They are not. They determine the fundamental interaction patterns of the system, and they do so mechanically, without design decisions.

Zero declares the boundary between what the software knows about and what it manages. A concept with Zero cardinality appears in the specification, participates in event flows, and has events — but no code creates, updates, or destroys instances of it. It exists so that the specification is complete. Consider firmware in an operating system: the OS does not manage the BIOS, but the BIOS performs actions that the OS must account for. Naming it with Zero cardinality means the specification includes the BIOS's events and their flows into the rest of the system, without pretending the OS has a BIOS entity to manage. Zero is not “optional” — it is categorically not instantiated. It can never become One or Infinity. It is the state of a named concept that the system references but does not implement.

One declares a singleton — a unique instance that exists for the lifetime of the system. Singletons are typically orchestrators, managers, or shared resources. The kernel is one. The scheduler is one. The filesystem layer is one. They coordinate and manage other things.

Infinity declares a population. Processes, files, network connections, devices — these are populations. Members are created and destroyed. The system manages N of them at any time, where N changes.

When two EntityGroups interact, their cardinalities determine the interaction pattern:

One interacting with Infinity is always fan-out or convergence. A singleton event triggers events on multiple members of a population (fan-out: the init system starts each service), or a specific member of a population reports to a singleton (convergence: a critical service failing triggers an init system event). The singleton addresses the population through constraint filtering. The population member addresses the singleton directly — there is only one.

Infinity interacting with Infinity is list-to-list. Build a list of matching members from population A, build a list of matching members from population B, iterate. A device becoming ready triggers the corresponding service to start. Both are populations, both filtered by constraint.

Zero interacting with anything is pure event sequencing. There is no entity data to query, no instance to address. The only constraint possible is whether prior events have fired.

These patterns are not designed. They are consequences of the cardinality declarations. The developer declares “there is one scheduler” and “there are many processes” and the

interaction pattern — the scheduler fans out to processes, processes converge back to the scheduler — falls out automatically.




Figure 1: Fig. 7: Cardinality Interaction Patterns — fan-out, convergence, and list-to-list as spatial geometry determined by Zero/One/Infinity.

4. The Execution Pipeline

A specification is inert without a runtime that executes it. Closed Loop Architecture connects to an execution pipeline with two paths that share a common mechanism.

The entity data model. Everything in the system that has a runtime instance (One or Infinity cardinality) is represented as an entity — a flat collection of optional subsystems. An entity can have a transform (position, velocity), a character system (stats, health, progression), an awareness system (proximity tracking), a combat system, a crafting system, a needs system, and roughly twenty-five others. Every entity has the same shape. Subsystems not relevant to a particular entity are inactive. All entity data is available for logical evaluation.

Path A: the per-entity update. Each entity has a state machine. Every tick, the state machine evaluates its transitions by testing logical rules against the entity's own data. If a transition's conditions pass and a minimum time in the current state has elapsed, the entity moves to a new state. The new state either forces a specific action (deterministic — the state dictates exactly what happens) or contains a behavior set that scores multiple possible actions using utility AI. The utility AI evaluates considerations — each one a logical gate combined with a normalized, curved, weighted score derived from entity data. Scores multiply across considerations, so any zero kills a behavior entirely. The winning behavior triggers an action. Actions flow through a skill chain that produces envelopes.

Envelopes. An envelope is a time-bounded modifier on entity data. It is a full signal envelope — attack, sustain, decay, release — with curve interpolation from start to end. It can modify a stat continuously over time (damage that ramps up along a curve), or function as a boolean toggle (a buff that is on then off). It can execute logic every tick, not just modify a number. Crucially, an envelope has three event hooks: it fires an event when it starts, an event every frame it is active, and an event when it ends. These events feed back into the system. A poison effect creates an envelope that fires a damage event every frame. A shield buff fires an expiration event when it ends. The envelope is both a write mechanism and an event source.




Figure 2: Fig. 4: Envelope ADSR Waveform — attack-sustain-decay-release with three event hooks feeding back into constraint evaluation.

Path B: system-level orchestration. Events fire when their constraints pass. Event flows determine what fires next. Events carry custom data. Events can trigger state machine transitions, create envelopes, spawn entities, or modify state directly. This path handles everything that is not a per-entity tick update — system lifecycle, initialization sequences, cross-component coordination, error handling.

The closed loop. Entity data is evaluated by logical rules. Rules determine state transitions and event firing. Transitions and events trigger actions. Actions produce envelopes. Envelopes modify entity data over time and fire events. Events feed back into the constraint evaluation. The loop is: data → evaluation → decision → action → data change → evaluation. Both paths read through the same logical evaluation. Both paths write through envelopes or direct modification. Both paths produce events. The system is

closed — there is no external control flow, no imperative orchestration, no ad-hoc logic. Every decision bottlenecks through declared rules evaluated against declared data.




Figure 3: Fig. 1: Closed Loop Execution Cycle — data feeds evaluation feeds action feeds data, two entry paths into one ring.

5. Worked Example: The Operating System

A computer powers on. Hardware initializes itself and selects a boot device. A boot-loader loads the kernel into memory. The kernel initializes memory, discovers hardware, and mounts the root filesystem. An init process starts system services. A display server presents a login screen. The user authenticates and arrives at a working desktop.

Seven sentences. From these, Closed Loop Architecture produces four lists that specify the entire system. What follows walks through each list and the process of constructing it.




Figure 4: Fig. 8: OS Boot Timeline — left-to-right progression from BIOS to desktop showing parallel forks, cardinality transitions, and fan-out points.

6. List 1: What Exists

The first step is naming every noun in the system and assigning its cardinality. This requires answering one question per noun: does the software manage zero, one, or many of this thing?

Zero cardinality — concepts with no runtime entity. The BIOS performs the power-on self test, enumerates hardware, selects a boot device, and hands off to the bootloader. The OS does not manage the BIOS. It does not create a BIOS entity, update its state, or track its lifecycle. But the BIOS's actions matter — they are preconditions for everything that follows. Naming the BIOS with Zero cardinality means its events exist in the specification, its flows connect to the rest of the boot sequence, but no code implements a BIOS subsystem. The same applies to the Bootloader — it executes before the OS exists.

One cardinality — singletons. The Kernel is one instance. The Init System is one. The Memory Manager, Scheduler, Virtual Filesystem, Network Stack, Display Server, Audio Mixer, Device Manager, Swap Manager, Firewall, DNS Resolver, Session Manager, System Logger, and Package Manager are each one. These are the orchestrators and shared resources of the OS. There is exactly one of each for the lifetime of the system.

Infinity cardinality — populations. Processes are a population. So are Threads, open Files, Filesystem Mounts, Network Connections, User Accounts, User Sessions, Devices, Kernel Modules, Services, Windows, Network Interfaces, Permission Rules, Timers, Signals, Pipes, Shared Memory Regions, Environment Variable Sets, Cron Jobs, and Log Entries. These are the managed things — created and destroyed dynamically, with the system handling N of them at any time.

The complete EntityGroup list for the OS contains 37 entries: 2 Zero, 15 One, 20 Infinity. This is the entire ontology. Every thing the OS knows about is on this list. If something is missing, it will be discovered when writing the events — a verb without a noun means a missing EntityGroup.

The first structural insight is already visible. The OS is 15 singletons managing 20 populations. The fundamental pattern is orchestrators coordinating populations. This ratio — roughly equal numbers of singletons and populations, with singletons doing the coordination — is the shape of the OS.




Figure 5: Fig. 2: Singleton-Population Orchestration Map — 15 One-cardinality hubs managing 20 Infinity-cardinality populations.

7. List 2: What Happens

Each EntityGroup gets its events — every state change that instances of that group can undergo. Events are written by reading the specification and extracting every verb-noun pair, then assigning each to its owning group.

Zero groups have events that describe what happens conceptually. The BIOS has five events: Power On Self Test, Hardware Enumerated, Boot Device Selected, MBR Loaded, Bootloader Transferred. The Bootloader has seven: Stage1 Loaded through

Control Transferred. These events exist in the specification, participate in flows, and have constraints — but they describe things happening outside the software’s control. They are the system’s awareness of its context.

One groups have events describing their lifecycle and operations. The Kernel has thirteen events covering entry, memory initialization, hardware discovery, filesystem mounting, module loading, and the panic case. The Init System has fifteen events covering its orchestration sequence from process start through network configuration, plus a failure event. The Memory Manager has eleven events covering initialization, allocation, freeing, compaction, reclamation, OOM triggering, and degradation states. Each singleton’s events tell the complete story of what that singleton does.

Infinity groups have events describing the lifecycle of individual members. A Process has sixteen events: Created, Forked, Exec, Ready, Running, Blocked, Sleeping, Resumed, Syscall, Page Fault, Signal Received, Yielded, Exited, Zombie, Waited, Terminated. A Service has fourteen events covering start, run, health check, degradation, failure, restart, reload, stop, and escalation. A Device has twelve events from discovery through driver loading, initialization, self-test, readiness, error, suspension, and removal.

Each event carries custom data — the specific information that event delivers. Process Created carries the PID and parent PID. Device Discovered carries the device ID, bus type, vendor ID, and product ID. Kernel Panic carries a reason string. The data is specific to each event, not a universal carrier.

The compression effect. In a flat event list without EntityGroups, each service would need unique events: SSH Started, Cron Started, Dbus Started, Network Manager Started. With EntityGroups, the Service group (Infinity cardinality) has generic lifecycle events — Service Start Requested, Service Started, Service Running, Service Failed — and the specific service (SSH, Cron, Dbus) is identified by the entity instance, not by the event name. Nine unique names become three generic event types on a population. The cardinality does the work that naming was doing manually.

The complete EventSet for the OS contains approximately 311 events across all 37 groups. This is everything that can happen in the system.

8. List 3: In What Order

Event flows declare the ordering relationships between events. They answer: after this event fires, what can happen next?

Intra-group flows are mostly simple. The BIOS events flow in strict linear sequence — POST, then enumerate, then select, then load, then transfer. The Bootloader is the same. The Kernel is mostly linear with one parallel opportunity: console initialization and PCI bus enumeration can happen simultaneously after the timer starts, and both must complete before block device discovery. The Init System is mostly linear with a similar parallel section: clock synchronization and loopback interface bring-up can happen simultaneously after swap is enabled.

Infinity groups have richer intra-group flows because their members have lifecycle state machines. A Process flows from Created to Ready to Running, with branches to Blocked, Sleeping, and back to Ready, eventually flowing to Exited, Zombie, Waited, and Terminated. A Service flows from Start Requested through Started, Running, and the health check cycle, with branches to Degraded, Failed, Restart, and Stop. These flows are the same for every member of the population — the specific instance is determined by constraint, not by flow.

Inter-group flows reveal the real architecture. The inter-group flows are where the system's structure becomes visible. They follow the cardinality patterns described earlier.

Zero to Zero: the BIOS's last event (Bootloader Transferred) flows to the Bootloader's first event (Stage1 Loaded). Pure sequencing between two concepts the OS doesn't manage.

Zero to One: the Bootloader's last event (Control Transferred) flows to the Kernel's first event (Kernel Entered). This is the moment the OS begins to exist. A concept hands off to a real entity.

One to One: the Kernel's Root Switched event flows to the Init System's Process Started event. The Init System's DNS Resolver Configured flows to the Display Server Started. These are singleton-to-singleton handoffs — one orchestrator completing a phase and enabling the next.

One to Infinity (fan-out): the Init System's Runlevel Determined event flows to Service Start Requested — not for one service, but for every service in the runlevel. One event on a singleton fans out to N events on a population. The Device Manager's Started event flows to Device Discovered for every detected hardware device. The Scheduler's initialization enables Process Created. These fan-outs are where singletons create and manage their populations.

Infinity to One (convergence): a specific Device entity reaching Ready flows back to the Kernel's Root Filesystem Mounted — but only if that device is the root disk. A specific Service entity reaching Running (the logging service) flows to the System Logger becoming fully operational. These are population members reporting back to singletons. The constraint filters which member triggers the convergence.

Infinity to Infinity: a Device entity reaching Ready triggers a Service entity starting (the GPU device enables the display driver service). A Process creating triggers Thread creation within it, File opening by it, Pipe creation by it. A Timer firing triggers a Cron Job executing. These are cross-population interactions, both sides filtered by constraint.

The complete flow list for the OS contains approximately 349 entries. Reading these flows from beginning to end, starting at BIOS Power On Self Test and following every path, tells the complete story of how the OS boots, runs, and manages its components. No code is needed to understand the system's behavior — the flows are the behavior.




Figure 6: Fig. 6: Inter-Group Flow Heatmap — 37x37 matrix showing where cross-group coupling concentrates in the OS specification.

9. List 4: Under What Conditions

Event constraints are logical conditions that must pass before an event can fire. They are expressed as rules evaluated against entity data, using a logic programming model where facts about the system's current state are tested against declared conditions.

Zero group constraints are trivial. The BIOS and Bootloader events have no entity data to test. Their constraints are purely: did the previous event complete? BIOS Hardware Enumerated fires when BIOS Power On Self Test has completed. Bootloader Stage2 Loaded fires when Stage1 Loaded has completed. This confirms what Zero cardinality means — these concepts have no state to query, only event ordering.

One group constraints read entity data. The Kernel's Block Devices Discovered event

requires that both Console Initialized and PCI Bus Enumerated have completed — this is the join point for the parallel section. But it also requires that the root device is ready, which is a fact about a Device entity (Infinity cardinality). The One singleton reaches into the Infinity population to test a specific member's state. The Init System's Filesystems Mounted event requires that all filesystem checks passed — a derived fact aggregated across the Filesystem Mount population. The Init System's Network Interfaces Configured requires that at least one network interface exists, reading from the Network Interface population. Singleton constraints routinely cross EntityGroup boundaries, querying populations to make orchestration decisions.

Infinity group constraints bind Self. Every constraint on a population event begins by binding a variable to the specific entity instance being evaluated. A Service's Running event requires: this service entity exists, it has started, and its first health check passed. A Device's Ready event requires: this device entity exists and its self-test passed. A Process's Blocked event requires: this process entity exists and it is waiting on a resource. The Self-binding is what makes population constraints work — the same constraint definition applies to every member, but evaluates against each member's individual data.

Cross-group constraints express the real dependencies. The Init System's Swap Enabled event requires that filesystems are mounted (an Init System event) and that the swap device is ready (a Device entity's state). The Display Server's Started event requires that Init has completed DNS configuration and that the GPU device is ready. A Service Start Requested requires that the service's dependencies — other services — are already in the Running state. These cross-group constraints make every dependency between subsystems explicit and visible. In a traditional OS codebase, these dependencies are implicit in function call chains, callback registrations, and initialization ordering buried across hundreds of source files. In CLA, they are individual entries in a flat list.

The complete constraint list contains approximately 311 entries — one per event. Reading the constraints for any event tells you exactly what must be true in the system before that event can fire. Reading all constraints for a single EntityGroup tells you every condition that affects that group's lifecycle. Reading all cross-group constraints tells you the complete dependency structure of the system.

10. States, Actions, and Decision Points




Figure 7: Fig. 3: UAI Consideration Curves — four urgency profiles for the Memory Manager, showing how curve shape determines response character.

With the four lists complete, the next step is assigning each EntityGroup its state machine — the states it can occupy, the actions it performs in each state, and whether those actions are deterministic or scored by utility AI.

Most EntityGroups use deterministic actions. The Kernel has seven states (Unloaded through Panic) and twelve actions (InitializePageTables, StartMemoryManager, BuildInterruptTable, and so on). Every state has a forced action — the state dictates exactly what happens, with no decision-making. The Init System is the same: fifteen deterministic actions driven by state. The VFS, Display Server, Audio Mixer, Device Manager, DNS Resolver, Session Manager, and Package Manager are all deterministic. They respond to events and execute the one appropriate action for their current state.

Most Infinity groups are also deterministic. Process, Thread, File, Pipe, Shared Memory Region, Signal, Timer, Permission Rule, Kernel Module, Filesystem Mount, Window, Network Interface, Environment Variable Set, Cron Job, and Log Entry all have states and actions driven entirely by events from other groups. They do not make autonomous decisions. They are acted upon.

Exactly nine EntityGroups have behavior sets — places where the system must choose between alternatives. The Memory Manager has a pressure response behavior set: when free pages are low, it scores whether to do nothing, compact memory, reclaim

cached pages, swap out, or invoke the OOM killer, based on considerations like free page ratio, swap usage, and allocation failure rate. The Scheduler has a scheduling decision behavior set: it scores whether to continue the current process, preempt it, rebalance across CPUs, migrate a process, or adjust priorities, based on run queue length, CPU load imbalance, time slice exhaustion, and whether interactive or real-time processes are waiting. The Network Stack scores congestion responses. The Swap Manager scores pressure responses. The System Logger scores buffer management. Network Connections score health responses. User Sessions score idle policy. Services score health monitoring. Devices score error recovery.

Nine behavior sets in the entire operating system. Nine places where the system weighs multiple options using scored considerations. Everything else — every other EntityGroup, every other state, every other action — is deterministic.




Figure 8: Fig. 5: Behavior Set Decision Landscape — nine pressure-response curves showing the OS has exactly nine autonomous decision points.

11. What the Specification Reveals

Constructing the four lists produces insights about OS design that are not visible in source code, in documentation, or in traditional design artifacts.

The OS has exactly nine decision points. Before this enumeration, the assumption is that an operating system is complex decision-making throughout. It is not. Nine behavior sets, nine places where the system weighs options. The rest is mechanical state transitions.

The complexity of an OS is overwhelmingly sequencing — getting things to happen in the right order — not deciding what to do.

Almost all decision-making is resource pressure response. Memory pressure, swap pressure, network congestion, log buffer pressure, connection health, device error recovery. The OS reacts to exhaustion. The utility AI considerations in these behavior sets are almost all ratio-of-capacity measurements: free pages over total pages, swap used over swap total, drop rate, buffer occupancy. The intelligence of an OS is pressure management.

The only user-facing decision is session idle policy. Out of nine behavior sets, one faces the user — deciding when to dim the screen, lock the session, or suspend. The rest are internal resource management invisible to anyone using the system. The OS makes almost no decisions that a human would perceive as a choice being made.

Zero-cardinality groups are real architectural components. The BIOS and Bootloader are part of the OS specification but have no runtime entities. Traditional OS design either ignores them (they are “not the OS”) or awkwardly includes them. Zero cardinality makes them first-class members of the specification — complete with events and flows — without forcing fake runtime representations. The specification is complete because Zero lets you name what you do not manage.

The fundamental pattern is singletons orchestrating populations. Fifteen singletons, twenty populations. The Scheduler manages Processes. The VFS manages Files and Filesystem Mounts. The Device Manager manages Devices. The Network Stack manages Connections. This is obvious in hindsight but is never stated this cleanly in traditional design artifacts because class hierarchies and module boundaries obscure the singleton-population relationship.

Populations are passive. Process, Thread, File, Pipe, Shared Memory, Signal, Timer, Permission Rule, Kernel Module, Filesystem Mount, Window, Network Interface, Environment Variable Set, Cron Job, Log Entry — all purely reactive. They have state machines, but every transition is driven by events from singletons or from other populations. They never autonomously decide anything. Complexity does not scale with entity count. A million processes are not complex. The one scheduler is complex.

Failure handling is structurally identical to normal operation. Device Failed, Service Failed, Kernel Panic — these are states in the same state machine, with the same flow and constraint mechanism. The error recovery behavior sets use the same utility AI scoring as normal operation. There is no separate “error handling architecture.” Failure is just another state with transitions and constraints. This means failure paths receive the same completeness guarantee as success paths — if the state exists, it has events, flows, and constraints.

Inter-group flows expose the actual dependency architecture. The fan-out from Init to Services and Devices, the convergence from specific Devices back to the Kernel, the cross-population flows between Devices and Services — these structural dependencies are invisible in source code, where they are spread across subsystem boundaries and encoded in function call chains. In the flow list, they are individual entries, each one a declared

relationship between two events in two groups.

Cross-group constraints are where coupling lives. Every place where one EntityGroup depends on another's data is visible as a constraint entry. The Init System reading Device states to decide when to mount filesystems. The Display Server requiring GPU readiness. Service start requiring dependency services to be running. In a traditional codebase, these dependencies are implicit. In the constraint list, they are explicit, enumerable, and auditable.

The entire OS is approximately 1,000 entries across four lists. Thirty-seven EntityGroups, 311 events, 349 flows, 311 constraints. This is the complete specification of an operating system from power-on to desktop, including boot sequencing, hardware management, process lifecycle, networking, display, audio, user session management, error handling, and all cross-subsystem dependencies. Readable in an afternoon. Not a diagram. Not a codebase. Four lists.

12. Closedness

The defining property of Closed Loop Architecture is that the specification is closed under addition. Adding a new component to the system means adding entries to the four lists. The existing entries do not change.

Consider adding Bluetooth support to the OS. This means adding one EntityGroup (Bluetooth Adapter, Infinity cardinality), its events (Adapter Discovered, Adapter Initialized, Device Paired, Device Connected, Data Transferred, Device Disconnected, Adapter Failed), its intra-group flows (Discovered through Initialized through Paired and the pairing lifecycle), its inter-group flows (Device Manager discovery fans out to Bluetooth Adapter Discovered; Bluetooth Adapter Ready converges to enable the Bluetooth Service), and its constraints (Adapter Discovered requires Device Manager running and Bluetooth hardware detected; Device Paired requires adapter initialized and pairing credentials valid).

None of the existing 37 EntityGroups change. None of the existing 311 events change. The existing flows and constraints are untouched. The new Bluetooth group interacts with existing groups — Device Manager, Service — through new flow entries that reference existing events, and new constraint entries that query existing entity data. The interaction surface is declared and visible. The Bluetooth addition cannot introduce implicit dependencies, cannot alter the Init sequence, cannot affect the Memory Manager's pressure response. It can only declare new flows from and to existing events and new constraints that read existing entity data.

This closedness comes from the architecture's constraints on interaction. EntityGroups do not share state. They interact through two mechanisms only: event flows (declared ordering) and constraint evaluation (logical queries against entity data, which are read-only). There is no shared mutable state between groups. There is no callback registration. There is no global event handler that might intercept events meant for other groups. Every

interaction between groups is an entry in the flow list or the constraint list, visible by inspection.

Contrast this with adding Bluetooth to a traditional OS architecture. The Device Manager module needs modification to recognize Bluetooth hardware. The service management system needs a new service definition. The network stack may need protocol extensions. The power management system needs to know about Bluetooth power states. The user settings interface needs Bluetooth configuration. Each of these modifications touches existing code, creates new implicit dependencies through function calls and shared data structures, and risks introducing bugs in components that were previously working. The blast radius of the addition is unbounded and must be tested empirically.

In CLA, the blast radius is bounded by the new entries. The existing entries are unchanged. The specification of the pre-Bluetooth system is a strict subset of the post-Bluetooth system. This is what it means for a specification to be closed under addition.

13. The Specification-Execution Bridge

The four lists specify what the system does. The execution pipeline, described in [\[HOWL-COMP-1-2026\]](#), runs it. The bridge between specification and execution is direct because both sides use the same primitives.

EntityGroups map to entity definitions in the runtime. Each entity is a flat bag of optional subsystems with known struct shapes. The EntityGroup's cardinality determines allocation strategy — singletons are pre-allocated, populations use pooled allocation.

Events map to entries in the entity's event system. Each event fires through the runtime's event processing, carrying its custom data. The event's EntityGroup determines how the runtime resolves which entity or entities are involved — singletons are direct references, populations require constraint evaluation to select members.

Flows map to the orchestrator's sequencing logic. The orchestrator walks flows, checking each target event's constraints, and fires events whose constraints pass. Parallel flows are evaluated concurrently. Branching flows are evaluated in declaration order with the first passing branch taken. Fan-out flows iterate over the population applying constraints to each member.

Constraints map to logical rules in the runtime's rule evaluation system. The rules reference entity data through the same fact-based query mechanism used by state machine transitions and utility AI considerations. There is one query mechanism, used everywhere.

The gap between specification and running software is the action logic behind each event — the code that executes when the event fires. The four lists tell you what every action is, what data it receives, what must be true before it runs, and what happens after it completes. The action implementation is the mechanical work of writing the code behind each name. Everything else — the sequencing, the gating, the cross-group coordination, the lifecycle management — is already specified in the lists and already executable by the pipeline.

14. Relationship to Name Driven Development

Closed Loop Architecture extends Name Driven Development [[HOWL-COMP-11-2026](#)]. NDD says: name every state change before writing code. The names become the specification, the architecture, the task list, and the documentation simultaneously. Implementation is the mechanical process of writing the action behind each name.

CLA adds structure to the names. NDD produces a flat list of events grouped by domain. CLA organizes those events into four related structures: what owns each event (Entity-Groups), how events sequence (Flows), and what gates each event (Constraints). The NDD event list is CLA's List 2 — but now it has context.

The key addition is the EntityGroup and its cardinality. NDD names events but does not formally declare what things exist in the system or how many. The developer's grouping of events into domains (BIOS, Kernel, Services) implies ontology but does not make it explicit. CLA makes it the first step — before naming events, name the things the events happen to, and declare how many of each thing exist. This single act determines the interaction patterns for the entire system.

The other addition is that CLA's specification is machine-readable data, not a document. NDD's event list is a markdown file that a human reads and then implements. CLA's four lists are data structures that the execution pipeline can consume directly. The distance between specification and execution shrinks because the specification is already in the shape the runtime expects.

15. How to Use Closed Loop Architecture

The method is sequential. Each step produces one list. Each list builds on the previous ones. Completeness checks are mechanical at each step.

Step 1: Write the EntityGroups. Read the specification or requirements and extract every noun. For each noun, answer: does the software manage zero, one, or many of this? Write the list. Check: does every concept in the requirements appear as a group? If a verb in the requirements has no corresponding noun in the groups, a group is missing.

Step 2: Write the EventSets. For each EntityGroup, extract every verb — every state change, every action, every transition. Each event belongs to exactly one group. Each event carries the custom data it needs. Check: does every group have events? Does every requirement verb appear as an event? If two events always fire together with identical data, they are one event. If one event does two things, it is two events.

Step 3: Write the EventFlows. For each event, declare what can follow it. Start with intra-group flows — the lifecycle within each group. Then write inter-group flows — the connections between groups. Check: does every event appear in at least one flow? Is there a path from the system's starting event to every other event? Are there events that are unreachable? Unreachable events are either errors in the flows or events that are

triggered externally (user input, hardware interrupts) and should be marked as external entry points.

Step 4: Write the EventConstraints. For each event, declare the conditions under which it fires. Zero-group events constrain on prior event completion. One-group events constrain on singleton entity data and cross-group queries. Infinity-group events bind Self and constrain on member data. Check: does every event have a constraint? Are there constraints that reference entity data fields that do not exist in the entity definitions? If so, the entity model is incomplete.

After all four lists are written, the specification is complete. Progress tracking is counting: events with implemented actions versus events without. The four lists are the project's task list. Estimation is per-event, not per-module. Each event is a unit of functionality — small, bounded, independently testable.

16. Boundaries

Closed Loop Architecture is suited to systems with a finite, enumerable set of state changes. This is most software: order processing, device management, user session handling, network protocol implementation, game loops, CI/CD pipelines, operating systems, enterprise platforms, IoT device management.

It is less natural for pure data transformation — compilers, image processors, numerical simulations — where complexity lives inside algorithms rather than between state transitions. The interesting work in a compiler is parsing and optimization, not the transitions between pipeline stages. CLA can describe the pipeline stages, but the value of the four lists is lower when the bulk of the work is inside a single action's implementation rather than in the sequencing of many actions.

It is also less natural for systems where the ontology is genuinely unknown at specification time — truly exploratory systems where you do not yet know what kinds of things will exist. CLA assumes you can enumerate EntityGroups before writing events. If the groups are unknowable in advance, the method's first step cannot be completed.

Within its domain — the majority of software that manages state transitions across sub-systems — the method is scale-independent. A script with ten events is a well-organized script. A platform with two thousand events across four lists is a comprehensible platform, readable in an afternoon. The same cannot be said of two thousand handlers scattered across hundreds of source files. The four lists do not grow less readable as they grow larger, because each entry is self-contained, references others by ID, and the flat structure eliminates nesting.

17. Conclusion

An operating system specified in four flat lists totals approximately 1,000 entries. Those entries contain the complete ontology (37 EntityGroups), the complete lifecycle of every

component (311 events), the complete behavior (349 flows), and the complete set of conditions governing every state change (311 constraints). The specification is readable in an afternoon, checkable for completeness by mechanical inspection, and closed under addition — new components add entries without modifying existing ones.

The specification reveals that the OS has nine autonomous decision points, that its intelligence is almost entirely resource pressure response, that its fundamental pattern is singletons orchestrating populations, that its populations are passive, and that its failure handling is structurally identical to its normal operation. These insights are not visible in source code or in traditional design artifacts. They are visible in four flat lists because the lists enforce exhaustive enumeration and explicit declaration of every dependency.

Closed Loop Architecture is not a new programming paradigm or a new runtime. It is a specification discipline: declare what exists, what happens, in what order, and under what conditions. Write it as data, not as diagrams. Keep the whole visible at every step. Slice the pie instead of projecting the shadow. The specification is the architecture, and the architecture is four lists.

Appendix: Supporting Tables

HOWL-COMP-12-2026

Table A: Entity Groups

ID	Name	Cardinality	Description
G1	BIOS	Zero	Firmware self-test and handoff to bootloader. Named so the specification includes pre-OS events. No runtime entity.
G2	Bootloader	Zero	Loads kernel into memory and transfers control. Executes before the OS exists. No runtime entity.
G3	Kernel	One	Core OS. Memory initialization, interrupt handling, hardware discovery, filesystem mounting, module loading.

ID	Name	Cardinality	Description
G4	Init System	One	System startup orchestration. Reads runlevel, configures hostname, devices, filesystems, network, and launches services.
G5	Memory Manager	One	Page allocation, deallocation, compaction, reclamation, and OOM handling.
G6	Scheduler	One	Process scheduling, CPU assignment, load balancing, priority management.
G7	VFS	One	Virtual filesystem layer. Filesystem type registration, mount management, file descriptor handling, path resolution.
G8	Network Stack	One	TCP/IP protocol handling. Packet processing, routing, congestion management, retransmission.
G9	Display Server	One	Compositor, window management, input routing, session management for graphical output.
G10	Audio Mixer	One	Audio stream mixing, volume control, device routing, suspend/resume.
G11	Device Manager	One	Hardware discovery, driver matching, driver loading, device node creation, hotplug notification.
G12	Swap Manager	One	Swap partition activation, page-level read/write, defragmentation, pressure monitoring.
G13	Firewall	One	Packet filtering. Ruleset loading, packet evaluation, allow/drop/reject decisions.
G14	DNS Resolver	One	Hostname resolution, response caching, cache eviction, nameserver failover.

ID	Name	Cardinality	Description
G15	Session Manager	One	Login presentation, credential validation, session creation/destruction, session switching.
G16	System Logger	One	Log collection, buffer management, file rotation, remote forwarding.
G17	Package Manager	One	Package index management, dependency resolution, download, install, remove, integrity verification.
G18	Process	Infinity	Running process instance. Fork, exec, scheduling states, syscalls, signals, exit, zombie/wait lifecycle.
G19	Thread	Infinity	Thread within a process. Start, block, resume, lock/unlock, condition wait/signal, join, detach, terminate.
G20	File	Infinity	Open file descriptor. Open, read, write, seek, lock, sync, close.
G21	Filesystem Mount	Infinity	Mounted filesystem instance. Check, mount, remount, sync, unmount.
G22	Network Connection	Infinity	TCP/UDP socket. Connect, establish, send, receive, retransmit, close, reset, terminate.
G23	User Account	Infinity	System user record. Create, activate, lock, unlock, disable, delete, password/permission changes.
G24	User Session	Infinity	Active login session. Authenticate, create, load environment, autostart, lock, suspend, logout.
G25	Device	Infinity	Hardware device instance. Discover, load driver, initialize, self-test, ready, error, suspend, remove.

ID	Name	Cardinality	Description
G26	Kernel Module	Infinity	Loaded kernel module. Load, initialize, run, unload.
G27	Service	Infinity	Managed daemon. Start, run, health check, degrade, fail, restart, reload, stop, escalate.
G28	Window	Infinity	Application window surface. Create, show, hide, focus, minimize, maximize, resize, move, close.
G29	Network Interface	Infinity	Network interface, physical or virtual. Detect, configure, address assign, up, degrade, down, DHCP renew, reset.
G30	Permission Rule	Infinity	ACL entry. Grant, evaluate, expire, revoke.
G31	Timer	Infinity	Scheduled callback. Arm, fire, reset, cancel.
G32	Signal	Infinity	Pending signal. Send, deliver, handle, ignore, default action.
G33	Pipe	Infinity	IPC pipe. Create, write, read, full, end close, break.
G34	Shared Memory Region	Infinity	Shared memory segment. Allocate, map, unmap, sync, free.
G35	Environment Variable Set	Infinity	Per-process environment block. Load, set, unset, export.
G36	Cron Job	Infinity	Scheduled recurring task. Schedule, execute, complete, fail, reschedule.
G37	Log Entry	Infinity	Log record. Buffer, write, rotate, archive, delete.

Summary: 2 Zero, 15 One, 20 Infinity. Total: 37 EntityGroups.

Table B: Event Sets

B.1 — BIOS (G1, Zero)

ID	Event	Carries	Description
EV1	BIOS Power On Self Test	diagnostic result:bool	Hardware self-test at power on
EV2	BIOS Hardware Enumerated	device count:i32	All hardware detected
EV3	BIOS Boot Device Selected	device path:Text	Boot device chosen
EV4	BIOS MBR Loaded	sector address:i32	Master boot record read
EV5	BIOS Bootloader Transferred	entry address:i32	Control passed to bootloader

B.2 — Bootloader (G2, Zero)

ID	Event	Carries	Description
EV6	Bootloader Stage1 Loaded	load address:i32	First stage loaded from MBR
EV7	Bootloader Stage2 Loaded	load address:i32	Second stage loaded
EV8	Bootloader Kernel Located	kernel path:Text	Kernel image found on disk
EV9	Bootloader Kernel Loaded To Memory	memory address:i32, kernel size:i32	Kernel copied to RAM
EV10	Bootloader Initrd Loaded	memory address:i32, initrd size:i32	Initial ramdisk copied to RAM
EV11	Bootloader Kernel Parameters Set	param string:Text	Boot parameters configured
EV12	Bootloader Control Transferred	entry address:i32	Execution jumps to kernel

B.3 — Kernel (G3, One)

ID	Event	Carries	Description
EV13	Kernel Entered	entry address:i32	First kernel instruction
EV14	Kernel Page Tables Initialized	page count:i32	Virtual memory mapping set up

ID	Event	Carries	Description
EV15	Kernel Memory Manager Started	total memory:i32	Allocator active
EV16	Kernel Interrupt Table Built	vector count:i32	Interrupt handlers registered
EV17	Kernel Timer Started	frequency hz:i32	System clock ticking
EV18	Kernel Console Initialized	console device:Text	Kernel console output available
EV19	Kernel PCI Bus Enumerated	device count:i32	PCI devices discovered
EV20	Kernel Block Devices Discovered	device count:i32	Storage devices found
EV21	Kernel Root Filesystem Mounted	device path:Text, mount point:Text	Root filesystem available
EV22	Kernel Initrd Unpacked	file count:i32	Initial ramdisk contents extracted
EV23	Kernel Modules Loaded	module count:i32	Kernel modules from initrd loaded
EV24	Kernel Root Switched	new root:Text	Pivot from initrd to real root
EV25	Kernel Panic	reason:Text	Unrecoverable error, system halt

B.4 — Init System (G4, One)

ID	Event	Carries	Description
EV26	Init Process Started	pid:i32	PID 1 running
EV27	Init Runlevel Determined	runlevel:i32	Target runlevel read from config
EV28	Init Hostname Set	hostname:Text	System hostname applied
EV29	Init Sysctl Applied	param count:i32	Kernel parameters tuned
EV30	Init Udev Started	pid:i32	Device manager daemon launched
EV31	Init Devices Populated	device count:i32	Device scan complete
EV32	Init Filesystems Checked	clean count:i32, dirty count:i32	fsck results

ID	Event	Carries	Description
EV33	Init Filesystems Mounted	mount count:i32	fstab entries mounted
EV34	Init Swap Enabled	swap size:i32	Swap partitions active
EV35	Init Clock Synchronized	offset ms:f32	System clock synced
EV36	Init Loopback Interface Up	address:Text	Loopback interface configured
EV37	Init Network Interfaces Configured	interface count:i32	Network interfaces up
EV38	Init Firewall Rules Applied	rule count:i32	Packet filter rules loaded
EV39	Init DNS Resolver Configured	nameserver count:i32	DNS resolution ready
EV40	Init Failed	reason:Text	Init step failed

B.5 — Memory Manager (G5, One)

ID	Event	Carries	Description
EV41	MemoryManager Initialized	total pages:i32	Allocator structures set up
EV42	MemoryManager Page Allocated	page address:i32, requesting process id:i32	Page given to requester
EV43	MemoryManager Page Freed	page address:i32	Page returned to pool
EV44	MemoryManager Compaction Started	fragmentation ratio:f32	Defragmentation begun
EV45	MemoryManager Compaction Completed	pages moved:i32	Defragmentation finished
EV46	MemoryManager Reclaim Started	target pages:i32	Cache eviction begun
EV47	MemoryManager Reclaim Completed	pages reclaimed:i32	Cache eviction finished
EV48	MemoryManager OOM Triggered	requesting process id:i32	Out of memory, victim selection begins
EV49	MemoryManager OOM Kill	killed process id:i32, memory freed:i32	Victim terminated

ID	Event	Carries	Description
EV50	MemoryManager Degraded	free ratio:f32	Free pages below warning threshold
EV51	MemoryManager Critical	free pages:i32	Free pages below critical threshold

B.6 — Scheduler (G6, One)

ID	Event	Carries	Description
EV52	Scheduler Initialized	cpu count:i32	Per-CPU run queues created
EV53	Scheduler Context Switch	from process id:i32, to process id:i32, cpu id:i32	CPU switches processes
EV54	Scheduler Rebalance Started	imbalance ratio:f32	Load rebalance begun
EV55	Scheduler Rebalance Completed	migrations:i32	Rebalance finished
EV56	Scheduler Priority Adjusted	process id:i32, old priority:i32, new priority:i32	Anti-starvation adjustment
EV57	Scheduler Process Migrated	process id:i32, from cpu:i32, to cpu:i32	Process moved to different CPU
EV58	Scheduler Preemption	process id:i32, reason:Text	Forced switch from current process
EV59	Scheduler Overloaded	run queue length:i32	Excessive run queue depth

B.7 — VFS (G7, One)

ID	Event	Carries	Description
EV60	VFS Initialized	filesystem type count:i32	VFS layer active
EV61	VFS Filesystem Registered	filesystem type:Text	New filesystem type available
EV62	VFS Mount Completed	device:Text, mount point:Text, filesystem type:Text	Filesystem attached to VFS

ID	Event	Carries	Description
EV63	VFS Unmount Completed	mount point:Text	Filesystem detached
EV64	VFS File Opened	fd:i32, path:Text, process id:i32	File descriptor created
EV65	VFS File Closed	fd:i32, process id:i32	File descriptor released
EV66	VFS Sync Completed	mount point:Text, pages flushed:i32	Dirty pages flushed
EV67	VFS Path Resolved	path:Text, inode:i32	Path walked to inode

B.8 — Network Stack (G8, One)

ID	Event	Carries	Description
EV68	NetworkStack Initialized	protocol count:i32	Protocol handlers registered
EV69	NetworkStack Packet Received	interface id:i32, size:i32, protocol:Text	Inbound packet for processing
EV70	NetworkStack Packet Sent	interface id:i32, size:i32, protocol:Text	Outbound packet transmitted
EV71	NetworkStack Packet Dropped	reason:Text	Packet discarded
EV72	NetworkStack Congestion Detected	interface id:i32, drop rate:f32	Drop rate exceeded threshold
EV73	NetworkStack Congestion Cleared	interface id:i32	Drop rate returned to normal
EV74	NetworkStack Route Updated	destination:Text, gateway:Text, interface id:i32	Routing table modified
EV75	NetworkStack Retransmit	connection id:i32, segment id:i32	Lost segment resent

B.9 — Display Server (G9, One)

ID	Event	Carries	Description
EV76	DisplayServer Started	backend:Text	Compositor initialized

ID	Event	Carries	Description
EV77	DisplayServer Frame Composited	window count:i32, frame time ms:f32	One frame rendered
EV78	DisplayServer Input Routed	window id:i32, input type:Text	Input delivered to window
EV79	DisplayServer Session Manager Started	pid:i32	Session manager launched
EV80	DisplayServer Login Screen Rendered	display id:i32	Login prompt visible
EV81	DisplayServer Suspended	reason:Text	Display off
EV82	DisplayServer Resumed	resume time ms:f32	Display restored
EV83	DisplayServer Failed	reason:Text	Unrecoverable display error

B.10 — Audio Mixer (G10, One)

ID	Event	Carries	Description
EV84	AudioMixer Initialized	device:Text, sample rate:i32	Audio hardware opened
EV85	AudioMixer Channels Mixed	channel count:i32	Active streams combined
EV86	AudioMixer Volume Adjusted	channel:Text, volume:f32	Volume changed
EV87	AudioMixer Muted	reason:Text	All output silenced
EV88	AudioMixer Unmuted	—	Output restored
EV89	AudioMixer Suspended	—	Hardware released
EV90	AudioMixer Resumed	—	Hardware reacquired
EV91	AudioMixer Failed	reason:Text	Unrecoverable audio error

B.11 — Device Manager (G11, One)

ID	Event	Carries	Description
EV92	DeviceManager Started	—	Device manager daemon running
EV93	DeviceManager Bus Scanned	bus type:Text, device count:i32	Bus enumeration complete
EV94	DeviceManager Driver Matched	device id:i32, driver:Text	Driver found for device
EV95	DeviceManager Driver Loaded	device id:i32, driver:Text	Kernel module loaded for device
EV96	DeviceManager Node Created	device path:Text	/dev entry created
EV97	DeviceManager Node Removed	device path:Text	/dev entry removed
EV98	DeviceManager Event Notified	device id:i32, event type:Text	Listeners notified of device change
EV99	DeviceManager Failed	reason:Text	Device manager error

B.12 — Swap Manager (G12, One)

ID	Event	Carries	Description
EV100	SwapManager Activated	device:Text, size:i32	Swap partition enabled
EV101	SwapManager Deactivated	device:Text	Swap partition disabled
EV102	SwapManager Page Written	page address:i32	Page swapped out
EV103	SwapManager Page Read	page address:i32	Page swapped in
EV104	SwapManager Defragment Started	fragmentation ratio:f32	Swap defrag begun
EV105	SwapManager Defragment Completed	pages moved:i32	Swap defrag finished
EV106	SwapManager Full	used ratio:f32	Swap space exhausted
EV107	SwapManager Degraded	io rate:f32	Excessive swap IO, possible thrashing

B.13 — Firewall (G13, One)

ID	Event	Carries	Description
EV108	Firewall Ruleset Loaded	rule count:i32	Packet filter rules active
EV109	Firewall Packet Allowed	source:Text, destination:Text, port:i32	Packet passed
EV110	Firewall Packet Dropped	source:Text, destination:Text, port:i32, rule id:i32	Packet silently discarded
EV111	Firewall Packet Rejected	source:Text, destination:Text, port:i32, rule id:i32	Packet discarded with ICMP response
EV112	Firewall Ruleset Reloaded	rule count:i32	Rules hot-reloaded
EV113	Firewall Failed	reason:Text	Firewall error

B.14 — DNS Resolver (G14, One)

ID	Event	Carries	Description
EV114	DNSResolver Configured	nameserver count:i32	Resolver ready
EV115	DNSResolver Query Resolved	hostname:Text, address:Text, ttl:i32	Successful resolution
EV116	DNSResolver Query Failed	hostname:Text, reason:Text	Resolution failed
EV117	DNSResolver Cache Hit	hostname:Text	Served from cache
EV118	DNSResolver Cache Evicted	entry count:i32	Expired entries removed
EV119	DNSResolver Failover	from server:Text, to server:Text	Switched nameserver
EV120	DNSResolver Failed	reason:Text	Resolver error

B.15 — Session Manager (G15, One)

ID	Event	Carries	Description
EV121	SessionManager Started	—	Session manager running
EV122	SessionManager Login Presented	display id:i32	Login prompt shown

ID	Event	Carries	Description
EV123	SessionManager Credentials Received	username:Text	User submitted credentials
EV124	SessionManager Session Created	session id:i32, user id:i32	New session allocated
EV125	SessionManager Session Destroyed	session id:i32	Session cleaned up
EV126	SessionManager Session Switched	from session id:i32, to session id:i32	Active session changed
EV127	SessionManager Session Locked	session id:i32	Session locked
EV128	SessionManager Failed	reason:Text	Session manager error

B.16 — System Logger (G16, One)

ID	Event	Carries	Description
EV129	SystemLogger Started	log path:Text	Logger running
EV130	SystemLogger Entry Written	severity:i32, source:Text	Log entry recorded
EV131	SystemLogger Buffer Flushed	entry count:i32	Buffer written to disk
EV132	SystemLogger Log Rotated	old path:Text, new path:Text	Log file cycled
EV133	SystemLogger Log Forwarded	destination:Text, entry count:i32	Entries sent to remote
EV134	SystemLogger Buffer Full	buffered count:i32	Buffer capacity reached
EV135	SystemLogger Failed	reason:Text	Logger error

B.17 — Package Manager (G17, One)

ID	Event	Carries	Description
EV136	PackageManager Index Refreshed	package count:i32	Package database updated

ID	Event	Carries	Description
EV137	PackageManager Dependencies Resolved	package:Text, dependency count:i32	Dependency graph computed
EV138	PackageManager Package Downloaded	package:Text, size:i32	Package fetched
EV139	PackageManager Package Installed	package:Text, version:Text	Package configured
EV140	PackageManager Package Removed	package:Text	Package uninstalled
EV141	PackageManager Integrity Verified	checked count:i32, failed count:i32	Installed packages checked
EV142	PackageManager Failed	package:Text, reason:Text	Package operation failed

B.18 — Process (G18, Infinity)

ID	Event	Carries	Description
EV143	Process Created	pid:i32, parent pid:i32	New process allocated
EV144	Process Forked	parent pid:i32, child pid:i32	Fork completed
EV145	Process Exec	pid:i32, executable:Text	Process image replaced
EV146	Process Ready	pid:i32	On run queue, waiting for CPU
EV147	Process Running	pid:i32, cpu id:i32	Executing on CPU
EV148	Process Blocked	pid:i32, reason:Text	Waiting on resource
EV149	Process Sleeping	pid:i32, duration ms:i32	Sleep syscall
EV150	Process Resumed	pid:i32	Unblocked, back to ready
EV151	Process Syscall	pid:i32, syscall id:i32	Trap to kernel
EV152	Process Page Fault	pid:i32, address:i32, fault type:Text	Virtual page missing
EV153	Process Signal Received	pid:i32, signal:i32	Signal delivered
EV154	Process Yielded	pid:i32	Voluntary CPU release
EV155	Process Exited	pid:i32, exit code:i32	Exit syscall or fatal signal

ID	Event	Carries	Description
EV156	Process Zombie	pid:i32	Exited, parent hasn't waited
EV157	Process Waited	parent pid:i32, child pid:i32, exit code:i32	Parent collected exit status
EV158	Process Terminated	pid:i32	Fully cleaned up

B.19 — Thread (G19, Infinity)

ID	Event	Carries	Description
EV159	Thread Created	thread id:i32, process id:i32	Thread allocated
EV160	Thread Started	thread id:i32	Thread running
EV161	Thread Blocked	thread id:i32, reason:Text	Waiting on lock/IO
EV162	Thread Resumed	thread id:i32	Unblocked
EV163	Thread Joined	thread id:i32, joining thread id:i32	Another thread waiting on this one
EV164	Thread Detached	thread id:i32	Detached from parent
EV165	Thread Lock Acquired	thread id:i32, mutex id:i32	Mutex obtained
EV166	Thread Lock Released	thread id:i32, mutex id:i32	Mutex released
EV167	Thread Condition Wait	thread id:i32, condition id:i32	Waiting on condition variable
EV168	Thread Condition Signaled	thread id:i32, condition id:i32	Condition variable signaled
EV169	Thread Terminated	thread id:i32	Thread done

B.20 — File (G20, Infinity)

ID	Event	Carries	Description
EV170	File Opened	fd:i32, path:Text, mode:Text, process id:i32	Descriptor created
EV171	File Read	fd:i32, bytes:i32	Data read
EV172	File Written	fd:i32, bytes:i32	Data written
EV173	File Seeked	fd:i32, position:i32	Position changed

ID	Event	Carries	Description
EV174	File Locked	fd:i32, lock type:Text	File lock acquired
EV175	File Unlocked	fd:i32	File lock released
EV176	File Synced	fd:i32	Dirty data flushed
EV177	File Error	fd:i32, error:Text	IO error
EV178	File Closed	fd:i32	Descriptor released

B.21 — Filesystem Mount (G21, Infinity)

ID	Event	Carries	Description
EV179	Filesystem Check Started	device:Text	fsck begun
EV180	Filesystem Check Completed	device:Text, clean:bool	fsck result
EV181	Filesystem Mount Started	device:Text, mount point:Text, fs type:Text	Mount in progress
EV182	Filesystem Mounted	device:Text, mount point:Text	Mount complete
EV183	Filesystem Remounted	mount point:Text, new options:Text	Mount options changed
EV184	Filesystem Sync Completed	mount point:Text, pages flushed:i32	Dirty pages written
EV185	Filesystem Unmount Started	mount point:Text	Unmount in progress
EV186	Filesystem Unmounted	mount point:Text	Unmount complete
EV187	Filesystem Error	mount point:Text, error:Text	Filesystem error

B.22 — Network Connection (G22, Infinity)

ID	Event	Carries	Description
EV188	Connection Initiated	connection id:i32, local address:Text, remote address:Text	Connect syscall
EV189	Connection SYN Sent	connection id:i32	TCP handshake begun
EV190	Connection Established	connection id:i32	Handshake complete

ID	Event	Carries	Description
EV191	Connection Data Sent	connection id:i32, bytes:i32	Data transmitted
EV192	Connection Data Received	connection id:i32, bytes:i32	Data received
EV193	Connection Retransmit	connection id:i32, segment id:i32	Lost segment resent
EV194	Connection Window Reduced	connection id:i32, new window:i32	Congestion backoff
EV195	Connection Close Initiated	connection id:i32	Graceful close begun
EV196	Connection Close Wait	connection id:i32	Waiting for remote FIN
EV197	Connection Time Wait	connection id:i32	2MSL timer running
EV198	Connection Reset	connection id:i32, reason:Text	Forced close
EV199	Connection Terminated	connection id:i32	Fully closed

B.23 — User Account (G23, Infinity)

ID	Event	Carries	Description
EV200	Account Created	user id:i32, username:Text	User added to system
EV201	Account Activated	user id:i32	Login enabled
EV202	Account Locked	user id:i32, reason:Text	Login temporarily blocked
EV203	Account Unlocked	user id:i32	Lock removed
EV204	Account Disabled	user id:i32, reason:Text	Administratively blocked
EV205	Account Deleted	user id:i32	User removed
EV206	Account Password Changed	user id:i32	Credentials updated
EV207	Account Permissions Updated	user id:i32, groups:Text	Group memberships changed

B.24 — User Session (G24, Infinity)

ID	Event	Carries	Description
EV208	Session Credentials Entered	session id:i32, username:Text	User submitted login
EV209	Session Authenticated	session id:i32, user id:i32	Credentials valid
EV210	Session Authentication Failed	session id:i32, reason:Text	Credentials invalid
EV211	Session Created	session id:i32, user id:i32	Session allocated
EV212	Session Environment Loaded	session id:i32, var count:i32	Profile and env vars applied
EV213	Session Autostart Launched	session id:i32, app count:i32	Session applications started
EV214	Session Desktop Rendered	session id:i32	Desktop visible
EV215	Session Input Ready	session id:i32	User can interact
EV216	Session Locked	session id:i32	Screen locked
EV217	Session Unlocked	session id:i32	Lock removed
EV218	Session Suspended	session id:i32	Session paused
EV219	Session Resumed	session id:i32	Session restored
EV220	Session Logout	session id:i32	User logged out
EV221	Session Terminated	session id:i32	Session cleaned up

B.25 — Device (G25, Infinity)

ID	Event	Carries	Description
EV222	Device Discovered	device id:i32, bus type:Text, vendor id:i32, product id:i32	Hardware detected
EV223	Device Driver Loading	device id:i32, driver:Text	Driver load in progress
EV224	Device Driver Loaded	device id:i32, driver:Text	Driver loaded

ID	Event	Carries	Description
EV225	Device Initializing	device id:i32	Device init sequence running
EV226	Device Self Test Passed	device id:i32	Self-test success
EV227	Device Self Test Failed	device id:i32, reason:Text	Self-test failure
EV228	Device Ready	device id:i32	Device operational
EV229	Device Error	device id:i32, error:Text, error count:i32	Device error
EV230	Device Reset	device id:i32	Recovery attempt
EV231	Device Suspended	device id:i32	Low power state
EV232	Device Resumed	device id:i32	Woken from suspend
EV233	Device Removed	device id:i32	Hotplug removal or unrecoverable

B.26 — Kernel Module (G26, Infinity)

ID	Event	Carries	Description
EV234	Module Load Started	module name:Text	Module load begun
EV235	Module Loaded	module name:Text	Module in kernel memory
EV236	Module Init Completed	module name:Text	Module init function succeeded
EV237	Module Init Failed	module name:Text, reason:Text	Module init function failed
EV238	Module Unload Started	module name:Text	Module unload begun
EV239	Module Unloaded	module name:Text	Module removed from kernel

B.27 — Service (G27, Infinity)

ID	Event	Carries	Description
EV240	Service Start Requested	service id:i32, service name:Text	Start command issued
EV241	Service Started	service id:i32, pid:i32	Process launched
EV242	Service Running	service id:i32	Healthy and operational

ID	Event	Carries	Description
EV243	Service Health Check Passed	service id:i32	Periodic check succeeded
EV244	Service Health Check Failed	service id:i32, reason:Text	Periodic check failed
EV245	Service Degraded	service id:i32, reason:Text	Partially functional
EV246	Service Failed	service id:i32, exit code:i32	Process died or unresponsive
EV247	Service Restart Requested	service id:i32, restart count:i32	Auto-restart triggered
EV248	Service Restarted	service id:i32, pid:i32	New process launched
EV249	Service Reload Requested	service id:i32	Config reload triggered
EV250	Service Reloaded	service id:i32	Config applied without restart
EV251	Service Stop Requested	service id:i32	Stop command issued
EV252	Service Stopped	service id:i32	Process terminated cleanly
EV253	Service Escalated	service id:i32, reason:Text	Retries exhausted, reported to Init

B.28 — Window (G28, Infinity)

ID	Event	Carries	Description
EV254	Window Created	window id:i32, process id:i32, title:Text	Surface allocated
EV255	Window Shown	window id:i32	Made visible
EV256	Window Hidden	window id:i32	Removed from composition
EV257	Window Focused	window id:i32	Receiving input
EV258	Window Unfocused	window id:i32	Lost input focus
EV259	Window Minimized	window id:i32	Reduced to taskbar
EV260	Window Maximized	window id:i32	Filled screen
EV261	Window Restored	window id:i32	Returned to normal size
EV262	Window Resized	window id:i32, width:i32, height:i32	Geometry changed

ID	Event	Carries	Description
EV263	Window Moved	window id:i32, x:i32, y:i32	Position changed
EV264	Window Closed	window id:i32	Destroyed

B.29 — Network Interface (G29, Infinity)

ID	Event	Carries	Description
EV265	Interface Detected	interface id:i32, name:Text, mac:Text	Hardware or virtual interface found
EV266	Interface Configuring	interface id:i32	Configuration in progress
EV267	Interface Address Assigned	interface id:i32, address:Text, mask:Text	IP address applied
EV268	Interface Up	interface id:i32	Interface operational
EV269	Interface Degraded	interface id:i32, reason:Text	Errors above threshold
EV270	Interface Down	interface id:i32	Interface disabled
EV271	Interface DHCP Renewed	interface id:i32, address:Text, lease seconds:i32	DHCP lease refreshed
EV272	Interface Failed	interface id:i32, reason:Text	Unrecoverable interface error
EV273	Interface Reset	interface id:i32	Recovery attempted

B.30 — Permission Rule (G30, Infinity)

ID	Event	Carries	Description
EV274	Permission Granted	rule id:i32, subject id:i32, resource:Text, action:Text	ACL entry created
EV275	Permission Evaluated	rule id:i32, result:bool	Access check performed
EV276	Permission Expired	rule id:i32	Time-based deactivation
EV277	Permission Revoked	rule id:i32	Explicitly removed

B.31 — Timer (G31, Infinity)

ID	Event	Carries	Description
EV278	Timer Armed	timer id:i32, duration ms:i32, callback event id:i32	Timer started
EV279	Timer Fired	timer id:i32, callback event id:i32	Timer expired, callback emitted
EV280	Timer Reset	timer id:i32, new duration ms:i32	Timer restarted
EV281	Timer Cancelled	timer id:i32	Timer deactivated

B.32 — Signal (G32, Infinity)

ID	Event	Carries	Description
EV282	Signal Sent	signal id:i32, signal number:i32, source pid:i32, target pid:i32	Signal queued
EV283	Signal Delivered	signal id:i32	Signal presented to target
EV284	Signal Handled	signal id:i32, handler address:i32	Custom handler executed
EV285	Signal Ignored	signal id:i32	Signal masked
EV286	Signal Default Action	signal id:i32, action:Text	Default behavior (term, stop, core)

B.33 — Pipe (G33, Infinity)

ID	Event	Carries	Description
EV287	Pipe Created	pipe id:i32, read fd:i32, write fd:i32	Pipe allocated
EV288	Pipe Written	pipe id:i32, bytes:i32	Data written to pipe
EV289	Pipe Read	pipe id:i32, bytes:i32	Data read from pipe
EV290	Pipe Full	pipe id:i32	Buffer capacity reached
EV291	Pipe End Closed	pipe id:i32, end:Text	One end closed
EV292	Pipe Broken	pipe id:i32	Writer gone

B.34 — Shared Memory Region (G34, Infinity)

ID	Event	Carries	Description
EV293	SharedMem Allocated	region id:i32, size:i32	Region reserved

ID	Event	Carries	Description
EV294	SharedMem Mapped	region id:i32, process id:i32, address:i32	Attached to process address space
EV295	SharedMem Unmapped	region id:i32, process id:i32	Detached from process
EV296	SharedMem Synced	region id:i32	Flushed to backing store
EV297	SharedMem Freed	region id:i32	Region released

B.35 — Environment Variable Set (G35, Infinity)

ID	Event	Carries	Description
EV298	EnvVars Loaded	process id:i32, var count:i32	Environment inherited or read from profile
EV299	EnvVar Set	process id:i32, key:Text, value:Text	Variable added or updated
EV300	EnvVar Unset	process id:i32, key:Text	Variable removed
EV301	EnvVars Exported	process id:i32, child pid:i32	Environment passed to child process

B.36 — Cron Job (G36, Infinity)

ID	Event	Carries	Description
EV302	CronJob Scheduled	job id:i32, expression:Text	Job registered with timer
EV303	CronJob Executing	job id:i32, pid:i32	Job process launched
EV304	CronJob Completed	job id:i32, exit code:i32	Job finished successfully
EV305	CronJob Failed	job id:i32, exit code:i32, reason:Text	Job exited with error
EV306	CronJob Rescheduled	job id:i32, next time:f32	Next run time calculated

B.37 — Log Entry (G37, Infinity)

ID	Event	Carries	Description
EV307	Log Buffered	entry id:i32, severity:i32, source:Text, message:Text	Entry accepted into memory buffer
EV308	Log Written	entry id:i32	Entry flushed to disk
EV309	Log Rotated	entry id:i32, new file:Text	Entry's file rotated
EV310	Log Archived	entry id:i32	Rotated file compressed
EV311	Log Deleted	entry id:i32	Archive aged out and removed

Event count summary: 311 total events across 37 EntityGroups.

Table C: Event Flows

C.1 — Intra-Group Flows

ID	From	To	Type	Description
FL1	EV1	EV2	linear	POST completes, enumerate hardware
FL2	EV2	EV3	linear	Hardware known, select boot device
FL3	EV3	EV4	linear	Boot device selected, read MBR
FL4	EV4	EV5	linear	MBR loaded, transfer to bootloader
FL5	EV6	EV7	linear	Stage1 loads stage2
FL6	EV7	EV8	linear	Stage2 locates kernel
FL7	EV8	EV9	linear	Kernel found, load to memory
FL8	EV9	EV10	linear	Kernel loaded, load initrd
FL9	EV10	EV11	linear	Initrd loaded, set kernel params
FL10	EV11	EV12	linear	Params set, transfer control
FL11	EV13	EV14	linear	Entered kernel, init page tables
FL12	EV14	EV15	linear	Pages ready, start memory manager
FL13	EV15	EV16	linear	Memory ready, build interrupt table
FL14	EV16	EV17	linear	Interrupts ready, start timer
FL15	EV17	EV18	parallel	Timer ready, init console

ID	From	To	Type	Description
FL16	EV17	EV19	parallel	Timer ready, enumerate PCI
FL17	EV18	EV20	converge	Console done, join for block device discovery
FL18	EV19	EV20	converge	PCI done, join for block device discovery
FL19	EV20	EV21	linear	Block devices known, mount root
FL20	EV21	EV22	linear	Root mounted, unpack initrd
FL21	EV22	EV23	linear	Initrd unpacked, load modules
FL22	EV23	EV24	linear	Modules loaded, switch root
FL23	EV13	EV25	branch	Any kernel event can panic on failure
FL24	EV26	EV27	linear	Init started, determine runlevel
FL25	EV27	EV28	linear	Runlevel known, set hostname
FL26	EV28	EV29	linear	Hostname set, apply sysctl
FL27	EV29	EV30	linear	Sysctl applied, start udev
FL28	EV30	EV31	linear	Udev running, populate devices
FL29	EV31	EV32	linear	Devices populated, check filesystems
FL30	EV32	EV33	linear	Filesystems clean, mount them
FL31	EV33	EV34	linear	Filesystems mounted, enable swap
FL32	EV34	EV35	parallel	Swap enabled, sync clock
FL33	EV34	EV36	parallel	Swap enabled, bring up loopback
FL34	EV35	EV37	converge	Clock synced, join for network config
FL35	EV36	EV37	converge	Loopback up, join for network config
FL36	EV37	EV38	linear	Network up, apply firewall
FL37	EV38	EV39	linear	Firewall applied, configure DNS
FL38	EV26	EV40	branch	Any init step can fail
FL39	EV41	EV42	linear	Initialized, ready for allocations
FL40	EV42	EV43	cycle	Alloc and free cycle continuously
FL41	EV43	EV42	cycle	Free and alloc cycle continuously

ID	From	To	Type	Description
FL42	EV50	EV44	linear	Degraded, start compaction
FL43	EV44	EV45	linear	Compaction started, completes
FL44	EV50	EV46	linear	Degraded, start reclaim
FL45	EV46	EV47	linear	Reclaim started, completes
FL46	EV51	EV48	linear	Critical, trigger OOM
FL47	EV48	EV49	linear	OOM triggered, kill process
FL48	EV52	EV53	linear	Initialized, begin scheduling
FL49	EV53	EV53	cycle	Continuous context switching
FL50	EV59	EV54	linear	Overloaded, start rebalance
FL51	EV54	EV55	linear	Rebalance started, completes
FL52	EV53	EV56	branch	Switch may trigger priority adjust
FL53	EV53	EV57	branch	Switch may trigger migration
FL54	EV53	EV58	branch	Switch may be preemption
FL55	EV60	EV61	linear	Initialized, register filesystem types
FL56	EV61	EV62	linear	Type registered, mounts can proceed
FL57	EV64	EV65	cycle	Open and close cycle
FL58	EV62	EV66	linear	Mounted, sync can occur
FL59	EV62	EV63	linear	Mounted, can unmount
FL60	EV68	EV69	linear	Initialized, ready to receive
FL61	EV69	EV70	linear	Received packet may generate outbound
FL62	EV69	EV71	branch	Received packet may be dropped
FL63	EV72	EV71	linear	Congestion detected, packets dropped
FL64	EV72	EV75	linear	Congestion causes retransmits
FL65	EV73	EV69	linear	Congestion cleared, resume normal
FL66	EV68	EV74	linear	Initialized, routes can be updated
FL67	EV76	EV79	linear	Started, start session manager
FL68	EV79	EV80	linear	Session manager up, render login
FL69	EV76	EV77	cycle	Started, composite every frame
FL70	EV77	EV78	linear	Frame composited, route input
FL71	EV76	EV81	branch	Can suspend
FL72	EV81	EV82	linear	Suspended, can resume
FL73	EV76	EV83	branch	Can fail

ID	From	To	Type	Description
FL74	EV84	EV85	cycle	Initialized, mix channels every tick
FL75	EV85	EV86	branch	Mix may adjust volume
FL76	EV84	EV87	branch	Can mute
FL77	EV87	EV88	linear	Muted, can unmute
FL78	EV84	EV89	branch	Can suspend
FL79	EV89	EV90	linear	Suspended, can resume
FL80	EV84	EV91	branch	Can fail
FL81	EV92	EV93	linear	Started, scan buses
FL82	EV93	EV94	linear	Bus scanned, match drivers
FL83	EV94	EV95	linear	Driver matched, load it
FL84	EV95	EV96	linear	Driver loaded, create dev node
FL85	EV96	EV98	linear	Node created, notify listeners
FL86	EV97	EV98	linear	Node removed, notify listeners
FL87	EV92	EV99	branch	Can fail
FL88	EV100	EV102	cycle	Activated, page writes begin
FL89	EV102	EV103	cycle	Write and read cycle
FL90	EV106	EV104	linear	Full, start defragment
FL91	EV104	EV105	linear	Defragment started, completes
FL92	EV107	EV101	branch	Degraded may deactivate
FL93	EV100	EV101	branch	Can deactivate
FL94	EV108	EV109	cycle	Loaded, evaluate packets continuously
FL95	EV108	EV110	cycle	Loaded, drop matching packets
FL96	EV108	EV111	cycle	Loaded, reject matching packets
FL97	EV108	EV112	branch	Can reload ruleset
FL98	EV108	EV113	branch	Can fail
FL99	EV114	EV115	cycle	Configured, resolve queries
FL100	EV114	EV116	branch	Query can fail
FL101	EV115	EV117	linear	Resolved, may cache
FL102	EV117	EV118	linear	Cache grows, eviction occurs
FL103	EV116	EV119	branch	Failure may trigger failover
FL104	EV114	EV120	branch	Can fail
FL105	EV121	EV122	linear	Started, present login
FL106	EV122	EV123	linear	Login shown, credentials received
FL107	EV123	EV124	branch	Valid credentials, create session

ID	From	To	Type	Description
FL108	EV123	EV122	branch	Invalid credentials, re-present login
FL109	EV124	EV125	branch	Session can be destroyed
FL110	EV124	EV126	branch	Can switch sessions
FL111	EV124	EV127	branch	Can lock session
FL112	EV121	EV128	branch	Can fail
FL113	EV129	EV130	cycle	Started, write entries continuously
FL114	EV134	EV131	linear	Buffer full, flush
FL115	EV130	EV132	branch	Write may trigger rotation
FL116	EV130	EV133	branch	Write may trigger forwarding
FL117	EV129	EV135	branch	Can fail
FL118	EV136	EV137	linear	Index refreshed, resolve deps
FL119	EV137	EV138	linear	Deps resolved, download
FL120	EV138	EV139	linear	Downloaded, install
FL121	EV139	EV141	linear	Installed, verify integrity
FL122	EV140	EV141	linear	Removed, verify integrity
FL123	EV136	EV142	branch	Any step can fail
FL124	EV143	EV146	linear	Created, become ready
FL125	EV146	EV147	linear	Ready, scheduled to run
FL126	EV147	EV148	branch	Running, can block
FL127	EV147	EV149	branch	Running, can sleep
FL128	EV148	EV150	linear	Blocked, resume when unblocked
FL129	EV149	EV150	linear	Sleeping, resume when woken
FL130	EV150	EV146	linear	Resumed, back to ready
FL131	EV147	EV151	branch	Running, may syscall
FL132	EV147	EV152	branch	Running, may page fault
FL133	EV147	EV153	branch	Running, may receive signal
FL134	EV147	EV154	branch	Running, may yield
FL135	EV154	EV146	linear	Yielded, back to ready
FL136	EV147	EV155	branch	Running, may exit
FL137	EV155	EV156	linear	Exited, become zombie
FL138	EV156	EV157	linear	Zombie, parent waits
FL139	EV157	EV158	linear	Waited, terminated
FL140	EV143	EV144	branch	Created by fork
FL141	EV144	EV145	branch	Forked, may exec
FL142	EV159	EV160	linear	Created, start
FL143	EV160	EV161	branch	Started, can block
FL144	EV161	EV162	linear	Blocked, resume
FL145	EV162	EV160	linear	Resumed, running again
FL146	EV160	EV165	branch	Running, may acquire lock
FL147	EV165	EV166	linear	Locked, eventually release

ID	From	To	Type	Description
FL148	EV160	EV167	branch	Running, may wait on condition
FL149	EV167	EV168	linear	Waiting, signaled
FL150	EV168	EV162	linear	Signaled, resume
FL151	EV160	EV163	branch	Running, may be joined
FL152	EV160	EV164	branch	Running, may detach
FL153	EV160	EV169	linear	Running, eventually terminate
FL154	EV170	EV171	cycle	Opened, read
FL155	EV170	EV172	cycle	Opened, write
FL156	EV170	EV173	branch	Opened, may seek
FL157	EV170	EV174	branch	Opened, may lock
FL158	EV174	EV175	linear	Locked, eventually unlock
FL159	EV172	EV176	branch	Write may trigger sync
FL160	EV170	EV177	branch	Any operation may error
FL161	EV170	EV178	linear	Opened, eventually close
FL162	EV179	EV180	linear	Check started, check completed
FL163	EV180	EV181	branch	If clean, start mount
FL164	EV181	EV182	linear	Mount started, mounted
FL165	EV182	EV183	branch	Mounted, may remount
FL166	EV182	EV184	branch	Mounted, may sync
FL167	EV182	EV185	branch	Mounted, may start unmount
FL168	EV185	EV186	linear	Unmount started, unmounted
FL169	EV181	EV187	branch	Mount can error
FL170	EV188	EV189	linear	Initiated, SYN sent
FL171	EV189	EV190	linear	SYN sent, established
FL172	EV190	EV191	cycle	Established, send data
FL173	EV190	EV192	cycle	Established, receive data
FL174	EV190	EV193	branch	Established, may retransmit
FL175	EV190	EV194	branch	Established, window may reduce
FL176	EV190	EV195	branch	Established, may close
FL177	EV195	EV196	linear	Close initiated, close wait
FL178	EV196	EV197	linear	Close wait, time wait
FL179	EV197	EV199	linear	Time wait, terminated
FL180	EV190	EV198	branch	Established, may reset
FL181	EV198	EV199	linear	Reset, terminated
FL182	EV200	EV201	linear	Created, activate
FL183	EV201	EV202	branch	Active, may lock
FL184	EV202	EV203	linear	Locked, may unlock
FL185	EV201	EV204	branch	Active, may disable
FL186	EV204	EV205	branch	Disabled, may delete
FL187	EV201	EV206	branch	Active, may change password

ID	From	To	Type	Description
FL188	EV201	EV207	branch	Active, may update permissions
FL189	EV208	EV209	branch	Credentials entered, authenticate success
FL190	EV208	EV210	branch	Credentials entered, authenticate fail
FL191	EV210	EV208	cycle	Failed, re-enter credentials
FL192	EV209	EV211	linear	Authenticated, create session
FL193	EV211	EV212	linear	Session created, load environment
FL194	EV212	EV213	linear	Environment loaded, launch autostart
FL195	EV213	EV214	linear	Autostart done, render desktop
FL196	EV214	EV215	linear	Desktop rendered, input ready
FL197	EV215	EV216	branch	Active, may lock
FL198	EV216	EV217	linear	Locked, may unlock
FL199	EV215	EV218	branch	Active, may suspend
FL200	EV218	EV219	linear	Suspended, may resume
FL201	EV215	EV220	branch	Active, may logout
FL202	EV220	EV221	linear	Logout, terminate
FL203	EV222	EV223	linear	Discovered, load driver
FL204	EV223	EV224	linear	Driver loading, loaded
FL205	EV224	EV225	linear	Driver loaded, initializing
FL206	EV225	EV226	branch	Initializing, self test pass
FL207	EV225	EV227	branch	Initializing, self test fail
FL208	EV226	EV228	linear	Test passed, ready
FL209	EV228	EV229	branch	Ready, may error
FL210	EV229	EV230	branch	Error, may reset
FL211	EV230	EV225	linear	Reset, re-initialize
FL212	EV228	EV231	branch	Ready, may suspend
FL213	EV231	EV232	linear	Suspended, may resume
FL214	EV228	EV233	branch	Ready, may be removed
FL215	EV227	EV233	branch	Test failed, may remove
FL216	EV229	EV233	branch	Error unrecoverable, remove
FL217	EV234	EV235	linear	Load started, loaded
FL218	EV235	EV236	branch	Loaded, init success
FL219	EV235	EV237	branch	Loaded, init failed
FL220	EV236	EV238	branch	Running, may start unload
FL221	EV238	EV239	linear	Unload started, unloaded
FL222	EV240	EV241	linear	Start requested, started
FL223	EV241	EV242	linear	Started, running
FL224	EV242	EV243	cycle	Running, health checks pass

ID	From	To	Type	Description
FL225	EV243	EV242	cycle	Health passed, continue running
FL226	EV242	EV244	branch	Running, health check fail
FL227	EV244	EV245	branch	Health failed, degraded
FL228	EV244	EV246	branch	Health failed, fully failed
FL229	EV246	EV247	branch	Failed, request restart
FL230	EV247	EV248	linear	Restart requested, restarted
FL231	EV248	EV242	linear	Restarted, running again
FL232	EV246	EV252	branch	Failed, may stop
FL233	EV246	EV253	branch	Failed, may escalate
FL234	EV242	EV249	branch	Running, reload requested
FL235	EV249	EV250	linear	Reload requested, reloaded
FL236	EV250	EV242	linear	Reloaded, continue running
FL237	EV242	EV251	branch	Running, stop requested
FL238	EV251	EV252	linear	Stop requested, stopped
FL239	EV254	EV255	linear	Created, show
FL240	EV255	EV257	branch	Shown, may focus
FL241	EV257	EV258	branch	Focused, may unfocus
FL242	EV255	EV259	branch	Shown, may minimize
FL243	EV255	EV260	branch	Shown, may maximize
FL244	EV259	EV261	linear	Minimized, restore
FL245	EV260	EV261	linear	Maximized, restore
FL246	EV255	EV262	branch	Shown, may resize
FL247	EV255	EV263	branch	Shown, may move
FL248	EV255	EV256	branch	Shown, may hide
FL249	EV255	EV264	branch	Shown, may close
FL250	EV265	EV266	linear	Detected, configuring
FL251	EV266	EV267	linear	Configuring, address assigned
FL252	EV267	EV268	linear	Address assigned, up
FL253	EV268	EV269	branch	Up, may degrade
FL254	EV268	EV270	branch	Up, may go down
FL255	EV268	EV271	branch	Up, DHCP renew
FL256	EV269	EV273	branch	Degraded, may reset
FL257	EV272	EV273	branch	Failed, may reset
FL258	EV273	EV266	linear	Reset, reconfigure
FL259	EV274	EV275	cycle	Granted, evaluated on access
FL260	EV274	EV276	branch	Granted, may expire
FL261	EV274	EV277	branch	Granted, may be revoked
FL262	EV278	EV279	linear	Armed, fires
FL263	EV279	EV278	cycle	Fired, may re-arm
FL264	EV278	EV280	branch	Armed, may reset
FL265	EV278	EV281	branch	Armed, may cancel
FL266	EV282	EV283	linear	Sent, delivered
FL267	EV283	EV284	branch	Delivered, handled

ID	From	To	Type	Description
FL268	EV283	EV285	branch	Delivered, ignored
FL269	EV283	EV286	branch	Delivered, default action
FL270	EV287	EV288	cycle	Created, write
FL271	EV287	EV289	cycle	Created, read
FL272	EV288	EV290	branch	Write may fill pipe
FL273	EV287	EV291	branch	Created, end may close
FL274	EV291	EV292	branch	End closed, may break
FL275	EV293	EV294	linear	Allocated, map
FL276	EV294	EV295	branch	Mapped, may unmap
FL277	EV294	EV296	branch	Mapped, may sync
FL278	EV295	EV297	branch	Unmapped, may free
FL279	EV298	EV299	cycle	Loaded, set vars
FL280	EV298	EV300	cycle	Loaded, unset vars
FL281	EV298	EV301	branch	Loaded, may export to child
FL282	EV302	EV303	linear	Scheduled, executing
FL283	EV303	EV304	branch	Executing, may complete
FL284	EV303	EV305	branch	Executing, may fail
FL285	EV304	EV306	linear	Completed, reschedule
FL286	EV305	EV306	linear	Failed, reschedule
FL287	EV306	EV302	cycle	Rescheduled, back to scheduled
FL288	EV307	EV308	linear	Buffered, written
FL289	EV308	EV309	branch	Written, may rotate
FL290	EV309	EV310	linear	Rotated, archive
FL291	EV310	EV311	linear	Archived, eventually delete

C.2 — Inter-Group Flows

ID	From	To	Type	Description
FL292	EV5	EV6	linear	BIOS transfers to Bootloader stage1
FL293	EV12	EV13	linear	Bootloader transfers to Kernel entry
FL294	EV24	EV26	linear	Kernel root switched, Init starts
FL295	EV15	EV41	linear	Kernel memory manager started, MemoryManager initializes
FL296	EV41	EV52	linear	MemoryManager ready, Scheduler initializes
FL297	EV21	EV60	linear	Kernel root mounted, VFS initializes

ID	From	To	Type	Description
FL298	EV37	EV68	linear	Init network configured, NetworkStack initializes
FL299	EV39	EV76	linear	Init DNS configured, DisplayServer starts
FL300	EV39	EV84	linear	Init DNS configured, AudioMixer initializes
FL301	EV39	EV129	linear	Init DNS configured, SystemLogger starts
FL302	EV38	EV108	linear	Init firewall applied, Firewall ruleset loads
FL303	EV39	EV114	linear	Init DNS configured, DNSResolver configured
FL304	EV80	EV121	linear	DisplayServer login rendered, SessionManager starts
FL305	EV34	EV100	linear	Init swap enabled, SwapManager activates
FL306	EV30	EV92	linear	Init udev started, DeviceManager starts
FL307	EV92	EV222	fan out	DeviceManager started, discover each device
FL308	EV27	EV240	fan out	Init runlevel determined, start each service in runlevel
FL309	EV31	EV265	fan out	Init devices populated, detect each network interface
FL310	EV32	EV179	fan out	Init filesystems checked, check each filesystem
FL311	EV33	EV181	fan out	Init filesystems mounted, mount each filesystem
FL312	EV52	EV143	fan out	Scheduler initialized, processes can be created
FL313	EV121	EV208	fan out	SessionManager started, user sessions can begin
FL314	EV76	EV254	fan out	DisplayServer started, windows can be created
FL315	EV129	EV307	fan out	SystemLogger started, log entries can be buffered
FL316	EV68	EV188	fan out	NetworkStack initialized, connections can be initiated
FL317	EV108	EV274	fan out	Firewall loaded, permission rules can be granted
FL318	EV84	EV85	fan out	AudioMixer initialized, channels mixed from process streams

ID	From	To	Type	Description
FL319	EV242	EV129	converge	Service[logging] running, SystemLogger fully operational
FL320	EV228	EV21	converge	Device[root disk] ready, Kernel can mount root
FL321	EV228	EV95	converge	Device[any] ready, DeviceManager creates node
FL322	EV182	EV33	converge	All Filesystems mounted, Init mount step complete
FL323	EV268	EV37	converge	All Interfaces up, Init network configured
FL324	EV246	EV253	converge	Service[critical] failed, escalate to Init
FL325	EV155	EV52	converge	Process exits, Scheduler reclaims slot
FL326	EV199	EV68	converge	Connection terminated, NetworkStack reclaims socket
FL327	EV264	EV76	converge	Window closed, DisplayServer removes from compositor
FL328	EV308	EV129	converge	LogEntry written, SystemLogger updates buffer count
FL329	EV228	EV240	fan out	Device[gpu] ready, Service[display driver] starts
FL330	EV242	EV240	fan out	Service[network manager] running, Service[vpn] can start
FL331	EV242	EV240	fan out	Service[dbus] running, dependent Services can start
FL332	EV143	EV159	fan out	Process created, Threads can be created within it
FL333	EV143	EV298	fan out	Process created, EnvironmentVars loaded for it
FL334	EV143	EV170	fan out	Process created, Files can be opened by it
FL335	EV143	EV287	fan out	Process created, Pipes can be created by it
FL336	EV143	EV293	fan out	Process created, SharedMem can be allocated by it
FL337	EV147	EV282	fan out	Process running, Signals can be sent to it

ID	From	To	Type	Description
FL338	EV147	EV151	fan out	Process running, Syscalls invoke kernel services
FL339	EV151	EV170	fan out	Process syscall[open], File opened
FL340	EV151	EV188	fan out	Process syscall[connect], Connection initiated
FL341	EV151	EV287	fan out	Process syscall[pipe], Pipe created
FL342	EV151	EV293	fan out	Process syscall[mmap], SharedMem allocated
FL343	EV151	EV278	fan out	Process syscall[timer create], Timer armed
FL344	EV279	EV303	linear	Timer[cron] fired, CronJob executes
FL345	EV303	EV143	fan out	CronJob executing, Process created for it
FL346	EV211	EV143	fan out	UserSession created, session processes spawned
FL347	EV211	EV298	fan out	UserSession created, session env vars loaded
FL348	EV155	EV282	fan out	Process exited, Signals sent to children
FL349	EV292	EV153	fan out	Pipe broken, Signal to writing process

Flow count summary: 291 intra-group + 58 inter-group = 349 total flows.

Table D: Event Constraints

D.1 — BIOS (G1, Zero)

ID	Event	Constraint	Note
EC1	EV1	true	Initial event, no precondition
EC2	EV2	event completed(ev1)	POST passed
EC3	EV3	event completed(ev2)	Hardware enumerated
EC4	EV4	event completed(ev3)	Boot device selected
EC5	EV5	event completed(ev4)	MBR loaded

D.2 — Bootloader (G2, Zero)

ID	Event	Constraint	Note
EC6	EV6	event completed(ev5)	BIOS transferred control
EC7	EV7	event completed(ev6)	Stage1 loaded
EC8	EV8	event completed(ev7)	Stage2 loaded
EC9	EV9	event completed(ev8)	Kernel located
EC10	EV10	event completed(ev9)	Kernel in memory
EC11	EV11	event completed(ev10)	Initrd loaded
EC12	EV12	event completed(ev11)	Params set

D.3 — Kernel (G3, One)

ID	Event	Constraint	Note
EC13	EV13	event completed(ev12)	Bootloader transferred control
EC14	EV14	event completed(ev13)	Kernel entered
EC15	EV15	event completed(ev14)	Page tables initialized
EC16	EV16	event completed(ev15)	Memory manager started
EC17	EV17	event completed(ev16)	Interrupt table built
EC18	EV18	event completed(ev17)	Timer started
EC19	EV19	event completed(ev17)	Timer started, parallel with console
EC20	EV20	event completed(ev18), event completed(ev19)	Console and PCI both done
EC21	EV21	event completed(ev20), device ready(Self, root disk, DevicePath)	Block devices found and root device ready
EC22	EV22	event completed(ev21)	Root filesystem mounted
EC23	EV23	event completed(ev22), filesystem contains(initrd, modules)	Initrd unpacked and modules present
EC24	EV24	event completed(ev23), filesystem mounted(Self, root, RootPath)	Modules loaded and root mounted
EC25	EV25	unrecoverable error(Self, Reason)	Any unrecoverable kernel error

D.4 — Init System (G4, One)

ID	Event	Constraint	Note
EC26	EV26	event completed(ev24)	Kernel root switched
EC27	EV27	event completed(ev26), config readable(inittab, RunLevel)	Init started, inittab readable
EC28	EV28	event completed(ev27)	Runlevel determined
EC29	EV29	event completed(ev28), config readable(sysctl conf, Params)	Hostname set, sysctl config readable
EC30	EV30	event completed(ev29)	Sysctl applied
EC31	EV31	event completed(ev30), device scan complete(Count), Count > 0	Udev started, devices found
EC32	EV32	event completed(ev31)	Devices populated
EC33	EV33	event completed(ev32), all checks passed(true)	Filesystems checked and clean
EC34	EV34	event completed(ev33), device ready(swap, SwapPath)	Filesystems mounted, swap device ready
EC35	EV35	event completed(ev34)	Swap enabled, parallel with loopback
EC36	EV36	event completed(ev34)	Swap enabled, parallel with clock
EC37	EV37	event completed(ev35), event completed(ev36), network interface exists(Iface, Count), Count > 0	Clock synced, loopback up, interfaces exist
EC38	EV38	event completed(ev37), config readable(firewall rules, Rules)	Network configured, rules readable
EC39	EV39	event completed(ev38), network interface active(Iface, true)	Firewall applied, interface active
EC40	EV40	error occurred(Self, Step, Reason)	Any init step failed

D.5 — Memory Manager (G5, One)

ID	Event	Constraint	Note
EC41	EV41	event completed(ev15)	Kernel memory manager started
EC42	EV42	initialized(Self, true), page available(Self, Address)	Initialized and free page exists
EC43	EV43	page allocated(Self, Address), refcount(Self, Address, 0)	Page allocated and no references
EC44	EV44	free page ratio(Self, R), $R < 0.3$, fragmentation ratio(Self, F), $F > 0.5$	Low free pages and high fragmentation
EC45	EV45	compaction running(Self, true)	Compaction was started
EC46	EV46	free page ratio(Self, R), $R < 0.2$	Very low free pages
EC47	EV47	reclaim running(Self, true)	Reclaim was started
EC48	EV48	free page ratio(Self, R), $R < 0.05$, reclaim exhausted(Self, true)	Critical, nothing left to reclaim
EC49	EV49	oom triggered(Self, true), victim selected(Self, PID)	OOM triggered, victim identified
EC50	EV50	free page ratio(Self, R), $R < 0.3$	Entering degraded
EC51	EV51	free page ratio(Self, R), $R < 0.05$	Entering critical

D.6 — Scheduler (G6, One)

ID	Event	Constraint	Note
EC52	EV52	event completed(ev41)	Memory manager initialized
EC53	EV53	run queue nonempty(Self, true)	At least one process ready
EC54	EV54	run queue imbalance(Self, R), $R > 0.3$	Significant CPU load imbalance
EC55	EV55	rebalance running(Self, true)	Rebalance was started
EC56	EV56	starvation detected(Self, PID, D), $D > 5.0$	Process starved 5+ seconds
EC57	EV57	process on wrong cpu(Self, PID, Cur, Best), $Cur = Best$	Process affinity mismatch

ID	Event	Constraint	Note
EC58	EV58	timeslice exhausted(Self, PID, true)	Current process used its quantum
EC59	EV59	run queue length(Self, L), $L > 100$	Run queue excessively long

D.7 — VFS (G7, One)

ID	Event	Constraint	Note
EC60	EV60	event completed(ev21)	Kernel root filesystem mounted
EC61	EV61	initialized(Self, true)	VFS initialized
EC62	EV62	filesystem type registered(Self, T), device ready(DevID, true)	Type registered, device ready
EC63	EV63	mount active(Self, MP), no open files(Self, MP)	Mount exists, no open files
EC64	EV64	mount active(Self, MP), path valid(Self, Path)	Mount active, path resolves
EC65	EV65	fd open(Self, FD, true)	File descriptor is open
EC66	EV66	mount active(Self, MP), dirty pages(Self, MP, C), $C > 0$	Dirty pages exist
EC67	EV67	mount active(Self, MP)	Mount active for path resolution

D.8 — Network Stack (G8, One)

ID	Event	Constraint	Note
EC68	EV68	event completed(ev37)	Init network interfaces configured
EC69	EV69	initialized(Self, true), packet in buffer(Self, Iface, true)	Inbound packet waiting
EC70	EV70	initialized(Self, true), packet in outbound queue(Self, true)	Outbound packet queued
EC71	EV71	packet matches drop rule(Self, Pkt, true)	Packet matches drop condition
EC72	EV72	drop rate(Self, Iface, R), $R > 0.05$	Drop rate exceeds 5%
EC73	EV73	drop rate(Self, Iface, R), $R < 0.01$	Drop rate below 1%

ID	Event	Constraint	Note
EC74	EV74	route change pending(Self, true)	Routing update received
EC75	EV75	segment ack timeout(Self, CID, SID, true)	ACK timeout on segment

D.9 — Display Server (G9, One)

ID	Event	Constraint	Note
EC76	EV76	event completed(ev39), gpu device ready(true)	Init complete, GPU ready
EC77	EV77	running(Self, true), frame due(Self, true)	Compositor running, frame tick
EC78	EV78	running(Self, true), input pending(Self, true)	Input event waiting
EC79	EV79	event completed(ev76)	Display server started
EC80	EV80	event completed(ev79)	Session manager started
EC81	EV81	suspend requested(Self, true)	System suspend requested
EC82	EV82	resume requested(Self, true)	System resume requested
EC83	EV83	unrecoverable error(Self, Reason)	Display server error

D.10 — Audio Mixer (G10, One)

ID	Event	Constraint	Note
EC84	EV84	event completed(ev39), audio device ready(true)	Init complete, audio device ready
EC85	EV85	running(Self, true), active channels(Self, C), $C > 0$	Running, channels to mix
EC86	EV86	running(Self, true), volume change requested(Self, Ch, V)	Volume change request
EC87	EV87	running(Self, true), mute requested(Self, true)	Mute requested
EC88	EV88	muted(Self, true), unmute requested(Self, true)	Unmute requested

ID	Event	Constraint	Note
EC89	EV89	running(Self, true), suspend requested(Self, true)	Suspend requested
EC90	EV90	suspended(Self, true), resume requested(Self, true)	Resume requested
EC91	EV91	unrecoverable error(Self, Reason)	Audio error

D.11 — Device Manager (G11, One)

ID	Event	Constraint	Note
EC92	EV92	event completed(ev30)	Init udev started
EC93	EV93	running(Self, true), bus scan requested(Self, BusType)	Bus scan triggered
EC94	EV94	device discovered(DID), driver exists(DID, Driver)	Device found, driver available
EC95	EV95	driver matched(DID, Driver), module available(Driver)	Driver matched, module loadable
EC96	EV96	driver loaded(DID, true)	Driver loaded for device
EC97	EV97	device removed(DID, true)	Device hotplug removal
EC98	EV98	device state changed(DID, true)	Any device state change
EC99	EV99	unrecoverable error(Self, Reason)	Device manager error

D.12 — Swap Manager (G12, One)

ID	Event	Constraint	Note
EC100	EV100	event completed(ev34), swap device valid(Device)	Init swap enabled, device valid
EC101	EV101	active(Self, Device), deactivate requested(Self, Device)	Deactivation requested
EC102	EV102	active(Self, true), page swap out requested(Self, Addr)	Swap out from memory manager
EC103	EV103	active(Self, true), page swap in requested(Self, Addr)	Swap in from memory manager

ID	Event	Constraint	Note
EC104	EV104	active(Self, true), fragmentation ratio(Self, R), R > 0.5	High fragmentation
EC105	EV105	defragmenting(Self, true)	Defrag was started
EC106	EV106	usage ratio(Self, R), R > 0.95	Swap nearly full
EC107	EV107	io rate(Self, R), R > 1000	Excessive swap IO

D.13 — Firewall (G13, One)

ID	Event	Constraint	Note
EC108	EV108	event completed(ev38), rules valid(Self, true)	Init firewall applied, rules valid
EC109	EV109	packet evaluated(Self, Pkt), rule result(Self, Pkt, allow)	Packet matches allow
EC110	EV110	packet evaluated(Self, Pkt), rule result(Self, Pkt, drop)	Packet matches drop
EC111	EV111	packet evaluated(Self, Pkt), rule result(Self, Pkt, reject)	Packet matches reject
EC112	EV112	reload requested(Self, true), rules valid(Self, true)	Reload requested, new rules valid
EC113	EV113	unrecoverable error(Self, Reason)	Firewall error

D.14 — DNS Resolver (G14, One)

ID	Event	Constraint	Note
EC114	EV114	event completed(ev39), config readable(resolv conf, Servers)	Init DNS configured, resolv.conf readable
EC115	EV115	query pending(Self, H), resolution succeeded(Self, H, Addr)	Query resolved
EC116	EV116	query pending(Self, H), resolution failed(Self, H, Reason)	Query failed

ID	Event	Constraint	Note
EC117	EV117	query pending(Self, H), cache contains(Self, H, true), cache ttl valid(Self, H, true)	Cache hit, not expired
EC118	EV118	cache size(Self, S), cache max(Self, M), $S > M$	Cache exceeds max
EC119	EV119	resolution failed(Self, H, R), alternate server available(Self, Srv)	Failure, alternate exists
EC120	EV120	unrecoverable error(Self, Reason)	Resolver error

D.15 — Session Manager (G15, One)

ID	Event	Constraint	Note
EC121	EV121	event completed(ev80)	Display server login rendered
EC122	EV122	running(Self, true), no active session(Self, true)	Running, no session active
EC123	EV123	login presented(Self, true), credentials submitted(Self, U)	Login shown, credentials received
EC124	EV124	credentials valid(Self, U, true), session slot available(Self, true)	Valid credentials, slot open
EC125	EV125	session active(Self, SID), logout requested(Self, SID)	Session exists, logout requested
EC126	EV126	session active(Self, F), session active(Self, T), switch requested(Self, T)	Both sessions exist, switch requested
EC127	EV127	session active(Self, SID), lock requested(Self, SID)	Session active, lock requested
EC128	EV128	unrecoverable error(Self, Reason)	Session manager error

D.16 — System Logger (G16, One)

ID	Event	Constraint	Note
EC129	EV129	event completed(ev39)	Init DNS configured
EC130	EV130	running(Self, true), entry pending(Self, true)	Running, log entry waiting

ID	Event	Constraint	Note
EC131	EV131	buffer count(Self, C), $C > 0$, flush requested(Self, true)	Buffer has entries, flush triggered
EC132	EV132	log file size(Self, P, S), max size(Self, P, M), $S > M$	Log file exceeds max
EC133	EV133	running(Self, true), remote configured(Self, D), entry pending forward(Self, true)	Remote configured, entry to forward
EC134	EV134	buffer count(Self, C), buffer max(Self, M), $C \geq M$	Buffer full
EC135	EV135	unrecoverable error(Self, Reason)	Logger error

D.17 — Package Manager (G17, One)

ID	Event	Constraint	Note
EC136	EV136	refresh requested(Self, true), network available(true)	Refresh requested, network up
EC137	EV137	index current(Self, true), install requested(Self, Pkg)	Index current, install requested
EC138	EV138	dependencies resolved(Self, Pkg, true), download source available(Self, true)	Deps resolved, source reachable
EC139	EV139	package downloaded(Self, Pkg, true), checksum valid(Self, Pkg, true)	Downloaded, verified
EC140	EV140	remove requested(Self, Pkg), no dependents(Self, Pkg, true)	Remove requested, nothing depends on it
EC141	EV141	verify requested(Self, true)	Integrity check requested
EC142	EV142	operation failed(Self, Pkg, Reason)	Any package operation failed

D.18 — Process (G18, Infinity)

ID	Event	Constraint	Note
EC143	EV143	fork requested(Parent, true)	Parent requested fork
EC144	EV144	process entity(Self), fork executing(Self, true)	Fork in progress
EC145	EV145	process entity(Self), exec requested(Self, Executable)	Exec requested
EC146	EV146	process entity(Self), resources allocated(Self, true)	Process resources ready
EC147	EV147	process entity(Self), scheduled(Self, CPU)	Scheduler assigned CPU
EC148	EV148	process entity(Self), waiting on(Self, Resource, true)	Waiting for IO/lock
EC149	EV149	process entity(Self), sleep requested(Self, Duration)	Sleep syscall
EC150	EV150	process entity(Self), wait condition met(Self, true)	Blocked condition resolved
EC151	EV151	process entity(Self), syscall requested(Self, SyscallID)	Trap to kernel
EC152	EV152	process entity(Self), page not present(Self, Address)	Virtual page missing
EC153	EV153	process entity(Self), signal pending(Self, Signal)	Signal queued
EC154	EV154	process entity(Self), yield requested(Self, true)	Voluntary yield
EC155	EV155	process entity(Self), exit requested(Self, ExitCode)	Exit syscall or fatal signal
EC156	EV156	process entity(Self), exited(Self, true), parent alive(Self, true)	Exited, parent hasn't waited
EC157	EV157	process entity(Self), zombie(Self, true), parent waiting(Self, true)	Parent called wait
EC158	EV158	process entity(Self), waited(Self, true)	Wait collected

D.19 — Thread (G19, Infinity)

ID	Event	Constraint	Note
EC159	EV159	thread create requested(Parent, ProcessID)	Creation requested
EC160	EV160	thread entity(Self), resources allocated(Self, true)	Resources ready

ID	Event	Constraint	Note
EC161	EV161	thread entity(Self), waiting on(Self, Resource, true)	Blocked on lock/condition/IO
EC162	EV162	thread entity(Self), wait condition met(Self, true)	Unblocked
EC163	EV163	thread entity(Self), join requested(Self, JoiningThread)	Another thread joining
EC164	EV164	thread entity(Self), detach requested(Self, true)	Detach from parent
EC165	EV165	thread entity(Self), mutex available(Self, MutexID)	Mutex is free
EC166	EV166	thread entity(Self), mutex held(Self, MutexID)	This thread holds mutex
EC167	EV167	thread entity(Self), condition wait requested(Self, CondID)	Waiting on condition
EC168	EV168	thread entity(Self), condition signaled(Self, CondID)	Condition signaled
EC169	EV169	thread entity(Self), exit requested(Self, true)	Thread termination

D.20 — File (G20, Infinity)

ID	Event	Constraint	Note
EC170	EV170	file open requested(ProcessID, Path, Mode)	Open syscall
EC171	EV171	file entity(Self), open(Self, true), read requested(Self, true)	Open, read requested
EC172	EV172	file entity(Self), open(Self, true), write requested(Self, true), writable(Self, true)	Open, writable, write requested
EC173	EV173	file entity(Self), open(Self, true), seek requested(Self, Pos)	Seek requested
EC174	EV174	file entity(Self), open(Self, true), lock requested(Self, LT), not locked(Self, true)	Open, unlocked, lock requested
EC175	EV175	file entity(Self), locked(Self, true), unlock requested(Self, true)	Locked, unlock requested
EC176	EV176	file entity(Self), open(Self, true), sync requested(Self, true)	Sync requested

ID	Event	Constraint	Note
EC177	EV177	file entity(Self), io error(Self, Error)	IO error occurred
EC178	EV178	file entity(Self), open(Self, true), close requested(Self, true)	Close requested

D.21 — Filesystem Mount (G21, Infinity)

ID	Event	Constraint	Note
EC179	EV179	mount entity(Self), check requested(Self, true)	fsck requested
EC180	EV180	mount entity(Self), check running(Self, true)	fsck completed
EC181	EV181	mount entity(Self), checked(Self, clean), device ready(Self, Device)	Clean, device ready
EC182	EV182	mount entity(Self), mount in progress(Self, true)	Mount completing
EC183	EV183	mount entity(Self), mounted(Self, true), remount requested(Self, Opts)	Remount requested
EC184	EV184	mount entity(Self), mounted(Self, true), dirty pages(Self, C), C > 0	Dirty pages to flush
EC185	EV185	mount entity(Self), mounted(Self, true), unmount requested(Self, true), no open files(Self, true)	Unmount requested, no open files
EC186	EV186	mount entity(Self), unmounting(Self, true)	Unmount completing
EC187	EV187	mount entity(Self), error occurred(Self, Error)	Filesystem error

D.22 — Network Connection (G22, Infinity)

ID	Event	Constraint	Note
EC188	EV188	connect requested(ProcessID, LocalAddr, RemoteAddr)	Connect syscall
EC189	EV189	connection entity(Self), initiated(Self, true)	Connection initiated

ID	Event	Constraint	Note
EC190	EV190	connection entity(Self), syn acked(Self, true)	SYN-ACK received
EC191	EV191	connection entity(Self), established(Self, true), send buffer nonempty(Self, true)	Data to send
EC192	EV192	connection entity(Self), established(Self, true), recv buffer nonempty(Self, true)	Data received
EC193	EV193	connection entity(Self), established(Self, true), ack timeout(Self, SegID)	Segment ACK timed out
EC194	EV194	connection entity(Self), established(Self, true), loss detected(Self, true)	Packet loss detected
EC195	EV195	connection entity(Self), established(Self, true), close requested(Self, true)	Close initiated
EC196	EV196	connection entity(Self), fin received(Self, true)	FIN from remote
EC197	EV197	connection entity(Self), both fins sent(Self, true)	Both sides closing
EC198	EV198	connection entity(Self), reset requested(Self, true)	RST condition
EC199	EV199	connection entity(Self), time wait expired(Self, true)	2MSL timer expired

D.23 — User Account (G23, Infinity)

ID	Event	Constraint	Note
EC200	EV200	account create requested(Username)	Admin create request
EC201	EV201	account entity(Self), created(Self, true), activation approved(Self, true)	Created, approved
EC202	EV202	account entity(Self), active(Self, true), lock condition(Self, Reason)	Lock triggered
EC203	EV203	account entity(Self), locked(Self, true), unlock authorized(Self, true)	Unlock authorized
EC204	EV204	account entity(Self), active(Self, true), disable requested(Self, Reason)	Admin disable

ID	Event	Constraint	Note
EC205	EV205	account entity(Self), disabled(Self, true), delete requested(Self, true)	Admin delete
EC206	EV206	account entity(Self), active(Self, true), password change requested(Self, true)	Password change
EC207	EV207	account entity(Self), active(Self, true), permission change requested(Self, Groups)	Permission update

D.24 — User Session (G24, Infinity)

ID	Event	Constraint	Note
EC208	EV208	session entity(Self), login presented(true), credentials entered(Self, Username)	Credentials submitted
EC209	EV209	session entity(Self), credentials valid(Self, true)	Valid credentials
EC210	EV210	session entity(Self), credentials valid(Self, false)	Invalid credentials
EC211	EV211	session entity(Self), authenticated(Self, true), session slot available(true)	Authenticated, slot open
EC212	EV212	session entity(Self), created(Self, true), home directory accessible(Self, true)	Session created, home accessible
EC213	EV213	session entity(Self), environment loaded(Self, true), autostart list resolved(Self, true)	Env loaded, autostart ready
EC214	EV214	session entity(Self), autostart complete(Self, true), window manager ready(Self, true)	Autostart done, WM ready
EC215	EV215	session entity(Self), desktop rendered(Self, true), input focus granted(Self, true)	Desktop rendered, input active
EC216	EV216	session entity(Self), active(Self, true), idle time(Self, T), idle lock threshold(Self, Th), $T > Th$	Idle exceeded lock threshold

ID	Event	Constraint	Note
EC217	EV217	session entity(Self), locked(Self, true), credentials valid(Self, true)	Locked, re-authenticated
EC218	EV218	session entity(Self), active(Self, true), suspend requested(Self, true)	Suspend requested
EC219	EV219	session entity(Self), suspended(Self, true), resume requested(Self, true)	Resume requested
EC220	EV220	session entity(Self), active(Self, true), logout requested(Self, true)	Logout requested
EC221	EV221	session entity(Self), logout complete(Self, true)	Logout cleanup done

D.25 — Device (G25, Infinity)

ID	Event	Constraint	Note
EC222	EV222	hardware detected(BusType, VID, PID), not(device entity exists(VID, PID))	Hardware found, no existing entity
EC223	EV223	device entity(Self), discovered(Self, true), driver available(Self, Driver)	Discovered, driver exists
EC224	EV224	device entity(Self), driver loading(Self, true)	Driver load completed
EC225	EV225	device entity(Self), driver loaded(Self, true), resources allocated(Self, true)	Driver loaded, resources ready
EC226	EV226	device entity(Self), initializing(Self, true), self test result(Self, pass)	Self test passed
EC227	EV227	device entity(Self), initializing(Self, true), self test result(Self, fail)	Self test failed
EC228	EV228	device entity(Self), self test passed(Self, true)	Test passed, device ready
EC229	EV229	device entity(Self), ready(Self, true), error detected(Self, Error)	Error on ready device

ID	Event	Constraint	Note
EC230	EV230	device entity(Self), error state(Self, true), reset possible(Self, true), recent reset count(Self, N), $N < 3$	Can reset, retries remaining
EC231	EV231	device entity(Self), ready(Self, true), suspend requested(Self, true)	Suspend requested
EC232	EV232	device entity(Self), suspended(Self, true), resume requested(Self, true)	Resume requested
EC233	EV233	device entity(Self), removal detected(Self, true)	Hotplug removal or unrecoverable

D.26 — Kernel Module (G26, Infinity)

ID	Event	Constraint	Note
EC234	EV234	module load requested(ModName), module available(ModName)	Load requested, module exists
EC235	EV235	module entity(Self), loading(Self, true)	Load completed
EC236	EV236	module entity(Self), loaded(Self, true), init result(Self, success)	Init succeeded
EC237	EV237	module entity(Self), loaded(Self, true), init result(Self, failure)	Init failed
EC238	EV238	module entity(Self), running(Self, true), unload requested(Self, true), refcount(Self, 0)	Unload requested, not in use
EC239	EV239	module entity(Self), unloading(Self, true)	Unload completed

D.27 — Service (G27, Infinity)

ID	Event	Constraint	Note
EC240	EV240	service entity(Self), start requested(Self, true), dependencies met(Self, true)	Start requested, deps running

ID	Event	Constraint	Note
EC241	EV241	service entity(Self), starting(Self, true), process alive(Self, PID)	Process launched
EC242	EV242	service entity(Self), started(Self, true), health check passed(Self, true)	Started, first health check passed
EC243	EV243	service entity(Self), running(Self, true), health check due(Self, true), health check result(Self, pass)	Periodic check passed
EC244	EV244	service entity(Self), running(Self, true), health check due(Self, true), health check result(Self, fail)	Periodic check failed
EC245	EV245	service entity(Self), health fail count(Self, N), $N > 1$, $N < 3$	Multiple failures, not terminal
EC246	EV246	service entity(Self), process alive(Self, false)	Process died
EC247	EV247	service entity(Self), failed(Self, true), restart policy(Self, auto), restart count(Self, N), max restarts(Self, M), $N < M$	Auto restart, retries remaining
EC248	EV248	service entity(Self), restarting(Self, true), restart delay elapsed(Self, true)	Restart delay passed
EC249	EV249	service entity(Self), running(Self, true), reload requested(Self, true)	Reload requested
EC250	EV250	service entity(Self), reloading(Self, true)	Reload completed
EC251	EV251	service entity(Self), running(Self, true), stop requested(Self, true)	Stop requested
EC252	EV252	service entity(Self), stopping(Self, true), process alive(Self, false)	Process terminated
EC253	EV253	service entity(Self), failed(Self, true), restart count(Self, N), max restarts(Self, M), $N \geq M$	Retries exhausted

D.28 — Window (G28, Infinity)

ID	Event	Constraint	Note
EC254	EV254	window create requested(ProcessID, Title)	Process requested window
EC255	EV255	window entity(Self), created(Self, true), show requested(Self, true)	Show requested
EC256	EV256	window entity(Self), visible(Self, true), hide requested(Self, true)	Hide requested
EC257	EV257	window entity(Self), visible(Self, true), focus requested(Self, true)	Focus requested
EC258	EV258	window entity(Self), focused(Self, true), focus lost(Self, true)	Another window took focus
EC259	EV259	window entity(Self), visible(Self, true), minimize requested(Self, true)	Minimize requested
EC260	EV260	window entity(Self), visible(Self, true), maximize requested(Self, true)	Maximize requested
EC261	EV261	window entity(Self), minimized or maximized(Self, true), restore requested(Self, true)	Restore requested
EC262	EV262	window entity(Self), visible(Self, true), resize requested(Self, W, H)	Resize requested
EC263	EV263	window entity(Self), visible(Self, true), move requested(Self, X, Y)	Move requested
EC264	EV264	window entity(Self), close requested(Self, true)	Close requested

D.29 — Network Interface (G29, Infinity)

ID	Event	Constraint	Note
EC265	EV265	interface hardware detected(Name, MAC)	Hardware detected
EC266	EV266	interface entity(Self), detected(Self, true), config available(Self, true)	Detected, config exists

ID	Event	Constraint	Note
EC267	EV267	interface entity(Self), configuring(Self, true), address assigned(Self, Addr, Mask)	Address obtained
EC268	EV268	interface entity(Self), address assigned(Self, true), link up(Self, true)	Address and link ready
EC269	EV269	interface entity(Self), up(Self, true), error rate(Self, R), $R > 0.01$	Errors exceeding threshold
EC270	EV270	interface entity(Self), up(Self, true), down requested(Self, true)	Down requested
EC271	EV271	interface entity(Self), up(Self, true), dhcp lease expiring(Self, true), dhcp renew succeeded(Self, Addr, Lease)	DHCP renewal
EC272	EV272	interface entity(Self), error rate(Self, R), $R > 0.1$	Severe errors
EC273	EV273	interface entity(Self), failed or degraded(Self, true), reset requested(Self, true)	Reset requested

D.30 — Permission Rule (G30, Infinity)

ID	Event	Constraint	Note
EC274	EV274	permission grant requested(SubjectID, Resource, Action)	Grant requested
EC275	EV275	permission entity(Self), active(Self, true), access requested(Self, SubjectID)	Access check
EC276	EV276	permission entity(Self), active(Self, true), expiry time(Self, T), current time(Now), $Now > T$	Expired
EC277	EV277	permission entity(Self), active(Self, true), revoke requested(Self, true)	Revocation

D.31 — Timer (G31, Infinity)

ID	Event	Constraint	Note
EC278	EV278	timer create requested(Duration, CallbackEventID)	Timer arm requested
EC279	EV279	timer entity(Self), armed(Self, true), elapsed(Self, E), duration(Self, D), E >= D	Timer expired
EC280	EV280	timer entity(Self), armed(Self, true), reset requested(Self, NewDuration)	Reset requested
EC281	EV281	timer entity(Self), armed(Self, true), cancel requested(Self, true)	Cancel requested

D.32 — Signal (G32, Infinity)

ID	Event	Constraint	Note
EC282	EV282	signal send requested(SourcePID, TargetPID, SignalNum)	kill/raise syscall
EC283	EV283	signal entity(Self), pending(Self, true), target ready(Self, TargetPID)	Target can receive
EC284	EV284	signal entity(Self), delivered(Self, true), handler registered(Self, Handler)	Custom handler exists
EC285	EV285	signal entity(Self), delivered(Self, true), signal masked(Self, true)	Signal in mask
EC286	EV286	signal entity(Self), delivered(Self, true), not(handler registered(Self,)), not(signal masked(Self, true))	No handler, not masked

D.33 — Pipe (G33, Infinity)

ID	Event	Constraint	Note
EC287	EV287	pipe create requested(ProcessID)	Pipe syscall
EC288	EV288	pipe entity(Self), open(Self, true), write requested(Self, true), not(full(Self, true))	Write requested, space available

ID	Event	Constraint	Note
EC289	EV289	pipe entity(Self), open(Self, true), read requested(Self, true), data available(Self, true)	Read requested, data present
EC290	EV290	pipe entity(Self), open(Self, true), buffer full(Self, true)	Buffer capacity reached
EC291	EV291	pipe entity(Self), open(Self, true), end close requested(Self, End)	One end closing
EC292	EV292	pipe entity(Self), write end closed(Self, true)	Writer gone

D.34 — Shared Memory Region (G34, Infinity)

ID	Event	Constraint	Note
EC293	EV293	shm allocate requested(ProcessID, Size)	mmap/shmget syscall
EC294	EV294	shm entity(Self), allocated(Self, true), map requested(Self, ProcessID)	Map requested
EC295	EV295	shm entity(Self), mapped(Self, ProcessID), unmap requested(Self, ProcessID)	Unmap requested
EC296	EV296	shm entity(Self), mapped count(Self, C), C > 0, sync requested(Self, true)	Sync requested
EC297	EV297	shm entity(Self), mapped count(Self, 0), free requested(Self, true)	No mappings, free requested

D.35 — Environment Variable Set (G35, Infinity)

ID	Event	Constraint	Note
EC298	EV298	env load requested(ProcessID)	Process starting, load env
EC299	EV299	env entity(Self), loaded(Self, true), set requested(Self, Key, Value)	Set var requested
EC300	EV300	env entity(Self), loaded(Self, true), unset requested(Self, Key)	Unset var requested

ID	Event	Constraint	Note
EC301	EV301	env entity(Self), loaded(Self, true), export requested(Self, ChildPID)	Fork/exec inheriting env

D.36 — Cron Job (G36, Infinity)

ID	Event	Constraint	Note
EC302	EV302	cron schedule requested(Expression, Command)	Crontab entry
EC303	EV303	cron entity(Self), scheduled(Self, true), timer fired(Self, true)	Cron timer expired
EC304	EV304	cron entity(Self), executing(Self, true), process exited(Self, 0)	Job exited success
EC305	EV305	cron entity(Self), executing(Self, true), process exited(Self, Code), Code = 0	Job exited failure
EC306	EV306	cron entity(Self), completed or failed(Self, true)	Ready to reschedule

D.37 — Log Entry (G37, Infinity)

ID	Event	Constraint	Note
EC307	EV307	log submit requested(Severity, Source, Message)	Any system submits log
EC308	EV308	log entity(Self), buffered(Self, true), flush triggered(Self, true)	Buffer flushed
EC309	EV309	log entity(Self), written(Self, true), rotation triggered(Self, true)	File rotated
EC310	EV310	log entity(Self), rotated(Self, true), archive triggered(Self, true)	Old file archived
EC311	EV311	log entity(Self), archived(Self, true), age(Self, A), max age(MA), A > MA	Aged past retention

Constraint count summary: 311 total constraints, one per event.

Table E: States and Behavior Sets

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G1 BIOS	Zero	—	—	—	—
G2 Boot- loader	Zero	—	—	—	—
G3 Kernel	One	Unloaded → Initial- izing → Memo- ryReady → Hard- war- eReady → Filesys- tem- Ready → Run- ning → Panic	12	None	force action

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G4 Init Sys- tem	One	NotStarted → Starting → Con- figur- ingSys- tem → Config- ur- ingDe- vices → Config- uring- Filesys- tems → Config- ur- ingNet- work → Ready → Failed Inactive	13	None	force action
G5 Mem- ory Man- ager	One	→ Initial- izing → Run- ning → De- graded → Critical Inactive	8	MemoryPressure	Response
G6 Sched- uler	One	→ Run- ning → Over- loaded → De- graded	7	SchedulingDecision	Resource

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G7 VFS	One	Inactive → Initial- izing → Run- ning → De- graded	9	None	force action
G8 Net- work Stack	One	Inactive → Initial- izing → Run- ning → De- graded → Con- gested	7	CongestionResponse	pressure
G9 Dis- play Server	One	Inactive → Starting → Run- ning → Sus- pended → Failed	8	None	force action
G10 Audio Mixer	One	Inactive → Initial- izing → Run- ning → Muted → Failed	8	None	force action
G11 De- vice Man- ager	One	Inactive → Run- ning → Failed	6	None	force action

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G12 Swap Man- ager	One	Inactive → Active → Full → De- graded	5	SwapPressureResponse	pressure
G13 Fire- wall	One	Inactive → Load- ing → Active → Failed	7	None	force action
G14 DNS Re- solver	One	Inactive → Con- figured → Run- ning → Failed	5	None	force action
G15 Ses- sion Man- ager	One	Inactive → Run- ning → Failed	6	None	force action
G16 Sys- tem Log- ger	One	Inactive → Run- ning → Buffer- Full → Failed	5	LogPressureResponse	pressure
G17 Pack- age Man- ager	One	Inactive → Ready → Up- dating → In- stalling → Failed	6	None	force action

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G18 Pro- cess	Infinity	Created → Ready → Run- ning → Blocked → Sleep- ing → Zombie → Termi- nated	8	None	force action
G19 Thread	Infinity	Created → Ready → Run- ning → Blocked → Termi- nated	7	None	force action
G20 File	Infinity	Closed → Open → Locked → Error	8	None	force action
G21 Filesys- tem Mount	Infinity	Unmounted → Check- ing → Mount- ing → Mounted → Read- Only → Un- mount- ing → Failed	5	None	force action

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G22 Net- work Con- nec- tion	Infinity	Closed → SynSent → Estab- lished → Close- Wait → Time- Wait → Termi- nated	7	ConnectionHealth	pressure
G23 User Ac- count	Infinity	Inactive → Active → Locked → Dis- abled → Deleted	8	None	force action
G24 User Ses- sion	Infinity	Authenticating → Active → Locked → Sus- pended → Termi- nated	8	SessionIdleResponse	user-facing

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G25 De- vice	Infinity	Discovered → Driver- Load- ing → Initial- izing → Ready → Error → Sus- pended → Re- moved	7	DeviceErrorRecovery	recovery
G26 Kernel Mod- ule	Infinity	Unloaded → Load- ing → Loaded → Failed → Un- loading	4	None	force action
G27 Ser- vice	Infinity	Stopped → Starting → Run- ning → De- graded → Failed → Restart- ing → Stop- ping	6	ServiceHealthMonitor	health

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G28 Win- dow	Infinity	Created → Visible → Fo- cused → Min- imized → Maxi- mized → Closed	10	None	force action
G29 Net- work Inter- face	Infinity	Down → Con- figuring → Up → De- graded → Failed	6	None	force action
G30 Per- mis- sion Rule	Infinity	Inactive → Active → Ex- pired → Re- voked	4	None	force action
G31 Timer	Infinity	Inactive → Armed → Fired → Re- peating → Can- celled	4	None	force action
G32 Signal	Infinity	Pending → De- livered → Han- dled → Ignored	5	None	force action

Group	Cardinality	States	Action Count	Behavior Set	Behavior Set Type
G33 Pipe	Infinity	Created → Open → Full → Closed → Broken	5	None	force action
G34 Shared Mem- ory Re- gion	Infinity	Allocated → Mapped → Shared → Un- mapped → Freed	5	None	force action
G35 Envi- ron- ment Vari- able Set	Infinity	Empty → Loaded → Modi- fied	4	None	force action
G36 Cron Job	Infinity	Inactive → Sched- uled → Execut- ing → Com- pleted → Failed	5	None	force action
G37 Log Entry	Infinity	Buffered → Written → Ro- tated → Archived → Deleted	5	None	force action

Behavior set summary: 9 behavior sets out of 37 EntityGroups. 28 EntityGroups are entirely deterministic.

Table F: Behavior Set Details

F.1 — MemoryPressureResponse (G5, Memory Manager)

Consideration	Input Source	Range	Curve	Weight	Description
FreePageRatio	free pages / total pages	0–1	InverseLinear	1.0	Low ratio = high urgency
SwapUsageRatio	swap used / swap total	0–1	Quadratic	0.8	High swap = running out of options
AllocationFailureRate	recent failures / recent requests	0–1	Exponential	1.2	Active failures = immediate problem
PageFaultRate	faults per second / max expected	0–1	Linear	0.6	Background pressure signal
Behavior	Action	Description			
DoNothing	—	Free pages healthy			
CompactMemory	CompactMemory	Moderate fragmentation, pages scattered			
ReclaimPages	ReclaimPages	Low free pages, cache evictable			
SwapOut	SwapOut	Very low free pages, must use disk			

Consideration	Input Source	Range	Curve	Weight	Description
ReportOOM	ReportOOM	Critical, nothing left			

F.2 — SchedulingDecision (G6, Scheduler)

Consideration	Input Source	Range	Curve	Weight	Description
RunQueueLength	queue length / max expected	0–1	Linear	1.0	Process pressure
CPUloadImbalance	variance across cpus / max variance	0–1	Quadratic	0.8	Rebalance signal
CurrentProcessTimeSlice	time used / quantum	0–1	Linear	1.0	Preemption signal
InteractiveProcessWaiting	Waiting / 1	0–1	Step	0.9	Interactive priority boost
RealTimeProcessPending	Pending / 1	0–1	Step	1.5	RT always preempts
Behavior	Action	Description			
ContinueCurrent	—	Time slice not ex- hausted			
PreemptProcess	PreemptProcess	Quantum ex- hausted or higher priority waiting			
RebalanceQueues	RebalanceQueues	CPUs un- evenly loaded			
MigrateProcess	MigrateProcess	Process on wrong CPU			
AdjustPriorities	AdjustPriorities	Starvation de- tected			

F.3 — CongestionResponse (G8, Network Stack)

Consideration	Input Source	Range	Curve	Weight	Description
PacketDropRate	drops / total packets	0–1	Exponential	.2	Primary congestion signal
RetransmitRate	retransmits / sent	0–1	Quadratic	1.0	Loss indicator
BufferOccupancy	buffer used / buffer total	0–1	Linear	0.8	Backpressure signal
ActiveConnectionCount	connections / max connections	0–1	Linear	0.5	Scale factor
Behavior	Action	Description			
ReduceWindow	ManageCongestionWindow	Widenate congestion, back off			
DropLowPriority	DropPacket	High congestion, shed non-critical			
RetransmitCritical	RetransmitPacket	Loss on critical connections			
ResetCongested	—	Congestion cleared, return to Running			

F.4 — SwapPressureResponse (G12, Swap Manager)

Consideration	Input Source	Range	Curve	Weight	Description
SwapUsageRatio	used / total	0–1	Quadratic	1.0	Space pressure
SwapIORate	reads writes per second / max expected	0–1	Exponential	.2	Thrashing signal

Consideration	Input Source	Range	Curve	Weight	Description
FreeSwapPages	free pages / total pages	0–1	InverseLinear	0.8	Absolute space remaining
MemoryPressureLevel	memory manager.free ratio	0–1	Linear	0.6	Cross-group pressure context
Behavior	Action	Description			
DoNothing	—	Swap healthy			
DefragmentSwap	DefragmentSwap	High fragmentation			
AlertMemoryManager		Swap filling, memory manager should reclaim harder			
DeactivateSwapPartition	DeactivateSwapPartition	Swap device failing			

F.5 — LogPressureResponse (G16, System Logger)

Consideration	Input Source	Range	Curve	Weight	Description
BufferOccupancy	buffer used / buffer total	0–1	Quadratic	1.0	Buffer pressure
LogRatePerSecond	entries per second / max expected	0–1	Linear	0.8	Burst signal
DiskSpaceRemaining	free space / partition size	0–1	InverseLinear	1.0	Storage pressure
CriticalEntryPending	pool 0/1	0–1	Step	1.5	Critical severity demands flush
Behavior	Action	Description			

Consideration	Input Source	Range	Curve	Weight	Description
DoNothing	—	Buffer healthy			
FlushBuffer	FlushBuffer	Buffer filling or critical pending			
RotateLog	RotateLog	Disk space low			
ForwardLog	ForwardLog	Local disk critical, send to remote			

F.6 — ConnectionHealth (G22, Network Connection)

Consideration	Input Source	Range	Curve	Weight	Description
RoundTripTime	rtt / max acceptable rtt	0–1	Quadratic	0.8	Latency
PacketLossRate	lost / sent	0–1	Exponential	0.2	Path quality
WindowUtilization	used / available	0–1	Linear	0.6	Saturation
IdleTime	seconds idle / max idle	0–1	Linear	0.5	Possibly dead connection
Behavior	Action	Description			
DoNothing	—	Connection healthy			
ReduceWindow	—	Loss detected, back off			
Retransmit	Retransmit	Specific segment lost			
Close	Close	Idle too long			
Reset	Reset	Unrecoverable state			

F.7 — SessionIdleResponse (G24, User Session)

Consideration	Input Source	Range	Curve	Weight	Description
IdleTime	seconds since input / max idle	0–1	Linear	1.0	Primary idle signal
BatteryLevel	battery percent	0–1	InverseLinear	0.6	Power save urgency
ActiveProcessCount	active processes / expected	0–1	Linear	0.4	User activity proxy
UnsavedWork	bool 0/1	0–1	Step	2.0	Blocks aggressive power save
Behavior	Action	Description			
DoNothing	—	User active			
DimScreen	—	Idle threshold 1			
LockScreen	LockSession	Idle threshold 2			
SuspendSession	SuspendSession	Idle threshold 3, blocked if unsaved work			

F.8 — ServiceHealthMonitor (G27, Service)

Consideration	Input Source	Range	Curve	Weight	Description
HealthCheckResult	pass=0, fail=1	0–1	Step	1.5	Primary health signal
MemoryUsage	rss / memory limit	0–1	Quadratic	0.8	Possible leak
CPUUsage	cpu percent / 100	0–1	Linear	0.6	Possible runaway

Consideration	Input Source	Range	Curve	Weight	Description
RestartCount	recent restarts / max restarts	0–1	Exponential	1.0	Flapping signal
DependencyHealth	unhealthy deps / total deps	0–1	Step	1.2	External failure
Behavior	Action	Description			
DoNothing	—	All healthy			
Reload	Reload	Config changed			
Restart	Restart	Health check failing			
Escalate	Escalate	Repeated failures			
Stop	Stop	Dependency down			

F.9 — DeviceErrorRecovery (G25, Device)

Consideration	Input Source	Range	Curve	Weight	Description
ErrorCount	errors / max tolerable	0–1	Linear	1.0	Cumulative errors
ErrorRate	errors per second / max rate	0–1	Exponential	1.2	Getting worse
TimeSinceLastReset	seconds / min reset interval	0–1	InverseLinear	0.8	Already tried recently
DeviceCriticality	bool 0/1 (root disk, boot NIC)	0–1	Step	2.0	Critical device escalates
Behavior	Action	Description			
Reset	Reset	Errors low, try recovery			

Consideration	Input Source	Range	Curve	Weight	Description
Suspend	Suspend	Errors climb- ing, take offline			
Remove	Remove	Unrecoverable or reset failed			
EscalateToKernel	—	Critical device failing			

Table G: Specification Summary

Metric	Count
EntityGroups (Zero)	2
EntityGroups (One)	15
EntityGroups (Infinity)	20
EntityGroups Total	37
Events	311
Flows (intra-group)	291
Flows (inter-group)	58
Flows Total	349
Constraints	311
Specification Entries Total	1,008
States (total across all groups)	~155
Actions (total across all groups)	~220
Behavior Sets	9
Deterministic EntityGroups	28
Behavior Set Considerations (total)	38
Behavior Set Behaviors (total)	41

HOWL-COMP-12-2026 Appendix. Supporting Tables for Closed Loop Architecture: A Complete OS in Four Flat Lists.

[[HOWL-COMP-12-2026](https://github.com/ghowland/papers/tree/main/papers/COMP-12-2026)] Closed Loop Architecture. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP-12-2026>

[[HOWL-COMP-1-2026](#)] Implementing a Tall-Infra Data-Only Execution System .

Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-1-2026>

[[HOWL-COMP-2-2026](#)] Tall-Infra, Data-Only Development. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-2-2026>

[[HOWL-COMP-3-2026](#)] Silo OS. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-3-2026>

[[HOWL-COMP-4-2026](#)] Geometric Security. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-4-2026>

[[HOWL-COMP-5-2026](#)] Partial Geometric Security. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-5-2026>

[[HOWL-COMP-6-2026](#)] SIML - Silo Markup Language (TOML Format). Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-6-2026>

[[HOWL-COMP-7-2026](#)] SiQL. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-7-2026>

[[HOWL-COMP-8-2026](#)] SiloSec Protocol Specification. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-8-2026>

[[HOWL-COMP-9-2026](#)] Building Applications with OpsDB Application Architecture. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-9-2026>

[[HOWL-COMP-10-2026](#)] Tall-Infra Data-Only Execution. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-10-2026>

[[HOWL-COMP-11-2026](#)] Name Driven Development. Github: <https://github.com/ghowland/papers/tree/main/papers/COMP/HOWL-COMP-11-2026>