



6-Pin DIP Optoisolators Darlington Output

The 4N29/A, 4N30, 4N31, 4N32⁽¹⁾ and 4N33⁽¹⁾ devices consist of a gallium arsenide infrared emitting diode optically coupled to a monolithic silicon photodarlington detector.

This series is designed for use in applications requiring high collector output currents at lower input currents.

- Higher Sensitivity to Low Input Drive Current
- Meets or Exceeds All JEDEC Registered Specifications
- **To order devices that are tested and marked per VDE 0884 requirements, the suffix "V" must be included at end of part number. VDE 0884 is a test option.**

Applications

- Low Power Logic Circuits
- Interfacing and coupling systems of different potentials and impedances
- Telecommunications Equipment
- Portable Electronics
- Solid State Relays

MAXIMUM RATINGS ($T_A = 25^\circ\text{C}$ unless otherwise noted)

Rating	Symbol	Value	Unit
--------	--------	-------	------

INPUT LED

Reverse Voltage	V_R	3	Volts
Forward Current — Continuous	I_F	60	mA
LED Power Dissipation @ $T_A = 25^\circ\text{C}$ Derate above 25°C	P_D	120 1.41	mW mW/ $^\circ\text{C}$

OUTPUT DETECTOR

Collector–Emitter Voltage	V_{CEO}	30	Volts
Emitter–Collector Voltage	V_{ECO}	5	Volts
Collector–Base Voltage	V_{CBO}	30	Volts
Collector Current — Continuous	I_C	150	mA
Detector Power Dissipation @ $T_A = 25^\circ\text{C}$ Derate above 25°C	P_D	150 1.76	mW mW/ $^\circ\text{C}$

TOTAL DEVICE

Isolation Surge Voltage ⁽²⁾ (Peak ac Voltage, 60 Hz, 1 sec Duration)	V_{ISO}	7500	Vac(pk)
Total Device Power Dissipation @ $T_A = 25^\circ\text{C}$ Derate above 25°C	P_D	250 2.94	mW mW/ $^\circ\text{C}$
Ambient Operating Temperature Range ⁽³⁾	T_A	-55 to $+100$	$^\circ\text{C}$
Storage Temperature Range ⁽³⁾	T_{stg}	-55 to $+150$	$^\circ\text{C}$
Soldering Temperature (10 sec, 1/16" from case)	T_L	260	$^\circ\text{C}$

1. Difference in 4N32 and 4N33 is JEDEC Registration for VISO only. All Motorola 6-Pin devices exceed JEDEC specification and are 7500 Vac(pk). The same applies for 4N29 and 4N30.
2. Isolation surge voltage is an internal device dielectric breakdown rating. For this test, Pins 1 and 2 are common, and Pins 4, 5 and 6 are common.
3. Refer to Quality and Reliability Section in Opto Data Book for information on test conditions.


Preferred devices are Motorola recommended choices for future use and best overall value.

GlobalOptoisolator is a trademark of Motorola, Inc.

4N29
4N29A
4N30 *
[CTR = 100% Min]
4N31
[CTR = 50% Min]
4N32 *
4N33 *
[CTR = 500% Min]


*Motorola Preferred Devices

STYLE 1 PLASTIC



STANDARD THRU HOLE
CASE 730A-04

SCHEMATIC



- PIN 1. LED ANODE
2. LED CATHODE
3. N.C.
4. EMITTER
5. COLLECTOR
6. BASE

4N29 4N29A 4N30 4N31 4N32 4N33

ELECTRICAL CHARACTERISTICS (T_A = 25°C unless otherwise noted)⁽¹⁾

Characteristic	Symbol	Min	Typ ⁽¹⁾	Max	Unit
INPUT LED					
*Reverse Leakage Current (V _R = 3 V, R _L = 1 M ohms)	I _R	—	0.05	100	μA
*Forward Voltage (I _F = 10 mA)	V _F	—	1.34	1.5	Volts
Capacitance (V _R = 0 V, f = 1 MHz)	C	—	1.8	—	pF
OUTPUT DETECTOR (T_A = 25°C and I_F = 0, unless otherwise noted)					
*Collector–Emitter Dark Current (V _{CE} = 10 V, Base Open)	I _{CEO}	—	—	100	nA
*Collector–Base Breakdown Voltage (I _C = 100 μA, I _E = 0)	V _{(BR)CBO}	30	—	—	Volts
*Collector–Emitter Breakdown Voltage (I _C = 100 μA, I _B = 0)	V _{(BR)CEO}	30	—	—	Volts
*Emitter–Collector Breakdown Voltage (I _E = 100 μA, I _B = 0)	V _{(BR)ECO}	5	—	—	Volts
DC Current Gain (V _{CE} = 5 V, I _C = 500 μA)	h _{FE}	—	16K	—	—
COUPLED (T_A = 25°C unless otherwise noted)					
*Collector Output Current ⁽³⁾ (V _{CE} = 10 V, I _F = 10 mA)	I _C (CTR) ⁽²⁾	50 (500) 10 (100) 5 (50)	— — —	— — —	mA (%)
Isolation Surge Voltage ^(4,5) (60 Hz ac Peak, 1 Second)	V _{ISO}	7500 2500 1500	— — —	— — —	Vac(pk)
Isolation Resistance ⁽⁴⁾ (V = 500 V)	R _{ISO}	—	10 ¹¹	—	Ohms
*Collector–Emitter Saturation Voltage ⁽³⁾ (I _C = 2 mA, I _F = 8 mA)	V _{CE(sat)}	— —	— —	1.2 1	Volts
Isolation Capacitance ⁽⁴⁾ (V = 0 V, f = 1 MHz)	C _{ISO}	—	0.2	—	pF
Turn–On Time ⁽⁶⁾ (I _C = 50 mA, I _F = 200 mA, V _{CC} = 10 V)	t _{on}	—	0.6	5	μs
Turn–Off Time ⁽⁶⁾ (I _C = 50 mA, I _F = 200 mA, V _{CC} = 10 V)	t _{off}	— —	17 45	40 100	μs

* Indicates JEDEC Registered Data. All Motorola 6–pin devices have V_{ISO} rating of 7500 Vac(pk).

1. Always design to the specified minimum/maximum electrical limits (where applicable).
2. Current Transfer Ratio (CTR) = I_C/I_F x 100%.
3. Pulse Test: Pulse Width = 300 μs, Duty Cycle ≤ 2%.
4. For this test, Pins 1 and 2 are common and Pins 4, 5 and 6 are common.
5. Isolation Surge Voltage, V_{ISO}, is an internal device dielectric breakdown rating.
6. For test circuit setup and waveforms, refer to Figure 11.

TYPICAL CHARACTERISTICS




Figure 1. LED Forward Voltage versus Forward Current




Figure 2. Output Current versus Input Current




Figure 3. Collector Current versus Collector-Emitter Voltage




Figure 4. Output Current versus Ambient Temperature




Figure 5. Collector-Emitter Voltage versus Ambient Temperature




Figure 6. Collector-Emitter Dark Current versus Ambient Temperature

4N29 4N29A 4N30 4N31 4N32 4N33




Figure 7. Turn-On Switching Times




Figure 8. Turn-Off Switching Times




Figure 9. DC Current Gain (Detector Only)




Figure 10. Capacitances versus Voltage





Figure 11. Switching Time Test Circuit and Waveforms

4N29 4N29A 4N30 4N31 4N32 4N33 **PACKAGE DIMENSIONS**




- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: INCH.
 3. DIMENSION L TO CENTER OF LEAD WHEN FORMED PARALLEL.

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.320	0.350	8.13	8.89
B	0.240	0.260	6.10	6.60
C	0.115	0.200	2.93	5.08
D	0.016	0.020	0.41	0.50
E	0.040	0.070	1.02	1.77
F	0.010	0.014	0.25	0.36
G	0.100 BSC		2.54 BSC	
J	0.008	0.012	0.21	0.30
K	0.100	0.150	2.54	3.81
L	0.300 BSC		7.62 BSC	
M	0°	15°	0°	15°
N	0.015	0.100	0.38	2.54

- STYLE 1:
- PIN 1. ANODE
 - CATHODE
 - NC
 - EMITTER
 - COLLECTOR
 - BASE

CASE 730A-04
ISSUE G




- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: INCH.

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.320	0.350	8.13	8.89
B	0.240	0.260	6.10	6.60
C	0.115	0.200	2.93	5.08
D	0.016	0.020	0.41	0.50
E	0.040	0.070	1.02	1.77
F	0.010	0.014	0.25	0.36
G	0.100 BSC		2.54 BSC	
H	0.020	0.025	0.51	0.63
J	0.008	0.012	0.20	0.30
K	0.006	0.035	0.16	0.88
L	0.320 BSC		8.13 BSC	
S	0.332	0.390	8.43	9.90

***Consult factory for leadform option availability**

CASE 730C-04
ISSUE D

4N29 4N29A 4N30 4N31 4N32 4N33




- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: INCH.
 3. DIMENSION L TO CENTER OF LEAD WHEN FORMED PARALLEL.

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.320	0.350	8.13	8.89
B	0.240	0.260	6.10	6.60
C	0.115	0.200	2.93	5.08
D	0.016	0.020	0.41	0.50
E	0.040	0.070	1.02	1.77
F	0.010	0.014	0.25	0.36
G	0.100 BSC		2.54 BSC	
J	0.008	0.012	0.21	0.30
K	0.100	0.150	2.54	3.81
L	0.400	0.425	10.16	10.80
N	0.015	0.040	0.38	1.02

*Consult factory for leadform option availability

CASE 730D-05
ISSUE D

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters can and do vary in different applications. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

How to reach us:

USA/EUROPE: Motorola Literature Distribution;
P.O. Box 20912; Phoenix, Arizona 85036. 1-800-441-2447

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, Toshikatsu Otsuki,
6F Seibu-Butsuryu-Center, 3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 03-3521-8315

MFAX: RMFA00@email.sps.mot.com - TOUCHTONE (602) 244-6609
INTERNET: <http://Design-NET.com>

HONG KONG: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.