

3.2 Targets

ID	Target	Construction	Used in
T2	Noise and registration plate	Uniform matte, NOISE_PLATE_SIZE_MM, flatness PLATE_FLATNESS_MM, no pattern. Registration uses its plane (Section 4)	4, A, B-Z, sentinels
T3a	Raised square	Square of side EDGE_SQUARE_SIZE_MM with knife edges, on hidden posts at G above a back plate. Spacers set G to GAP_SMALL_MM or GAP_LARGE_MM.	B-HV, E
T3b	Square window	Front plate with a square window of the same size and knife edges; back plate at G behind it	B-HV, E
T4	Disk plate	Back-beveled disks on thin posts at G above a back plate: FEATURE_COUNT disks on the feature ladder, BLANK_SITES_PER_PLATE blank sites, and POST_SITES_PER_PLATE post-only control sites	C, D, E
T5	Cutout plate	Back-beveled holes in a front plate, with the back plate at G, removable for the open-background variant of Section 7: FEATURE_COUNT holes on the feature ladder and BLANK_SITES_PER_PLATE blank sites	C, D, E

Feature ladder. The sensor responds to the subtended size $D_{px} = D \cdot f_x / Z$. The robot sweeps each feature through the Z stations from Z_MIN to Z_MAX, a factor of 4, so one feature covers two octaves of D_{px} . Diameters start at FEATURE_MIN_PX_AT_Z_MAX pixels at the far station and grow by FEATURE_LADDER_RATIO, so neighbors overlap by half an octave; the overlap is the scaling test of Sections 12 and 13. With FEATURE_COUNT features this gives, at $f_x \approx 688$ px (unconfirmed; superseded once SENSOR_FX_PX is known), 7.0, 19.7, and 55.8 mm, covering 3 to 96 px. The lower end sits below the minimum detectable size expected for the VSX3000: about 300,000 depth pixels share about 30,000 projected laser pencils, 10 pixels per pencil, and the path correlation needs at least 4 pencil detections, about 40 pixels of area or a diameter of 7 px; the matcher's support window (7 to 13 px in documented active-stereo processors) puts the plausible threshold at 10 to 15 px. Features on a plate are spaced at least FEATURE_ISOLATION_PX apart at Z_MAX, so the sensor's spatial interpolation cannot couple neighboring features at any station. Plate extents follow from the features and the isolation: the plan tool's layout is the source of the as-built drawing, and each plate must fit the field of view at Z_MIN.

Blank and control sites. Each plate has BLANK_SITES_PER_PLATE blank sites, patches of back plate at least as large as the largest search window. These give the false-alarm rate in D at every station. The disk plate also has POST_SITES_PER_PLATE post-only sites (a post with no disk). These show whether the support post itself is detected.

Datum and plate extents. Every target mounts on the same dowel datum, and the as-built record (Section 3.3) includes each feature's offset from that datum. Registration from the plane of T2 does not observe where a target sits sideways on the flange, so the once-per-mount check of Section 4, Step 8 locates each mounted target in the camera frame: its front plane from the depth data (Z and tilt) and one feature edge in the left IR image (H and V). The back plates of T3a and T3b extend past the square by at least the boundary band plus the shadow at GAP_LARGE_MM and the worst ray angle of Section 3.3; the front plate of T3b and the plates of T4 and T5 extend past their features by at least FEATURE_ISOLATION_PX at Z_MAX.

Surface finish. All front and back surfaces use one finish, for example bead-blasted aluminum or a matte coating, with mid-range IR reflectance. Record the finish and its measured reflectance at the projector wavelength in targets_asbuilt.csv. A reflectance difference between plates would bias the edge and area results.