Compatible Equipment & Options

S2014 - 2.5A PSU

S406 - 5.25A PSU

S408 - 10.25A PSU

Overview

The HFP PSU range of 24V DC power supplies are designed to meet the exacting requirements of fire detection and alarm systems and fire protection systems.

All models charge sealed lead acid batteries using sophisticated, temperature compensated charging and monitoring techniques to keep the batteries in the best possible condition.

Over depletion of batteries is prevented by a low battery voltage disconnection function which removes the load from the batteries when their terminal voltage reduces to a level which would damage them.

A low battery voltage fault warning is given when the batteries reach the minimum terminal voltage recommended by the battery manufacturers.

A high series resistance in the battery supply circuit which would allow the power supply output voltage to fall outside of the specified range is indicated as a fault condition.

All models are fitted with a dual output board to provide redundant power paths for fire alarm applications and are available in a range of enclosures to accommodate different battery sizes.

On-board LED indicators are provided to indicate the status of the unit and an on-board header is available to extend status signals to other systems volt free relay contact that operates upon any fault condition or total power failure.

Enclosures are designed to match both HFP AP and HFP CP fire panel ranges and are constructed from 1.2mm mild steel and are finished with epoxy powder coating.

The HFP PSU boxed range is available in the following power outputs:

- HFP PSU-2.5/12SS - 2.5A output and up to 12Ah batteries
- HFP PSU-5.25/26SS - 5.25A output and up to 26Ah batteries
- HFP PSU-10.25/45SS - 10.25A output and up to 45Ah batteries

Unboxed or caged power supplies for incorporation into other equipment are available as follows:

- S2014 - 2.5A output
- S406 - 5.25A output
- S408 - 10.25A output