



<u>Title</u>	<u>Instruction 1/1</u>
<u>Overhaul Of Electrical Apparatus</u>	Pages: 2
<u>Engineering Instruction 1</u>	Date Issued : 03 August 2009
	Supersedes: 20 August 2007
Prepared By T. S. Sithole Checked By B. Siso (<i>DSM</i>) Approved By M. J. Chinembiri (<i>T&DD</i>)	Review / Approved Date

1 GENERAL

- 1.1 Overhaul Report forms Ref. E / 16 are to be filled in triplicate. The forms are to be distributed as follows: one copy remains in the book, the original copy to the Network Manager / Section Head and the remainder to the Customer Services Officer / Foreman.
- 1.2 Where the equipment is oil-filled, the oil tests shall be taken during the overhaul, and the results should be stated on the form.
Where the equipment is gas-filled, pressure readings or indications should be recorded before and after the overhaul.
- 1.3 On some equipment such as transformers, insulation tests shall be taken both before and after the maintenance work has been done. Both sets of results should be noted on the form; and in each case the temperature of the oil when the tests are done should be noted.
- 1.4 The back of each form is reserved for a detailed report, which may be warranted when an unusual type of fault occurs. It should be pointed out, however, that whenever equipment is damaged while in service, full details must be given on the Overhaul report regarding the primary cause of the fault, or if this is unknown, any conclusions that Divisional Staff may have formed as to the probable cause and, in addition, full details of the damage sustained.
- 1.5 Referring to the Engineering Instruction No 4/1 where it is necessary to inspect a transformer internally, in accordance with Section 6 of this Instruction, the result of the inspection should be detailed on the back of the Overhaul Report in the following manner:-

INTERNAL INSPECTION 8.1(a); 8.1(b); 8.1(c); 8.1(d);