DeviceType	IO port mapping		IO port							IO signal	Device parameter			
	PortType	Is required	Linear offset	RAM offset dec	RAM offset hex	Value type	Operation mode	Name	Description	Name	Name	Is required	Format	Description
SimplePic											HandlersTableEntrySize	Optional	^[0-9]$	Integer
	state	Mandatory												
			0	0	0x0000	u8	Duplex Register	InterruptedInstructionAddress	is being set on interrupt according to the machine state					
Each device allowed to publish certain amount of symbolical signals. Each signal might optionally be mapped to a certain interrupt Id, each may be shared between different signals. Platform Interupt Controller is able to transfer control flow to the appropriate interrupt handler when needed.			1	8	0x0008	i4	Duplex Register	InterruptHandlersTableEntrySize	used as mutiplier to compute interrupt vector, is being initialized from the corresponding parameter					
			2	12	0x000C	b	Duplex Register	InterruptsAllowed	set to allow interrupts being triggered, reset to postone them; is being reset on interrupt					
			3	16	0x0010	b	Duplex Register	QueueInterrupts	set to allow interrupts being queued to be triggered later, reset to completely ignore them					
			4	20	0x0014	b	Duplex Register	InterruptHappened	is being set when interrupt is being triggered; to be reset manually if needed					
			5	24	0x0018	i4	Duplex Register	DeviceTypeId	is being set on interrupt according to signal info					
			6	28	0x001C	i4	Duplex Register	DeviceId	is being set on interrupt according to signal info					
			7	32	0x0020	i4	Duplex Register	SignalId	is being set on interrupt according to signal info					
			8	36	0x0024	i4	Duplex Register	InterruptId	is being set on interrupt according to signal info					
			9	40	0x0028	bool	Blocking In Register	NextInterrupt	when interrupts queueing is enabled, blocks until the next interrupt will arrive and returns nonzero; otherwise returns zero immediately					
	handlers-map	Mandatory												
			0	0	0x0000	u1[]	Duplex Buffer	HandlersTable	each <entrySize> bytes treated as an address to jump to when the interrupt is being triggered as codeRamBank:entrySize[bindingStartAddress + entrySize*interruptId]					
SimpleClock														
	state	Mandatory							registers [0..9] represent current UTC time stamp					
Clock device state reflects current date and time information and also allows configurable signals based on the time intervals or amount of instructions executed			0	0	0x0000	i8	In Register	Ticks	1 second = 10000000 ticks					
			1	8	0x0008	i8	In Register	UnixTime	number of non-leap seconds which have passed since 00:00:00 UTC on Thursday, 1 January 1970					
			2	16	0x0010	i4	In Register	DayOfYear	component of the current time stamp					
			3	20	0x0014	i4	In Register	Year	component of the current time stamp					
			4	24	0x0018	i4	In Register	Month	component of the current time stamp					
			5	28	0x001C	i4	In Register	Day	component of the current time stamp					
			6	32	0x0020	i4	In Register	Hour	component of the current time stamp					
			7	36	0x0024	i4	In Register	Minute	component of the current time stamp					
			8	40	0x0028	i4	In Register	Second	component of the current time stamp					
			9	44	0x002C	i4	In Register	Millisecond	component of the current time stamp					
			10	48	0x0030	u8	In Register	Cycles	amount of instructions executed					
			11	56	0x0038	i8	Duplex Register	TicksSignalPeriod	set to enable timer signal, reset to disable	on-ticks				
			12	64	0x0040	u8	Duplex Register	CyclesSignalPeriod	set to enable cycles signal, reset to disable	on-cycles				
BlockDevice														
	control	Mandatory												
Block device allows position-based read-write operations over a contiguous stream of bytes, emulating storage device like disk drive, operating in half-duplex mode: either read or write operation is being executed at a given moment of time, but not both of the simultaneously.			0	0	0x0000	i8	Duplex Register	Position	byte offset to apply IO operation to		InteractiveFileServicePipe	Optional	InteractiveFileService pipe name to connect to	
			1	8	0x0008	i4	Duplex Register	Length	amount of bytes to operate with or affected by the operation		ServiceKey	Optional	InteractiveFileService connection key	
			2	12	0x000C	b	Duplex Register	SignalOnReady	set for next IO operation to emit signal on completion	on-read, on-write	FileName	Optional	Local file name to operate with	
			3	16	0x0010	b	Duplex Register	AsyncOperation	set for next IO operation to happen in background		InteractiveFileMode	Optional	CreateNew | Create | Open | OpenOrCreate | Truncate | Append	default is Open
			4	20	0x0014	b	Duplex Register	Reading	set to trigger read operation, get returns non-zero when in progress					
			5	24	0x0018	b	Duplex Register	Writing	set to trigger write operation, get returns non-zero when in progress					
			6	28	0x001C	b	In Register	IsBusy	get returns non-zero while any operation is in progress					
			7	32	0x0020	b	Duplex Register	HasError	is being set on error during operation					
	buffer	Mandatory												
			0	0	0x0000	u1[]	Duplex Buffer	Data	data buffer to operate with					
	error	Optional												
			0	0	0x0000	u1[]	Duplex Buffer	ErrorMessage	is being set to contain error message on operation error					
SimplePipe, SharedBusPipe														
	control	Mandatory												
			0	0	0x0000	u1[]	Blocking Out Register	SyncSend	set to this register immediately performs blocking send operation					
Pipe devices emulate various communication channels providing interactivity and communication capabilities to the machine. They operate in a full-duplex mode, allowing simultaneous send-receive operations transferring data in a different directions.			1	8	0x0008	u1[]	Blocking In Register	SyncReceive	get from this register immediately performs blocking receive operation					
			2	16	0x0010	i4	Duplex Register	InboxOffset	set to byte offset in the inbox buffer to read to		for SimplePipe			
			3	20	0x0014	i4	Duplex Register	InboxLength	set amount of bytes to read		PlainPipe	Optional	plain pipe name to connect to	
			4	24	0x0018	i4	Duplex Register	OutboxOffset	set to byte offset in the outbox buffer to send from		PipeSpec	Optional	pipe specification (see help or use 'stdio' with -ip)	
			5	28	0x001C	i4	Duplex Register	OutboxLength	set amount of bytes to send		AttachmentTimeout	Optional	^[0-9]$	
			6	32	0x0020	b	Duplex Register	SignalOnReceived	set for next receive operation to emit signal on completion	on-received	OperationMode	Optional	ByteStream|MessageFrames	
			7	36	0x0024	b	Duplex Register	AsyncReceving	set for next receive operation to happen in background					
			8	40	0x0028	b	Duplex Register	Receiving	set to trigger receive operation, get returns non-zero while in progress					
			9	44	0x002C	i4	Duplex Register	ReceivedLength	is being set to amount of data received on completion					
			10	48	0x0030	b	Duplex Register	Received	is being set to non-zero on receive completion; to be reset manually if needed					
			11	52	0x0034	b	Duplex Register	SignalOnSent	set for next send operation to emit signal on completion	on-sent	for SharedBusPipe:			
			12	56	0x0038	b	Duplex Register	AsyncSending	set for next send operation to happen in background		BusServicePipeName	Mandatory	LocalSharedBus service pipe name	
			13	60	0x003C	b	Duplex Register	Sending	set to trigger send operation, get returns non-zero while in progress		BusId	Mandatory	^[0-9]$	Integer
			14	64	0x0040	i4	Duplex Register	SentLength	is being set to amount of data sent on completion		AttachmentTimeout	Optional	^[0-9]$	Milliseconds
			15	68	0x0044	b	Duplex Register	Sent	is being set to non-zero on send completion; to be reset manually if needed		OperationMode	Optional	ByteStream|MessageFrames	
	inbox	Optional												
			0	0	0x0000	u1[]	Duplex Buffer	Data	data buffer for receive operations to operate with					
	outbox	Optional												
			0	0	0x0000	u1[]	Duplex Buffer	Data	data buffer for send operations to operate with					