

CSA Group Testing & Certification Inc.
CSA Group Bayern GmbH
Straubinger Straße 100, 94447 Plattling,
Germany.

Customer ID	0006025564	Account	JZPE POWER TRANSFORMER INC.
Contact	Han Meng	Address	Longxi Industrial Zone , JiangYan District, Taizhou, Jiangsu 225500 China
Project Number	80228493		

Special Inspection Report

Work Order	00035689	Usage Decision	Product labeled
Work Order Line Item Number	00000001	Label Applied	Yes
		Start Date	10/18/2024 12:00 PM
Product	THREE PHSAE TRANSFORMER	Report Generation Date	12/20/2024 5:19 PM
Model	1RZ.720.C225		
Manufacturer's Name	JZP POWER TRANSFORMER		

Inspection Address

Longxi Industrial Zone ,
JiangYan District,
Taizhou, Jiangsu 225500
China

Labels Applied

Material	Label Serial Number	Quantity	Unit Serial Number
1002210	C2937189	1.00	MY24091632
1002210	C2937188	1.00	MY24091596

Inspection Method QD-1055-WI-INSP

Electrical Ratings

Voltage Values Transformer: H.V.: 27600/15935 V GrdY, L.V.: 4160 V Delta; Terminal box: 120 V

Frequency 60 Hz

Power Values Transformer:9.8 MVA; Terminal box: 20 A

No of Wires Transformer:4; Terminal box: 2

No of phases Transformer:3; Terminal box: 1

SCCR: N/A

Connection type Permanently connected

Enclosure Type Outdoor use

Environmental Test Conditions Indoor, Normal Temperature and Humidity.

Test Results

Test Type	Duration of Test	Test Value	Pass/Fail	Test Equipment	Cal Due Date	S/N or ID	Number of Units
-----------	------------------	------------	-----------	----------------	--------------	-----------	-----------------

Test Result Summary

The following design tests on serial no MYY24091596 of transformer were performed at Longxi Industrial Zone ,JiangYan District,Taizhou, Jiangsu 225500, China, in accordance with CSA C88:16, with satisfactory result.
Refer to Illustration 7.

Note: Lab capacity was evaluated before performing the tests according to IEC 17025.

a) information on other third-party qualifications, if available;

N/A

b) relevant test procedures or other information to ensure the tests are conducted correctly;

Witness tests by CSA SIR

c) training records for staff performing testing or other evidence of staff competence;

Refer to training records

d) information on the calibration procedures;

Have CNAS and ilac-MRA marked.

e) list of test equipment and their calibration certificates; and

Refer to calibration certificates

f) sign-off by technical staff or responsible management.

Sign-off by technical staff and responsible management.

1. Resistance measurement

2. Ratio tests

3. No load losses and excitation current

4. Load losses and impedance voltage

- 5 Insulation resistance tests
6. Lightning impulse test
7. Applied voltage tests
8. Induced voltage tests
9. Temperature test
10. Tank pressure (leakage) Test

The following routine tests of remaining 1 unit of transformer were performed at Longxi Industrial Zone ,JiangYan District,Taizhou, Jiangsu 225500, China, in accordance with CSA C88:16, with satisfactory result.
Refer to Illustration 8.

1. Resistance measurement
2. Ratio tests
3. No load losses and excitation current
4. Load losses and impedance voltage
- 5 Insulation resistance tests
6. Applied voltage tests
7. Induced voltage tests
8. Tank pressure (leakage) Test

Applicable Standards

SPE-1000:21

List of Alterations

2024-11-01: No warning on the terminal box
2024-12-11: Done

List of Safety Critical Components

Enclosure Components	Transformer: Detail see att4 outline drawing. Terminal box: Detail see att3 enclosure.
Ground/Bonding Components	Transformer: All exposed non-current-carrying metal parts that could become energized were properly bonded. Terminal box: The equipment was provided with an adequately sized bonding terminal and found to be suitable for bonding the equipment to ground in accordance with the requirements of the Canadian Electrical Code, Part I. All exposed non-current-carrying metal parts that could become energized were properly bonded.
Disconnect Components	Provided at installation site.
Main Overcurrent Protection Components	The same as the disconnect components

Branch Overcurrent Protection Components	Transformer: N/A Terminal box: Branch circuit breaker: cULus listed, by Nader, model NDB2T-63, 277/120 ACV, 50/60 Hz, 60 VDC, 10 KA, 2P and 1P, certified to UL489, specific rated current rating refers to electrical drawing electrical drawing.
Overload Components	Transformer: N/A Terminal box: Thermal relay: cULus listed, by SIEMENS, model 3RU6116-1FB1, 3.5~5.0 A, 460 VAC.
Temperature device Components	N/A
Safety Circuit Components	N/A
Other Components	Detail see Bom list

Equipment Description and Function

The unit is a THREE PHASE TRANSFORMER with terminal box. Installation Requirements Reviewed: Yes

Construction Review

Components	Components were confirmed to be accurately identified on the drawings and bill of material. Critical components were marked with an acceptable approval mark from an accepted NRTL. The components were installed in accordance with the manufacturer's instructions, used for their intended application, and were used within their electrical ratings. Critical safety components that were not approved are identified in the component list of the report.
Mechanical Assembly	The mechanical assembly was reviewed and found to be smooth and free of sharp edges and burrs. The equipment provided with adequate guarding and the structure was mechanically stable and structurally sound. Adequate guarding of dangerous moving parts.
Disconnecting Means	N/A
Bonding	The equipment was provided with an adequately sized bonding terminal and found to be suitable for bonding the equipment to ground in accordance with the requirements of the Canadian Electrical Code, Part I. All exposed non-current-carrying metal parts that could become energized were properly bonded. There was a sufficient number of bonding terminals provided for each incoming and each outgoing circuit.
Enclosure	The enclosure was found to be constructed and assembled to provide the strength and rigidity necessary to resist the

abuses to which it will be subjected in the environment in which the equipment is intended to be used without resulting in a fire or shock hazard. The enclosure was made of suitable material to prevent corrosion. Doors and covers were adequately fastened such that live parts were not accessible without the use of a tool. Openings were reviewed and found sized to prevent the test probe from contacting bare live parts of hazard voltages.

Terminals	Conductors were found to be secured in a manner as to obtain good permanent contact. Conductors were firmly gripped in a manner that stray strands cannot cause short-circuits or grounds. Terminals were adequately sized with an ampacity not less than required for application in the device.
Wiring	Internal conductors were found to be suitable for the service intended with respect to voltage, temperature and grouping. The conductors were supported so that there was no undue mechanical strain on the conductors or their terminals. There were no apparent rough edges, burrs or sharp edges that would likely damage the insulation. The conductors were evaluated for the load ampacity.
Overcurrent Protection	Transformer: N/A Terminal box: Overcurrent and overload devices were found to be suitable for the application, approved for the intended use, and adequately sized for the circuit they are protecting.
Supplementary Protectors	N/A
Motors	Transformer: Each motor nameplate was reviewed and confirmed to have proper protection sized in accordance with Canadian Electrical Code, Part 1. Cable connections were tight and of the correct size and suitable for the intended environment. Terminal box: N/A
Motor Controllers	Transformer: N/A Terminal box: Each Motor controller was reviewed to determine it was properly rated for the intended application and sized for the load that it is controlling. Overloads range are within the motors FLA.
Receptacles	N/A
Lighting	Transformer: N/A Terminal box: Lighting circuits were branch circuit protected in accordance with the C22.1. Fixtures were installed in a location where they were protected from mechanical damage.
Drives	N/A
Safety Circuits	N/A

Conditions of Acceptability

CSA Group Testing & Certification Inc.
CSA Group Bayern GmbH
Straubinger Straße 100, 94447 Plattling,
Germany.

1. The acceptance of the final installation shall be determined by the authority having jurisdiction.
2. The equipment has been evaluated for electrical safety only, for installation and use in ordinary (non hazardous) locations in accordance with National and Local Code; requirements other than electrical safety may be mandated by local/ provincial/federal authorities, and are responsibility of the Submitter.

Att1 - Nameplate
Att2 - Calibration certificate
Att3 - Enclosure
Att4 - Outline drawing
Att5 - Electrical drawing
Att6 - Bom list for terminal box
Att6 - Bom list for transformer
Att7 - Design tests report
Att8 - Routine tests report
Att9 - Test report for oil
Att10 - Lab evaluated

Markings

Verified Bilingual Yes
Cautions/Warning Detail see the photo
Markings

Customer Signature

Signature
Signed By
Date
Type Facility Representative

Prepared By Mark Xin

The Client acknowledges that the equipment described in the related report has not been rejected due to unacceptable results of a previous evaluation conducted by a certification organization through any other existing certification service.

NOTE: EVALUATION BY SPECIAL INSPECTION SERVICE SHALL NOT BE CONSIDERED EQUIVALENT OF CSA CERTIFICATION.

The Client agrees to the Conditions of the signed/accepted Quote on file, and Alteration(s) listed on the related report. This report addresses only the product described in the report, as the product existed at the time of the inspection.