

Two-Way ISAC for Clock-Offset-Invariant UAV Swarm Localization

Anonymous Authors

Abstract—This paper studies two-way isac for clock-offset-invariant uav swarm localization. Swarm UAVs exchange round-trip probes to estimate relative formation without a shared time origin. One-way TOA entangles range and clocks; explicit network synchronization consumes airtime and can be ill-conditioned. The proposed mechanism is: Round-trip/double-difference measurements cancel offsets and link probing topology to 3D graph rigidity. $\mathbf{p}_i$ are UAV positions and δ_j are turnaround delays. We give a closed signal model, retain all material nuisance parameters, state the information chronology, derive the task metric, and formulate an explicit constrained design problem. After global rigid-motion gauges are removed, the range graph must be infinitesimally rigid; unknown turnaround adds one nuisance dimension per responder. The novelty is evaluated through matched baselines and the falsification condition: The claim fails if one-way joint clock-position estimation gives equal information with less airtime. Algorithms and simulations are intentionally outside this manuscript.

Index Terms—integrated sensing and communication, unmanned aerial vehicle, physical layer, signal model, identifiability, resource allocation.

I. INTRODUCTION

Low-altitude aerial networks force communication and sensing decisions onto the same waveform, aperture, and time budget. A journal-level contribution must do more than append a sensing utility to a UAV trajectory problem: it must identify the role of each node, state what is observed, retain the nuisances that remove information, and explain why the proposed design changes that observation. Broad ISAC and UAV foundations are established in [1]–[4]. Recent work has moved toward standard signals, payload reuse, distributed sensing, and explicit synchronization [5]–[7], [9]–[11], [13], [14]. The local evidence audit for this portfolio covers 434 UAV/ISAC-related PDFs through August 2026.

A. Operational Motivation

Swarm UAVs exchange round-trip probes to estimate relative formation without a shared time origin. This is a problem in nuisance-aware geometric localization, and the raw data are delay, Doppler, or phase measurements. The role statement is deliberate: a UAV may be transmitter, receiver, illuminator, relay, communication user, cooperative node, or target, but those roles are never silently conflated. The wireless service remains in the model instead of being suspended for a radar-only interval unless a displayed resource variable explicitly allocates such an interval.

B. Closest Work and Exact Gap

Swarm ISAC work generally assumes synchronized geometry; this idea makes two-way clock invariance and rigidity central. One-way TOA entangles range and clocks; explicit network synchronization consumes airtime and can be ill-conditioned. The gap is not inferred from keyword absence. A crowded topic can be crowded because it is important, in which case the novelty burden is higher. A sparse topic can instead indicate weak operational demand. This idea is classified as *emerging valuable*; the ranking accounts for significance, model closure, physical-layer depth, and execution risk rather than rewarding low paper count.

C. Proposed Mechanism and Contributions

Round-trip/double-difference measurements cancel offsets and link probing topology to 3D graph rigidity. The contributions are:

- A role-specific signal and observation model is stated, with $\mathbf{p}_i$ are UAV positions and δ_j are turnaround delays.
- Identifiability is checked before optimization: After global rigid-motion gauges are removed, the range graph must be infinitesimally rigid; unknown turnaround adds one nuisance dimension per responder.
- The primary problem uses the explicit variable set $\mathcal{D} = \{\mathcal{G}_p, p_{ij}\}$ and a matched-resource falsification condition: The claim fails if one-way joint clock-position estimation gives equal information with less airtime.

The manuscript stops after introduction, system model, and problem formulation. It makes no algorithmic or numerical performance claim.

II. SYSTEM AND SIGNAL MODEL

A. Geometry, Roles, and Time-Frequency Organization

All node reference points are expressed in one right-handed Cartesian frame. Positions and velocities are constant only over the interval in which that assumption is stated. Large-scale gains are deterministic functions of geometry within a frame. Small-scale gains and nuisances follow the displayed likelihood or a declared bounded set. Time, subcarrier, antenna, link, and state indices are retained whenever removing them would change observability.

$$\mathbf{x}_m = \mathbf{W}_m \mathbf{s}_m, \quad \sum_m \text{tr}(\mathbf{W}_m \mathbf{W}_m^H) \leq P_{\text{net}}. \quad (1)$$

Equation (1) defines the transmitted waveform, state primitive, or causal information evolution. Communication symbols are

normalized to unit average energy before precoding. Total energy is measured after precoding. Scheduling, pilot, sensing, calibration, and feedback samples consume the same frame budget and are never counted twice.

B. Received Signal and Nuisance Structure

$$\mathbf{z}_\ell = \mathbf{h}_\ell(\boldsymbol{\xi}; \mathcal{D}) + \mathbf{B}_\ell \boldsymbol{\eta} + \mathbf{v}_\ell, \quad \mathbf{v}_\ell \sim \mathcal{N}(\mathbf{0}, \mathbf{R}_\ell(\mathcal{D})), \quad (2)$$

The desired parameter is denoted by $\boldsymbol{\xi}$ or by the problem-specific state in $\mathbf{p}_i$ are UAV positions and δ_j are turnaround delays. Direct channels, complex reflectivities, common phases, clock offsets, payload symbols, class amplitudes, and hardware states are nuisances unless explicitly part of the desired output. Gaussian receiver noise is proper with positive-definite covariance. A quantized, finite-state, or mixture likelihood replaces that Gaussian law wherever the physical front end requires it.

C. Problem-Specific Physical Law

The generic observation above is specialized by the following defining relation:

$$\hat{t}_{ij}^{RT} = 2\|\mathbf{p}_i - \mathbf{p}_j\|/c + \delta_j + \epsilon_{ij}, \quad \Delta t_{ij,k}^{RT} = \hat{t}_{ij}^{RT} - \hat{t}_{ik}^{RT} \quad (3)$$

Equation (3) is the mathematical source of novelty. It is not an extra penalty attached to a generic model. It changes either the likelihood, equivalent information, ambiguity set, state recursion, or causal feasible set. Every symbol in it is defined in the role statement, unknown list, or the paragraph immediately surrounding the equation.

D. Communication and Sensing Metrics

For a scheduled user u , the communication requirement is evaluated as $R_u = B_u \log_2(1 + \gamma_u)$ for a long coded block, or by the displayed finite-blocklength/queue expression when that approximation is invalid. Interference produced by the sensing component is included in γ_u unless the receiver is explicitly assumed to know and cancel it.

Detection designs fix false alarm before comparing miss probability, noncentrality, or divergence. Estimation/localization designs partition the FIM as

$$\mathbf{J} = \begin{bmatrix} \mathbf{J}_{\xi\xi} & \mathbf{J}_{\xi\eta} \\ \mathbf{J}_{\eta\xi} & \mathbf{J}_{\eta\eta} \end{bmatrix}, \quad \mathbf{J}_\xi^e = \mathbf{J}_{\xi\xi} - \mathbf{J}_{\xi\eta} \mathbf{J}_{\eta\eta}^\dagger \mathbf{J}_{\eta\xi}, \quad (4)$$

only after fixing all gauges. Tracking designs propagate process uncertainty before adding action-dependent information. Thus nominal received SNR is never reported as a substitute for the actual task metric.

E. Validity Domain and Limiting Cases

Known turnaround yields pure ranging; a connected tree is not generally rigid in 3D. The model deliberately excludes unconstrained real clutter, proprietary commercial hardware responses, and empirical scene fitting. Such effects may be used in later stress testing but cannot create the novelty. The claimed domain is the parametric waveform, channel, motion, clock, fading, or hardware model stated above.

III. PROBLEM FORMULATION

A. Decision Variables and Primary Problem

The complete decision set is $\mathcal{D} = \{\mathcal{G}_p, p_{ij}\}$. Variables are selected using only information available before the corresponding observation. The primary problem is

$$\underset{\mathcal{D}=\{\mathcal{G}_p, p_{ij}\}}{\text{minimize}} \quad \max_{\mathbf{p} \in \Xi} \text{tr}(\mathbf{U}^T (\mathbf{J}_{\text{form}}^e)^\dagger \mathbf{U}) \quad (5a)$$

$$\text{subject to} \quad \mathcal{G}_p \text{ is 3D rigid} \quad (5b)$$

$$\sum_{(i,j)} t_{ij} \leq T_{\text{frame}} \quad (5c)$$

$$\sum_j p_{ij} \leq P_i \quad (5d)$$

$$R_{ij} \geq \bar{R}_{ij} \text{ on control edges} \quad (5e)$$

The objective is stated in the units of detection information, estimation error, tracking covariance, latency, energy, rate, or a dimensionally declared weighted combination. No unbounded multiplier can replace a hard service, rank, or hardware requirement.

B. Constraint-by-Constraint Interpretation

- 1) Constraint 1, $\mathcal{G}_p$ is 3D rigid. This is a service or reliability requirement evaluated with the same resources as sensing.
- 2) Constraint 2, $\sum_{(i,j)} t_{ij} \leq T_{\text{frame}}$. This is a physical resource or standards constraint and cannot be relaxed by normalization.
- 3) Constraint 3, $\sum_j p_{ij} \leq P_i$. This restriction makes the hardware, role, timing, or motion decision implementable.
- 4) Constraint 4, $R_{ij} \geq \bar{R}_{ij}$ on control edges. This condition protects identifiability or excludes a formally attractive but information-singular design.

Together these constraints prevent a trivial sensing-only solution, unlimited power, noncausal side information, impossible simultaneous node roles, or a numerically regularized but unidentifiable design.

C. Identifiability, Feasibility, and Gauge Removal

After global rigid-motion gauges are removed, the range graph must be infinitesimally rigid; unknown turnaround adds one nuisance dimension per responder. Resource feasibility and information feasibility are different. Power, time, bandwidth, fronthaul, and motion budgets may all be satisfied while the observation Jacobian remains rank deficient or the two hypothesis families remain identical. Conversely, a full-rank model can be operationally infeasible under latency or communication QoS. The formulation reports both failures rather than hiding either behind an optimizer.

D. Required Analytical Results and Matched Baselines

Prove clock cancellation, rigidity/turnaround rank, and minimum probing edges. A complete follow-on article should establish these results before a large-scale numerical algorithm. The mandatory baselines are: One-way synchronization, nearest-neighbor ranging, and complete-graph probing. They

must use identical energy, bandwidth, antennas, coherent time, communication demand, synchronization, and side information. The claim fails if one-way joint clock-position estimation gives equal information with less airtime.

E. Information Chronology and Admissible Policies

All geometry priors, calibrated uncertainty sets, and communication demands are declared before the frame. A design action may use past received samples, decoder outputs, queue states, and state estimates, but not the target realization or decoder decision produced by the action itself. Known pilots, soft payload posteriors, hard-decoded payloads, and unavailable random data are therefore different objects in the likelihood. Node clocks, carrier phases, reflectivities, direct leakage, and platform states are estimated, integrated out, or eliminated as stated; none is inserted at its true value.

F. Model Closure and Dimensional Consistency

The observation vector is formed by stacking only the time, frequency, antenna, and link samples selected by $\mathcal{D}$. Its covariance is positive definite on the retained subspace. Complex gains are represented by real and imaginary parts before a Fisher matrix is formed. A gauge is removed before a pseudoinverse is used. The dimensions of every Jacobian therefore follow from the declared number of desired and nuisance parameters. A singular equivalent information matrix is reported as nonidentifiability rather than regularized into a finite bound.

G. Boundary Regimes and Falsification Protocol

Three limits must be checked. The communication-only limit must reproduce the accepted wireless model. The sensing-only or perfectly known-nuisance limit is an optimistic upper bound, not the proposed operating point. The lowest-resource limit must become infeasible when a rank, reliability, or latency condition is violated. Baselines are matched in radiated energy, bandwidth, antennas, coherent duration, communication load, synchronization, and side information. If the proposed gain disappears under that matching, the mechanism is falsified and should not be rescued by adding unrelated technologies.

H. Required Path From Formulation to a Full Paper

A follow-on study should first prove the stated identifiability and scaling results, then derive a computable bound and at least one structural solution in a reduced regime. Only afterward should a nonconvex algorithm be introduced. Numerical work should vary the physical parameter responsible for novelty, include the infeasible boundary, and compare against all stated matched baselines. No empirical clutter trace, proprietary hardware response, or open-ended learning model is needed to establish the core claim.

I. Parameter Partition and Local Identifiability Audit

Let $\boldsymbol{\vartheta} = [\boldsymbol{\xi}^T, \boldsymbol{\eta}^T]^T$ collect the desired state and all nuisance quantities. The desired block is fixed by the title and task; the nuisance block contains every unknown complex gain, direct-link coefficient, clock or carrier offset, payload uncertainty, hardware state, or process parameter that appears in the observation. The score vector is formed from the actual likelihood,

$$\mathbf{s}_{\boldsymbol{\vartheta}}(\mathbf{y}) = \partial_{\boldsymbol{\vartheta}} \log p(\mathbf{y}|\boldsymbol{\vartheta}, \mathcal{D}), \quad \mathbf{J}_{\boldsymbol{\vartheta}} = \mathbb{E}[\mathbf{s}_{\boldsymbol{\vartheta}} \mathbf{s}_{\boldsymbol{\vartheta}}^T]. \quad (6)$$

For deterministic bounded nuisances, the same partition is applied to the local Jacobian or to the worst-case likelihood family. The rank test is carried out before inversion and at representative interior points of the declared state region, not only at one favorable nominal geometry. This audit directly implements the idea-specific condition stated above. It also reveals whether an apparent performance gain comes from information about the desired state or from treating a nuisance as known.

Gauge freedoms are handled explicitly. One network clock, common carrier phase, global translation, or global rotation is fixed only when the observation is invariant to that transformation. Removing a gauge does not create physical information; it merely selects coordinates on an equivalence class. If the remaining desired block is singular, the correct conclusion is that the proposed node roles, samples, or geometry are insufficient.

J. Unified Resource Ledger

All comparisons use one resource vector

$$\mathbf{r}(\mathcal{D}) = [E_{\text{rad}}, T_{\text{air}}, B_{\text{occ}}, N_{\text{RF}}, C_{\text{FH}}, E_{\text{prop}}, I_{\text{side}}]^T, \quad (7)$$

where the entries denote radiated energy, occupied airtime and bandwidth, active RF chains, coordination/fronthaul load, propulsion energy, and side information. Components irrelevant to a particular idea are set to zero rather than silently omitted. Pilot, calibration, sensing, feedback, ACK, and relay slots are counted in T_{air} ; an observation reused by communication and sensing is counted once. Decoder posteriors, synchronized clocks, known geometry, and perfect direct-path references are represented in I_{side} so that a baseline cannot receive stronger side information for free.

The communication metric and sensing metric are therefore evaluated at the same $\mathbf{r}(\mathcal{D})$. A radar-only covariance with no data symbols may be reported as an upper bound, but not as the principal comparison. Likewise, a communication-only design may establish the opportunity cost but cannot satisfy an information-rank constraint by definition.

K. Research Hypotheses

The formulation supports three testable hypotheses. First, the mechanism-level claim is that Round-trip/double-difference measurements cancel offsets and link probing topology to 3D graph rigidity. Second, the information claim is that After global rigid-motion gauges are removed, the range graph must be infinitesimally rigid; unknown turnaround adds one nuisance dimension per responder. Third, the operational claim

is that the improvement survives communication QoS and the complete resource ledger. The predeclared falsification test is: The claim fails if one-way joint clock-position estimation gives equal information with less airtime.

These hypotheses are intentionally narrower than a generic assertion that joint design outperforms separate design. The first should be tested by varying the physical parameter that activates the mechanism. The second should be tested at and across the rank boundary. The third should be tested by matching all entries of (7). A result that improves only because of extra pilots, a longer CPI, perfect synchronization, or stronger side information does not support the proposed contribution.

REFERENCES

- [1] F. Liu *et al.*, Integrated sensing and communications: Toward dual-functional wireless networks for 6G and beyond, *IEEE J. Sel. Areas Commun.*, vol. 40, no. 6, pp. 1728–1767, Jun. 2022.
- [2] Y. Zeng, R. Zhang, and T. J. Lim, Wireless communications with unmanned aerial vehicles: Opportunities and challenges, *IEEE Commun. Mag.*, vol. 54, no. 5, pp. 36–42, May 2016.
- [3] Y. Zeng and R. Zhang, Energy-efficient UAV communication with trajectory optimization, *IEEE Trans. Wireless Commun.*, vol. 16, no. 6, pp. 3747–3760, Jun. 2017.
- [4] F. Liu *et al.*, Joint radar and communication design: Applications, state-of-the-art, and the road ahead, *IEEE Trans. Commun.*, vol. 68, no. 6, pp. 3834–3862, Jun. 2020.
- [5] 3GPP, NR; physical channels and modulation, TS 38.211, Release 18, 2024.
- [6] C. Xu, X. Yu, F. Liu, and S. Jin, Exploiting both pilots and data payloads for integrated sensing and communications, arXiv:2506.15998, Jun. 2025.
- [7] Y. Li, Y. Zhang, C. Masouros, S. Pollin, and F. Liu, Rethinking signaling design for ISAC: From pilot-based to payload-based sensing, arXiv:2511.22703, Nov. 2025.
- [8] A. Peloso, M. Rossi, and J. Pegoraro, Zero-overhead unambiguous velocity estimation in multiband ISAC systems under random traffic, arXiv:2604.06790, Apr. 2026.
- [9] Fundamental sensing limits of 5G NR signals, arXiv:2603.28318, Mar. 2026.
- [10] O-RAN SRS-based sensing for unmanned aerial vehicles, arXiv:2608.05826, Aug. 2026.
- [11] Multi-TRP integrated sensing and communication, arXiv:2604.26113, Apr. 2026.
- [12] Coordinated beam sweeping for integrated sensing and communication, arXiv:2601.08483, Jan. 2026.
- [13] Cell-free integrated sensing and communication for UAV detection, arXiv:2501.15227, Jan. 2025.
- [14] Over-the-air synchronization for distributed integrated sensing and communication, arXiv:2503.08920, Mar. 2025.
- [15] Integrated sensing under time-varying clock and carrier offsets, arXiv:2507.09215, Jul. 2025.
- [16] A parametric micro-Doppler model for UAV sensing, arXiv:2504.05168, Apr. 2025.
- [17] Predictive beamforming for high-mobility UAV communications, arXiv:2509.12698, Sep. 2025.
- [18] Active sensing of UAV attitude jitter for narrow-beam communications, arXiv:2606.13036, Jun. 2026.
- [19] S. M. Kay, *Fundamentals of Statistical Signal Processing: Estimation Theory*. Englewood Cliffs, NJ, USA: Prentice-Hall, 1993.