- **Technical Parameters:**

Power supply: AC100～240V, 50Hz/60Hz
Scanning system: Galvo scanning system 15kpps/±25°
Luminous color：RGB
Wavelength：R 660nm G 532nm B 450nm
Power Connection: Power Cord
Signal connection: Signal input line/output line
Control channels: 16 DMX-512 signal channels
Control mode: DMX-512 control, Sound control, Auto, Master-slave, Remote and APP Control
Cooling system: Pure aluminum chassis cooling system
Working environment: Indoor

- **Menu Function Introduction:**

1	ADDR	1-512	Address Code Setting, DMX Mode/Slave Mode
2	SHOW	SHOW 0	SHOW 0 All programs are played randomly
		SHOW 1	SHOW 1 Line Effect Program Playback
		SHOW 2	SHOW 2 Animation Effect Program Playback
		SHOW 3	SHOW 3 Built-in Text Program Playback
		SHOW 4	SHOW 4 Christmas and New Year Program Playback
		SHOW 5	SHOW 5 Outdoor Landmark Program Playback
		SHOW 6	SHOW 6 Personalized Programming Program Playback
		SHOW 7	SHOW 7 Hand-painted Graffiti Program Playback
3	SPEED	SP 0-SP 9	SP 0-9 Program playback speed from slow to fast
4	SOUND	S_ON	ON :Sound control ON, program playback is in sound control mode (only SHOW 0, SHOW 1, SHOW 2, SHOW 4, SHOW 5 supports sound control)
		S_OFF	OFF:Sound control OFF, after sound control off, the program playback is automatic mode
5	SENSE	SE 0-SE 9	SE 0-9 Acoustic sensitivity from low to high

- **DMX512 Channel Function:**

		DMX-512 value	Control content
CH1	Main switch	0-9	Laser OFF
		10-255	Laser ON (dimming)
CH2	Color	0-69	White-Red-Blue-Pink-Cyan-Yellow-Green (Fixed color selection)
		70-79	Overall color change (flow rate controlled by CH3)
		80-89	Pattern initial color (flow rate controlled by CH3)
		90-92	Seven rainbow colors (flow rate controlled by CH3)
		93-110	2-segment color selection 4 numerical steps (flow rate controlled by CH3)
		111-131	3-segment color selection 4 numerical steps (flow rate controlled by CH3)
		132-149	4-segment color selection 4 numerical steps (flow rate controlled by CH3)

		150-182	8-segment color selection 4 numerical steps (flow rate controlled by CH3)
		183-218	16-segment color selection 4 numerical steps (flow rate controlled by CH3)
		219-253	32-segment color selection 4 numerical steps (flow rate controlled by CH3)
		254-255	Color gradient (flow rate controlled by CH3)
CH3	Color flow speed	0-9	Color does not run
		10-127	Color positive running, speed from slow to fast
		128-255	Color flow in reverse, speed from slow to fast
CH4	Graphics Group Selection	0-24	Built-in static graphics group 1 (basic geometric patterns)
		25-49	Built-in static graphics group 2 (basic geometric patterns)
		50-74	Built-in static graphics group 3 (edge highlight pattern)
		75-99	Built-in static graphics group 4 (punched graphics)
		100-124	Built-in Static Graphics Group 5 (Christmas Graphics)
		125-149	ILDA Animation Category 1
		150-174	ILDA Animation Category 2
		175-199	ILDA Animation Category 3 (Reserved)
		200-224	ILDA Animation Category 4 (Reserved)
		225-255	ILDA Animation Category 5 (Reserved)
CH5	Graphics Selection	0-255	Pattern selection (**pattern grouping is controlled by CH4**)
CH6	Built-in dynamic effects	0-1	No function
		2-206	Built-in dynamic effects radio selection, one effect per 2 values (color CH2 control, CH2=0 default color, speed CH7 control)
		207-216	Line effect random playback (color CH2 control, CH2=0 default color, speed CH7 control)
		217-226	Animation effect random playback (color CH2 control, CH2=0 default color, speed CH7 control)
		227-236	Christmas effect random playback (color CH2 control, CH2=0 default color, speed CH7 control)
		237-246	Outdoor effect random playback (color CH2 control, CH2=0 default color, speed CH7 control)
		247-253	All effects play randomly (color CH2 control, CH2=0 default color, speed CH7 control)
		254-255	Sound control (color CH2 control, CH2=0 default color, speed CH7 control)
CH7	Built-in dynamic effect speed	0-1	System default speed
		2-255	Manual Adjustment Built-in effect speed from slow to fast
CH8	Pattern size	0-255	Manual selection of pattern size
CH9	Automatic scaling of patterns	0-15	Pattern size selection
		16-55	Selection of speed from small to large
		56-95	Selection of speed from large to small
		96-135	Size Zoom Speed Selection
		136-175	Two-point irregular loop scaling
		176-215	Three-point irregular loop scaling
		216-255	Four-point irregular loop scaling
CH10	Pattern rotate around the center	0-127	Rotation angle selection
		128-191	Positive rotation speed selection
		192-255	Counter-rotation speed selection
CH11	Pattern rotate around the X-axis	0-127	Horizontal flip position selection
		128-255	Horizontal flip speed selection
CH12	Pattern rotate around the Y-axis	0-127	Vertical flip position selection
		128-255	Vertical flip speed selection
CH13	Horizontal movement	0-127	Horizontal position selection
		128-255	Horizontal circular movement, speed from fast to slow
CH14	Vertical movement	0-127	Vertical position selection
		128-255	Vertical circular movement, speed from fast to slow
CH15	X-direction wave	0-1	No wave
		2-255	Wave amplitude and speed adjustment (amplitude from small to large, speed from slow to fast, one step for every 32 values, 8 steps in total)
CH16	Pattern gradual drawing	0-1	No gradual drawing
		2-63	Manual graduated drawing 1
		64-127	Manual graduated drawing 2
		128-153	Auto gradient (Increase)
		154-179	Auto gradient (Decrease)
		180-205	Auto gradient (Increase first, then decrease - Reverse)
		206-255	Auto gradient (Increase first, then decrease - Isotropic)

- **IR Remote Control Instruction:**

Note: Before using the remote control, please pull out the plastic sheet under the remote control so that the remote can work.



Pull out the plastic sheet before use