

802.11a_g_n_ac_ax 速率对照表

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
1	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	8.603	8.125	7.313	17.206	16.250	14.625	36.029	34.028	30.625	72.059	68.056	61.250
	1	QPSK	1/2		2	17.206	16.250	14.625	34.412	32.500	29.250	72.059	68.056	61.250	144.118	136.111	122.500
	2	QPSK	3/4		2	25.809	24.375	21.938	51.618	48.750	43.875	108.088	102.083	91.875	216.176	204.167	183.750
	3	16-QAM	1/2		4	34.412	32.500	29.250	68.824	65.000	58.500	144.118	136.111	122.500	288.235	272.222	245.000
	4	16-QAM	3/4		4	51.618	48.750	43.875	103.235	97.500	87.750	216.176	204.167	183.750	432.353	408.333	367.500
	5	64-QAM	2/3		6	68.824	65.000	58.500	137.647	130.000	117.000	288.235	272.222	245.000	609.071	544.444	490.000
	6	64-QAM	3/4		6	77.426	73.125	65.813	154.853	146.250	131.625	324.265	306.250	275.625	648.529	612.500	551.250
	7	64-QAM	5/6		6	86.029	81.250	73.125	172.059	162.500	146.250	360.294	340.278	306.250	720.588	680.556	612.500
	8	256-QAM	3/4		8	103.235	97.500	87.750	206.471	195.000	175.500	432.353	408.333	367.500	864.706	816.667	735.000
	9	256-QAM	5/6		8	114.706	108.333	97.500	229.412	216.667	195.000	480.392	453.704	408.333	960.784	907.407	816.667
	10	1024-QAM	3/4		10	129.044	121.875	109.688	258.088	243.750	219.375	540.441	510.417	459.375	1080.882	1020.833	918.750
	11	1024-QAM	5/6		10	143.382	135.417	121.875	286.765	270.833	243.750	600.490	567.130	510.417	1200.980	1134.259	1020.833

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
2	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	17.206	16.250	14.625	34.412	32.500	29.250	72.059	68.056	61.250	144.118	136.111	122.500
	1	QPSK	1/2		2	34.412	32.500	29.250	68.824	65.000	58.500	144.118	136.111	122.500	288.235	272.222	245.000
	2	QPSK	3/4		2	51.618	48.750	43.875	103.235	97.500	87.750	216.176	204.167	183.750	432.353	408.333	367.500
	3	16-QAM	1/2		4	68.824	65.000	58.500	137.647	130.000	117.000	288.235	272.222	245.000	576.471	544.444	490.000
	4	16-QAM	3/4		4	103.235	97.500	87.750	206.471	195.000	175.500	432.353	408.333	367.500	864.706	816.667	735.000
	5	64-QAM	2/3		6	137.647	130.000	117.000	275.294	260.000	234.000	576.471	544.444	490.000	1211.361	1088.889	980.000
	6	64-QAM	3/4		6	154.853	146.250	131.625	309.706	292.500	263.250	648.529	612.500	551.250	1297.059	1225.000	1102.500
	7	64-QAM	5/6		6	172.059	162.500	146.250	344.118	325.000	292.500	720.588	680.556	612.500	1441.176	1361.111	1225.000
	8	256-QAM	3/4		8	206.471	195.000	175.500	412.941	390.000	351.000	864.706	816.667	735.000	1729.412	1633.333	1470.000
	9	256-QAM	5/6		8	229.412	216.667	195.000	458.824	433.333	390.000	960.784	907.407	816.667	1921.569	1814.815	1633.333
	10	1024-QAM	3/4		10	258.088	243.750	219.375	516.176	487.500	438.750	1080.882	1020.833	918.750	2161.765	2041.667	1837.500
	11	1024-QAM	5/6		10	286.765	270.833	243.750	573.529	541.667	487.500	1200.980	1134.259	1020.833	2401.961	2268.519	2041.667

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
3	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	25.809	24.375	21.938	51.618	48.750	43.875	108.088	102.083	91.875	216.176	204.167	183.750
	1	QPSK	1/2		2	51.618	48.750	43.875	103.235	97.500	87.750	216.176	204.167	183.750	432.353	408.333	367.500
	2	QPSK	3/4		2	77.426	73.125	65.813	154.853	146.250	131.625	324.265	306.250	275.625	648.529	612.500	551.250
	3	16-QAM	1/2		4	103.235	97.500	87.750	206.471	195.000	175.500	432.353	408.333	367.500	864.706	816.667	735.000
	4	16-QAM	3/4		4	154.853	146.250	131.625	309.706	292.500	263.250	648.529	612.500	551.250	1297.059	1225.000	1102.500
	5	64-QAM	2/3		6	206.471	195.000	175.500	412.941	390.000	351.000	864.706	816.667	735.000	1806.982	1633.333	1470.000
	6	64-QAM	3/4		6	232.279	219.375	197.438	464.559	438.750	394.875	972.794	918.750	826.875	1945.588	1837.500	1653.750
	7	64-QAM	5/6		6	258.088	243.750	219.375	516.176	487.500	438.750	1080.882	1020.833	918.750	2161.765	2041.667	1837.500
	8	256-QAM	3/4		8	309.706	292.500	263.250	619.412	585.000	526.500	1297.059	1225.000	1102.500	2594.118	2450.000	2205.000
	9	256-QAM	5/6		8	344.118	325.000	292.500	688.235	650.000	585.000	1441.176	1361.111	1225.000	2882.353	2722.222	2450.000
	10	1024-QAM	3/4		10	387.132	365.625	329.063	774.265	731.250	658.125	1621.324	1531.250	1378.125	3242.647	3062.500	2756.250
	11	1024-QAM	5/6		10	430.147	406.250	365.625	860.294	812.500	731.250	1801.471	1701.389	1531.250	3602.941	3402.778	3062.500

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
4	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	34.412	32.500	29.250	68.824	65.000	58.500	144.118	136.111	122.500	288.235	272.222	245.000
	1	QPSK	1/2		2	68.824	65.000	58.500	137.647	130.000	117.000	288.235	272.222	245.000	576.471	544.444	490.000
	2	QPSK	3/4		2	103.235	97.500	87.750	206.471	195.000	175.500	432.353	408.333	367.500	864.706	816.667	735.000
	3	16-QAM	1/2		4	137.647	130.000	117.000	275.294	260.000	234.000	576.471	544.444	490.000	1152.941	1088.889	980.000
	4	16-QAM	3/4		4	206.471	195.000	175.500	412.941	390.000	351.000	864.706	816.667	735.000	1729.412	1633.333	1470.000
	5	64-QAM	2/3		6	275.294	260.000	234.000	550.588	520.000	468.000	1152.941	1088.889	980.000	2396.045	2177.778	1960.000
	6	64-QAM	3/4		6	309.706	292.500	263.250	619.412	585.000	526.500	1297.059	1225.000	1102.500	2594.118	2450.000	2205.000
	7	64-QAM	5/6		6	344.118	325.000	292.500	688.235	650.000	585.000	1441.176	1361.111	1225.000	2882.353	2722.222	2450.000
	8	256-QAM	3/4		8	412.941	390.000	351.000	825.882	780.000	702.000	1729.412	1633.333	1470.000	3458.824	3266.667	2940.000
	9	256-QAM	5/6		8	458.824	433.333	390.000	917.647	866.667	780.000	1921.569	1814.815	1633.333	3843.137	3629.630	3266.667
	10	1024-QAM	3/4		10	516.176	487.500	438.750	1032.353	975.000	877.500	2161.765	2041.667	1837.500	4323.529	4083.333	3675.000
	11	1024-QAM	5/6		10	573.529	541.667	487.500	1147.059	1083.333	975.000	2401.961	2268.519	2041.667	4803.922	4537.037	4083.333

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
5	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	43.015	40.625	36.563	86.029	81.250	73.125	180.147	170.139	153.125	360.294	340.278	306.250
	1	QPSK	1/2		2	86.029	81.250	73.125	172.059	162.500	146.250	360.294	340.278	306.250	720.588	680.556	612.500
	2	QPSK	3/4		2	129.044	121.875	109.688	258.088	243.750	219.375	540.441	510.417	459.375	1080.882	1020.833	918.750
	3	16-QAM	1/2		4	172.059	162.500	146.250	344.118	325.000	292.500	720.588	680.556	612.500	1441.176	1361.111	1225.000
	4	16-QAM	3/4		4	258.088	243.750	219.375	516.176	487.500	438.750	1080.882	1020.833	918.750	2161.765	2041.667	1837.500
	5	64-QAM	2/3		6	344.118	325.000	292.500	688.235	650.000	585.000	1441.176	1361.111	1225.000	2978.657	2722.222	2450.000
	6	64-QAM	3/4		6	387.132	365.625	329.063	774.265	731.250	658.125	1621.324	1531.250	1378.125	3242.647	3062.500	2756.250
	7	64-QAM	5/6		6	430.147	406.250	365.625	860.294	812.500	731.250	1801.471	1701.389	1531.250	3602.941	3402.778	3062.500
	8	256-QAM	3/4		8	516.176	487.500	438.750	1032.353	975.000	877.500	2161.765	2041.667	1837.500	4323.529	4083.333	3675.000
	9	256-QAM	5/6		8	573.529	541.667	487.500	1147.059	1083.333	975.000	2401.961	2268.519	2041.667	4803.922	4537.037	4083.333
	10	1024-QAM	3/4		10	645.221	609.375	548.438	1290.441	1218.750	1096.875	2702.206	2552.083	2296.875	5404.412	5104.167	4593.750
	11	1024-QAM	5/6		10	716.912	677.083	609.375	1433.824	1354.167	1218.750	3002.451	2835.648	2552.083	6004.902	5671.296	5104.167

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
6	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	51.618	48.750	43.875	103.235	97.500	87.750	216.176	204.167	183.750	432.353	408.333	367.500
	1	QPSK	1/2		2	103.235	97.500	87.750	206.471	195.000	175.500	432.353	408.333	367.500	864.706	816.667	735.000
	2	QPSK	3/4		2	154.853	146.250	131.625	309.706	292.500	263.250	648.529	612.500	551.250	1297.059	1225.000	1102.500
	3	16-QAM	1/2		4	206.471	195.000	175.500	412.941	390.000	351.000	864.706	816.667	735.000	1729.412	1633.333	1470.000
	4	16-QAM	3/4		4	309.706	292.500	263.250	619.412	585.000	526.500	1297.059	1225.000	1102.500	2594.118	2450.000	2205.000
	5	64-QAM	2/3		6	412.941	390.000	351.000	825.882	780.000	702.000	1729.412	1633.333	1470.000	3554.923	3266.667	2940.000
	6	64-QAM	3/4		6	464.559	438.750	394.875	929.118	877.500	789.750	1945.588	1837.500	1653.750	3891.176	3675.000	3307.500
	7	64-QAM	5/6		6	516.176	487.500	438.750	1032.353	975.000	877.500	2161.765	2041.667	1837.500	4323.529	4083.333	3675.000
	8	256-QAM	3/4		8	619.412	585.000	526.500	1238.824	1170.000	1053.000	2594.118	2450.000	2205.000	5188.235	4900.000	4410.000
	9	256-QAM	5/6		8	688.235	650.000	585.000	1376.471	1300.000	1170.000	2882.353	2722.222	2450.000	5764.706	5444.444	4900.000
	10	1024-QAM	3/4		10	774.265	731.250	658.125	1548.529	1462.500	1316.250	3242.647	3062.500	2756.250	6485.294	6125.000	5512.500
	11	1024-QAM	5/6		10	860.294	812.500	731.250	1720.588	1625.000	1462.500	3602.941	3402.778	3062.500	7205.882	6805.556	6125.000

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
7	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	60.221	56.875	51.188	120.441	113.750	102.375	252.206	238.194	214.375	504.412	476.389	428.750
	1	QPSK	1/2		2	120.441	113.750	102.375	240.882	227.500	204.750	504.412	476.389	428.750	1008.824	952.778	857.500
	2	QPSK	3/4		2	180.662	170.625	153.563	361.324	341.250	307.125	756.618	714.583	643.125	1513.235	1429.167	1286.250
	3	16-QAM	1/2		4	240.882	227.500	204.750	481.765	455.000	409.500	1008.824	952.778	857.500	2017.647	1905.556	1715.000
	4	16-QAM	3/4		4	361.324	341.250	307.125	722.647	682.500	614.250	1513.235	1429.167	1286.250	3026.471	2858.333	2572.500
	5	64-QAM	2/3		6	481.765	455.000	409.500	963.529	910.000	819.000	2017.647	1905.556	1715.000	4124.947	3811.111	3430.000
	6	64-QAM	3/4		6	541.985	511.875	460.688	1083.971	1023.750	921.375	2269.853	2143.750	1929.375	4539.706	4287.500	3858.750
	7	64-QAM	5/6		6	602.206	568.750	511.875	1204.412	1137.500	1023.750	2522.059	2381.944	2143.750	5044.118	4763.889	4287.500
	8	256-QAM	3/4		8	722.647	682.500	614.250	1445.294	1365.000	1228.500	3026.471	2858.333	2572.500	6052.941	5716.667	5145.000
	9	256-QAM	5/6		8	802.941	758.333	682.500	1605.882	1516.667	1365.000	3362.745	3175.926	2858.333	6725.490	6351.852	5716.667
	10	1024-QAM	3/4		10	903.309	853.125	767.813	1806.618	1706.250	1535.625	3783.088	3572.917	3215.625	7566.176	7145.833	6431.250
	11	1024-QAM	5/6		10	1003.676	947.917	853.125	2007.353	1895.833	1706.250	4203.431	3969.907	3572.917	8406.863	7939.815	7145.833

802.11ax						HE20 (Mbps)			HE40 (Mbps)			HE80 (Mbps)			HE160 (Mbps)		
						符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)			符号间隔 GI (n S)		
空间流	MCS	调制方式	码率	有效子载波数量	子载波携带数据位	800	1600	3200	800	1600	3200	800	1600	3200	800	1600	3200
8	0	BPSK	1/2	HE20:234 HE40:468 HE80:980 HE160:1960	1	68.824	65.000	58.500	137.647	130.000	117.000	288.235	272.222	245.000	576.471	544.444	490.000
	1	QPSK	1/2		2	137.647	130.000	117.000	275.294	260.000	234.000	576.471	544.444	490.000	1152.941	1088.889	980.000
	2	QPSK	3/4		2	206.471	195.000	175.500	412.941	390.000	351.000	864.706	816.667	735.000	1729.412	1633.333	1470.000
	3	16-QAM	1/2		4	275.294	260.000	234.000	550.588	520.000	468.000	1152.941	1088.889	980.000	2305.882	2177.778	1960.000
	4	16-QAM	3/4		4	412.941	390.000	351.000	825.882	780.000	702.000	1729.412	1633.333	1470.000	3458.824	3266.667	2940.000
	5	64-QAM	2/3		6	550.588	520.000	468.000	1101.176	1040.000	936.000	2305.882	2177.778	1960.000	4688.830	4355.556	3920.000
	6	64-QAM	3/4		6	619.412	585.000	526.500	1238.824	1170.000	1053.000	2594.118	2450.000	2205.000	5188.235	4900.000	4410.000
	7	64-QAM	5/6		6	688.235	650.000	585.000	1376.471	1300.000	1170.000	2882.353	2722.222	2450.000	5764.706	5444.444	4900.000
	8	256-QAM	3/4		8	825.882	780.000	702.000	1651.765	1560.000	1404.000	3458.824	3266.667	2940.000	6917.647	6533.333	5880.000
	9	256-QAM	5/6		8	917.647	866.667	780.000	1835.294	1733.333	1560.000	3843.137	3629.630	3266.667	7686.275	7259.259	6533.333
	10	1024-QAM	3/4		10	1032.353	975.000	877.500	2064.706	1950.000	1755.000	4323.529	4083.333	3675.000	8647.059	8166.667	7350.000
	11	1024-QAM	5/6		10	1147.059	1083.333	975.000	2294.118	2166.667	1950.000	4803.922	4537.037	4083.333	9607.843	9074.074	8166.667

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
1	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	6.500	7.222	13.500	15.000	29.250	32.500	58.500	65.000
	1	QPSK	1/2		2	13.000	14.444	27.000	30.000	58.500	65.000	117.000	130.000
	2	QPSK	3/4		2	19.500	21.667	40.500	45.000	87.750	97.500	175.500	195.000
	3	16-QAM	1/2		4	26.000	28.889	54.000	60.000	117.000	130.000	234.000	260.000
	4	16-QAM	3/4		4	39.000	43.333	81.000	90.000	175.500	195.000	351.000	390.000
	5	64-QAM	2/3		6	52.000	57.778	108.000	120.000	234.000	260.000	468.000	520.000
	6	64-QAM	3/4		6	58.500	65.000	121.500	135.000	263.250	292.500	526.500	585.000
	7	64-QAM	5/6		6	65.000	72.222	135.000	150.000	292.500	325.000	585.000	650.000
	8	256-QAM	3/4		8	78.000	86.667	162.000	180.000	351.000	390.000	702.000	780.000
	9	256-QAM	5/6		8	——	——	180.000	200.000	390.000	433.333	780.000	866.667

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
2	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	13.000	14.444	27.000	30.000	58.500	65.000	117.000	130.000
	1	QPSK	1/2		2	26.000	28.889	54.000	60.000	117.000	130.000	234.000	260.000
	2	QPSK	3/4		2	39.000	43.333	81.000	90.000	175.500	195.000	351.000	390.000
	3	16-QAM	1/2		4	52.000	57.778	108.000	120.000	234.000	260.000	468.000	520.000
	4	16-QAM	3/4		4	78.000	86.667	162.000	180.000	351.000	390.000	702.000	780.000
	5	64-QAM	2/3		6	104.000	115.556	216.000	240.000	468.000	520.000	936.000	1040.000
	6	64-QAM	3/4		6	117.000	130.000	243.000	270.000	526.500	585.000	1053.000	1170.000
	7	64-QAM	5/6		6	130.000	144.444	270.000	300.000	585.000	650.000	1170.000	1300.000
	8	256-QAM	3/4		8	156.000	173.333	324.000	360.000	702.000	780.000	1404.000	1560.000
	9	256-QAM	5/6		8	——	——	360.000	400.000	780.000	866.667	1560.000	1733.333

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
3	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	19.500	21.667	40.500	45.000	87.750	97.500	175.500	195.000
	1	QPSK	1/2		2	39.000	43.333	81.000	90.000	175.500	195.000	351.000	390.000
	2	QPSK	3/4		2	58.500	65.000	121.500	135.000	263.250	292.500	526.500	585.000
	3	16-QAM	1/2		4	78.000	86.667	162.000	180.000	351.000	390.000	702.000	780.000
	4	16-QAM	3/4		4	117.000	130.000	243.000	270.000	526.500	585.000	1053.000	1170.000
	5	64-QAM	2/3		6	156.000	173.333	324.000	360.000	702.000	780.000	1404.000	1560.000
	6	64-QAM	3/4		6	175.500	195.000	364.500	405.000	789.750	877.500	1579.500	1755.000
	7	64-QAM	5/6		6	195.000	216.667	405.000	450.000	877.500	975.000	1755.000	1950.000
	8	256-QAM	3/4		8	234.000	260.000	486.000	540.000	1053.000	1170.000	2106.000	2340.000
	9	256-QAM	5/6		8	——	——	540.000	600.000	1170.000	1300.000	2340.000	2600.000

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
4	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	26.000	28.889	54.000	60.000	117.000	130.000	234.000	260.000
	1	QPSK	1/2		2	52.000	57.778	108.000	120.000	234.000	260.000	468.000	520.000
	2	QPSK	3/4		2	78.000	86.667	162.000	180.000	351.000	390.000	702.000	780.000
	3	16-QAM	1/2		4	104.000	115.556	216.000	240.000	468.000	520.000	936.000	1040.000
	4	16-QAM	3/4		4	156.000	173.333	324.000	360.000	702.000	780.000	1404.000	1560.000
	5	64-QAM	2/3		6	208.000	231.111	432.000	480.000	936.000	1040.000	1872.000	2080.000
	6	64-QAM	3/4		6	234.000	260.000	486.000	540.000	1053.000	1170.000	2106.000	2340.000
	7	64-QAM	5/6		6	260.000	288.889	540.000	600.000	1170.000	1300.000	2340.000	2600.000
	8	256-QAM	3/4		8	312.000	346.667	648.000	720.000	1404.000	1560.000	2808.000	3120.000
	9	256-QAM	5/6		8	——	——	720.000	800.000	1560.000	1733.333	3120.000	3466.667

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
5	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	32.500	36.111	67.500	75.000	146.250	162.500	292.500	325.000
	1	QPSK	1/2		2	65.000	72.222	135.000	150.000	292.500	325.000	585.000	650.000
	2	QPSK	3/4		2	97.500	108.333	202.500	225.000	438.750	487.500	877.500	975.000
	3	16-QAM	1/2		4	130.000	144.444	270.000	300.000	585.000	650.000	1170.000	1300.000
	4	16-QAM	3/4		4	195.000	216.667	405.000	450.000	877.500	975.000	1755.000	1950.000
	5	64-QAM	2/3		6	260.000	288.889	540.000	600.000	1170.000	1300.000	2340.000	2600.000
	6	64-QAM	3/4		6	292.500	325.000	607.500	675.000	1316.250	1462.500	2632.500	2925.000
	7	64-QAM	5/6		6	325.000	361.111	675.000	750.000	1462.500	1625.000	2925.000	3250.000
	8	256-QAM	3/4		8	390.000	433.333	810.000	900.000	1755.000	1950.000	3510.000	3900.000
	9	256-QAM	5/6		8	——	——	900.000	1000.000	1950.000	2166.667	3900.000	4333.333

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
6	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	39.000	43.333	81.000	90.000	175.500	195.000	351.000	390.000
	1	QPSK	1/2		2	78.000	86.667	162.000	180.000	351.000	390.000	702.000	780.000
	2	QPSK	3/4		2	117.000	130.000	243.000	270.000	526.500	585.000	1053.000	1170.000
	3	16-QAM	1/2		4	156.000	173.333	324.000	360.000	702.000	780.000	1404.000	1560.000
	4	16-QAM	3/4		4	234.000	260.000	486.000	540.000	1053.000	1170.000	2106.000	2340.000
	5	64-QAM	2/3		6	312.000	346.667	648.000	720.000	1404.000	1560.000	2808.000	3120.000
	6	64-QAM	3/4		6	351.000	390.000	729.000	810.000	1579.500	1755.000	3159.000	3510.000
	7	64-QAM	5/6		6	390.000	433.333	810.000	900.000	1755.000	1950.000	3510.000	3900.000
	8	256-QAM	3/4		8	468.000	520.000	972.000	1080.000	2106.000	2340.000	4212.000	4680.000
	9	256-QAM	5/6		8	——	——	1080.000	1200.000	2340.000	2600.000	4680.000	5200.000

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
7	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	45.500	50.556	94.500	105.000	204.750	227.500	409.500	455.000
	1	QPSK	1/2		2	91.000	101.111	189.000	210.000	409.500	455.000	819.000	910.000
	2	QPSK	3/4		2	136.500	151.667	283.500	315.000	614.250	682.500	1228.500	1365.000
	3	16-QAM	1/2		4	182.000	202.222	378.000	420.000	819.000	910.000	1638.000	1820.000
	4	16-QAM	3/4		4	273.000	303.333	567.000	630.000	1228.500	1365.000	2457.000	2730.000
	5	64-QAM	2/3		6	364.000	404.444	756.000	840.000	1638.000	1820.000	3276.000	3640.000
	6	64-QAM	3/4		6	409.500	455.000	850.500	945.000	1842.750	2047.500	3685.500	4095.000
	7	64-QAM	5/6		6	455.000	505.556	945.000	1050.000	2047.500	2275.000	4095.000	4550.000
	8	256-QAM	3/4		8	546.000	606.667	1134.000	1260.000	2457.000	2730.000	4914.000	5460.000
	9	256-QAM	5/6		8	——	——	1260.000	1400.000	2730.000	3033.333	5460.000	6066.667

802.11ac						HT20 (Mbps)		HT40 (Mbps)		HT80 (Mbps)		HT160 (Mbps)	
						GI (nS)		GI (nS)		GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400	800	400	800	400
8	0	BPSK	1/2	HE20:52 HE40:108 HE80:234 HE160:468	1	52.000	57.778	108.000	120.000	234.000	260.000	468.000	520.000
	1	QPSK	1/2		2	104.000	115.556	216.000	240.000	468.000	520.000	936.000	1040.000
	2	QPSK	3/4		2	156.000	173.333	324.000	360.000	702.000	780.000	1404.000	1560.000
	3	16-QAM	1/2		4	208.000	231.111	432.000	480.000	936.000	1040.000	1872.000	2080.000
	4	16-QAM	3/4		4	312.000	346.667	648.000	720.000	1404.000	1560.000	2808.000	3120.000
	5	64-QAM	2/3		6	416.000	462.222	864.000	960.000	1872.000	2080.000	3744.000	4160.000
	6	64-QAM	3/4		6	468.000	520.000	972.000	1080.000	2106.000	2340.000	4212.000	4680.000
	7	64-QAM	5/6		6	520.000	577.778	1080.000	1200.000	2340.000	2600.000	4680.000	5200.000
	8	256-QAM	3/4		8	624.000	693.333	1296.000	1440.000	2808.000	3120.000	5616.000	6240.000
	9	256-QAM	5/6		8	——	——	1440.000	1600.000	3120.000	3466.667	6240.000	6933.333

802.11n						HT20 (Mbps)		HT40 (Mbps)	
						GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400
1	0	BPSK	1/2	HE20:52 HE40:108	1	6.500	7.222	13.500	15.000
	1	QPSK	1/2		2	13.000	14.444	27.000	30.000
	2	QPSK	3/4		2	19.500	21.667	40.500	45.000
	3	16-QAM	1/2		4	26.000	28.889	54.000	60.000
	4	16-QAM	3/4		4	39.000	43.333	81.000	90.000
	5	64-QAM	2/3		6	52.000	57.778	108.000	120.000
	6	64-QAM	3/4		6	58.500	65.000	121.500	135.000
	7	64-QAM	5/6		6	65.000	72.222	135.000	150.000

802.11n						HT20 (Mbps)		HT40 (Mbps)	
						GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400
2	0	BPSK	1/2	HE20:52 HE40:108	1	13.000	14.444	27.000	30.000
	1	QPSK	1/2		2	26.000	28.889	54.000	60.000
	2	QPSK	3/4		2	39.000	43.333	81.000	90.000
	3	16-QAM	1/2		4	52.000	57.778	108.000	120.000
	4	16-QAM	3/4		4	78.000	86.667	162.000	180.000
	5	64-QAM	2/3		6	104.000	115.556	216.000	240.000
	6	64-QAM	3/4		6	117.000	130.000	243.000	270.000
	7	64-QAM	5/6		6	130.000	144.444	270.000	300.000

802.11n						HT20 (Mbps)		HT40 (Mbps)	
						GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400
3	0	BPSK	1/2	HE20:52 HE40:108	1	19.500	21.667	40.500	45.000
	1	QPSK	1/2		2	39.000	43.333	81.000	90.000
	2	QPSK	3/4		2	58.500	65.000	121.500	135.000
	3	16-QAM	1/2		4	78.000	86.667	162.000	180.000
	4	16-QAM	3/4		4	117.000	130.000	243.000	270.000
	5	64-QAM	2/3		6	156.000	173.333	324.000	360.000
	6	64-QAM	3/4		6	175.500	195.000	364.500	405.000
	7	64-QAM	5/6		6	195.000	216.667	405.000	450.000

802.11n						HT20 (Mbps)		HT40 (Mbps)	
						GI (nS)		GI (nS)	
空间流	MCS	调制方式	码率	有效子载波数量	每个子载波携带数据位	800	400	800	400
4	0	BPSK	1/2	HE20:52 HE40:108	1	26.000	28.889	54.000	60.000
	1	QPSK	1/2		2	52.000	57.778	108.000	120.000
	2	QPSK	3/4		2	78.000	86.667	162.000	180.000
	3	16-QAM	1/2		4	104.000	115.556	216.000	240.000
	4	16-QAM	3/4		4	156.000	173.333	324.000	360.000
	5	64-QAM	2/3		6	208.000	231.111	432.000	480.000
	6	64-QAM	3/4		6	234.000	260.000	486.000	540.000
	7	64-QAM	5/6		6	260.000	288.889	540.000	600.000

802.11a/g					速率
					GI (nS)
空间流	调制方式	码率	有效子载波数量	每个子载波携带数据位	800
1	BPSK	1/2	48	1	6.000
	BPSK	3/4		1	9.000
	QPSK	1/2		2	12.000
	QPSK	3/4		2	18.000
	16-QAM	1/2		4	24.000
	16-QAM	3/4		4	36.000
	64-QAM	2/3		6	48.000
	64-QAM	3/4		6	54.000