Int 16/AH=02h

KEYBOARD - GET SHIFT FLAGS

```
AH = 02h
```

Return:
```
AL = shift flags (see #00582)
AH destroyed by many BIOSes
```

See Also: AH=12h - AH=22h - INT 17/AH=0Dh - INT 18/AH=02h

Bitfields for keyboard shift flags:

```
Bit(s)  Description     (Table 00582)
7      Insert active
6      CapsLock active
5      NumLock active
4      ScrollLock active
3      Alt key pressed (either Alt on 101/102-key keyboards)
2      Ctrl key pressed (either Ctrl on 101/102-key keyboards)
1      left shift key pressed
0      right shift key pressed
```

See Also: #00587 - #03743 - MEM 0040h:0017h - #M0010

Category: Bios - Int 16h - K

open in browser PRO version Are you a developer? Try out the HTML to PDF API pdfcrowd.com

Rate My Photo

Computer Tyme Web Hosting
Good Reliable Hosting - Flat Pricing Structure

open in browser PRO version Are you a developer? Try out the HTML to PDF API pdfcrowd.com