CHASSIS	CUSTOM I/O (CARD-BASED)	ANALOG INPUTS	DIGITAL INPUTS	AEC INPUTS	ANALOG OUTPUTS	DIGITAL OUTPUTS	TELEPHONE CONNECTION	VoIP CONNECTION	CONFIGURED VIA	LCD DISPLAY	LOGIC PROCESSING	ETHERNET	RS-232	GPIO	SIGNAL PROCESSING (MHz)	COBRANET	AVB	DANTE	SOUNDWEB LONDON DIGITAL AUDIO BUS
BLU-806	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6	800			✓	256 ch.
BLU-326	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6				✓	256 ch.
BLU-805	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6	800		✓		256 ch.
BLU-325	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6			✓		256 ch.
BLU-800	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6	800	✓			256 ch.
BLU-320	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6		✓			256 ch.
BLU-160	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6	800	✓			256 ch.
BLU-120	✓	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 16 *	≤ 4 *		SOFTWARE	✓	✓	✓	✓	12 X 6					256 ch.
BLU-103					8	8		1 (2 LINES)	SOFTWARE		✓	✓	✓	12 X 6	400				48 ch.
BLU-102		10			8	8	1		SOFTWARE		✓	✓	✓	12 X 6	400				48 ch.
BLU-101			12			8			SOFTWARE		✓	✓	✓	12 X 6	400				48 ch.
BLU-100		12				8			SOFTWARE		✓	✓	✓	12 X 6	400				48 ch.
BLU-50		4			4				SOFTWARE		✓	✓	✓	12 X 6	400				48 ch.
BLU-BIB		8							DIP SWITCH										256 ch.
BLU-BOB1					8				DIP SWITCH										256 ch.
BLU-BOB2					8				DIP SWITCH										256 ch.
BLU-80	✓	≤ 16 *	≤ 16 *		≤ 16 *	≤ 16 *			SOFTWARE	✓	✓	✓	✓	12 X 6	200		✓		
BLU-32	✓	≤ 16 *	≤ 16 *		≤ 16 *	≤ 16 *			SOFTWARE	✓	✓	✓	✓	12 X 6			✓		
BLU-16	✓	≤ 16 *	≤ 16 *		≤ 16 *	≤ 16 *			SOFTWARE	✓	✓	✓	✓	12 X 6	200	✓			
BLU-GPX									SOFTWARE	✓	✓	✓	✓	36 X 23					
BLU-DAN									SOFTWARE		✓	✓	✓					✓	256 ch.

Chassis: BLU-50, BLU-BIB, BLU-BOB1, BLU-DAN are HALF-RACK; all others 19".

*16 total inputs/outputs (4 cards) allowed per device