@25

Intro

Get site device list

Copy Url Copy

GET /openapi/v1/{omadacId}/sites/{siteId}/devices

produces application/x-www-form-urlencoded **consumes** ["*/*"]

Note

Get site device list.

The interface requires one of the permissions:
Site Device Manager View Only
MSP Device Manager View Only

Params

name	description	in	require	type	schema
omadacId	Omada ID	path	true	string	
siteId	Site ID	path	true	string	
page	Start page number. Start from 1.	query	true	integer(int32)	
pageSize	Number of entries per page. It should be within the range of 1~1000.	query	true	integer(int32)	
sorts.name	Sort parameter may be one of asc or desc. Optional parameter. If it is not carried, it means it is not sorted by this field. When there are more than one, the first one takes effect	query	false	string	
sorts.status	Sort parameter may be one of asc or desc. Optional parameter. If it is not carried, it means it is not sorted by this field. When there are more than one, the first one takes effect	query	false	string	
sorts.ip	Sort parameter may be one of asc or desc. Optional parameter. If it is not carried, it means it is not sorted by this field. When there are more than one, the first one takes effect	query	false	string	
searchKey	Fuzzy query parameters, support field name,mac,ip	query	false	string	
filters.tag	Filter query parameters, support field tag name	query	false	string	

Response Params

name	description	type	schema
errorCode		integer(int32)	integer(int32)
msg		string	
- result		GridVODeviceInfo	GridVODeviceInfo
totalRows	Total rows of all items.	integer(int64)	
currentPage	Current page number.	integer(int32)	
currentSize	Number of entries per page.	integer(int32)	
- data		array	DeviceInfo
mac	Device MAC	string	
name	Device name	string	
type	Device type	string	
subtype	Switch subtype should be a value as follows: smart: Non-Agile Series Switch; es: Agile Series Switch	string	
deviceSeriesType	Device series type: 0 means basic, 1 means pro.	integer(int32)	
model	Device model name with version	string	
modelName	Device model name	string	
ip	Device IP	string	
ipv6	Device IPv6 list	array	string
uptime	Device uptime	string	
status	Device status should be a value as follows: 0: Disconnected; 1: Connected; 2: Pending; 3: Heartbeat Missed; 4: Isolated	integer(int32)	
detailStatus	Status of device,status should be a value as follows: 0:Disconnected,1:Disconnected(Migrating),10:Provisioning,11:Configuring,12:Upgrading,13:Rebooting,14:Connected;15:Connected(Wireless),16:Connected(Migrating),17:Connected(Wireless,Migrating),20:Pending,21:Pending(Wireless),22:Adopting,23:Adopting(Wireless),24:Adopt Failed,25:Adopt Failed(Wireless),26:Managed By Others,27:Managed By Others(Wireless),30:Heartbeat Missed,31:Heartbeat Missed(Wireless),32:Heartbeat Missed(Migrating),33:Heartbeat Missed(Wireless,Migrating),40:Isolated,41:Isolated(Migrating),50:Slice Configuring	integer(int32)	
modelVersion	Model version of device,for example:3.0	string	
lastSeen	Device lastSeen	integer(int64)	
cpuUtil	Device cpuUtil	integer(int32)	

memUtil	Device memUtil	integer(int32)
sn	Device serial number	string
licenseStatus	Device license status (Only for cloud base) should be a value as follows: 0: unActive; 1: Unbind; 2: Expired; 3: active	integer(int32)
tagName	Device tag name	string
uplinkDeviceMac	Uplink device mac	string
uplinkDeviceName	Uplink device name	string
uplinkDevicePort	Uplink device port	string
linkSpeed	Device uplink port linkSpeed, linkSpeed should be a value as follows: 0: Auto; 1: 10M; 2: 100M; 3: 1000M; 4: 2500M; 5: 10G; 6: 5G; 7: 25G, 8: 100G.	integer(int32)
duplex	Device uplink port duplex mode, duplex should be a value as follows: 0: Auto; 1: Half; 2: Full.	integer(int32)

switchConsistent	Whether the device can be adopted by the site.	boolean
publicIp	Device public IP	string
firmwareVersion	The device firmware version.	string
compatible	The compatible type of device.	integer(int32)
active	Indicates whether the device is activated.	boolean
inWhiteList	Whether the device is in white list.	boolean
supportAfc	Whether the device supports AFC.	boolean

Response Example


```
{
    "errorCode": 0,
    "msg": "",
    "result": {
        "totalRows": 0,
        "currentPage": 0,
        "currentSize": 0,
        "data": [
            {
                "mac": "",
                "name": "",
```

```
                "type": "",
                "subtype": "",
                "deviceSeriesType": 0,
                "model": "",
                "modelName": "",
                "ip": "",
                "ipv6": [],
                "uptime": "",
                "status": 0,
                "detailStatus": 0,
                "modelVersion": "",
                "lastSeen": 0,
                "cpuUtil": 0,
                "memUtil": 0,
                "sn": "",
                "licenseStatus": 0,
                "tagName": "",
                "uplinkDeviceMac": "",
                "uplinkDeviceName": "",
                "uplinkDevicePort": "",
                "linkSpeed": 0,
                "duplex": 0,
                "switchConsistent": true,
                "publicIp": "",
                "firmwareVersion": "",
                "compatible": 0,
                "active": true,
                "inWhiteList": true,
                "supportAfc": true
            }
        ]
    }
}
```