

REP 105 SPATIAL TRANSFORM TREE & COVARIANCE PROPAGATION

Decoupling Continuous Dead Reckoning from Discontinuous Global Localization Across Embodied Coordinate Frames

COORDINATE FRAME KINEMATIC HIERARCHY

SE(3) RIGID TRANSFORMS & DRIFT

earth Earth-Centered Geodetic Frame (ECEF / UTM / WGS-84) GLOBAL PLANETARY

Static planetary origin for GNSS / RTK constellations and geospatial coordinates

$T_{\text{earth_to_map}}$ (Fixed Datum)

map World-Fixed Metric Map Reference Frame GLOBAL CONSISTENT

Characteristics: Non-drifting global frame. Long-term accuracy bounded by map survey.

Update Properties: Low rate (1–10 Hz); **Discontinuous step-jumps allowed** on relocalization.

$T_{\text{map_to_odom}}(t)$ [Discontinuous Step Jumps on Loop Closure]

odom Locally Smooth Odometry Reference Frame STRICTLY CONTINUOUS

Characteristics: Dead reckoning (wheels + IMU + VO). Continuous & differentiable (C^1/C^2).

Drift Behavior: High rate (50–200 Hz); **Continuous drift:** $\Sigma_{\text{drift}}(t) \propto Q_{\text{rw}} \cdot \sqrt{t}$ without step jumps.

$T_{\text{odom_to_body}}(t)$ [High-Rate Continuous Kinematic Pose]

base_link Robot Physical Center / Chassis Origin (body) PHYSICAL CHASSIS

Kinematic Anchor: Center of mass / drive axle midpoint. Swept volume origin.

Consumers: Motor torque & velocity controllers consume $\text{odom} \rightarrow \text{base_link}$ directly.

camera_optical

Z-forward / X-right / Y-down

$T_{\text{body_cam}}$ [Σ_{ext}]

lidar_link

Laser emitter / range center

$T_{\text{body_lidar}}$ [Σ_{ext}]

imu_link / radar

Specific force & Doppler array

$T_{\text{body_imu}}$ [Σ_{ext}]

z_obs $\in$ F_sensor Physical Observation with Measurement Covariance $\Sigma_z \in \mathbb{R}^{3 \times 3}$

Full Spatial Mapping: $p_{\text{map}} = T_{\text{map}^{\text{odom}}} \cdot T_{\text{odom}^{\text{body}}} \cdot T_{\text{body}^{\text{sensor}}} \cdot z_{\text{obs}}$

1. THE DOWNSTREAM CONSUMER SPLIT (REP 105 INVARIANT)

A. Real-Time Tracking & Enforcement (50 Hz – 1 kHz)

Consumes: $T_{\text{odom_to_body}}(t)$ (Smooth Odometric Frame)

Systems Invariant: Must be **strictly C^1/C^2 continuous**. Any step jump creates infinite derivative jerk ($\ddot{x} \rightarrow \infty$), tripping motor inverter overcurrent.

B. Global Path Planning & Memory (1 Hz – 10 Hz)

Consumes: $T_{\text{map_to_body}} = T_{\text{map}^{\text{odom}}} \cdot T_{\text{odom}^{\text{body}}}$ (Global Frame)

Systems Invariant: Absorbs SLAM loop closures & GPS corrections in $T_{\text{map}^{\text{odom}}}$ via discrete jumps without shaking the tracking controller.

2. SPATIAL UNCERTAINTY COMPOSITION ACROSS FRAMES

First-Order Spatial Covariance Chain:

$$\Sigma_{\text{map}} \approx J_{\text{odom}} \cdot \Sigma_{\text{drift}} \cdot J_{\text{odom}}^T + R_{\text{body}} \cdot \Sigma_{\text{ext}} \cdot R_{\text{body}}^T + R_{\text{tot}} \cdot \Sigma_z \cdot R_{\text{tot}}^T$$

• **Extrinsic Mounting Drift (Σ_{ext}):** Thermal baseline expansion
 $\Delta b = \alpha \cdot L \cdot \Delta T$ (e.g., 25°C rise on 120mm Al bar = 0.069mm shift)

• **Long-Range Lever-Arm Error:** Angular mount drift θ yields lateral error $\delta x \approx z \cdot \theta$ (0.29° error at 10m range = **50.0 mm lateral bias**).

3. MANDATORY OBSERVATION HANDOFF CONTRACT

- **Capture Timestamp t_0 (Midpoint):** Eliminates velocity lag $\Delta x = v \cdot \tau$.
- **Reference Frame Key F_{sensor} :** Binds measurement to kinematic tree.
- **Uncertainty Envelope Σ_z :** Weights Kalman innovation; avoids chatter.

SAFETY RULE: Downstream enforcers reject any packet missing t_0 , F_{sensor} , or Σ_z