

Linux MPU (Untrusted System 1.5)

Real-Time MCU (Trusted System 1)

1. Proposes Action Chunk A_t

MPU generates $H = 16$ trajectory chunk A_t from observation O_t and predicted q_{expected} .

SPSC Queue

1. Normal 1 kHz Spline Execution

MCU consumes waypoints from lock-free SRAM queue, interpolates C^2 splines to PWM.

2. Open-Loop Inference Running

MPU computes next chunk A_{t+1} assuming previous chunk is executing smoothly.

VETO

2. Safety Veto Intervention

CBF detects obstacle ($h(x) < 0$). MCU **vetoes proposal**, overrides PWM, holds at q_{veto} .

3. State Divergence Detected

$\|q_{\text{actual}} - q_{\text{expected}}\| > \epsilon_{\text{diverge}}$. If MPU kept streaming, violent snap-back would occur!

VETO_ACTIVE

3. Sets Atomic VETO Bit

MCU sets VETO_ACTIVE = 1, writes true $q_{\text{actual}} = q_{\text{veto}}$ to SRAM, trips NMI interrupt.

4. Flush Queue & Re-Anchor

MPU flushes unexecuted waypoints, clears KV-cache, re-seeds planner from q_{actual} .

Chunk from q_{actual}

4. Resume Bumpless Motion

MCU clears VETO_ACTIVE, verifies C^2 boundary from q_{actual} , and resumes.

The Anti-Windup Guarantee: Without the asynchronous state re-anchoring handshake, a neural planner continues predicting from hallucinated positions while the robot is stopped, causing catastrophic snap-back when released. The shared SRAM mailbox protocol guarantees bumpless recovery.