

NZ Residential EV Charger — Detailed Electrician Guide

Mode 3 EVSE up to 32 A / ~7.4 kW single-phase and up to ~22 kW three-phase

Quick reference, location rules, compliance checklist, and worked examples

Document version: 1.0 | May 2026 | For registered electrical workers in New Zealand

Disclaimer: Educational field guide only — not legal advice. Mandatory requirements come from the Electricity (Safety) Regulations 2010 (ESR), cited AS/NZS 3000:2018 + Amendments 1–3 (legally cited from 13 November 2025 per SL 2025/225), and WorkSafe EV charging guidance. Purchase current standards; confirm distributor rules and CoC obligations before work.

Installer quick reference (tear-out summary)

Item	Requirement	Clause / source
Who may install	Registered electrical worker only; issue CoC	ESR; EWRB
Wiring Rules edition	AS/NZS 3000:2018 + Amd 1, 2, 3 (use now; mandatory for new work after 12 Nov 2026)	ESR Sch 2; WorkSafe Dec 2025
Domestic Mode 3/4	Dedicated final subcircuit; Type B 30 mA (all poles) OR Type A + IEC 62955 RDC-DD; direct fixed connection	7.9.3.3 (NZ)
Single-phase subcircuit	Minimum 32 A current-carrying capacity	7.9.3.3(a)
Three-phase subcircuit	7.9.3.3(a) states 32 A minimum for single-phase only — size 3-phase per EVSE rating + AS/NZS 3008; still apply 7.9.3.3(b)–(f)	7.9.3.3; 3.4
Height	Socket / EVSE cable outlet ≥ 800 mm above floor or ground	7.9.3.3(f)
Isolator	≥ 32 A, adjacent to charging facility	7.9.3.3(e); 2.3.2.2.1
Origin	From MEN switchboard (WorkSafe Jan 2026 addendum)	WorkSafe addendum §3
Mode 1	No socket-outlets for Mode 1 charging	7.9.2.2
Max demand	Assess full load; LMS often required for 32 A continuous	2.2.2; WorkSafe addendum
RCD test	Include DC leakage in function test where applicable	ESR mod. 8.3.10
Product	SDoC; IEC 61851; 230/400 V 50 Hz; RDC-DD if Type A path	ESR; WorkSafe

Contents

- 1. Regulatory stack
- 2. Power levels: single-phase vs three-phase

3. Mandatory NZ rules (Clause 7.9)

4. Protection: Type B vs Type A + RDC-DD

5. Where NOT to install (restricted zones)

6. Heights, clearances, and mounting

7. Recommended locations and examples

8. Cable, submain, and capacity

9. Testing, CoC, and records

10. Worked examples (5 scenarios)

11. Master installer checklist

12. References (fact-checked)

1. Regulatory stack

Instrument	Role for residential EVSE
Electricity Act 1992	Overarching electrical safety duties
Electricity (Safety) Regulations 2010	Installation work, product conformity, CoC
ESR Reg 59 + Schedule 2	Low-voltage installations must comply with Part 2 of cited AS/NZS 3000
AS/NZS 3000:2018 + Amd 1, 2, 3	Wiring Rules — Clause 7.9 (NZ only) for EV supplies
WorkSafe EV Charging Safety Guidelines (3rd ed.) + Jan 2026 Addendum	Regulator expectations (MEN board, load management, 32 A sockets)
AS/NZS 3008.1.1	Cable current capacity and voltage drop
IEC 61851-1 / -22	Mode 3 EVSE product safety
IEC 62955	RDC-DD (Type A alternative path)
SNZ PAS 6011:2023	Voluntary consumer/installer good practice (not cited in ESR)
Distributor Service & Installation Rules	Notification, capacity, controlled loads

Fact check: ESR citation update and transition dates verified against WorkSafe (19 Dec 2025) and EWRB guidance (Mar 2026).

2. Power levels: single-phase vs three-phase

Residential Mode 3 chargers in NZ are commonly supplied at 230 V single-phase or 400 V three-phase (line-to-line). The on-board charger limits what the vehicle accepts.

Supply	Typical installer setting	Approx. AC power	Notes
1-phase, 16 A	16 A circuit (Mode 2 path 7.9.3.2 uses 20 A min.)	~3.7 kW	Lower demand; not full 7.9.3.3 single-phase 32 A path
1-phase, 32 A	32 A dedicated subcircuit	~7.4 kW	7.9.3.3(a) minimum capacity for single-phase Mode 3/4

3-phase, 16 A / phase	Subcircuit sized per load (e.g. 20 A or 32 A per phase per design)	~11 kW	Common “fast AC” residential cap; verify EVSE SDoC
3-phase, 32 A / phase	Heavy demand; submain and mains upgrade often required	~22 kW	Maximum typical residential AC; full max-demand study essential

Important distinction: Clause 7.9.3.3(a) explicitly requires a minimum **32 A current-carrying capacity for single-phase** final subcircuits. It does not state the same numeric minimum for three-phase. Three-phase installations must still comply with 7.9.3.3(b)–(f), general cable sizing (Section 3 / AS/NZS 3008), maximum demand (2.2.2), and WorkSafe principles (equipment rated 230 V or 400 V as applicable).

WorkSafe’s Jan 2026 addendum notes that with load management, a 32 A (7.5 kW) charger can often satisfy daily driving without exceeding typical domestic peak demand — but this is **not** permission to skip design.

3. Mandatory NZ rules (Clause 7.9)

3.1 Clause 7.9.3.3 — Domestic Mode 3 and Mode 4 (verified text)

Ref	Requirement
(a)	Single-phase final subcircuits: minimum 32 A current-carrying capacity
(b)	Final subcircuit shall supply no other point in the wiring
(c)	Separate Type B RCD 30 mA, all live conductors (active and neutral); RCBO allowed
(c) exc.	Type A 30 mA + RDC-DD per IEC 62955 (≥ 6 mA DC detected)
(d)	Direct connection (fixed wiring) — not a general-purpose socket circuit
(e)	Isolator $\geq$ 32 A , adjacent to charging facility (Clause 2.3.2.2.1)
(f)	Socket-outlet or EVSE cable $\geq$ 800 mm above floor/ground
NOTE	If equipment > 20 A single-phase: consider mains upgrade and/or load management

Source: AS/NZS 3000:2018 Amendment 1, Clause 7.9 (NZ only) — electrotraining / Standards extract.

3.2 Other Clause 7.9 items

- **7.9.2.2:** Socket-outlets shall **not** be installed for Mode 1 charging.
- **7.9.3.1:** New domestic installations with defined integral garage **shall** provide a Mode 2 or Mode 3/4 charging facility.
- **7.9.3.2:** Mode 2 — 20 A minimum dedicated subcircuit; approved socket types; 800 mm height.
- **7.9.4:** Non-residential — Type B (or Type A + RDC-DD for Mode 3) on final subcircuit.

3.3 Transition (ESR 2025)

When	Rule
From 13 Nov 2025	May use AS/NZS 3000:2018 + Amd 1–3 for alterations/new work
New construction after 12 Nov 2026	Must use cited 2018 edition + amendments
Alteration started after 13 Nov 2025, unfinished by 12 Nov 2026	CoC completed portion; balance to new standard

4. Protection: Type B vs Type A + RDC-DD

Board	EVSE	Compliance path
2-pole Type B RCBO/RCD 30 mA	Any compliant Mode 3	7.9.3.3(c) — simplest
2-pole Type A RCBO/RCD 30 mA	Built-in IEC 62955 RDC-DD (verify SDoC)	7.9.3.3 exception
EVSE with integrated Type B	Per manufacturer	WorkSafe addendum: no duplicate Type B required at board, but subcircuit still needs RCD coverage per 3000 note

Protection must cover the **entire final subcircuit** from origin to EVSE (cable between board and charger included). Single-pole devices are not acceptable where all poles must be protected.

RCD function testing per modified **8.3.10** must include DC leakage checks where applicable (2025 ESR). This verifies installation — not factory certification of the RCD-DD.

5. Where NOT to install (restricted zones)

Use this table on site before mounting. “Mandatory” items derive from AS/NZS 3000 or ESR; “Do not” items are strong guidance from Appendix P, WorkSafe, or related clauses.

Zone / condition	EVSE / socket?	Basis
Bathroom, shower, or bath Zone 0, 1, or 2 (wet areas per Section 6, Table 6.1)	Not permitted (socket-outlets excluded; EVSE is fixed electrical equipment — treat as prohibited in wet zones unless full IP and clause-by-clause compliance)	AS/NZS 3000 Section 6
Within 0.6 m of bath edge, 0.4 m above basin, shower Zone 2 without IPX4	Not permitted for standard accessories	Figs 6.1, 6.8, 6.13
Swimming pool zones 0, 1, 2	Not permitted without pool-specific compliance	Section 6 pool rules
Mode 1 charging from general socket-outlets	Prohibited — no sockets for Mode 1	7.9.2.2 (NZ)
Below 800 mm above floor or ground	Non-compliant for 7.9.3.2 / 7.9.3.3	7.9.3.3(f)
Shared final subcircuit with other loads (lights, power, HWS)	Non-compliant for Mode 3/4 domestic	7.9.3.3(b)
Hazardous area (flammable gas/vapour/dust) without appropriate Ex equipment	Not permitted unless classified and designed to AS/NZS 60079 series	Section 7 hazardous installations
Immediately behind vehicle bumper path, tight driveway turn, or unprotected car wash bay	Do not install without mechanical protection (bollards, barriers)	Appendix P (informative)
Outdoor exposed weather without adequate IP (see Section 6)	Non-compliant if IP rating inadequate for location	4.1.3; Section 6
Inside cupboard storing chemicals, pool chlorine, or flammable liquids (poor ventilation + corrosion)	Do not install — manufacturer environment limits	Risk assessment; PAS 6011 good practice
Where cable could be damaged by doors, gates, or vehicle doors	Do not install without mechanical protection	Appendix H / P
Detached garage subboard without confirmed MEN / outbuilding supply compliance	Do not energise until design verified	7.2.4.5; WorkSafe addendum
32 A continuous load on unknown/old consumer mains	Do not install without max-demand and volt-drop study	EWRB; WorkSafe addendum

5.1 Mode 2 vs Mode 3 location note

Mode 2 (IC-CPD plugged into socket) is discouraged by WorkSafe for employer vehicles and high sustained current. Mode 3 fixed EVSE is the preferred residential solution for 32 A equivalent charging.

6. Heights, clearances, and mounting

Dimension	Requirement	Type
Minimum height to socket / EVSE cable outlet	≥ 800 mm above floor or ground	Mandatory (7.9.3.3(f), 7.9.3.2(c))
Recommended ergonomic height	900–1 200 mm AFFL to centre of unit (cable hang, accessibility)	Good practice / manufacturer
Maximum practical height	Typically ≤ 1 500 mm unless ladder access agreed (maintenance, cable weight)	Good practice
Side clearance from wall corner	Often ≥ 300 mm from corner (manufacturer); allows door swing and cable bend	Manufacturer install manual
Vehicle reach	Charging port reachable without trailing cable across traffic path	Site layout
Outdoor IP	IP44 minimum typical (Appendix P informative); IP55+ recommended exposed rain	Appendix P; Section 6
Impact	IK07+ where vehicle impact foreseeable (car parks, tight garages)	Appendix P (informative)
Isolator	Adjacent to charging facility; visible or identifiable from EVSE	7.9.3.3(e)

7. Recommended locations and examples

7.1 Suitable location checklist

- ☐ Within dedicated garage or carport bay — wall facing vehicle charge port
- ☐ Exterior wall near parking with weather-rated EVSE (IP55+ if exposed)
- ☐ Close to MEN main switchboard when practical (short subcircuit, clear max-demand path)
- ☐ Protected from vehicle contact (bollard, wheel stop, offset from door travel)
- ☐ Ventilation and manufacturer temperature range met
- ☐ Distributor notification completed if required

7.2 Worked location examples

Example A — Integral garage (new build): Mode 3 wallbox on rear wall of garage, 1 000 mm AFFL, 400 mm from internal corner, IP44 minimum (dust/moisture). Dedicated 32 A subcircuit from garage MSB (MEN). Type A RCBO + EVSE RDC-DD. Vehicle parks nose-in; Type 2 tethered cable reaches port without crossing pedestrian door path. *Complies: 7.9.3.3, 7.9.3.1 facility provided.*

Example B — Carport (no full enclosure): IP55 wallbox on house wall facing carport slab, 900 mm AFFL, conduit in wall from MSB 6 m away. Concrete-mounted bollard in front of charger. Load management set to 16 A evening peak. *Complies if IP, height, protection, and max demand documented.*

Example C — Driveway beside house: Three-phase 11 kW EVSE near meter/MSB; 3-pole Type B RCBO; subcircuit sized 20 A/phase (or per EVSE). Height 850 mm; cable route in UV-stable conduit above ground level. 7.9.3.3(b)–(f)

apply; 32 A single-phase rule (a) N/A to 3-phase.

Example D — What to refuse: Customer requests charger inside ensuite bathroom Zone 2, 600 mm from basin.

Decline — wet zone prohibition; propose external garage or exterior IP-rated location outside classified zones.

Example E — Detached garage: 25 m submain; EVSE on front wall. Confirm MEN/outbuilding rules before choosing garage DB as subcircuit origin. RCBO at origin of final subcircuit; 32 A isolator at EVSE; submain sized for 32 A + other garage loads. *See Section 10 Example 5.*

8. Cable, submain, and capacity

- Size cable per **AS/NZS 3008.1.1**: installation method, grouping, ambient, length.
- Voltage drop: typically $\leq 5\%$ from origin to load (AS/NZS 3000 / 3008).
- Single-phase 32 A: many installs use **6 mm²** Cu for short runs — always calculate; do not copy blindly.
- Three-phase: size each phase conductor for design current; neutral and earthing per 3000.
- **Maximum demand** (2.2.2): EV often at full rated current unless proven assessment, limitation, or LMS.
- Notify electricity distributor when required by network rules.

9. Testing, CoC, and records

1. Visual: location, height ≥ 800 mm, IP rating, labelling, dedicated circuit, isolator position.
2. Section 8: continuity, insulation, polarity, earth fault-loop impedance where required.
3. RCD operation including **DC leakage** per ESR-modified 8.3.10.
4. EVSE operational checks per manufacturer (earth monitoring, etc.).
5. Record energization date at switchboard (2018 edition).
6. Issue **Certificate of Compliance**; attach EVSE SDoC to CoC (EWRB good practice).

10. Worked installation examples

1. Single-phase 7.4 kW (32 A) — MSB in garage

63 A supply; 8 m run; Type 2 wallbox with RDC-DD; Type A 2-pole RCBO 32 A; 6 mm² V75; LMS throttles to 20 A when oven on. CoC references 7.9.3.3 and LMS settings.

2. Single-phase — old 50 A board, no spare capacity

Install 3.7 kW (16 A) on dedicated 20 A Mode 2 facility OR Mode 3 with LMS cap 12 A overnight OR supply upgrade. Do not fit 32 A hardware without assessment.

3. Three-phase 11 kW (16 A/phase)

400 V supply; 3-pole Type B 30 mA; cable 4 mm² per phase (verify); EVSE SDoC 400 V 50 Hz; max demand includes other 3-phase loads. 7.9.3.3(a) not applicable; (b)–(f) are.

4. Three-phase 22 kW (32 A/phase) — high-end home

Distributor upgrade likely; 10 mm² or larger per phase per 3008; main switch and submain upgraded; fixed load management mandatory; CoC documents full calculation.

5. Detached garage subboard

Verify MEN switchboard origin per WorkSafe; size 25 m submain; protection at final subcircuit origin; local isolator at EVSE; 8.3.9 outbuilding tests.

11. Master installer checklist

- ☐ Design to AS/NZS 3000:2018 + Amendments 1, 2, 3
- ☐ Site survey: restricted zones (Section 6 wet areas, impact, hazardous)
- ☐ Height ≥ 800 mm; IP/IK suitable for environment
- ☐ Dedicated final subcircuit; direct connection Mode 3

- ☐ Type B 2-pole 30 mA OR Type A + IEC 62955 RDC-DD (SDoC on file)
- ☐ Subcircuit from MEN switchboard (confirm detached garage case)
- ☐ Single-phase: 32 A min. subcircuit capacity; three-phase: sized per load + 7.9.3.3(b)–(f)
- ☐ 32 A isolator adjacent to EVSE
- ☐ Max demand / volt drop / cable size calculated (3008)
- ☐ Load management or upgrade if sustained 32 A exceeds capacity
- ☐ SDoC, IEC 61851, 230/400 V 50 Hz confirmed
- ☐ Section 8 tests + DC leakage; CoC issued
- ☐ Distributor notified if required

12. References (fact-checked May 2026)

1. AS/NZS 3000:2018 Amendment 1 — Clause 7.9 (NZ) — [electrotraining PDF](#)
2. Electricity (Safety) Regulations 2010 — [legislation.govt.nz](#)
3. Electricity (Safety) Amendment Regulations 2025 (SL 2025/225) — [legislation.govt.nz](#)
4. WorkSafe — ESR changes Dec 2025 — [worksafe.govt.nz](#)
5. WorkSafe — EV guidelines addendum Jan 2026 — [worksafe.govt.nz](#)
6. WorkSafe — EV charging safety guidelines (3rd ed.) — [worksafe.govt.nz](#)
7. EWRB — EV charging installations — [ewrb.govt.nz](#)
8. EWRB — Installation of EV charging equipment — [ewrb.govt.nz](#)
9. SNZ PAS 6011:2023 — Residential EV charging (voluntary) — [standards.govt.nz](#)
10. MBIE Build — Dedicated home charging units — [buildmagazine.org.nz PDF](#)

Companion summary: *NZ-Residential-EV-Charger-Installation-Guide.pdf* (shorter 32 A single-phase focus). Standards change — verify before use.