

Standard Operating Procedure
Remote Support Sessions

ShivTrix Admin v4.2 PRO

SOP | Version 1.0 | 11 October 2026

Document control

Item	Detail
Title	SOP - Remote support sessions with ShivTrix Admin
Version / date	1.0 / 11 October 2026
Applies to	ShivTrix Admin v4.2 PRO (web/PWA, Windows companion or EXE, Android app)
Owner	IT / Support lead (fill in)
Review cycle	Every 6 months, and after any security incident or major release
Related document	White Paper - Secure Browser-Native Remote Assistance & IT Diagnostics

1. Purpose and scope

This procedure defines how technicians and users run **remote support sessions** with ShivTrix Admin: preparing, starting, operating, ending and recording a session, what to do when something goes wrong, and how to accept the system into service. It covers screen viewing, laser pointer, Assisted Control (mouse, touch, keyboard) and running diagnostic tools on the host system. It does not cover unattended access (not supported in this version).

2. Roles and responsibilities

Role	Responsibilities
Host (user at the PC)	Starts the session, shares the entire screen, decides the access level, answers the Windows consent dialog, watches the session, and ends it when finished. Never leaves the PC unattended during Assisted Control.
Technician	Joins only with a link/ID received from the host, states the purpose, asks before taking control, keeps actions within the agreed task, and records the session.
Administrator	Deploys and updates the software, maintains signaling/TURN services, reviews incidents and keeps this SOP current.

3. Before you start

☐ Checklist	Host	Technician
Stable internet connection	☐	☐
Windows PC with ShivTrix Admin installed (EXE, or Python + companion.bat)	☐	-
Modern browser (Chrome or Edge recommended) - or the PWA / Android app	☐	☐
Identity confirmed by a second channel (phone call or message from a known number)	☐	☐
Sensitive windows closed (banking, private mail, password managers)	☐	-
Purpose and expected duration agreed	☐	☐

> **Security rule**
> Never share the room link or QR code in public places. The link is the key to the room. Use **Change ID** to create a new room for every session.

4. Installation and updates

Platform	Procedure
Windows - EXE	Run ShivTrixAdmin-Setup.exe (per-user install, no administrator rights) or copy ShivTrixAdmin.exe. If Windows SmartScreen warns about an unknown publisher: More info -> Run anyway (the binary is unsigned until your organisation signs it). Use the Administrator-mode shortcut only when a technician must control windows that run as administrator.
Windows - Python	Install Python 3 (tick "Add to PATH"), then double-click companion.bat. It installs psutil and opens http://127.0.0.1:9871.
PWA (any device)	Open the published address in Chrome/Edge -> menu -> Install app (Android: Install app / Add to Home screen).
Android app	Install ShivTrixAdmin-debug.apk (allow "Install unknown apps") or use the PWA. Android is for technicians; phones cannot host a screen share.
Updating	Web: upload new files, wait about a minute, hard-refresh (Ctrl+Shift+R). EXE/APK: install the new build over the old one. After an update, close and re-open the app; if the old screen persists unregister the service worker (DevTools -> Application -> Service Workers).

5. Procedure A - Host starts a session

1. Start the companion: open **ShivTrix Admin** (EXE) or double-click **companion.bat**. Keep the black console window open. Your browser opens http://127.0.0.1:9871.
2. Open **Remote Resolve** in the left menu. Check the pill reads "ONLINE" (relay connected). If it shows "CONNECTING TO PEERJS CLOUD..." wait up to a minute; see Troubleshooting.
3. Click **Capture & Share Screen**. In the browser picker choose the **Entire Screen** tab (not a window or tab) and press Share. A "sharing your screen" bar appears.
4. Send the technician the **Copy Link** (or the QR code, or the 8-character Room ID) through a private channel.
5. Leave the access level on **View Only** until the technician has introduced themselves. The Room Hub shows "n/10 peers connected"; each peer has a **Remove** button.
6. If you have several monitors, choose the one to be controlled in **Controlled display** (it should be the one you shared).

6. Procedure B - Technician joins

1. Open the link or scan the QR code. Or open ShivTrix Admin, choose **Remote Resolve**, type the Room ID and press **Join**.
2. Wait for the host screen to appear. The toolbar shows **VIEW ONLY**.
3. Introduce yourself to the host and state what you intend to do. Ask the host to raise the access level only when needed.
4. If the app says the room is full, the host already has 10 peers: ask the host to remove an idle one.

7. Procedure C - Assisted Control (mouse, touch, keyboard)

7.1 Host: approve control

1. Click **Assisted Control**. The status shows "APPROVE THE DIALOG ON THIS PC" and Windows opens **"ShivTrix Core - Remote Control Request"** (look in the taskbar if it is hidden).
2. Click **Yes** only if you started the session and recognise the technician. Click **No** otherwise. The status changes to **CONTROL ACTIVE**.
3. Stay at the PC and watch. To stop at any time click **View Only** or **Revoke Access**, or press **Stop Screen Share**. Closing the page also ends control within about 45 seconds.

7.2 Technician: operate the host

When the toolbar shows **CONTROLLING HOST** the picture is outlined in green and input is live.

Device	How
Mouse	Move, click, drag, right-click, middle-click and scroll over the picture
Keyboard	Click the picture once, then type. Shortcuts such as Ctrl+C / Ctrl+V work
Keys menu	Esc, Tab, Enter, Backspace, Del, Win, Alt+Tab, Alt+F4, Win+D, Win+R, Task Mgr, Ctrl+C/V/X/A/Z, arrows - for keys a browser cannot capture
Touch - Direct touch	Tap = click; long-press = right-click; one-finger drag = drag; two-finger drag = scroll; two-finger tap = right-click
Touch - Touchpad	Drag = move cursor; tap = click; two-finger tap = right-click; double-tap then drag = hold-and-drag; two fingers = scroll
Phone keyboard	Press **Keyboard** to open the on-screen keyboard; text, accents and Backspace are sent to the host

> **Limits to know**
>
> Ctrl+Alt+Del cannot be sent by any web app. Windows ignores input for windows running as administrator and for the sign-in / UAC secure screen unless the Administrator-mode build is used. Only one technician controls at a time; others see "busy".

8. Procedure D - Run diagnostics on the host

1. Technician: with Assisted Control active open **Advanced Power Toys**.
2. In the bar "Run tools on" choose **Host system**. The note changes to "All tools below run on the HOST system". The button stays disabled if control is not approved.
3. Run **Ping**, **Continuous Ping**, **Traceroute**, **NSLookup**, **Port Check** or **Network Adapters**. Results stream back live.
4. Typical sequence for "no internet": adapters (link and IP) -> ping the gateway -> ping 1.1.1.1 -> NSLookup a website -> Port Check 443.
5. Switch back to **This device** when finished. The host sees each request in its audit log as "[Remote Tool]".

9. Procedure E - End the session

1. Technician: tell the host you are finished and what was done.

2. Host: click **View Only** (this withdraws control and disarms the companion), then **Stop Screen Share**.
3. Host: use **Remove** on any remaining peers, and **Change ID** so the old link no longer works.
4. Both: complete the session record (section 12). Close the companion window if it is no longer needed.

10. Security rules

Do	Do not
Confirm the technician by phone before approving control	Approve a control request you did not expect
Share the Entire Screen and stay at the PC	Leave the PC unattended during Assisted Control
Use a new Room ID for every session	Post room links or QR codes in public chats
Remove unknown peers immediately	Type passwords the technician could read; use the host keyboard privately
Keep the software updated; use self-hosted signaling/TURN for sensitive work	Run the Administrator-mode build unless it is needed
Record every session	Use the product for anything beyond the agreed task

11. Troubleshooting

Symptom	Likely cause	Action
Pill stays on "CONNECTING TO PEERJS CLOUD..."	Internet or firewall blocks the signaling service (0.peerjs.com, port 443); free service busy	It retries automatically. Check the connection and firewall; try another network or mobile data; use Manual SDP Exchange; administrators can self-host a PeerServer
"Companion not running" when choosing Assisted Control	Companion/EXE not started, or the browser blocked access to this device	Start the companion and open the app. If the browser asks to allow access to devices on this network/computer, choose Allow
No Windows consent dialog	Dialog is behind other windows; or a refusal was given less than 8 seconds ago	Check the taskbar; wait 8 seconds and select Assisted Control again
Clicks land in the wrong place	A window or tab was shared instead of the Entire Screen, or the wrong display is selected	Stop sharing; share the Entire Screen; set Controlled display to the shared monitor
Some windows ignore the mouse/keyboard	They run as administrator or are the secure desktop	Use the Administrator-mode build, or ask the host to operate that step
Browser shortcuts (Ctrl+W, Win key) do not reach the host	Browsers keep some keys for themselves	Use the Keys menu
Touch does not scroll	One finger drags in Direct mode	Use two fingers to scroll; or switch to Touchpad
Black or frozen picture	Host minimised/protected content; poor connection	Re-share the Entire Screen; check latency in the toolbar; close bandwidth-heavy apps
"Room is full"	10 peers already connected	Host removes an idle peer
"Host system" button disabled	Control not approved, or not connected	Ask the host to enable Assisted Control and approve
Old version keeps appearing after an update	Cached files	Hard-refresh (Ctrl+Shift+R); unregister the service worker; reinstall the PWA
Port 9871 already in use	Companion already running	The second launch just opens the running one; close duplicates
SmartScreen "unknown publisher"	Binary is unsigned	More info -> Run anyway, or have the administrator sign the build

12. Incident handling and records

12.1 Suspected misuse

1. Host: immediately click **View Only** and **Stop Screen Share**; close the companion window if in doubt.
2. Remove the peer, press **Change ID**, and disconnect the PC from the network if the situation is serious.
3. Change passwords that may have been visible, and run your normal malware checks.
4. Save the Remote Audit log (screenshot or copy) with the date and time, then report to the Administrator.

12.2 Accidental approval

Click **View Only** or close the companion window. Control is withdrawn at once and all held keys and buttons are released. Report it so the room link can be treated as compromised.

12.3 Session record

Field	Entry
Date / start - end time	
Host (name, PC)	
Technician	
Reason / ticket number	
Access level used	View / Laser / Assisted Control
Tools run on host	
Outcome / follow-up	
Peers removed or incidents	

13. Pilot acceptance test

Run this once before production use, on real devices and networks (including a phone on mobile data to exercise the relay path). Initial each line.

#	Test	Expected result	Pass
1	Start companion; open app	App opens at 127.0.0.1:9871 with the ShivTrix logo and black theme	☐
2	Share Entire Screen; join from a second device	Picture appears; "1/10 peers connected"	☐
3	Laser pointer	Red dot appears on host screen at the tapped position	☐
4	Select Assisted Control; answer No	Status "YOU DENIED CONTROL"; technician cannot control	☐
5	Select Assisted Control; answer Yes	Status "CONTROL ACTIVE"; technician shows "CONTROLLING HOST"	☐
6	Mouse: move, click, drag, right-click, scroll	Host cursor follows and acts at the same position	☐
7	Keyboard: type text, Ctrl+C / Ctrl+V, Keys menu (Win, Alt+Tab)	Text and shortcuts arrive on the host	☐
8	Touch (phone): Direct touch and Touchpad gestures; on-screen keyboard	All gestures in section 7.2 work; accents and Backspace work	☐
9	Elevated window (e.g. Task Manager) with normal build	Ignores input (expected); works with Administrator-mode build	☐
10	Run tools on Host system: adapters, ping gateway, NSLookup, port check	Results show the host's network; host log shows [Remote Tool]	☐
11	Click View Only	Control stops immediately; tools target returns to This device	☐

#	Test	Expected result	Pass
12	Close the host page while control is active	Control stops within about 45 seconds	☐
13	Connect 11 technicians	The 11th is told the room is full	☐
14	Measure latency (toolbar) on the real network	Acceptable to the team (record the value)	☐

14. Quick reference card

Task	Where / how
Start (host)	ShivTrix Admin EXE or companion.bat -> Remote Resolve -> Capture & Share Screen (Entire Screen)
Invite	Copy Link / QR / Room ID. Change ID after every session
Allow control	Assisted Control -> click Yes on the Windows dialog
Stop control	View Only, Revoke Access, Stop Screen Share, or close the page
Right-click on touch	Long-press (Direct) or two-finger tap
Scroll on touch	Two-finger drag
Special keys	Keys menu in the toolbar
Tools on host	Advanced Power Toys -> Run tools on -> Host system
Maximum peers	10 (one controller at a time)