

LIBXSTREAM

LIBXSTREAM is an OpenCL-based accelerator backend library providing streams, events, and device memory management for GPU offloading. It implements the DBCSR ACC interface, making it a drop-in OpenCL backend for CP2K/DBCSR.

Targets OpenCL devices across vendors (Intel, AMD, NVIDIA). Depends on LIBXS for utility infrastructure.

Build

LIBXS must be a sibling directory (controlled by LIBXSROOT). An OpenCL SDK must be available.

Library -- build both LIBXS and LIBXSTREAM as separate libraries:

```
git clone https://github.com/hfp/libxs.git
git clone https://github.com/hfp/libxstream.git
```

```
cd libxs && make GNU=1 -j $(nproc)
cd ../libxstream && make GNU=1 -j $(nproc)
```

This produces `lib/libxstream.a` and `lib/libxstream.so`.

Header-only (explicit) -- include `libxstream_source.h` (no separate library needed for either LIBXSTREAM or LIBXS). Safe to include from multiple translation units:

```
#include <libxstream_source.h>
```

Header-only (implicit) -- compile with `-DLIBXSTREAM_SOURCE`. Any LIBXSTREAM or LIBXS public header then automatically includes the implementation. No special include order is required. `-DLIBXSTREAM_SOURCE` implies `-DLIBXS_SOURCE`; LIBXS can also be made header-only independently with `-DLIBXS_SOURCE`.

The library is compiled for SSE4.2 by default but dynamically dispatches to the best ISA available at runtime (up to AVX-512). Use `SSE=0` to compile natively for the build host.

Variable	Default	Description		GNU	0	Use GNU GCC-compatible compiler		DBG	0	Debug build		SYM	0	Include debug symbols (-g)		SSE	1	x86 baseline: 0=native, 1=SSE4.2 (portable)	
----------	---------	-------------	--	-----	---	---------------------------------	--	-----	---	-------------	--	-----	---	----------------------------	--	-----	---	---	--

pkg-config support: `lib/libxstream.pc`.

Installation

Install into a chosen prefix (LIBXS must be built first):

```
make GNU=1 -j $(nproc) install PREFIX=$HOME/libxstream
```

This installs headers, the static and shared libraries, and the header-only source tree under `PREFIX`.

Out-of-tree builds are also supported:

```
mkdir /tmp/libxstream-build && cd /tmp/libxstream-build
make -j $(nproc) -f /path/to/libxstream/Makefile
```

API

The public C API is declared in `include/libxstream.h`. All implementation details are sealed behind opaque types.

Devices

```
int libxstream_init(void);
int libxstream_finalize(void);
int libxstream_device_count(int* ndevices);
int libxstream_device_set_active(int device_id);
int libxstream_device_sync(void);
```

Streams

```
int libxstream_stream_create(libxstream_stream_t** stream_p,
                             const char* name, int priority);
int libxstream_stream_destroy(libxstream_stream_t* stream);
int libxstream_stream_sync(libxstream_stream_t* stream);
int libxstream_stream_wait_event(libxstream_stream_t* stream,
                                 libxstream_event_t* event);
```

Events

```
int libxstream_event_create(libxstream_event_t** event_p);
int libxstream_event_destroy(libxstream_event_t* event);
int libxstream_event_record(libxstream_event_t* event,
                            libxstream_stream_t* stream);
int libxstream_event_query(libxstream_event_t* event,
                           libxstream_bool_t* has_occurred);
int libxstream_event_sync(libxstream_event_t* event);
```

Memory

Device and host memory allocation, transfers (H2D, D2H, D2D), and initialization:

```
int libxstream_mem_allocate(void** dev_mem, size_t nbytes);
int libxstream_mem_deallocate(void* dev_mem);
int libxstream_mem_host_allocate(void** host_mem, size_t nbytes,
                                 libxstream_stream_t* stream);
int libxstream_mem_host_deallocate(void* host_mem,
                                   libxstream_stream_t* stream);
int libxstream_mem_copy_h2d(const void* host_mem, void* dev_mem,
                            size_t nbytes, libxstream_stream_t* stream);
int libxstream_mem_copy_d2h(const void* dev_mem, void* host_mem,
                            size_t nbytes, libxstream_stream_t* stream);
int libxstream_mem_copy_d2d(const void* src, void* dst,
                            size_t nbytes, libxstream_stream_t* stream);
int libxstream_mem_zero(void* dev_mem, size_t offset, size_t nbytes,
                        libxstream_stream_t* stream);
```

DBCSR Compatibility

The header `include/libxstream_dbcsr.h` provides the `c_dbcsr_acc_*` symbols expected by DBCSR, allowing LIBXSTREAM to serve as a drop-in accelerator backend.

CP2K Offload Interface

The header `include/libxstream_cp2k.h` implements CP2K's offload runtime interface -- the `offload_*` functions for general GPU operations (memory, streams, events, synchronization).

Samples

Each sample has its own Makefile under `samples/`:

```
cd samples/smm && make GNU=1
cd samples/ozaki && make GNU=1
```

SMM -- Small Matrix Multiplication

Implements the ACC LIBSMM interface for batched small matrix multiply and transpose on OpenCL devices. Includes an auto-tuning framework and pre-tuned parameter sets for A100, BMG, GH200, H100, Mi250, P100, PVC, and V100. See `samples/smm/README.md`.

Ozaki -- High-Precision GEMM

Ozaki scheme for high-precision GEMM emulation, fully offloaded to OpenCL. Two schemes (mantissa slicing and CRT) with automatic detection of Intel XMV matrix engines. See [samples/ozaki/README.md](#). The CPU-side GEMM wrapper is part of LIBXS Ozaki.

License

BSD 3-Clause

LIBXSTREAM Domains

CP2K Offload Interface

`include/libxstream_cp2k.h` implements CP2K's offload runtime interface — the hardware-abstraction layer that CP2K uses for GPU-accelerated operations beyond DBCSR (grid integration, PW operations, etc.). The original interface provides `static inline` wrappers for CUDA, HIP, and OpenCL; LIBXSTREAM replaces the OpenCL path with a dedicated translation unit (`src/libxstream_cp2k.c`) that routes directly through LIBXSTREAM's internal API.

Relationship to the DBCSR Interface

CP2K's code has two accelerator interfaces:

| Interface | Header | Purpose | |||| | **DBCSR ACC** | `libxstream_dbcsr.h` | Sparse matrix operations (DBCSR library) |
| **Offload Runtime** | `libxstream_cp2k.h` | General offload (memory, streams, events, synchronization) |

The DBCSR adapter (`src/libxstream_dbcsr.c`) uses opaque `void*` handles and translates to LIBXSTREAM's typed API. The offload runtime adapter does the same but uses CP2K's `offloadStream_t/offloadEvent_t` typedefs (also `void*`). Both share the underlying LIBXSTREAM implementation.

API

The header is self-contained (C99, no LIBXSTREAM headers required) and provides opaque handle types, an error-checking macro, and functions covering five domains.

```
typedef void* offloadStream_t;
typedef void* offloadEvent_t;
typedef int   offloadError_t;
```

```
#define offloadSuccess EXIT_SUCCESS
```

```
const char* offloadGetErrorName(offloadError_t error);
offloadError_t offloadGetLastError(void);
```

`offloadGetErrorName` maps error codes to OpenCL error strings via `libxstream_opengl_strerror`. `offloadGetLastError` consumes and clears the last recorded error.

The `OFFLOAD_CHECK` macro aborts on failure after printing the error name and source location:

```
OFFLOAD_CHECK(offloadMalloc(&ptr, nbytes));
```

```

void offloadStreamCreate(offloadStream_t* stream);
void offloadStreamDestroy(offloadStream_t stream);
void offloadStreamSynchronize(offloadStream_t stream);
void offloadStreamWaitEvent(offloadStream_t stream, offloadEvent_t event);

```

`offloadStreamCreate` creates a stream with default priority (`LIBXSTREAM_STREAM_DEFAULT`).

```

void offloadEventCreate(offloadEvent_t* event);
void offloadEventDestroy(offloadEvent_t event);
void offloadEventRecord(offloadEvent_t event, offloadStream_t stream);
void offloadEventSynchronize(offloadEvent_t event);
bool offloadEventQuery(offloadEvent_t event);

```

```

void offloadMalloc(void** ptr, size_t size);
void offloadFree(void* ptr);
void offloadMallocHost(void** ptr, size_t size);
void offloadFreeHost(void* ptr);

```

```

void offloadMemcpyAsyncHtoD(void* ptr_dev, const void* ptr_hst, size_t size, offloadStream_t stream);
void offloadMemcpyAsyncDtoH(void* ptr_hst, const void* ptr_dev, size_t size, offloadStream_t stream);
void offloadMemcpyAsyncDtoD(void* dst, const void* src, size_t size, offloadStream_t stream);
void offloadMemcpyHtoD(void* ptr_dev, const void* ptr_hst, size_t size);
void offloadMemcpyDtoH(void* ptr_hst, const void* ptr_dev, size_t size);
void offloadMemsetAsync(void* ptr, int val, size_t size, offloadStream_t stream);
void offloadMemset(void* ptr, int val, size_t size);

```

The synchronous variants (`offloadMemcpyHtoD`, `offloadMemcpyDtoH`, `offloadMemset`) pass a `NULL` stream. `offloadMemsetAsync` supports arbitrary fill values via `libxstream_opengl_memset`.

```

void offloadDeviceSynchronize(void);

```

```

void offloadMemcpyToSymbol(const void* symbol, const void* src, size_t count);
void offloadEnsureMallocHeapSize(size_t required_size);

```

These are CUDA-specific operations (constant-memory writes and device-heap sizing) that have no direct OpenCL equivalent. They are currently stubs guarded by assertions. CP2K's OpenCL path disables the GPU grid subsystem (`__NO_OFFLOAD_GRID`) that would call them.

See Also

- `LIBXSTREAM` API (`include/libxstream.h`) — the underlying OpenCL backend API
- DBCSR ACC Interface — the DBCSR adapter layer
- CP2K `offload_runtime.h` — upstream interface definition

DBCSR ACC Interface

`include/libxstream_dbcsr.h` implements the DBCSR ACC interface — the accelerator backend contract defined by the DBCSR sparse-matrix library used in CP2K. By providing this interface on top of LIBXSTREAM's OpenCL runtime, the library acts as a **drop-in OpenCL backend** for DBCSR: no changes to DBCSR or CP2K source code are required.

Purpose

DBCSR expects every accelerator backend to expose a flat C API with the `c_dbcsr_acc_*` prefix covering five domains:

Domain	Functions	Description		Initialization	<code>c_dbcsr_acc_init</code> , <code>c_dbcsr_acc_finalize</code>	Library setup and teardown
				Devices	<code>c_dbcsr_acc_get_ndevices</code> , <code>c_dbcsr_acc_set_active_device</code> , <code>c_dbcsr_acc_device_synchronize</code>	Device enumeration, selection, and synchronization
				Streams	<code>c_dbcsr_acc_stream_create</code> , <code>c_dbcsr_acc_stream_destroy</code> , <code>c_dbcsr_acc_stream_sync</code> , <code>c_dbcsr_acc_stream_wait_event</code> , <code>c_dbcsr_acc_stream_priority_range</code>	Asynchronous command queues
				Events	<code>c_dbcsr_acc_event_create</code> , <code>c_dbcsr_acc_event_destroy</code> , <code>c_dbcsr_acc_event_record</code> , <code>c_dbcsr_acc_event_query</code> , <code>c_dbcsr_acc_event_synchronize</code>	Fine-grained synchronization primitives
				Memory	<code>c_dbcsr_acc_dev_mem_allocate</code> , <code>c_dbcsr_acc_dev_mem_deallocate</code> , <code>c_dbcsr_acc_dev_mem_set_ptr</code> , <code>c_dbcsr_acc_host_mem_allocate</code> , <code>c_dbcsr_acc_host_mem_deallocate</code> , <code>c_dbcsr_acc_memcpy_h2d</code> , <code>c_dbcsr_acc_memcpy_d2h</code> , <code>c_dbcsr_acc_memcpy_d2d</code> , <code>c_dbcsr_acc_memset_zero</code> , <code>c_dbcsr_acc_dev_mem_info</code>	Device/host allocation, transfers (H2D, D2H, D2D), and memory queries

Every function delegates to the corresponding `libxstream_*` routine (e.g., `c_dbcsr_acc_stream_create` calls `libxstream_stream_create`), translating between DBCSR's opaque `void*` handles and LIBXSTREAM's typed `libxstream_stream_t` / `libxstream_event_t` pointers.

Profiling

The header also declares `c_dbcsr_timeset` and `c_dbcsr_timestop`, which are DBCSR's Fortran-side timer callbacks. When profiling is enabled (`LIBXSTREAM_PROFILE_DBCSR`), every ACC function is bracketed by these calls so that individual backend operations appear in DBCSR's timing report.

Utility Macros

Macro	Description		DBCSR_STRINGIFY(SYMBOL)	Stringifies a preprocessor token		DBCSR_CONCATENATE(A, B)	Concatenates two preprocessor tokens
			DBCSR_MARK_USED(x)	Silences unused-variable warnings			

See Also

- LIBXSTREAM API (`include/libxstream.h`) — the underlying OpenCL backend API
- DBCSR ACC specification — upstream interface definition

Visit LIBXS

OpenCL Backend

`include/libxstream_opengl.h` is the internal OpenCL layer that powers every public `libxstream_*` function. It owns the OpenCL platform/device/context lifecycle, memory management, kernel compilation, and error handling. Sample code and other LIBXSTREAM extensions (e.g., LIBSMM, Ozaki) include this header to access the OpenCL runtime directly.

Compile-Time Configuration

The header is guarded by `__OPENCL` (set automatically when `__OFFLOAD_OPENCL` is defined). Key compile-time knobs:

Macro	Default	Description
<code>LIBXSTREAM_MAXALIGN</code>	2 MB	Maximum alignment for device allocations
<code>LIBXSTREAM_BUFFERSIZE</code>	8 KB	Internal scratch-buffer size
<code>LIBXSTREAM_MAXSTRLEN</code>	48	Maximum string length for names
<code>LIBXSTREAM_MAXNDEVS</code>	64	Maximum number of OpenCL devices
<code>LIBXSTREAM_MAXNITEMS</code>	1024	Per-thread maximum item count
<code>LIBXSTREAM_USM</code>	SVM coarse-grain	Runtime Unified Shared Memory level (unset = OpenCL 2.0 SVM coarse-grain with non-USM fallback, 0 = off, 1 = Intel USM, 2 = OpenCL 2.0 SVM coarse-grain, 3 = OpenCL 2.0 SVM reported caps)

Data Types

`libxstream_opengl_config_t` The central singleton (`libxstream_opengl_config`) populated by `libxstream_init`. It holds:

- **Device table** — ordered array of discovered `cl_device_id` entries.
- **Active device** (`libxstream_opengl_device_t`) — context, default stream, error slot, OpenCL standard level, workgroup limits, memory caps, vendor flags, and optional USM function pointers.
- **Resource pools** — lock objects, streams, events, memory-pointer registrations, and a host-memory pool (`libxs_malloc_pool_t`).
- **Runtime switches** — verbosity, async mode, debug/dump level, profiling, execution hints, and workaround level.
- **Histograms** — optional transfer-time histograms for H2D, D2H, and D2D copies.

`libxstream_opengl_stream_t` / `libxstream_event_t` Thin wrappers around `cl_command_queue` and `cl_event` respectively. Streams additionally carry a thread-ID and optional priority.

`libxstream_opengl_info_memptr_t` Associates a `cl_mem` buffer object with its host-side pointer, used to translate between SVM/USM pointers and buffer-based memory.

`libxstream_opengl_atomic_fp_t` Enumerates floating-point atomics support: none, 32-bit, or 64-bit.

Error Handling Macros

Macro	Description
<code>CL_CHECK(RESULT, CALL)</code>	Execute an OpenCL call; on failure record the error code and human-readable name
<code>CL_ERROR_REPORT(NAME)</code>	Print the last error to stderr (if verbosity is enabled)
<code>CL_RETURN(RESULT, NAME)</code>	Return from function, reporting the error if non-zero

Key Functions

Device and Context | Function | Description | ||| | `libxstream_opengl_set_active_device` | Internal device activation (lock-aware) | | `libxstream_opengl_create_context` | Create an OpenCL context for a given device | | `libxstream_opengl_device_name` | Return device name, platform name, and UID | | `libxstream_opengl_device_level` | Query OpenCL version and device type | | `libxstream_opengl_device_vendor` | Confirm a device's vendor string | | `libxstream_opengl_device_ext` | Check for required OpenCL extensions | | `libxstream_opengl_device_uid` | Capture or compute a unique device identifier | | `libxstream_opengl_info_devmem` | Query free/total/local device memory |

Memory | Function | Description | ||| | `libxstream_opengl_info_devptr` | Look up a device-pointer registration (read-only) | | `libxstream_opengl_info_devptr_modify` | Look up a device-pointer registration (writable) | | `libxstream_opengl_info_hostptr` | Look up a host-pointer registration | | `libxstream_opengl_memset` | Fill device memory with an arbitrary byte pattern | | `libxstream_opengl_use_cmem` | Whether OpenCL constant-memory hints apply | | `libxstream_opengl_set_kernel_ptr` | Set a pointer kernel argument (USM-aware) |

Kernel Build | Function | Description | ||| | `libxstream_opengl_program` | Compile an OpenCL program from source, file, or binary | | `libxstream_opengl_kernel_query` | Extract a named kernel from a compiled program | | `libxstream_opengl_kernel` | Convenience: build + extract + release in one call | | `libxstream_opengl_kernel_flags` | Assemble combined build flags from params, options, and extras | | `libxstream_opengl_defines` | Merge user defines with internal definitions | | `libxstream_opengl_flags_atomics` | Generate compiler flags for FP-atomic extensions |

Streams, Events, and Timing | Function | Description | ||| | `libxstream_opengl_stream` | Find an existing stream for a thread-ID | | `libxstream_opengl_stream_default` | Return the device's default (internal) stream | | `libxstream_opengl_device_synchronize` | Per-thread device synchronization | | `libxstream_opengl_duration` | Measure elapsed seconds from a `cl_event` |

Error Utilities | Function | Description | ||| | `libxstream_opengl_strerror` | Map a `cl_int` error code to a string | | `libxstream_opengl_error_consume` | Clear and return the last recorded error |

See Also

- LIBXSTREAM API (`include/libxstream.h`) — public API built on top of this layer
- DBCSR ACC Interface — the DBCSR compatibility shim

Start Presentation

Appendix

Scripts

Helper scripts for building, inspecting, and maintaining LIBXSTREAM.

`tool_checkabi.sh`

Checks the ABI (Application Binary Interface) stability of the LIBXSTREAM shared library. The script uses `nm` to extract exported symbols from `lib/*.so` (or `lib/*.a` as fallback) and verifies that no previously published symbol has been removed or renamed compared to an earlier baseline (`.abi.txt`). Non-conforming symbol names cause an immediate error.

`scripts/tool_checkabi.sh`

NOTE: For full coverage the library must be built with `make STATIC=0 SYM=1` (or `DBG=1`) so that symbol information is present.

tool_getenvvars.sh

Scans the LIBXSTREAM source tree (`src/*.c`) for calls to `getenv` and prints a sorted, deduplicated list of every environment variable used at runtime, separated into LIBXSTREAM-specific (`LIBXSTREAM_*`) and other variables.

```
scripts/tool_getenvvars.sh
```

tool_opencl.sh

Converts OpenCL kernel files (`.cl`) — and optionally CSV parameter files — into a C header whose string literals can be compiled straight into the host binary. Include guards are stripped by default, and `#include` directives inside kernels are recursively resolved (inline).

```
scripts/tool_opencl.sh [options] infile.cl [infile2.cl ..] [infile.csv ..] outfile.h
```

Flag	Description		-k, --keep	Keep include guards (normally stripped)		-b N, --banner N	Copy the first N
							lines of the first .cl file as a banner
							-p DIR, --params DIR
							Directory containing CSV parameter files
							-c, -d, --debug,
							--comments
							Preserve comments in the generated source
							-v, --verbose
							Echo the command line

tool_version.sh

Derives the project version from Git tags and revision count. It can emit a plain version string, individual version components, or a complete C header with `#define` guards.

```
## full version string (branch-tag-patch)
```

```
scripts/tool_version.sh
```

```
## generate a C version header with a given symbol prefix
```

```
scripts/tool_version.sh LIBXSTREAM -1
```

```
## single component: 1=major, 2=minor, 3=update, 4+=patch
```

```
scripts/tool_version.sh LIBXSTREAM 2
```

Argument	Description		PREFIX	Symbol prefix used in the generated header (uppercased)		CMPNT	0 (default)
— version string; negative — C header; 1–3 — major/minor/update; >3 — patch count							
						SHIFT	Added to the patch
							count (default: 0)