

PHASE

1

x86 Assembly and the Boot Process

Learn enough assembly to read and write kernel glue code, and follow a PC from power-on to your first instruction

Overall progress toward Turk-OS 1.0 (this phase in red)

5% → 10%

🕒 Duration	2–3 weeks
★ Difficulty	★★★★☆ (3/5)
✂ You need	Phase 0 complete: cross toolchain, NASM, QEMU, GDB
🔑 You will have	A NASM “phrase book” in your journal, two assembly functions called from C, a 512-byte boot sector that prints a message, and a Multiboot kernel that both <code>qemu -kernel</code> and a GRUB ISO boot. You will prove it runs by finding <code>0xCAFEBAFE</code> in EAX.

1 Why this phase

You don’t need to become an assembly programmer to write an operating system. Turk-OS will contain a few hundred lines of assembly in total. But those lines do the things C cannot do: set up the very first stack, load descriptor tables, save and restore registers on an interrupt, switch between processes, and drop into user mode. If you can’t read them, you can’t debug them. And the only way to see what is really happening when the kernel crashes is to read the machine state in terms of registers, the stack and instructions.

The second half of the phase answers a question that feels like magic until you see it: how does a PC go from power-on to running *your* code? You will follow that path once by hand, writing a boot sector the BIOS loads directly, and then hand the job to GRUB, which is what Turk-OS will use from here on.

2 Concepts you need

2.1 Registers

The 32-bit x86 CPU has eight general-purpose registers. Each can be used as a whole (32 bits) or, for the first four, in smaller pieces that keep their names from the 8086 era (Figure 1). The remaining registers have fixed jobs, and several of them will get a phase of their own.




Figure 1: One register, four names. The same split applies to EBX, ECX and EDX.

Register(s)	Job	Where Turk-OS uses it
EAX, EBX, ECX, EDX	general purpose; EAX holds function return values	everywhere; EAX also carries the system call number (Phase 10)
ESI, EDI	general purpose; source and destination for string instructions	copying memory
ESP	stack pointer: address of the top of the stack	set up before any C runs (Phase 2); swapped on every context switch (Phase 8)
EBP	frame pointer: base of the current function's stack frame	walking the stack for backtraces (Phase 3)
EIP	instruction pointer: address of the next instruction	printed in every crash report
EFLAGS	condition flags (zero, carry, sign...) and the interrupt flag IF	cli/sti (Phase 4)
CS, DS, SS, ES, FS, GS	segment selectors	loaded from your own GDT (Phase 3)
CR0, CR2, CR3, CR4	control registers: protected mode, paging, fault address	paging (Phase 6)

2.2 A small instruction vocabulary

About twenty instructions cover nearly all the assembly in this project. NASM uses Intel syntax, where the destination comes first: `mov eax, 5` means `eax = 5`. Square brackets mean “the memory at this address”: `mov eax, [ebx+4]` reads four bytes starting at address `ebx+4`. When the size is ambiguous, say it: `mov dword [eax], 0`.

Instruction	Meaning	C equivalent
<code>mov dst, src</code>	copy a value	<code>dst = src;</code>
<code>add, sub, inc, dec</code>	arithmetic; results set EFLAGS	<code>a += b; a--;</code>
<code>and, or, xor, not, shl, shr</code>	bitwise operations and shifts	<code>a &= m; a <<= 2;</code>
<code>cmp a, b</code> then <code>je/jne/jl/jg/jge</code>	compare (a subtraction that only sets flags), then jump on the result	<code>if (a == b) goto L;</code>
<code>test a, a</code> then <code>jz</code>	bitwise AND that only sets flags; common zero check	<code>if (a == 0) goto L;</code>
<code>jmp label</code>	unconditional jump	<code>goto label;</code>
<code>push x, pop x</code>	<code>esp -= 4; [esp] = x</code> and the reverse	(the call stack)
<code>call f, ret</code>	push the return address and jump; pop it and jump back	<code>f(); return;</code>
<code>lea eax, [ebx+ecx*4]</code>	compute an address without reading memory	<code>eax = &ebx[ecx];</code>
<code>in al, dx, out dx, al</code>	read or write an I/O port	(device access, Phase 2)
<code>cli, sti, hlt</code>	disable or enable interrupts; halt until the next interrupt	(Phase 4)
<code>int n, iret</code>	software interrupt; return from an interrupt handler	(Phases 3 and 10)

2.3 The stack and the cdecl calling convention

C code compiled for 32-bit x86 follows the **cdecl** convention, and your assembly must follow it too whenever it calls C or is called from C. The caller pushes the arguments *right to left*, then executes `call`, which pushes the return address. Inside the callee, the first argument is therefore at `[esp+4]`, the second at `[esp+8]`, and so on. The return value goes in EAX. The callee may freely overwrite EAX, ECX and EDX (*caller-saved*), but must restore EBX, ESI, EDI, EBP and ESP before returning (*callee-saved*). The caller removes the arguments afterwards. Most functions start by saving EBP

and pointing it at their frame, so arguments sit at fixed offsets from EBP (Figure 2). Remember the callee-saved list: it is the reason the context switch in Phase 8 only saves four registers.




Figure 2: Stack frame inside `f(a, b)` after `push ebp; mov ebp, esp`. Higher addresses are at the top.

2.4 Real mode, protected mode, and how a PC boots

An x86 CPU wakes up in **real mode**, pretending to be a 1978 8086: 16-bit registers, addresses formed as `segment * 16 + offset`, one megabyte of reachable memory, no protection at all. The BIOS runs in real mode and so does the boot sector it loads. Operating systems switch to **protected mode** as soon as they can: 32-bit registers, a 4 GiB address space, privilege levels, and (later) paging. GRUB does this switch for you. Figure 3 shows the whole chain.




Figure 3: From power-on to the kernel. In Task 1.3 you replace the boot sector with your own; from Task 1.4 on GRUB (or QEMU) does it.

The boot sector is loaded low in memory because the first megabyte is crowded (Figure 4). Your kernel goes at 1 MiB, the first address above all of it.




Figure 4: The first megabyte of a PC's physical memory (not to scale). Addresses mark the bottom of each region.

The Multiboot contract

When GRUB or QEMU jumps to your kernel, the Multiboot specification (§3.2, *Machine state*) guarantees: EAX holds the magic value `0x2BADB002`; EBX holds the physical address of the *Multiboot information* structure (memory size, memory map, boot modules); the CPU is in 32-bit protected mode with paging off; the segment registers describe flat 4 GiB segments; interrupts are disabled. It also warns you of two things it does *not* give you. **ESP is undefined**, so you must set up your own stack before calling any C function (Phase 2). And **the GDTR may be invalid**, so you must not reload a segment register until you have installed your own GDT (Phase 3). To be recognised, the kernel must contain a 12-byte Multiboot header (magic `0x1BADB002`, flags, checksum) aligned to 4 bytes within the first 8 KiB of the file.

3 Reading plan

Priority	Book	What to read	Pages	Why now
REQUIRED	LOB	Ch. 2 <i>First Steps</i> : Booting, Hello Cafebabe (compiling, linking, GRUB, ISO, running)	12–17	The exact steps of Tasks 1.4–1.5.
REQUIRED	OSC	§2.9 <i>Building and Booting an Operating System</i>	92–95	Firmware, boot loaders and the boot sequence in general.
RECOMMENDED	MOS	§1.3.1 <i>Processors</i> ; §1.3.6 <i>Booting the Computer</i>	21–24, 34–35	Registers, pipelines and privileged mode; the BIOS boot path.
RECOMMENDED	OSDI	§2.6.6 <i>Bootstrapping MINIX 3</i>	156–160	How a real x86 OS gets from the boot sector to its kernel.
OPTIONAL	OSDI	§4.6.2 <i>Segmentation with Paging: The Intel Pentium</i>	415–420	First look at real versus protected mode addressing.
OPTIONAL	OSC	§9.6 <i>Example: Intel 32- and 64-bit Architectures</i>	379–383	Preview of the address translation you will build in Phase 6.

Three external references matter here. The **NASM manual**, chapters 2–3, covers syntax, labels and directives. The **Multiboot Specification 0.6.96**, section 3, defines the header and the machine state above. The **Intel SDM Volume 1**, chapter 3 (basic execution environment) and chapter 6 (procedure calls and the stack), is the authoritative version of Figure 2.

Real-system lens: how MINIX 3 does it

MINIX 3 does not use GRUB. It ships its own boot monitor, and **OSDI** §2.6.6 walks through what it does: load the kernel and the system processes into memory, switch to protected mode, and jump to the kernel's assembly entry point in `kernel/mpx386.s` (`06300`). Skim the first page of that file now. You won't understand all of it yet, but you will recognise the stack setup and the jump into C (`kernel/start.c` (`06900`)), which is exactly what you build in Phase 2.

4 Build it

Task 1.1 Learn to read compiler output

Continue the phrase book you started in Phase 0. For each C construct below, write the smallest function that uses it, compile with `i686-elf-gcc -O0 -S -masm=intel`, and annotate every instruction in your journal: a local variable, an if, a for loop, an array index, a struct field access, a pointer dereference, and a call with two arguments. Then compile the same code with `-O2` and notice what disappears.

✓ **Verify:** For the two-argument call, you can find the two push instructions, the `call`, and the `add esp, 8` that removes the arguments.

Task 1.2 Write assembly that C can call

Install the 32-bit C runtime on your host (`sudo dnf install glibc-devel.i686 libgcc.i686`) so you can build 32-bit Linux test programs. Then write two functions in NASM and call them from a C test with `assert`. The first is a leaf function that reads its arguments straight from ESP. The second builds a proper frame and uses a callee-saved register, so it must preserve it.

playground/funcs.s

```
; int max(int a, int b)      cdecl: a at [esp+4], b at [esp+8], result in eax
global max
global sum_array
section .text
max:
    mov     eax, [esp + 4]    ; eax = a
    mov     ecx, [esp + 8]    ; ecx = b    (ecx is caller-saved: free to use)
    cmp     eax, ecx
    jge     .done            ; if (a >= b) return a
    mov     eax, ecx         ; else return b
.done:
    ret

; int sum_array(const int *a, int n)
sum_array:
    push    ebp
    mov     ebp, esp         ; now [ebp+8] = a, [ebp+12] = n
    push    ebx              ; ebx is callee-saved: we must restore it
    mov     ebx, [ebp + 8]    ; ebx = a
    mov     ecx, [ebp + 12]   ; ecx = n
    xor     eax, eax         ; sum = 0
.loop:
    test    ecx, ecx
    jz      .done
    add     eax, [ebx]        ; sum += *a
    add     ebx, 4            ; a++    (an int is 4 bytes)
    dec     ecx
    jmp     .loop
.done:
    pop     ebx
    pop     ebp
    ret
```

terminal

```
nasm -f elf32 playground/funcs.s -o build/funcs.o
gcc -m32 -g playground/test_funcs.c build/funcs.o -o build/test_funcs && ./build/test_funcs
```

✓ **Verify:** The asserts pass. Then step through `sum_array` in GDB with `layout asm`, `stepi` and `info registers`, and watch ESP change on every push and pop.

Task 1.3 A boot sector that says hello

This is a detour, and a valuable one. You will write the first 512 bytes a PC executes from disk, in 16-bit real mode, using a BIOS service to print. Turk-OS itself will not use this code; GRUB replaces it in the next task.

playground/boot.s

```
bits 16                ; the CPU is in 16-bit real mode
org 0x7C00             ; the BIOS loads us at this address

start:
    xor ax, ax
    mov ds, ax        ; data segment = 0, so [si] means address si
    mov si, msg
.next:
    lodsb             ; al = [ds:si], then si = si + 1
    test al, al
    jz .halt          ; stop at the terminating zero
    mov ah, 0x0E       ; BIOS "teletype output" function
    int 0x10          ; ask the BIOS video service to print al
    jmp .next
.halt:
    cli
    hlt
    jmp .halt

msg: db "Merhaba, Turk-OS!", 0

times 510 - ($ - $$) db 0 ; pad with zeros up to byte 510
dw 0xAA55                 ; boot signature: bytes 0x55, 0xAA
```

terminal

```
nasm -f bin playground/boot.s -o build/boot.bin
ls -l build/boot.bin          # exactly 512 bytes
hexdump -C build/boot.bin | tail -n 2 # last bytes: 55 aa
qemu-system-i386 -drive format=raw,file=build/boot.bin
```

✓ **Verify:** QEMU prints your message after the SeaBIOS banner. Delete the `dw 0xAA55` line and confirm that the BIOS now refuses to boot the disk.

Task 1.4 Hello Cafebabe: a Multiboot kernel

Now the real Turk-OS entry point, following **LOB** chapter 2. The kernel only loads a recognisable value into EAX and spins, so you can prove your code is running by inspecting the register. Put the Multiboot header in its own section and have the linker place it first, which guarantees it lands in the first 8 KiB of the file.

boot/loader.s

```
global loader          ; the entry symbol, named in link.ld

MAGIC_NUMBER equ 0x1BADB002 ; tells GRUB this is a Multiboot kernel
FLAGS equ 0x0             ; no extra requests yet (Phase 2 changes this)
CHECKSUM equ -(MAGIC_NUMBER + FLAGS) ; magic + flags + checksum == 0

section .multiboot
align 4
    dd MAGIC_NUMBER
    dd FLAGS
    dd CHECKSUM
```

```

section .text
loader:
    mov eax, 0xCAFEBAE           ; a value you will recognise in a register dump
.loop:
    jmp .loop                    ; spin forever

```

link.ld

```

ENTRY(loader)                  /* where execution starts */
SECTIONS
{
    . = 0x00100000;             /* load everything from 1 MiB upwards */

    .text ALIGN(0x1000) : {
        *(.multiboot)           /* Multiboot header first */
        *(.text)
    }
    .rodata ALIGN(0x1000) : { *(.rodata*) }
    .data  ALIGN(0x1000) : { *(.data) }
    .bss   ALIGN(0x1000) : { *(COMMON) *(.bss) }
}

```

Build it with `nasm -f elf32 boot/loader.s -o build/loader.o`, then `i686-elf-ld -T link.ld -o build/kernel.elf build/loader.o`. Run it with QEMU's built-in Multiboot loader and open the monitor on your terminal:

terminal

```

grub2-file --is-x86-multiboot build/kernel.elf && echo "multiboot header OK"
qemu-system-i386 -kernel build/kernel.elf -monitor stdio
(qemu) info registers

```

✓ **Verify:** info registers shows EAX=cafebabe and an EIP just above 0x00100000.

Task 1.5 Boot through a real GRUB ISO

LOB builds its ISO with GRUB Legacy's stage2_eltorito. On a current Fedora system, GRUB 2 does the whole job with `grub2-mkrescue`. Create a GRUB configuration and let the tool assemble a bootable CD image around your kernel:

boot/grub.cfg

```

set timeout=0
set default=0

menuentry "Turk-OS" {
    multiboot /boot/kernel.elf
    boot
}

```

terminal

```

mkdir -p build/iso/boot/grub
cp build/kernel.elf build/iso/boot/
cp boot/grub.cfg build/iso/boot/grub/
grub2-mkrescue -o build/turkos.iso build/iso
qemu-system-i386 -cdrom build/turkos.iso -monitor stdio

```

✓ **Verify:** Same result as Task 1.4: EAX=cafebabe. You now boot exactly like a real PC would.

Task 1.6 A Makefile for the kernel

Typing these commands gets old fast. Write a Makefile with the targets `all`, `run`, `iso`, `debug` and `clean`. Remember that recipe lines must start with a real Tab character.

Makefile

```
AS := nasm
LD := i686-elf-ld
BUILD := build
OBJS := $(BUILD)/loader.o

all: $(BUILD)/kernel.elf

$(BUILD)/kernel.elf: $(OBJS) link.ld
    $(LD) -T link.ld -o $@ $(OBJS)

$(BUILD)/%.o: boot/%.s
    @mkdir -p $(BUILD)
    $(AS) -f elf32 $< -o $@

run: $(BUILD)/kernel.elf
    qemu-system-i386 -kernel $< -monitor stdio

iso: $(BUILD)/kernel.elf boot/grub.cfg
    mkdir -p $(BUILD)/iso/boot/grub
    cp $< $(BUILD)/iso/boot/kernel.elf
    cp boot/grub.cfg $(BUILD)/iso/boot/grub/
    grub2-mkrescue -o $(BUILD)/turkos.iso $(BUILD)/iso

debug: $(BUILD)/kernel.elf
    qemu-system-i386 -kernel $< -s -S &
    gdb $< -ex "target remote localhost:1234" -ex "break loader" -ex "continue"

clean:
    rm -rf $(BUILD)

.PHONY: all run iso debug clean
```

✓ **Verify:** `make clean` && `make run` rebuilds and boots from scratch.

Task 1.7 Your first kernel debugging session

Run `make debug`. QEMU starts frozen (`-s`) and waits for GDB on port 1234 (`-S`). GDB stops at `loader`. Try `info registers`, `stepi`, `x/4xw $esp` and `p/x $eax`, and use `layout asm` for a live disassembly view. You will use this workflow in every phase from now on, so practise it while the kernel is still two instructions long.

✓ **Verify:** After one `stepi`, `p/x $eax` prints `0xcafebabe`.

5 Testing and debugging

Symptom	Likely cause	What to do
QEMU or BIOS: “No bootable device” with your boot sector	File is not exactly 512 bytes, or the last two bytes are not <code>55 AA</code>	Check with <code>ls -l</code> and <code>hexdump -C</code> ; keep the times padding line.
Boot sector prints garbage	Missing <code>org 0x7C00</code> or bits 16, or DS not zero	All label addresses depend on <code>org</code> ; set DS before <code>lods b</code> .
GRUB: “no multiboot header found”	Header not in the first 8 KiB, not 4-byte aligned, or a bad checksum	Keep <code>*(.multiboot)</code> first in <code>.text</code> ; run <code>grub2-file --is-x86-multiboot</code> .

Symptom	Likely cause	What to do
QEMU -kernel: “Error loading uncompressed kernel without PVH ELF Note”	QEMU found no Multiboot header, or the ELF is 64-bit	Same checks; make sure you used <code>nasm -f elf32</code> and the <code>i686-elf</code> linker.
objdump output looks backwards	AT&T syntax (source first)	Use <code>objdump -d -M intel</code> to match NASM.
Your C test crashes after calling <code>sum_array</code>	A callee-saved register (EBX) was not restored, or the stack is unbalanced	Every push needs a matching pop before <code>ret</code> .

6 Milestone

🚩 Milestone: The kernel boots

- ☐ `max` and `sum_array` in NASM pass their C tests, and you stepped through them in GDB.
- ☐ Your boot sector prints “Merhaba, Turk-OS!” in QEMU and is exactly 512 bytes.
- ☐ `kernel.elf` boots with `make run` and with the GRUB ISO; `EAX=0xCAFEBAE` in both.
- ☐ `make debug` stops at loader and you can single-step.
- ☐ You can draw the `cdecl` stack frame for a two-argument call from memory.

? Self-check questions

1. Why is the boot sector loaded at `0x7C00`, and why must it end with `0x55 0xAA`?
2. What does the Multiboot checksum guarantee? Compute it for `FLAGS = 0x3`.
3. Right after `call f`, what is at `[esp]`? Inside `f`, after `push ebp; mov ebp, esp`, where is the first argument?
4. Which registers must a `cdecl` function preserve, and which may it destroy?
5. Why is the kernel linked at 1 MiB rather than at address 0?
6. What two things does the Multiboot contract explicitly *not* set up for you?
7. How does a real-mode address like `0x07C0:0x0000` map to a physical address?

7 Going further

Extend the boot sector: read a key with BIOS `int 0x16` and echo it, write a routine that prints a register in hex, or load a second sector from disk with `int 0x13`. That last one is the first step of a custom boot loader. It is a fun rabbit hole, but only a detour for this project, so set yourself a time limit. For deeper assembly practice, read the Intel SDM Volume 1 chapter on procedure calls, then write `memcpy` and `strlen` in NASM and test them against your C versions from Phase 0.

Next: **Phase 2 Getting to C: Screen, Serial and `kprintf`** →

 Books used in this plan

- LOB** Erik Helin, Adam Renberg. *The little book about OS development*, 2015. The hands-on x86 guide. Free at <https://littleosbook.github.io>.
- OSTEP** Remzi H. Arpaci-Dusseau, Andrea C. Arpaci-Dusseau. *Operating Systems: Three Easy Pieces*, v0.90, Arpaci-Dusseau Books, 2015. Main theory text. Free at <https://pages.cs.wisc.edu/~remzi/OSTEP/>.
- OSC** A. Silberschatz, P.B. Galvin, G. Gagne. *Operating System Concepts*, 10th ed., Wiley, 2018. Reference theory text.
- MOS** Andrew S. Tanenbaum, Herbert Bos. *Modern Operating Systems*, 4th ed., Pearson, 2015. Hardware, I/O, design, security.
- OSDI** Andrew S. Tanenbaum, Albert S. Woodhull. *Operating Systems: Design and Implementation*, 3rd ed., Pearson Prentice Hall, 2006. MINIX 3 with full source listing.

The books do not come with this plan. **LOB** and **OSTEP** are free online; buy or borrow the other three (the roadmap lists their ISBNs). Page numbers are the *printed* page numbers of these editions, not PDF page indices. With another edition, or with the free **OSTEP** chapters (each one starts at page 1), find the reading by its chapter and section numbers. MINIX source references like `kernel/proc.c (07400)` give the file and its starting line in **OSDI** Appendix B.