Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL MULTIMETER · TRUE-RMS, MANUAL RANGING

DM 321T

True-RMS · 3½-digit · manual ranging · hFE · capacitance · backlit

01 KEY SPECIFICATIONS

MEASUREMENT	True-RMS AC
DC VOLTAGE	Up to 1000 V
DC CURRENT	Up to 20 A
CAPACITANCE	6 nF – 20 mF, auto-ranging
DISPLAY	3½-digit, backlit
TESTS	Continuity, diode, hFE



DM 321T · DIGITAL MULTIMETER

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION & ACCURACY
DISPLAY & RANGING	
Measurement Type	True-RMS
Ranging	Manual
Display	3½-digit with backlight
VOLTAGE & CURRENT	
DC Voltage	200 mV / 2 V / 20 V / 200 V / 1000 V | ±(0.5% rdg + 3 digits)
AC Voltage (True-RMS)	2 V / 20 V / 200 V / 750 V | ±(0.8% rdg + 5 digits) @ 40 Hz–1 kHz
DC Current	200 µA / 2 mA / 20 mA / 200 mA / 20 A | ±(0.8% rdg + 10 digits)
AC Current (True-RMS)	20 mA / 200 mA / 20 A | ±(1.0% rdg + 15 digits) @ 40 Hz–400 Hz
OTHER MEASUREMENTS	
Resistance	200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ | ±(0.8% rdg + 3 digits)
Capacitance (Auto Ranging)	6 nF – 20 mF | ±(3.5% rdg + 20 digits)
Transistor Test	hFE
Additional Functions	Continuity, diode test, REL, AC mains frequency test (750 V range), data hold, backlight, auto power-off, low battery
GENERAL	
Power Supply	2 × AA battery
Dimensions (L×W×H)	178 × 86 × 52 mm
Weight	Approx. 360 g (incl. battery & holster)
Warranty	12 months against manufacturing defects only

03 APPLICATIONS

- General electrical maintenance and panel testing
- Accurate AC measurement on non-sinusoidal loads (True-RMS)
- Basic electronic troubleshooting incl. transistor testing

04 WHAT'S IN THE BOX

✓ Test leads ✓ User manual ✓ Battery ✓ Holster

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DM 321T Product Catalogue.