Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

CIE/666 Range Guide

Hand-driven, seasoned wooden body

Every standard voltage and range

Hand-driven generator, rated voltages 100, 250, 500, 1,000, 2,500, 5,000 and 10,000 V. Pick the rated test voltage first, then the insulation resistance range that suits your equipment. Each combination below is a standard build.

7	32	10,000 V
RATED VOLTAGES	STANDARD RANGES	TOP VOLTAGE



CIE/666 · ILLUSTRATIVE IMAGE

01 STANDARD RANGES BY RATED VOLTAGE

RATED VOLTAGE	INSULATION RESISTANCE RANGE (MΩ)
100 V	0–20 · 0–50 · 0–100
250 V	0–50 · 0–100 · 0–250
500 V	0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000
1,000 V	0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000
2,500 V	0–1,000 · 0–2,000 · 0–2,500 · 0–5,000 · 0–10,000 · 0–20,000 · 50–50,000
5,000 V	0–5,000 · 0–10,000 · 0–20,000 · 50–50,000 · 100–100,000
10,000 V	0–10,000 · 0–20,000 · 50–50,000 · 100–100,000

Ranges shown are the standard builds. Any other range can be manufactured against specific requirements.

02 COMBINING VOLTAGES AND RANGES

Dual voltage & dual insulation range

One instrument, two rated voltages, each with its own insulation range, selected by a switch. The selected range must lie within the rated resistance listed for that voltage (voltage to measurable insulation range ratio up to 1:2 only; for any other ratio, enquire). Not available for the 10,000 V instrument.

Single voltage, dual insulation range

One rated voltage with two insulation ranges. Both ranges must lie within the rated resistance listed for that voltage. Not available for the 10,000 V instrument.

Continuity range (500 V and 1,000 V only)

Built in as an optional extra on single-voltage, single-range instruments, or on dual-voltage, dual-range instruments.

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

CIE/666 Range Guide

Multi-range options, specifications, accessories and ordering

03 MULTIRANGE SERIES: CIE/666/MR

SERIES	RATED VOLTAGE / INSULATION RANGE (MΩ)	CONTINUITY
MR-1	1,000 V / 0–2,000 500 V / 0–1,000 250 V / 0–500	0–20 kΩ
MR-2	1,000 V / 0–200 500 V / 0–100 250 V / 0–50	0–1 kΩ
MR-3	500 V / 0–1,000 250 V / 0–500 100 V / 0–200	0–5 kΩ
MR-4	500 V / 0–100 250 V / 0–50 100 V / 0–20	0–1 kΩ

SERIES	RATED VOLTAGE / INSULATION RANGE (MΩ)	CONTINUITY
MR-5	2,500 V / 0–5,000 1,000 V / 0–2,000 500 V / 0–1,000	0–20 kΩ
MR-6	2,500 V / 0–1,000 1,000 V / 0–200 500 V / 0–100	0–1 kΩ
MR-7	5,000 V / 0–20,000 2,500 V / 0–10,000	0–20 kΩ
MR-8	5,000 V / 0–5,000 2,500 V / 0–2,500	0–5 kΩ

Multirange instruments carry a range selector switch, so one instrument covers every voltage and range listed in its series. Anti-parallax mirror scale is not provided on triple-range and above instruments. Other configurations are available on request.

04 KEY SPECIFICATIONS

Body	Seasoned wooden with sunmica finish; detachable lid, carrying handle, and lock
Generator Type	Hand-driven, silent generator with centrifugal governor (clutch)
Scale Length	100 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m. or more
Response Time	3 seconds
Weight	4.1 kg (approx.)
Dimensions (L×W×H)	265 × 165 × 185 mm (approx.)

05 OPTIONAL ACCESSORIES (AT EXTRA COST)

- Carrying case
- Testing leads, 1 m or 2 m (up to 1,000 V)
- H.V. testing leads, 2 m (general / special)

06 HOW TO ORDER

To order, quote the **model**, the **rated voltage** and the **insulation range**, for example `CIE/666, 500 V / 0–2,000 MΩ`. Any range not listed can be manufactured against specific requirements - enquire.

cieinstruments@gmail.com · +91 98300 91260 · +91 98300 92117

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.