



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

DIGITAL MULTIMETER · 3½-DIGIT, MANUAL RANGING

DM 235

3½-digit manual-ranging DMM - DC/AC voltage, DC/AC current, resistance, capacitance, continuity, diode, hFE. 9V battery.

1000V DC / 750V AC

VOLTAGE RANGE

Up to 20A

DC/AC CURRENT

200 MΩ

MAX RESISTANCE

Digital Multimeter

A 3½-digit manual-ranging digital multimeter for general electrical and electronic measurement - DC voltage to 1000V, AC voltage to 750V, DC/AC current to 20A, resistance to 200MΩ, and capacitance, plus continuity, diode, and transistor (hFE) test.

- **DC voltage to 1000V** - AC voltage to 750V
- **DC/AC current to 20A** - manual ranging
- **Resistance to 200MΩ** - plus capacitance measurement
- **hFE transistor test** - built-in socket, PNP/NPN
- **Continuity & diode test** - audible buzzer
- **Auto power-off** - 9V battery, low-batt indication

Manufactured in India since 1963 - trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors.



DM 235 · DIGITAL MULTIMETER

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Display	3½-digit
Ranging	Manual
DC Voltage	200 mV / 2 V / 20 V / 200 V / 1000 V
AC Voltage	2 V / 20 V / 200 V / 750 V
DC Current	2 mA / 20 mA / 200 mA / 20 A
AC Current	20 mA / 200 mA / 20 A
Resistance	200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ / 200MΩ
Capacitance	2000 pF / 20 nF / 200 nF / 2 μF / 20 μF
Additional Functions	Continuity, diode, transistor (hFE) test, auto power-off, low battery
Power Supply	9 V battery
Dimensions (L×W×H)	170 × 87 × 35 mm
Weight	Approx. 210 g (incl. battery)
Warranty	12 months against manufacturing defects

02 Typical Applications

- General electrical measurement
- Panel testing
- Workshop and field use

03 What's in the Box

- ✓ Test leads
- ✓ User manual
- ✓ Battery
- ✓ Holster

Cambridge Instruments & Engg. Co.

cieinstruments.in

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DM 235 Product Catalogue.