



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

PHASE SEQUENCE INDICATOR · ABS MOULDED

PSI-2

ABS moulded 96×96 mm phase sequence indicator, 50–500 V AC
(position-dependent). Supplied with case and leads.

50–500V AC

POSITION-DEPENDENT RANGE

25–60Hz

OPERATING FREQUENCY

Not for Circuit Use

NOT TO BE LEFT IN CIRCUIT

Phase Sequence Indicator

A phase sequence indicator in a compact ABS moulded enclosure, suitable for panel mounting or handheld use - verifies the phase rotation (RYB or RBY) of a 3-phase AC supply before motors, generators, or other rotating equipment are energised. More compact than the disc-rotating PSI-1, preferred where a smaller form factor is needed.

- **Compact ABS body** - 96×96×45mm, panel or handheld use
- **50–500V AC** - range depends on mounting orientation
- **25–60Hz** - wide frequency range
- **30 seconds @ 500V rating** - 15VA burden
- **Not to be left in the circuit** - per manufacturer instruction

*Manufactured in India since 1963 - trusted by various State Electricity Boards,
Indian Railways, cement and metal industries, and other sectors.*



PSI-2 · PHASE SEQUENCE INDICATOR

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	ABS moulded
Dimensions	96 × 96 × 45 mm
Operating Voltage (Horizontal)	50–500 V AC
Operating Voltage (Vertical)	100–500 V AC
Frequency	25–60 Hz
Rating	30 seconds at 500 V
Burden	15 VA at 500 V
Important	Not to be left in the circuit
Accessories	Carrying case and test leads (supplied)
Warranty	12 months against manufacturing defects

02 Typical Applications

- 3-phase phase sequence check
- Switchboard commissioning
- Motor connection verification

03 What's in the Box

- ✓ Carrying case
- ✓ Test leads