Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

CIE/666/MR

Multirange · series MR-1 to MR-8 · up to 5000 V · built-in continuity range

MR-1 to MR-8
FULL SERIES, WOODEN BODY

Built-In
CONTINUITY RANGE, STANDARD

Up to 5000V
MR-7/MR-8 WIDEST COVERAGE

01 KEY SPECIFICATIONS

SERIES	MR-1 to MR-8
MAX. VOLTAGE	Up to 5000 V (MR-7 / MR-8)
CONTINUITY	Built-in, all series
GENERATOR	Hand-driven · no battery
BODY	Seasoned wood, sunmica finish



CIE/666/MR · INSULATION TESTER

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
Body	Seasoned wooden, sunmica finish
Generator Type	Hand-driven
Series Available	MR-1 to MR-8 (full range, incl. HV series MR-5–8)
Continuity Range	Built-in as standard on all MR series
Warranty	12 months against manufacturing defects

Any configuration apart from the standard MR series above can be built to order.

03 AVAILABLE SERIES - VOLTAGE, RANGE & CONTINUITY

SERIES	VOLTAGE & RESISTANCE RANGES	CONTINUITY RANGE
MR-1	1000V/0–2000MΩ · 500V/0–1000MΩ · 250V/0–500MΩ	0–20 KΩ
MR-2	1000V/0–200MΩ · 500V/0–100MΩ · 250V/0–50MΩ	0–1 KΩ
MR-3	500V/0–1000MΩ · 250V/0–500MΩ · 100V/0–200MΩ	0–5 KΩ
MR-4	500V/0–100MΩ · 250V/0–50MΩ · 100V/0–20MΩ	0–1 KΩ
MR-5	2500V/0–5000MΩ · 1000V/0–2000MΩ · 500V/0–1000MΩ	0–20 KΩ
MR-6	2500V/0–1000MΩ · 1000V/0–200MΩ · 500V/0–100MΩ	0–1 KΩ
MR-7	5000V/0–20000MΩ · 2500V/0–10000MΩ	0–20 KΩ
MR-8	5000V/0–5000MΩ · 2500V/0–2500MΩ	0–5 KΩ

04 APPLICATIONS

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

05 OPTIONAL ACCESSORIES

+ Carrying case
+ Test leads, 1m
+ H.V. test leads, 2m (general)
+ H.V. test leads, 2m (special)

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666/MR Product Catalogue.