Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

# CIE/666 Range Guide

Hand-driven, seasoned wooden body

## Every standard voltage and range

Hand-driven generator, rated voltages 100, 250, 500, 1,000, 2,500, 5,000 and 10,000 V. Pick the rated test voltage first, then the insulation resistance range that suits your equipment. Each combination below is a standard build.

| 7 | 32 | 100–10,000 |
|---|---|---|
| RATED VOLTAGES | STANDARD RANGES | VOLTS |



CIE/666 · ILLUSTRATIVE IMAGE

## 01 STANDARD RANGES BY RATED VOLTAGE

| RATED VOLTAGE | INSULATION RESISTANCE RANGE (MΩ) |
|---|---|
| 100 V | 0–20 · 0–50 · 0–100 |
| 250 V | 0–50 · 0–100 · 0–250 |
| 500 V | 0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000 |
| 1,000 V | 0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000 |
| 2,500 V | 0–1,000 · 0–2,000 · 0–2,500 · 0–5,000 · 0–10,000 · 0–20,000 · 50–50,000 |
| 5,000 V | 0–5,000 · 0–10,000 · 0–20,000 · 50–50,000 · 100–100,000 |
| 10,000 V | 0–10,000 · 0–20,000 · 50–50,000 · 100–100,000 |

*Ranges shown are the standard builds. Any other range can be manufactured against specific requirements.*

## 02 COMBINING VOLTAGES AND RANGES

### Dual voltage & dual insulation range

One instrument, two rated voltages, each with its own insulation range, selected by a switch. The selected range must lie within the rated resistance listed for that voltage (voltage to measurable insulation range ratio up to 1:2 only; for any other ratio, enquire). Not available for the 10,000 V instrument.

### Single voltage, dual insulation range

One rated voltage with two insulation ranges. Both ranges must lie within the rated resistance listed for that voltage. Not available for the 10,000 V instrument.

### Continuity range (500 V and 1,000 V only)

Built in as an optional extra on single-voltage, single-range instruments, or on dual-voltage, dual-range instruments.



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

# CIE/666 Range Guide

Multi-range options, specifications, accessories and ordering

## 03 MULTIRANGE SERIES: CIE/666/MR

| SERIES | RATED VOLTAGE / INSULATION RANGE (MΩ) | CONTINUITY |
|---|---|---|
| MR-1 | 1,000 V / 0–2,000<br>500 V / 0–1,000<br>250 V / 0–500 | 0–20 kΩ |
| MR-2 | 1,000 V / 0–200<br>500 V / 0–100<br>250 V / 0–50 | 0–1 kΩ |
| MR-3 | 500 V / 0–1,000<br>250 V / 0–500<br>100 V / 0–200 | 0–5 kΩ |
| MR-4 | 500 V / 0–100<br>250 V / 0–50<br>100 V / 0–20 | 0–1 kΩ |

| SERIES | RATED VOLTAGE / INSULATION RANGE (MΩ) | CONTINUITY |
|---|---|---|
| MR-5 | 2,500 V / 0–5,000<br>1,000 V / 0–2,000<br>500 V / 0–1,000 | 0–20 kΩ |
| MR-6 | 2,500 V / 0–1,000<br>1,000 V / 0–200<br>500 V / 0–100 | 0–1 kΩ |
| MR-7 | 5,000 V / 0–20,000<br>2,500 V / 0–10,000 | 0–20 kΩ |
| MR-8 | 5,000 V / 0–5,000<br>2,500 V / 0–2,500 | 0–5 kΩ |

*Multirange instruments carry a range selector switch, so one instrument covers every voltage and range listed in its series. Anti-parallax mirror scale is not provided on triple-range and above instruments. Any other configuration can be built to order.*

## 04 KEY SPECIFICATIONS

| | |
|---|---|
| Body | Seasoned wooden with sunmica finish; detachable lid, carrying handle, and lock |
| Generator Type | Hand-driven, silent generator with centrifugal governor (clutch) |
| Scale Length | 100 mm (approx.) |
| Accuracy | Conforms to IS: 2992-1987 |
| Rotation Speed | 160 r.p.m. or more |
| Response Time | 3 seconds |
| Weight | 4.1 kg (approx.) |
| Dimensions (L×W×H) | 265 × 165 × 185 mm (approx.) |

## 05 OPTIONAL ACCESSORIES (AT EXTRA COST)

- Carrying case
- Testing leads, 1 m or 2 m (up to 1,000 V)
- H.V. testing leads, 2 m (general / special)

## 06 HOW TO ORDER

To order, quote the **model**, the **rated voltage** and the **insulation range**, for example `CIE/666, 500 V / 0–2,000 MΩ`. Any range not listed can be manufactured against specific requirements - enquire.

**cieinstruments@gmail.com · +91 98300 91260 · +91 98300 92117**



All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.