Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

DIGITAL MULTIMETER · 3½-DIGIT, MANUAL RANGING

DM 235

3½-digit digital multimeter · manual ranging · capacitance · hFE · continuity

01 KEY FEATURES

- 3½-digit display
- Manual ranging
- Capacitance measurement
- hFE transistor test
- Continuity buzzer and diode test
- Auto power-off, low-battery indication



DM 235 · DIGITAL MULTIMETER

02 TECHNICAL SPECIFICATIONS

PARAMETER	SPECIFICATION
DISPLAY & RANGING	
Display	3½-digit LCD, maximum reading 1999
Ranging	Manual
VOLTAGE & CURRENT	
DC Voltage	200 mV / 2 V / 20 V / 200 V / 1000 V · ±(0.5% + 3) on 200 mV, ±(0.8% + 5) on 2-200 V, ±(1.0% + 5) on 1000 V
AC Voltage	2 V / 20 V / 200 V / 750 V · ±(1.0% + 5) on 2-20 V, ±(1.2% + 5) on 200-750 V · 40-400 Hz
DC Current	2 mA / 20 mA / 200 mA / 20 A · ±(1.8% + 2) on 2 mA, ±(2.0% + 2) on 20-200 mA, ±(2.0% + 10) on 20 A
AC Current	20 mA / 200 mA / 20 A · ±(2.0% + 3) on 20 mA, ±(2.0% + 5) on 200 mA, ±(2.5% + 10) on 20 A · 40-400 Hz
OTHER MEASUREMENTS	
Resistance	200Ω / 2KΩ / 20KΩ / 200KΩ / 2MΩ / 20MΩ / 200MΩ · ±(1.0% + 4) on 2KΩ-2MΩ
Capacitance	2000 pF / 20 nF / 200 nF / 2 µF / 20 µF · ±(4% + 5) · Cx socket
Additional Functions	Continuity buzzer (below approx. 30 ± 20 Ω), diode test, auto power-off after approx. 15 min, low battery indication
Transistor (hFE) Test	PNP and NPN, 0-1000
GENERAL	
Power Supply	9 V battery (6F22 / NEDA 1604 or equivalent)
Input Protection	1000 V DC / 750 V AC rms (voltage) · mA input F0.5 A / 250 V fast fuse, 20 A input unfused
Operating Temperature	0 °C to 40 °C, below 80% RH (indoor use)
Dimensions (L×W×H)	170 × 87 × 35 mm
Weight	Approx. 211 g
Warranty	12 months against manufacturing defects only

03 APPLICATIONS

- General electrical measurement
- Panel testing
- Workshop and field use

04 WHAT'S IN THE BOX

✓ Test leads ✓ User manual ✓ Battery ✓ Holster

ISO 9001:2015 CERTIFIED

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - DM 235 Product Catalogue.