Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN · BAKELITE BODY

CIE/555 Range Guide

Compact, silent, moulded bakelite body

Every standard voltage and range

Hand-driven generator, 100 V to 1,000 V. Pick the rated test voltage first, then the insulation resistance range that suits your equipment. Each combination below is a standard build.

4	11	100–1,000
RATED VOLTAGES	STANDARD RANGES	VOLTS



CIE/555 · ILLUSTRATIVE IMAGE

01 STANDARD RANGES BY RATED VOLTAGE

RATED VOLTAGE	INSULATION RESISTANCE RANGE (MΩ)
100 V	0–10 · 0–20
250 V	0–20 · 0–50
500 V	0–50 · 0–100 · 0–200 · 0–500
1,000 V	0–100 · 0–200 · 0–500

Ranges shown are the standard builds. Any other range can be manufactured against specific requirements.

02 KEY SPECIFICATIONS

Body	Moulded high-grade bakelite
Generator Type	Hand-driven, clutch-type generator
Indicator	High-sensitivity cross-coil
Scale Length	75 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m.

03 OPTIONAL ACCESSORIES (AT EXTRA COST)

- Carrying case (bakelite body)
- Testing leads, 1 m

04 HOW TO ORDER

To order, quote the **model**, the **rated voltage** and the **insulation range**, for example `CIE/555, 500 V / 0–500 MΩ`. Any range not listed can be manufactured against specific requirements - enquire.

cieinstruments@gmail.com · +91 98300 91260 · +91 98300 92117 · cieinstruments.in

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/555 Range Guide.