Cambridge Instruments & Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

CIE/666 Range Guide

Hand-driven, seasoned wooden body

Every standard voltage and range

Hand-driven generator, 100 V to 10,000 V. Pick the rated test voltage first, then the insulation resistance range that suits your equipment. Each combination below is a standard build.

7	32	100–10,000
RATED VOLTAGES	STANDARD RANGES	VOLTS



CIE/666 · ILLUSTRATIVE IMAGE

01 STANDARD RANGES BY RATED VOLTAGE

RATED VOLTAGE	INSULATION RESISTANCE RANGE (MΩ)
100 V	0–20 · 0–50 · 0–100
250 V	0–50 · 0–100 · 0–250
500 V	0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000
1,000 V	0–100 · 0–200 · 0–500 · 0–1,000 · 0–2,000
2,500 V	0–1,000 · 0–2,000 · 0–2,500 · 0–5,000 · 0–10,000 · 0–20,000 · 50–50,000
5,000 V	0–5,000 · 0–10,000 · 0–20,000 · 50–50,000 · 100–100,000
10,000 V	0–10,000 · 0–20,000 · 50–50,000 · 100–100,000

Ranges shown are the standard builds. Any other range can be manufactured against specific requirements.

02 COMBINING VOLTAGES AND RANGES

Dual voltage & dual insulation range

One instrument, two rated voltages, each with its own insulation range, selected by a switch. The selected range must lie within the rated resistance listed for that voltage (voltage to measurable insulation range ratio up to 1:2 only; for any other ratio, enquire). Not available for the 10,000 V instrument.

Single voltage, dual insulation range

One rated voltage with two insulation ranges. Both ranges must lie within the rated resistance listed for that voltage. Not available for the 10,000 V instrument.

Continuity range (500 V and 1,000 V only)

Built in as an optional extra on single-voltage, single-range instruments, or on dual-voltage, dual-range instruments.

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.

INSULATION TESTER · HAND-DRIVEN · WOODEN BODY

CIE/666 Range Guide

Multi-range options, specifications, accessories and ordering

03 MULTIRANGE SERIES: CIE/666/MR

SERIES	RATED VOLTAGE / INSULATION RANGE (MΩ)	CONTINUITY
MR-1	1,000 V / 0–2,000 500 V / 0–1,000 250 V / 0–500	0–20 kΩ
MR-2	1,000 V / 0–200 500 V / 0–100 250 V / 0–50	0–1 kΩ
MR-3	500 V / 0–1,000 250 V / 0–500 100 V / 0–200	0–5 kΩ
MR-4	500 V / 0–100 250 V / 0–50 100 V / 0–20	0–1 kΩ

SERIES	RATED VOLTAGE / INSULATION RANGE (MΩ)	CONTINUITY
MR-5	2,500 V / 0–5,000 1,000 V / 0–2,000 500 V / 0–1,000	0–20 kΩ
MR-6	2,500 V / 0–1,000 1,000 V / 0–200 500 V / 0–100	0–1 kΩ
MR-7	5,000 V / 0–20,000 2,500 V / 0–10,000	0–20 kΩ
MR-8	5,000 V / 0–5,000 2,500 V / 0–2,500	0–5 kΩ

Multirange instruments carry a range selector switch, so one instrument covers every voltage and range listed in its series. Anti-parallax mirror scale is not provided on triple-range and above instruments. Any other configuration can be built to order.

04 KEY SPECIFICATIONS

Body	Seasoned wooden with sunmica finish; detachable lid, carrying handle, and lock
Generator Type	Hand-driven, silent generator with centrifugal governor (clutch)
Scale Length	100 mm (approx.)
Accuracy	Conforms to IS: 2992-1987
Rotation Speed	160 r.p.m. or more
Response Time	3 seconds
Weight	4.1 kg (approx.)
Dimensions (L×W×H)	265 × 165 × 185 mm (approx.)

05 OPTIONAL ACCESSORIES (AT EXTRA COST)

- Carrying case (wooden body)
- Testing leads, 1 m or 2 m (up to 1,000 V)
- H.V. testing leads, 2 m (general / special)

06 HOW TO ORDER

To order, quote the **model**, the **rated voltage** and the **insulation range**, for example `CIE/666, 500 V / 0–2,000 MΩ`. Any range not listed can be manufactured against specific requirements - enquire.

cieinstruments@gmail.com · +91 98300 91260 · +91 98300 92117 · cieinstruments.in

All specifications are subject to change without prior notice. © Cambridge Instruments & Engg. Co. - CIE/666 Range Guide.