



**Cambridge Instruments  
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, METAL BODY

# CIE/444/MR

Selectable multi-voltage insulation tester in metal body, with built-in continuity range as standard — Series MR-1 to MR-4.

MR-1 TO MR-4

## Multirange Insulation Tester — Metal Body

A multirange version of the hand-driven CIE/444, with a selector switch providing multiple rated test voltages on one instrument, plus a continuity range built in as standard.

- **Selectable multi-voltage** — one instrument, 3 ranges per series
- **Continuity range built-in** — standard on all MR series
- **Hand-driven** — no batteries required
- **Anti-magnetic aluminium body** — die-cast, rugged
- **4 series available** — MR-1 to MR-4, metal body

MR-5 to MR-8 are wooden-body only (see **CIE/666/MR**) — not available in this metal-body configuration.

*Manufactured in India since 1963 — trusted by MSEB, Indian Railways, WBSETCL, etc.*



- M** MR-1 to MR-4 Series available, metal body
- ✓** Built-In Continuity range, standard
- 0** Battery-Free Hand-cranked generator

### 01 Full Specification Sheet

| PARAMETER                     | SPECIFICATION                               |
|-------------------------------|---------------------------------------------|
| Body                          | Anti-magnetic aluminium (pressure die-cast) |
| Generator Type                | Hand-driven                                 |
| Series Available (Metal Body) | MR-1 to MR-4 only                           |
| Continuity Range              | Built-in as standard on all MR series       |
| Warranty                      | 12 months against manufacturing defects     |

**BUILD TO ORDER** Specify required MR series — other configurations to order

### 02 Available Series — Voltage, Range & Continuity

| SERIES | VOLTAGE & RESISTANCE RANGES                   | CONTINUITY RANGE |
|--------|-----------------------------------------------|------------------|
| MR-1   | 1000V/0–2000MΩ · 500V/0–1000MΩ · 250V/0–500MΩ | 0–20 KΩ          |
| MR-2   | 1000V/0–200MΩ · 500V/0–100MΩ · 250V/0–50MΩ    | 0–1 KΩ           |
| MR-3   | 500V/0–1000MΩ · 250V/0–500MΩ · 100V/0–200MΩ   | 0–5 KΩ           |
| MR-4   | 500V/0–100MΩ · 250V/0–50MΩ · 100V/0–20MΩ      | 0–1 KΩ           |

### 03 Typical Applications

- Multi-voltage insulation testing on a single instrument
- Utilities needing flexible voltage selection
- Cable and transformer testing at varying voltages
- Substation and EPC commissioning

### 04 Optional Accessories

- + Carrying case
- + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special)

#### OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,  
Kolkata 700001, West Bengal, India

#### WORKS

23/2, Maulana Abul Kalam Azad  
Road, Howrah 71101, West  
Bengal, India

#### CONTACT

+91 98300 91260  
+91 98300 92117  
cieinstruments@gmail.com

#### ONLINE

cieinstruments.in  
Instruments for accuracy and  
reliability since 1963.