



Cambridge Instruments  
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, WOODEN BODY

# CIE/666/MR

Selectable multi-voltage insulation tester in wooden body — full series MR-1 to MR-8, including HV series MR-5 to MR-8.

MR-1 TO MR-8

## Multirange Insulation Tester — Wooden Body

A multirange version of the hand-driven wooden-body CIE/666, covering the full MR-1 to MR-8 series — including HV series MR-5 to MR-8, not available in the metal-body CIE/444/MR — with continuity range built in as standard.

- **Full MR-1 to MR-8 series** — including HV series MR-5–8
- **Continuity range built-in** — standard on all MR series
- **Hand-driven** — no batteries required
- **Seasoned wooden body** — sunmica finish
- **MR-7 / MR-8 to 5000V** — widest single-instrument coverage



- MR-1 to MR-8** Full series, wooden body
- Built-In** Continuity range, standard
- Up to 5000V** MR-7/MR-8 widest coverage

### 01 Full Specification Sheet

| PARAMETER        | SPECIFICATION                                     |
|------------------|---------------------------------------------------|
| Body             | Seasoned wooden, sunmica finish                   |
| Generator Type   | Hand-driven                                       |
| Series Available | MR-1 to MR-8 (full range, incl. HV series MR-5–8) |
| Continuity Range | Built-in as standard on all MR series             |
| Warranty         | 12 months against manufacturing defects           |

Any configuration apart from the standard MR series above can be built to order.

### 02 Available Series — Voltage, Range & Continuity

| SERIES | VOLTAGE & RESISTANCE RANGES                                             | CONTINUITY RANGE |
|--------|-------------------------------------------------------------------------|------------------|
| MR-1   | 1000V/0–2000M $\Omega$ · 500V/0–1000M $\Omega$ · 250V/0–500M $\Omega$   | 0–20 K $\Omega$  |
| MR-2   | 1000V/0–200M $\Omega$ · 500V/0–100M $\Omega$ · 250V/0–50M $\Omega$      | 0–1 K $\Omega$   |
| MR-3   | 500V/0–1000M $\Omega$ · 250V/0–500M $\Omega$ · 100V/0–200M $\Omega$     | 0–5 K $\Omega$   |
| MR-4   | 500V/0–100M $\Omega$ · 250V/0–50M $\Omega$ · 100V/0–20M $\Omega$        | 0–1 K $\Omega$   |
| MR-5   | 2500V/0–5000M $\Omega$ · 1000V/0–2000M $\Omega$ · 500V/0–1000M $\Omega$ | 0–20 K $\Omega$  |
| MR-6   | 2500V/0–1000M $\Omega$ · 1000V/0–200M $\Omega$ · 500V/0–100M $\Omega$   | 0–1 K $\Omega$   |
| MR-7   | 5000V/0–20000M $\Omega$ · 2500V/0–10000M $\Omega$                       | 0–20 K $\Omega$  |
| MR-8   | 5000V/0–5000M $\Omega$ · 2500V/0–2500M $\Omega$                         | 0–5 K $\Omega$   |

### 03 Typical Applications

- High-voltage multi-voltage field insulation testing
- Multi-voltage transformer and cable testing to 5000V
- Both low- and high-voltage testing in one instrument

### 04 Optional Accessories

- + Carrying case
- + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special)

#### OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,  
Kolkata 700001, West Bengal, India

#### WORKS

23/2, Maulana Abul Kalam Azad  
Road, Howrah 711101, West  
Bengal, India

#### CONTACT

+91 98300 91260  
+91 98300 92117  
cieinstruments@gmail.com

#### ONLINE

cieinstruments.in  
Instruments for accuracy and  
reliability since 1963.