



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

PHASE SEQUENCE INDICATOR · ABS MOULDED

PSI-2

ABS moulded 96×96 mm phase sequence indicator, 50–500 V AC
(position-dependent). Supplied with case and leads.

50–500V AC

Phase Sequence Indicator

A phase sequence indicator in a compact ABS moulded enclosure, suitable for panel mounting or handheld use — verifies the phase rotation (RYB or RBY) of a 3-phase AC supply before motors, generators, or other rotating equipment are energised. More compact than the disc-rotating PSI-1, preferred where a smaller form factor is needed.

- **Compact ABS body** — 96×96×45mm, panel or handheld use
- **50–500V AC** — range depends on mounting orientation
- **25–60Hz** — wide frequency range
- **30 seconds @ 500V rating** — 15VA burden
- **Not to be left in the circuit** — per manufacturer instruction



- V **50–500V AC** Position-dependent range
- F **25–60Hz** Operating frequency
- ! **Not for Circuit Use** Not to be left in circuit

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors across India.

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Body	ABS moulded
Dimensions	96 × 96 × 45 mm
Operating Voltage (Horizontal)	50–500 V AC
Operating Voltage (Vertical)	100–500 V AC
Frequency	25–60 Hz
Rating	30 seconds at 500 V
Burden	15 VA at 500 V
Important	Not to be left in the circuit
Accessories	Carrying case and test leads (supplied)
Warranty	12 months against manufacturing defects

02 Typical Applications

- 3-phase phase sequence check
- Switchboard commissioning
- Motor connection verification

03 What's in the Box

- ✓ Carrying case
- ✓ Test leads

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.