



**Cambridge Instruments
& Engg. Co.**

EST. 1963 · HOWRAH, INDIA

RELAY TEST SET · PORTABLE TROLLEY

RTS-5A

Portable trolley-style single-phase relay test set — 0–200 A AC (6V/50V), AC or DC voltage output, dual-range timer.

0–200A TROLLEY

Portable Trolley Relay Test Set

A portable secondary current injection relay test set in a single trolley-style unit (top-hinged lid), for testing protective relays, earth fault relays, circuit breakers, and tripping coils in both laboratory and field. An AC/DC changeover switch selects either output; these are alternatives, not simultaneous.

- **0–200A across 7 ranges** — continuously variable, 6V or 50V
- **AC or DC voltage output** — 0–230V AC / 0–240V DC, 240VA
- **Digital timer** — 0–9.999s or 0–99.99s, ±1% accuracy
- **Digital ammeter & voltmeter** — built-in, multi-range
- **Portable trolley construction** — single unit, top-hinged lid

Manufactured in India since 1963 — trusted by various State Electricity Boards, Indian Railways, cement and metal industries, and other sectors across India.



- A 0–200A** 7 continuously variable ranges
- V AC/DC Output** 0–230V AC or 0–240V DC
- T Dual-Range Timer** 0–9.999s or 0–99.99s, ±1%

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Input	230 V, single phase, 50 Hz A.C.
Current Output	0–1/5/10/20A at 6V or 50V; 0–50/100/200A at 6V – continuously variable
Measuring CT	Multi-ratio wound primary CT, ratio 1-5-10-20-50-100-200 A/5A
AC Voltage Output	Continuously variable 0–230 V A.C., 240 VA max
DC Voltage Output	Continuously variable 0–240 V D.C., 240 VA (not simultaneous with AC)
Timer	0–9.999 sec or 0–99.99 sec, ±1% accuracy
Current Meter	Digital, 0–5A A.C. basic range, 0–100% scaled, ±2% of full range
Voltage Meter	Digital, 0–500 V A.C./D.C., ±2% of full range
Construction	Portable trolley-type, single unit, top-hinged lid
Mains Cable	2 metres, 3-pin plug
Warranty	12 months against manufacturing defects

02 Typical Applications

- Protective relay testing and commissioning
- Over-current and earth fault relay testing
- Circuit breaker and tripping coil testing
- Field and laboratory relay calibration

03 What's in the Box

- ✓ Operation manual
- ✓ Schematic circuit diagram
- ✓ Works test report

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.