



Cambridge Instruments
& Engg. Co.

EST. 1963 · HOWRAH, INDIA

INSULATION TESTER · MULTIRANGE, MOTOR-CUM-HAND, DUAL-SCALE

CIE/777 HM/MR

Dual-scale motor-cum-hand driven insulation tester — inner and outer scale readings cover two ranges per voltage, with hand-crank backup. Series MR-A to MR-E.

MR-A TO MR-E

Multirange Motor-cum-Hand Driven Insulation Tester

Combines the dual-scale (inner/outer) multirange capability of the CIE/777/MR with the motor-and-hand dual-drive of the CIE/777 HM. The motor-driven mode enables sustained PI and dielectric absorption testing; the hand-crank backup allows operation where mains power is unavailable. All five series (MR-A to MR-E) are available in this configuration.

- **Motor + hand-crank backup** — works with or without mains
- **Dual-scale display** — inner & outer ranges, no switching
- **5 series, MR-A to MR-E** — different range combinations
- **Up to 5000V** — widest coverage across series
- **Sustained PI & DAR testing** — motor-driven mode

Manufactured in India since 1963 — trusted by MSEB, Indian Railways, WBSETCL, etc.



- M** **Motor + Hand** Works with or without mains
- ✓** **Dual-Scale** Inner + outer range, no switch
- V** **Up to 5000V** 5 series, MR-A to MR-E

01 Full Specification Sheet

PARAMETER	SPECIFICATION
Drive	Mains motor (230 V, 50 Hz A.C.) + collapsible hand-crank
Series Available	MR-A to MR-E
Display	Dual-scale inner/outer (MR-A, MR-B, MR-D) or single-scale (MR-C, MR-E)
Physical Specs	Varies by series — contact us to confirm
Ordering	Specify required MR series when ordering
Warranty	12 months against manufacturing defects

02 Available Series — Voltage, Inner Scale & Outer Scale

SERIES	VOLT.	INNER	OUTER
MR-A	5000 V	0–5000 M Ω	50–100000 M Ω
MR-A	2500 V	0–2500 M Ω	25–50000 M Ω
MR-A	1000 V	0–1000 M Ω	10–20000 M Ω
MR-B	5000 V	0–2000 M Ω	10–10000 M Ω
MR-B	2500 V	0–1000 M Ω	5–5000 M Ω
MR-B	1000 V	0–500 M Ω	2–2000 M Ω

SERIES	VOLT.	INNER	OUTER
MR-C	5000 V	100–100000 M Ω	—
MR-C	2500 V	50–50000 M Ω	—
MR-D	5000 V	0–5000 M Ω	50–100000 M Ω
MR-D	2500 V	0–2500 M Ω	25–50000 M Ω
MR-E	5000 V	50–50000 M Ω	—
MR-E	2500 V	25–25000 M Ω	—
MR-E	1000 V	10–10000 M Ω	—

03 Typical Applications

- Remote field testing with backup hand drive — dual-scale multirange coverage
- Multi-voltage HV commissioning and PI testing
- EPC contractors and utilities needing both motor and hand-drive flexibility

04 Optional Accessories

- + Carrying case
- + Test leads, 1m
- + H.V. test leads, 2m (general)
- + H.V. test leads, 2m (special)
- + Timer
- + Any other range — on request

OFFICE

55, Ezra Street, 4th Floor, Yamuna Bhawan,
Kolkata 700001, West Bengal, India

WORKS

23/2, Maulana Abul Kalam Azad
Road, Howrah 71101, West
Bengal, India

CONTACT

+91 98300 91260
+91 98300 92117
cieinstruments@gmail.com

ONLINE

cieinstruments.in
Instruments for accuracy and
reliability since 1963.